PVM-9041QM/9044QM

SERVICE MANUAL

AEP Model

PVM-9041QM
Chassis No. SCC-F09B-A
PVM-9044QM
Chassis No. SCC-F09A-A

SP 00151



SPECIFICATIONS

Video signal

Color system	PAL, SECAM, NTSC3.58, NTSC4.43
Resolution	**PVM-9044QM:** 450 TV lines **PVM-9041QM:** 250 TV lines
Aperture correction	–4.0 dB – +6.0 dB (at 3.0 MHz)
Frequency response	6.0 MHz (–3.0 dB) at all inputs
Synchronization	AFC time constant 1.0 msec.

Picture performance

Normal scan	6% over scan of CRT effective screen area
Underscan	3% underscan of CRT effective screen area
H. linearity	Less than 7.0% (typical)
V. linearity	Less than 7.0% (typical)
Convergence	Central area: 0.43mm (typical) Peripheral area: 0.53mm (typical)
Raster size stability	H: 1.0%, V: 1.5%
High voltage regulation	3.0%
Color temperature	D65

Inputs and Outputs

Inputs	Y/C IN: 4-pin mini DIN connector (See the pin assignment on page 2.) VIDEO IN: BNC connector 1 Vp-p ± 6dB, sync negative AUDIO IN: phono jack, –5 dBs, less than 47k ohms R/R-Y, G/Y, B/B-Y: BNC connector R, G, B channels: 0.7 Vp-p, ±6 dB Sync on green : 0.3 Vp-p, negative, 75 ohms terminated R-Y, Y, B-Y channels: 0.7 Vp-p, ±6 dB (Standard color bar signal of 100% chrominance) EXT SYNC IN: BNC connector Composite sync 4 Vp-p, ±6 dB, negative
Loop-through outputs	Y/C OUT: 4-pin mini DIN connector VIDEO OUT: BNC connector, 75 ohms terminated AUDIO OUT: phono jack Output level 0.5 W EXT SYNC OUT: BNC connector, 75 ohms terminated
Tally/remote input	TALLY/REMOTE: 8-pin mini DIN connector (See the pin assignment on page 2.)

General

Power consumption	43 W at AC operation 40 W at DC operation

— Continued on next page —

MICROFILM

TRINITRON® COLOR VIDEO MONITOR

SONY®

Power requirements	100 – 240 V AC, 50/60 Hz (for all models) 12 V DC, with the Sony (NP-1A/1B) battery pack (not supplied) or AC-500/500CE AC power adaptor (not supplied)
Operating temperature range	0 – 35 °C
Storage temperature range	–10 – +40 °C
Humidity	0 – 90%
Dimensions	Approx. 217 x 217 x 352.5 mm (w/h/d) (8 5/8 x 8 5/8 x 14 inches) not incl. projecting parts and controls
Weight	Approx. 7.8 kg (17 lb 3 oz) not incl. battery packs
Accessory supplied	AC power cord (1) Cable with an 8-pin connector

Design and specifications are subject to change without notice.

Pin Assignment

Y/C IN connector (4-pin mini DIN)



Pin No.	Signal	Description
1	Y-input	1 Vp-p, sync negative, 75 ohms
2	CHROMA sub-carrier-input	300 mVp-p, burst Delay time between Y and C: within 0±100 nsec., 75 ohms
3	GND for Y-input	GND
4	GND for CHROMA-input	GND

TALLY/REMOTE connector (8-pin mini DIN)



Pin No.	Signal
1	Blue only
2	H/V delay
3	GND
4	INT/EXT SYNC
5	Tally
6	Underscan/normal scan
7	A/B or RGB/Y R-Y B-Y
8	RGB/LINE

For remote control, connect the pin of the desired function to pin 3 (GND).

TABLE OF CONTENTS

Section	Title	Page
1.	GENERAL	
1-1.	Features	4
1-2.	Location and Function of Parts and Controls	5
1-3.	Power Sources	8
2.	DISASSEMBLY	
2-1.	Cabinet Removal	9
2-2.	B Board Removal	9
2-3.	Switching Regulator Removal	10
2-4.	D Board Removal	10
2-5.	P Board Removal	11
2-6.	Rear Assy Removal	11
2-7.	HA and FA Boards Removal	12
2-8.	Picture Tube Removal	13
3.	SET-UP ADJUSTMENTS	
3-1.	Beam Landing	14
3-2.	Convergence	15
3-3.	Focus	17
3-4.	White Balance	17
4.	SAFETY RELATED ADJUSTMENT	
4-1.	Safety Related Adjustments	18
5.	CIRCUIT ADJUSTMENTS	
5-1.	D Board Adjustments	20
	B Board Adjustments	23
	S Board Adjustments	28
6.	DIAGRAMS	
6-1.	Frame Schematic Diagram	29
6-2.	Block Diagram (1)	32
6-3.	Block Diagram (2)	35
6-4.	Circuit Boards Location	40
6-5.	Printed Wiring Boards and Schematic Diagrams	40
6-6.	Semiconductors	76
7.	EXPLODED VIEWS	
7-1.	Chassis	78
7-2.	Picture Tube	79
8.	ELECTRICAL PARTS LIST	80

(CAUTION)

SHORT CIRCUIT THE ANODE OF THE PICTURE TUBE AND THE ANODE CAP TO THE METAL CHASSIS, CRT SHIELD, OR CARBON PAINTED ON THE CRT, AFTER REMOVING THE ANODE.

WARNING!!

AN ISOLATION TRANSFORMER SHOULD BE USED DURING ANY SERVICE TO AVOID POSSIBLE SHOCK HAZARD, BECAUSE OF LIVE CHASSIS.
THE CHASSIS OF THIS RECEIVER IS DIRECTLY CONNECTED TO THE AC POWER LINE.

SAFETY-RELATED COMPONENT WARNING !!

COMPONENTS IDENTIFIED BY SHADING AND MARK ⚠ ON THE SCHEMATIC DIAGRAMS, EXPLODED VIEWS AND IN THE PARTS LIST ARE CRITICAL TO SAFE OPERATION. REPLACE THESE COMPONENTS WITH SONY PARTS WHOSE PART NUMBERS APPEAR AS SHOWN IN THIS MANUAL OR IN SUPPLEMENTS PUBLISHED BY SONY. CIRCUIT ADJUSTMENTS THAT ARE CRITICAL TO SAFE OPERATION ARE IDENTIFIED IN THIS MANUAL. FOLLOW THESE PROCEDURES WHENEVER CRITICAL COMPONENTS ARE REPLACED OR IMPROPER OPERATION IS SUSPECTED.

SECTION 1
GENERAL

1-1. FEATURES

Four color systems available

The monitor can display PAL, SECAM, NTSC3.58 and NTSC4.43* signals. The appropriate color system is selected automatically.

* A signal of NTSC4.43 is used for playing back NTSC recorded video cassettes with a video tape recorder/player especially designed for use with this system.

Super Fine Pitch Trinitron picture tube

(PVM-9044QM only)

The Super Fine Pitch Trinitron picture tube provides a high resolution picture. Horizontal resolution is more than 450 TV lines at the center of the picture.

Blue only picture

The picture can be displayed in blue and black only. This facilitates hue adjustment and the observation of video noise.

Analog RGB/component input connectors

Analog RGB or component (Y, R-Y and B-Y) signals from video equipment can be input through these connectors.

Y/C input connector

The video signal, split into the chrominance signal (C) and the luminance signal (Y), can be input through this connector, eliminating the interference between the two signals, which tends to occur in a composite video signal, assuring video quality.

Beam current feedback circuit

The built-in beam current feedback circuit assures stable white balance.

Comb filter

When NTSC video signals are received, a comb filter activates to increase the resolution, resulting in fine picture detail without color spill or color noise.

Automatic termination

The Y/C, VIDEO IN and EXT SYNC IN connectors are terminated at 75 ohms inside, when no cable is connected to the loop-through output connectors. When a cable is connected to an output connector, the 75-ohm termination is automatically released.

EIA standard 19-inch rack mounting

By using an MB-507 mounting bracket (not supplied), the monitor can be mounted in an EIA standard 19-inch rack. For details on mounting, see the instruction manual of the MB-507.



1-2. LOCATION AND FUNCTION OF PARTS AND CONTROLS

Front



1 Tally lamp

2 POWER switch and indicator
Depress to turn the monitor on. The indicator will light up in green.
The POWER indicator also functions as the battery indicator. When the internal battery becomes weak or the power supplied through the DC12V IN jack decreases, the indicator flashes.

3 VOLUME control
Turn this control clockwise or counterclockwise to obtain the desired volume.

4 CONTR (contrast) control
Turn clockwise to make the contrast stronger and counterclockwise to make it weaker.

5 PHASE control
This control is effective only for the NTSC3.58 and NTSC4.43 color systems. Turn clockwise to make the skin tones greenish and counterclockwise to make them purplish.

Notes

- The PHASE, CHROMA and APER control settings have no effect on an analog RGB signal.
- The PHASE control has no effect on component singals.
- The PHASE control setting is effective only for the NTSC system.

6 CHROMA control
Turn clockwise to make the color intensity stronger and counterclockwise to make it weaker.

7 BRIGHT (brightness) control
Turn clockwise for more brightness and counterclockwise for less.

8 APER (aperture) control
Turn clockwise for more sharpness and counterclockwise for less.

9 SYNC INT/EXT (sync internal/external) selector
Keep this button released (INT) to operate the monitor on the sync signal from the displayed composite video signal.
Depress this button (EXT) to operate the monitor on an external sync signal fed through the EXT SYNC connector on the rear panel.

[10] **LINE/RGB input selector**
Select the program to be monitored. Keep this button released (LINE) for a signal fed through the LINE A or LINE B connectors. Depress this button (RGB) for a signal fed through the RGB connectors.

[11] **A/B, RGB/Y R-Y B-Y input selector**
When the LINE/RGB input selector is set to LINE, keep this button released (A) for a signal fed through the LINE A connectors. Depress this button (B) for a signal fed through the LINE B connectors.

When the LINE/RGB input selector is set to RGB, select the RGB signal or the component signal which is fed through the RGB input connectors. Keep this button released (RGB) for the RGB signal. Depress this button (Y R-Y B-Y) for the component signal.

[12] **BLUE ONLY selector**
Depress this button to turn off the red and green signals. A blue signal is displayed as an apparent monochrome picture on the screen. This facilitates "chroma" and "phase" control adjustments and the observation of video noise.

[13] **UNDER SCAN selector**
Depress this button for underscanning. The display size is reduced by approximately 3% so that four corners of the raster are visible.

[14] **H/V DELAY selector**
Depress this button to observe the horizontal and vertical sync signals at the same time. The horizontal sync signal is displayed in the left quarter of the screen; the vertical sync signal is displayed near the center of the screen.

[15] **R/G/B BIAS and GAIN adjustment controls**
Used for white balance fine adjustment.
BIAS and GAIN controls are provided for the R (red), G (green) and B (blue) screens.

BIAS: Adjust the white balance and brightness of the screen at the lowlight.
GAIN: Adjust the white balance and brightness of the screen at the highlight.

Rear



16 LINE A connectors
To monitor the signal fed through these connectors, keep the LINE/RGB selector and the A/B, RGB/Y R-Y B-Y selector on the front panel released (LINE and A).

Note

The Y/C IN connector has a priority over the VIDEO IN connector.
When a plug is connected to the Y/C IN connector, the VIDEO IN connector is automatically disconnected.

17 LINE B connectors
To monitor the signal fed through these connectors, keep the LINE/RGB selector released (LINE) and depress the A/B, RGB/Y R-Y B-Y selector (B) on the front panel.

***VIDEO IN* (BNC):** Connect to the video output of a video camera, VCR or other video equipment.
VIDEO OUT (BNC): Loop-through output of the VIDEO IN connector. Connect to the video input of a VCR or another monitor.
AUDIO IN (phono jack): Connect to the audio output of a VCR or a microphone (through a suitable microphone amplifier).
AUDIO OUT (phono jack): Loop-through output of the AUDIO IN connector. Connect to the audio input of a VCR or another monitor.

18 TALLY/REMOTE connector (8-pin mini DIN)
Connect to the tally output of a control console, special-effect generator, etc. The tally lamp on the front panel will be turned on and off by the connected equipment. This connector can be used for connecting a remote controller. For the pin assignment of this connector, see "Specifications" on page 2.

19 EXT SYNC (external sync) connectors
IN (BNC): When this monitor operates on an external sync signal, connect the reference signal from a sync generator to this connector. In this case, depress the SYNC INT/EXT selector (EXT) on the front panel.
OUT (BNC): Loop-through output of the EXT SYNC IN connector. Connect to the external sync input of video equipment to be synchronized with this monitor.

20 V HOLD (vertical hold) control
Turn to stabilize the picture if it rolls vertically.

21 DC 12V IN jack (XLR, 4 pin)
Connect the Sony AC-500/500CE AC power adaptor (not supplied).

22 RGB/component input connectors

R/R-Y, G/Y, B/B-Y (BNC), AUDIO (phono):
To monitor a signal fed through these connectors, depress the LINE/RGB selector on the front panel (RGB). When the SYNC INT/EXT selector on the front panel is released (INT), the monitor operates on the sync signal from the G/Y channel.

To monitor the analog RGB signal
Connect to the analog RGB signal outputs of a video camera having no sync signal. Keep the A/B, RGB/Y R-Y B-Y selector on the front panel released (RGB).

To monitor the component signal
Connect to the R-Y/Y/B-Y component signal outputs of a Sony BetaCam video camera. Depress the A/B, RGB/Y R-Y B-Y selector on the front panel (Y R-Y B-Y).

23 AC IN socket
Connect the supplied AC power cord to this socket and to a wall outlet.

24 EJECT buttons
Press the EJECT button upwards to remove the battery pack.

25 BATTERY compartments
Insert the NP-1A/1B battery pack (not supplied).

1-3. POWER SOURCES

House Current

Connect the supplied AC power cord to the AC IN socket and to a wall outlet.



When the AC power cord is plugged into the AC IN socket, the battery pack (if installed) or the AC power adaptor (if connected) is automatically disconnected.

Rechargeable Battery

The monitor can operate with one or two battery packs. For extended use, two battery packs are recommended.



To remove the battery pack, press the EJECT button upwards.

For charging, use the BC-1WA battery charger (not supplied) for the NP-1A or the BC-1WB for the NP-1B.

Note

Make sure that the AC power cord and the AC power adaptor are disconnected from the monitor. Otherwise, the monitor cannot operate on the battery pack(s).

SECTION 2
DISASSEMBLY

2-1. CABINET REMOVAL



2-2. B BOARD REMOVAL



2-3. SWITCHING REGULATOR REMOVAL



2-4. D BOARD REMOVAL



2-5. P BOARD REMOVAL



2-6. REAR ASSY REMOVAL



2-7. HA AND FA BOARDS REMOVAL



2-8. PICTURE TUBE REMOVAL

Note : Caution for ANODE CAP installation.
When you replace PICTURE TUBE or FBT, remove RTV on ANODE CAP so that PICTURE TUBE and FBT can be separated. Please adhere picture tube and anode cap in accordance with the following procedure.

ADHERING PROCEDURE OF ANODE CAP.

1. Clean PICTURE TUBE ANODE CAP with ethnaol to remove original RTV.
2. Dry clean face with air.
3. Use KE-490RTV (RTV silicone adhesive, SHIN-ETSU CHEMICAL).

Part. No.	Description
7-322-065-19	Silicone (RTV) KE-490W

4. Install ANODE CAP.
5. Adeguately apply RTV to the entire picture tube anode area, piace the anode cap onto the picture tube and push it down securety so that no air pockets remain beneath the cap.
6. Dry more than 12 hours at room temperature.



• REMOVAL OF ANODE-CAP

• REMOVING PROCEDURES



① Turn up one side of the rubber cap in the direction indicated by the arrow ⓐ.



② Using a thumb pull up the rubber cap firmly in the direction indicated by the arrow ⓑ.



③ When one side of the rubber cap is separated from the anode button, the anode-cap can be removed by turning up the rubber cap and pulling up it in the direction of the arrow ⓒ.

• HOW TO HANDLE AN ANODE-CAP

① Don't hurt the surface of anode-caps with sharp shaped material!

② Don't press the rubber hardly not to hurt inside of anode-caps!
A metal fitting called as shatter-hook terminal is built in the rubber.

③ Don't turn the foot of rubber over hardly!





SECTION 3
SET-UP ADJUSTMENTS

- The following adjustments should be made when a complete realignment is required or a new picture tube is installed.
- These adjustments should be performed with rated power supply voltage unless otherwise noted.

The control and switch below should be set as follows unless otherwise noted:

CONTRAST control 80%
BRIGHTNESS control 50%

Perform the adjustments in order as follows:

3-1. Beam Landing
3-2. Convergence
3-3. Focus
3-4. White Balance

Note: Test equipment Required.

1. Color Bar/Pattern Generator
2. Degausser
3. Color Analyzer (Minolta)
4. Luminance Level Meter

3-1. BEAM LANDING

Precaution

1. Set the side of the unit with the PICTURE TUBE so that it faces east or west in order to reduce the influence of external magnetic force.
2. Turn the power switch for the unit ON and erase the magnetic force using a degausser.

(1) Beam Landing

1. Receive an entirely white signal with the pattern generator.
   CONTRAST ..... MAX.
   BRIGHTNESS ..... set easy to observe
2. Adjust the white balance, G2 voltage and convergence roughly.
3. Loosen the deflection yoke mounting screw, and set the purity control to the center as shown in Fig.3-1.
4. Switch over the pattern generator to green.
5. Move the deflection yoke backward, and adjust with the purity control so that green is in the center and blue and red are at the sides, evenly. (Fig.3-2)
6. Move the deflection yoke forward, and adjust so that the entire screen becomes green. Repeat 5 to 7 as to red and blue.
7. When landing at the corners is not right, correct by using the magnet. (Fig.3-3)
8. When the position of the deflection yoke is determined, tighten it with a deflection yoke mounting screw.

CAUTION: When correction magnet is used, be sure to degauss the unit.





Fig.3-1



Fig.3-2



Fig.3-3

3-2. CONVERGENCE

(1) Horizontal and vertical Static Convergence Adjustment on the Center of Screen.

- Before starting, perform V. SIZE, V. CENT, H.SIZE, H.CENT and Screen Distortion Adjustment rightly.

(Static Convergence Adjustment)

1. Receive a dot signal, setting BRIGHTNESS minimum and set CONTRAST to normal.
2. Adjust H.STAT VR to coincide red, green and blue dots on the center of screen. (Horizontal movement)
3. Adjust V.STAT magnet to coincide red, green and blue dots on the center of screen. (Vertical movement)



* If the red, green and blue dots do not coincide on the center of screen with H.STAT VR, perform adjustment using V.STAT at the same time while tracking.
(Tilt the V.STAT magnet and adjust static convergence to open or close the V.STAT magnet.)



4. When the V.STAT magnet is moved in the direction of arrow A and b, red, green and blue dots move as shown below.

① When moving the V.STAT Magnet open or close.



② When moving the V.STAT magnet counterclockwise.



③ When moving the V.STAT magnet clockwise.



④ When tilt the V.STAT magnet and open or close.



* If the red and green dots do not coincide with blue dot, adjustment with BMC (6-poles) magnet.

5. HMC and VMC correction for BMC (6-Poles) magnet.

① HMC (Horizontal Misconvergence) correction and motion of the Electron Beam with the BMC (6-poles) magnet.



② VMC (Vertical Misconvergence) correction and motion of the Electron Beam with the BMC (6-poles) magnet.





(2) Horizontal and Vertical Dynamic Convergence Adjustment at the Environs of the Screen (Dynamic Convergence Adjustment)

1. When there is misconvergence at the sides of screen, adjust for best convergence as follows by moving the deflection yoke.
2. Loosen deflection yoke screw. Remove deflection yoke spacers. Move the deflection yoke for best convergence. Tighten the deflection yoke screw. Install three deflection yoke spacers.



Screen-corner Convergence





3-3. FOCUS

1. Receive the broadcast.
2. CONTRAST → Normal
3. Adjust FOCUS control so that the focus on the center of screen becomes to the best.



3-4. WHITE BALANCE

[Screen (G2) Voltage Adjustment]

1. Receive a dot signal with the pattern generator.
2. Adjust R. G. B cut-off controls so that respective cathode voltage against ground becomes 103V DC.
3. Observing the screen, adjust SCREEN control so that the background of the dot signal is bright dimly.



[White Balance]

1. Receive a color-bar pattern signal with the pattern generator. (Make black and white screen by chroma switch off.)
2. • BRIGHTNESS 50%
   • CONTRAST ..... Minimum
   • CHROMA 50%
   • DRIVE control ..... Mechanical center
   • BKG control ..... Mechanical center
3. Adjust RV118 (SUB BRT) on B board so that the blue stripe portion on the color-bar pattern signal is bright dimly.



4. Receive an entirely white signal from the pattern generator.
5. CONTRAST ..... 70% (90 degree clockwise from mechanical center.)
6. Using the luminance level meter, adjust the luminance level of the pattern generator becomes 3 Nits. (The condition the screen is bright dimly.)
7. Adjust white balance at cut-off using RV119 (G-C/O) and RV121 (B-C/0).
8. Change the all-white signal luminance level to 100 IREs.
9. Adjust white balance at high-light using RV120 (G-GAIN) and RV121 (B-GAIN).
10. Change the unit to blue ONLY mode.
11. Adjust white balance (at high-light) in blue ONLY mode using RV124 *R-GAIN/BL) and RV125 (G-GAIN/BL).
12. Using the luminance level meter, adjust the luminance level of the pattern generator becomes 8 Nits. Confirm that white balance at cut-off is satisfactory..

SECTION 4
SAFETY RELATED ADJUSTMENT

4-1. SAFETY RELATED ADJUSTMENTS

B+ ADJUSTMENT AND B+ MAX CHECK FOR SERVICING (⊠ RV651)

The following adjustments should always be performed when replacing the following components (marked with ◪ on the schematic diagram).

◪ on G board : (Power supply block)
IC601, IC651, PH601, C654, R653, R655, R656, R657, RV651.

1. Input the AC power supply voltage 240V $^{+1}_{-0}$ V.
2. Input the monoscope signal.
3. Set as follows.
   - CONTRAST 80%
   - BRIGHTNESS 50%
4. Connect the digital multimeter to RY1601 pin-⑦ on the D board.
5. Adjust RV651 on the G board so that the +B voltage becomes 40.0 ± 0.1V.
6. After adjusting RV651, fix it with an epoxy.
7. Input the AC power supply voltage 240V $^{+1}_{-0}$ V.
8. Input the dot signal.
9. Set as follows.
   - CONTRAST ..... Minimum
   - BRIGHTNESS ..... Minimum
10. Check that the B+ voltage is below 41.9V.
    If it is above this value, repeat from step 1.

B+ MAX IN DC POWER INPUT MODE, CONFIRMATION (⊠ RV1603)

The following adjustments should always be performed when replacing the following components (marked with ◪ on the schematic diagram).

◪ on D board :
Q1601, Q1602, Q1603, D1601, D1602, D1603, D1604, D1605, C1601, C1602, R1601, R1602, R1603, R1604, R1605, R1606, R1607, R1608, R1629, R1628, R1630, RV1601, RV1603.

1. Supply DC 12V $^{+0.4}_{-0}$ V from DC 12V IN connector.
2. Receive a dot signal.
3. • CONTRAST ..... Minimum
   • BRIGHTNESS ..... Minimum
4. Connect a digital multimeter to C1605 positive + side of D board.
5. Turn RV1601 on the D board fully clockwise. Confirm that the voltage of C1605 + pin is less than 41.9V DC.
6. If step 5 is not satisfied, readjust the RV1603. After adjusting, fasten RV1603 in place with epoxy.

HOLD-DOWN CIRCUIT CONFIRMATION (⊠ RV833) AND READJUSTMENTS

The following adjustments should always be performed when replacing the following components (marked with ◪ on the schematic diagram).

◪ on D board:
IC502, Q833, Q834, Q835, Q836, D835, D836, C519, C843, C844, C845, C846, C847, C848, RV833, R523, R850, R851, R852, R853, R854, R855, R856, R857, R858, R859, R861, R862, R863.
◪ on P board:NL801,T802 (FBT),C814.

1. Receive an entire white signal.
2. • CONTRAST ..... Maximum
   • BRIGHTNESS ..... Maximum
3. Connect a digital multimeter to the TP85 (CN503 pin-⑥).
4. Confirm the voltage is 14.1 ± 3.0V DC.
5. Receive a dot signal.
6. Connect an ammeter between D board CN503 pin-⑧ and P board CN801 pin-⑧.
7. Adjust BRIGHTNESS and CONTRAST so that the current is IABL = 160 ± 30 μA.
8. Apply an external DC voltage gradually to TP85. When the voltage becomes 18.5V ± 0.1V DC, confirm the HOLD-DOWN circuit operates immediately and raster disappears.
9. When external DC voltage at TP85 becomes 17.5V ± 0.1V DC, confirm the HOLD-DOWN circuit doesn't operate.
10. Receive an entire white signal.
11. Adjust with BRIGHTNESS and CONTRAST controls so that the current is IABL = 520 ± 30 μA.
12. Apply DC voltage of 17.8V ± 0.1V to TP85. Confirm the HOLD-DOWN circuit operates immediately and raster disappears.
13. With the same set-up as steps 10 and 11, supply 16.8V ± 0.1V DC to TP85. Confirm that the HOLD-DOWN circuit doesn't operate.
14. When above specifications are not satisfied, readjust RV833. After adjusting, fasten RV833 in place with epoxy.


RY1601
4
1
5
7
8
RV833
— D Board —
TP85
RV1601
C1605
CN503
RV1603
1
6
8
14
digital multimeter
digital multimeter
digital multimeter
ammeter
— G Board —
RV651
CN801
1
8
14
— P Board —

SECTION 5
CIRCUIT ADJUSTMENTS

5-1. D BOARD ADJUSTMENTS

—D BOARD (COMPONENT SIDE)—



HORIZONTAL OSCILLATION FREQUENCY ADJUSTMENT (RV503)

1. Receive a monoscope signal.
2. Connect pin-① of IC502 to ground with 100µF/16V electrolytic capacitor.
3. Adjust RV503 (H.FREQ) so that the screen streaming to stops.



SCREEN PHASE ADJUSTMENTS (RV502, RV512, RV516)

1. Receive a monoscope signal.
2. Set U/S (Under Scan) switch to Under mode.
3. • CONTRAST ..... Minimum
   • BRIGHTNESS ..... Maximum.
4. Adjust RV512 (U/H. SIZE) so that the white frame of monoscope signal becomes visible.
5. Adjust RV516 (H.BLK) for minimum BLKG width so that all the deflection area becomes visible.
6. Adjust RV502 (VIDEO PHASE) so that the monoscope's white frames should have equal width.



H.V BLK ADJUSTMENTS (RV501,RV516)

1. Receive a monoscope signal.
2. Set U/S (Under Scan) switch to Under mode.
3. • CONTRAST ..... Minimum
   • BRIGHTNESS ..... Maximum.
4. V. BLK Adjustment (RV501)

(1) Adjust RV501(V. BLK) so that the upper side white frame of monoscope signal is not blanked.



5. H. BLK Adjustment (RV516)

(1) Adjust with RV516 (H. BLK) so that the left end white vertical line of the white frame of monoscope signal is not blanked as following figure.



VERTICAL DEFLECTION PART ADJUSTMENTS (RV504, RV505, RV506, RV507)

1. Receive a monoscope signal.
2. • CONTRAST 70%
   • BRIGHTNESS 50%
3. Adjust RV505 (V. SIZE) so that the vertical size of monoscope signal becomes 12 frames.



4. Adjust RV507 (V.LIN) the vertical linearity.



5. Adjust RV504 (V. CENT) the vertical position.



6. V. SIZE ADJUSTMENT (RV505)

(1) Adjust RV505 (V. SIZE) so that the vertical size of monoscope signal becomes 11.75 +0.2 frames.

7. V.SIZE IN UNDERSCAN MODE ADJUSTMENT (RV506)

(1) Set U/S (Under Scan) switch to Under mode.

(2) Adjust the Under V.SIZE with RV506 (U/V. SIZE) as follows.



HORIZONTAL DEFLECTION PART ADJUSTMENTS (RV508, RV509, RV511, RV514, RV515, RV801/P board)

1. Receive a monoscope signal.
2. • CONTRAST 70%
   • BRIGHTNESS 50%
3. H. CENT Adjustment (RV801 on P board)

(1) Adjust RV801 on P board (H. CENT) the horizontal position.



4. H. SIZE Adjustment (RV511)

(1) Adjust RV511 (H. SIZE) the horizontal size of 16 frames of monoscope signal.



5. PIN AMP. PIN PHASE, V. ANG, BOW ADJUSTMENTS (RV508 RV509, RV514, RV515)

Adjust RV514 (V. ANG) and RV515 (BOW) to correct vertical angular distortion and bow distortion. Adjust RV509 (PIN AMP) and RV508 (PIN PHASE) so that vertical lines become straight.

- V. ANG (RV514)

- BOW (RV515)



- PIN AMP (RV509)

- PIN PHASE (RV508)



6. H. SIZE ADJUSTMENT (RV511)

(1) Adjust RV511 (H. SIZE) so that the horizontal size becomes 16 ± 0.2 frames.

7. UNDERSCAN MODE H.SIZE ADJUSTMENT (RV512)

(1) Set U/S (Under Scan) switch to Under mode.

(2) Adjust RV512 (U/H. SIZE) the Under H. SIZE as shown in the figure.



H V DELAY ADJUSTMENT (RV831, RV832)

1. Receive a monoscope signal.
2. • CONTRAST 70%
   • BRIGHTNESS 50%
3. Set H V DELAY switch to DELAY mode.
4. H. DELAY Adjustment (RV832)

(1) Connect an oscilloscope to pin-④ of IC831.

(2) Adjust RV832 (H. DELAY) to becomes 41 ± 1 µsec.



5. V. DELAY Adjustment (RV831)

(1) Connect an oscilloscope to pin-⑨ of IC833.

(2) Adjust RV831 to become 8.0 ± 0.4msec as follows.



SHUT-DOWN VOLTAGE ADJUSTMENT (RV1602)

1. Fully rotate RV1602 in the direction that does not shut-down.
2. Supply a 9.4V $^{+0.1}_{-0}$V voltage to the C1602 side of L1602 on the D board.
3. Turn AC power switch ON.
4. Rotate D board RV1602 (SHT DOWN) slowly to the point that shuts-down the unit.

B+ VOLTAGE DURING DC OPERATE MODE, ADJUSTMENT (RV1601)

1. Supply DC12V±0.2V to DC 12V IN connector.
2. Receive a monoscope signal.
3. • CONTRAST 80%
   • BRIGHTNESS 50%
4. Connect a digital voltmeter to C1605 + positive side on D board.
5. Adjust RV1601 on the D board for 40.0±0.1V DC.

B BOARD ADJUSTMENT

-B BOARD (COMPONENT SIDE)-



-B BOARD (CONDUCTOR SIDE)-



PRIMARY COLOR MATRIX ADJUSTMENT (RV115, RV116, RV123)

1. Supply component color bar signal (75% chroma color bar) to the equipment so that Y signal is supplied to EXT SYNC and R-Y signal to R-Y connectors Operate the equipment in external sync mode.
2. Connect oscilloscope to IC124 pin-㉚ (B-OUT).
3. Adjust RV115 (SUB HUE) to obtain the Blue output as shown in figure.



4. Supply component color bar signal (75% color bar) to the component input connector to feed R-Y and B-Y signals. Operate the equipment in internal SYNC mode.
5. Connect oscilloscope to IC124 pin-㉚ (SUB-COL). Adjust RV116 (SUB-COL) so that waveform peaks should have the same level.



6. Connect oscilloscope to IC124 pin-㊶ (R-OUT).
7. Adjust RV123 ((R-Y)-IN) so that waveform peaks should have the same level.



BURST GATE PULSE WIDTH ADJUSTMENT (RV109)

1. Receive color bar signal.
2. Connect dual trace oscilloscope to CN104 connector pin-⑩ (COMP-SYNC) and IC113 (M51279) pin-① (BGP-WIDTH). Adjust RV109 (BGP-WIDTH) to obtain the relationship as shown in the figure.



VXO ADJUSTMENT (CV101,CV102)

1. 3.58MHz VXO adjustment (CV101)

(1) Receive NTSC color bar signal.
(2) Connect +5V power line to IC113 pin-㉖ (ID-FILT-REF) via a 4700Ω resistor.
(3) Ground IC109 pin-② by connecting it to ground.
(4) Ground C162 – negative side by connecting it to ground.
(5) Connect frequency counter to IC113 pin-㉑. Adjust CV101 (358FO) for 3579545±20Hz.
(This adjustment can be alternatively done by observing screen as below.)

Adjust color synchronization by CV101 (358FO).



Adjust so that color stripes disappear and the hue change is stabilized extremely.

2. 4.43MHz VXO adjustment (CV102)
(1) Receive PAL colour bar signal.
(2) Connect +12V power line to IC109 pin-②.
(3) Connect frequency counter to IC113 pin-㉑. Adjust CV102 (443FO) for 4433619±20Hz.
(This adjustment can be alternatively done by observing screen as below.)

Adjust colour synchronization by CV102(443FO).



Adjust so that colour stripes disappear and the hue change is stabilized extremely.

NTSC COMB FILTER ADJUSTMENT (RV1,T1/CFM101 BOARD)

1. Receive NTSC 3.58 color bar signal.
2. Connect an oscilloscope to C202 – negative side.
3. Confirm the Y OUT is 0.78±0.5 Vp p.
4. Confirm the residual chroma is 32 mVp-p below. If it is above 35 mVp p, adjust with RV1 and T1 on CFM201 board while tracking.



NTSC COLOR DEMODULATION ADJUSTMENT (RV114,RV111,RV104,RV107)

1. NTSC 3.58MHz - HUE adjustment (RV114)
(1) Supply NTSC color bar signal including burst and R-Y component. (For example, Tektronix 1410SG output color bar signal with B-Y component removed.)
(2) Connect an oscilloscope to Q128 emitter (B-Y OUT).
(3) Adjust RV114 (358NT - HUE) so that all the waveform peaks should have equal amplitude (look flat) except burst. (Level difference should be less than 10mV p-p.)

2. NTSC 3.58MHz - COLOR adjustment (RV111)
(1) Receive NTSC 3.58 color bar signal.
(2) Connect an oscilloscope to IC124 pin-㉚ (B-OUT).
(3) Adjust RV111(358NT-COL) so that waveform peaks should have the same level (most flat).



3. NTSC 3.58MHz - COLOR (R-Y) adjustment (RV104, RV107)
(1) Receive the color bar signal.
(2) Connect an oscilloscope to the Q127 emitter (R-Y OUT), and adjust RV104 (358NT-SHIFT) so that the output of the burst section (B-Y axis signal output) becomes 0.
(3) Connect an oscilloscope to IC124 pin-㊶ (R-OUT). Adjust RV107 (358NT-COL (R-Y)) so that the level difference should be minimum.



(Adjust for B=D. [less than 20mV] Also level difference between B and C should be less than 60mV.)

NTSC 4.43MHZ COLOR DEMODULATION ADJUSTMENT (RV108,RV112,RV103,RV106)

1. NTSC 4.43MHz - COLOR adjustment (RV108,RV112)

(1) Receive NTSC 4.43 color bar signal (75% color bar).

(2) Connect an oscilloscope to IC124 pin-㉚ (B-OUT).

(3) Adjust RV108 (443NT-COL) so that waveform peaks should have the same level (most flat).



(4) When cyan and magenta have level difference, adjust RV112 (443NT-HUE) and RV108 (443NT-COL) alternatively to remove, by tracking.



2. NTSC 4.43MHz - COLOR (R-Y) adjustment (RV103, RV106)

(1) Receive the NTSC 4.43 color bar signal (75%, chroma color bar).

(2) Connect an oscilloscope to the Q127 emitter (R-Y OUT), and adjust RV103(443NT-SHIFT) so that the output of the burst section (B-Y axis signal output) becomes 0.

(3) Connect an oscilloscope to IC124 pin-㊶ (R-OUT). Adjust RV106 (443NT-COL (R-Y)) so that the level difference should be minimum.



(Adjust for B=D. [less than 20mV] Also level difference between B and C should be less than 60mV.)

PAL COLOR DEMODULATION ADJUSTMENT (RV113,RV2/SEP101, RV110,RV105,RV205)

1. PAL PHASE Adjustment (RV113,RV2/SEP101)

(1) Receive the special PAL color-bar.

(2) Connect an oscilloscope to emitter of Q127 (R-Y OUT).

(3) Adjust RV113 (PAL-PHASE) so that B-Y (0/180°) anti-PAL portion (in the R-Y demodulated output) becomes "0" (flat) as following figure.



* The anti-PAL portion has a small level difference in every other horizontal period. So, adjust so that average becomes "0".

(4) Connect an oscilloscope to emitter of Q128 (B-Y OUT).

(5) Adjust RV2 inside SEP101 so that R-Y (90°/90°) anti-PAL portion (in B-Y demodulated output) becomes "0" (flat) as following figure.



* The anti-PAL portion has a small level difference in every other horizontal period. So, adjust so that average becomes "0".

(For the adjustments of (3) and (5), it is also possible to set the color level to MAX with the chroma adjusting knob of the unit and erase the color of the anti-pal signal section.)

2. PAL COLOR ADJUSTMENT (RV110)
(1) Receive PAL color bar signal (75% color bar).
(2) Connect an oscilloscope to IC124 pin-㉚ (B-OUT).
(3) Adjust RV110 (PAL-COL) so that waveform peaks should have the same level (most flat).



3. PAL-COLOR-(R-Y) ADJUSTMENT (RV105)
(1) Connect an oscilloscope to IC124 pin-㊶ (R-OUT).
(2) Adjust RV105 (PAL-COL-(R-Y)) so that waveform peaks should have the same level (most flat).



(Adjust for B=D. [less than 20mV] Also level difference between B and C should be less than 60mV.)

SUB-SHARP ADJUSTMENT (RV205)

(1) Receive a sweep signal (or multi-burst).
* • Bandwidth should be more than 10MHz (flat).
• Composite sync should be included.
• Turn burst off.
(2) Connect an oscilloscope to IC124 pin-㊱ (G-OUT).
(3) Adjust RV205 (SUB-SHARP) as shown.



Example of sweep signal output waveform

[specification]
6MHz/0.5MHz=0±0.5dB

CHROMA H PULSE POSITION ADJUSTMENT (RV101,RV102)

(1) Receive the SECAM color bar signal.
(The left edge of the screen should not be colored.)
(2) Set to the under-scan mode.
(3) Adjust RV101 (PLUSE-WIDTH) until the point immediately before the color on the left edge of the screen disappears.
(4) Release the under-scan mode.
(5) Set the HV DELAY mode.
(6) Adjust RV102 (PULSE-POSI) untill the point immediately before the rising color of the image after back porch diappears.

Note : If image phase adjustment or HV DELAY amount adjustment during HV DELAY is performed after completing the adjustment in this section, re-adjustments will be required. Therefore, performed this adjustment after the two mentioned have been performed.

S BOARD ADJUSTMENTS

—S BOARD (COMPONENT SIDE)—



SECAM (T1101,L1102,L1103)

1. Receive SECAM color-bar.
2. Bell Filter Adjustment (T1101)

(1) Connect an oscilloscope to IC1101 pin-㉔.

(2) Adjust T1101 (Bell Filter) so that the chroma waveform becomes smooth. (Uneven level should be minimum.)



3. Color Balance Adjustment (L1102,L1103)

(1) Connect an oscilloscope to pin-⑨ (R-Y) of CN1101 connector.

(2) Adjust L1102 (R-Y) so that the non-colored portion level becomes flat.



(3) Connect an oscilloscope to pin-⑧ (B-Y) of CN1101 connector.

(4) Adjust L1103 (B-Y) so that the non-colored portion level becomes flat.



(5) When adjusting the color level of the unit to MAX or MIN using the chroma adjusting knob, check that the white balance of the colorless section does not change.

DEMODULATION LEVEL ADJUSTMENT (RV1101,RV1102)

1. Receive SECAM color-bar.
2. Connect an oscilloscope to IC124 pin-㉚ (B-OUT).
3. Adjust S board RV1101 (SEC-COL) so that waveform peaks should have the same level (most flat).

(B-OUT)



4. Connect an oscilloscope to IC124 pin-㊶ (R-OUT).
5. Adjust S board RV1102 (SEC-COL (R-Y)) so that the level difference should be minimum.

(R-OUT)



(Adjust for B=D. [less than 20mV] Also level difference between B and C should be less than 60mV.)

SECTION 6
DIAGRAMS

6-1. FRAME SCHEMATIC DIAGRAM



7 8 9 10 11 12 13 14 15 16 17 18 19 20 21 22



PVM-9041QM/9044QM PVM-9041QM

6-2. BLOCK DIAGRAM (1)






D (DEFLECTION SYSTEM)
NOR/UNDER
NOR/UNDER
50/60
V HOLD
COMP SYNC
NOR/DELAY
HP
H FREQ
DC 12V
D.D COM
40V ON
SW
OFF
V ZOMMING Q512
U/S SW Q510
U/V SW Q511
RV507 V LIN
RV505 V SIZE
RV506 U/V SIZE
Q535
Q517 V CENT SW
RV509 PIN AMP
Q506 PIN AMP SW1
Q507 PIN AMP SW2
RV508 PIN PHASE
Q513 PIN COMP Q514
PIN OUT Q515
L503 LMC
D507 PIN AMP
CS
PIN
V(-)
VP
V(+)
V BLK
RV501 V BLKG
V BLK SW Q503
D503 V BLK SW
IC502 (2/3)
V BLK
V OSC
V DRIVE
DEFLECTION
IC505 (2/2)
H,V. PLUSE
IC503 V OUT
V BLK BUF Q525
RV831 V DELAY
IC831 (4/4)
IC831 (1/4)
IC833 (2/2) V DELAY
IC832 (1/4)
D837 PROTECT
V SYNC SEP
IC502 (1/3)
D501 V SYNC SW
IC833 (1/2) V DELAY
IC832 (2/4)
IC832 (3/4)
IC832 (4/4)
D832 H SYNC 1
D833 H SYNC 2
D834 H SYNC
IC831 (2/4)
IC831 (3/4)
RV832 H DELAY
V PULSE SW Q501
IC501 50/60 SW
D509 PROTECT
D510 PROTECT
H PULSE SW Q502
RV515 BOW
BOW Q512
V ANG Q518
RV514 V ANG
RV516 H BLK
IC505 (1/2)
H BLK1 Q532
H BLK2 Q533
H BLK Q534
RV502 VIDEO PHASE
RV503 H FREQ
SYNC SEP
H AFC
H OSC
H DRIVE
PROTECT
IC502 (3/3) DEFLECTION
+B
D836 HV PROTECT2
D835 HV PROTECT1
TP85
HV BUFF2 Q835
HV BUFF1 Q836
CURR LIM2 Q833
CURR LIM1 Q834
RV833 H/DAR
H DRV
△HV
ABL
H BLK
DC 12V IN
BATT
PULSE Q508,505
H TRIGGER Q617
TRIANGLE GEN Q1616, 1611
DC LEVEL SIRT Q1613,1614,1615
COMPARATOR Q1612,1610
RV1601 B+ ADJ
RV1603 B+ ΔR
ERROR AMP Q1601
COMPARATOR Q1602,1603
PRE DRIVE Q1604
LIMIT SW Q509
SPEED UP Q1618
DRIVE Q1605
T1601 DRVT
CHOPPER OUT Q1606
+40V RECT D1606,1607
B+
RY1601
LED DRIVE Q1609
POWER LED
+12V
COMPARATOR IC1601 (2/2)
COMPARATOR IC1601 (1/2)
RV1602 SHUT DOWN
+40V/RELAY SW Q1607
RELAY SW Q1608
TO B BOARD
TO P BOARD
TO B BOARD
Y/VIDEO
Y/C-H
Y/C-C,BL-ONLY
R-Y/R
Y/G
B-Y/B
SYNC
IC403 AUDIO OUT
SP
VOL
LINE/RGB
A/B
NOR/UNDER
NOR/EXT
RV401 V HOLD
V HOLD
NOR/DELAY
TALLY
B+ RECT D201, 651
40V
UNT REG IC651
RV651 B+ADJ

6-3. BLOCK DIAGRAM (2)




Y AMP Q107,108
IC119 G/Y SW
G/Y BUFF Q138
Y BUFF Q139
LINE/RGB
Y/G
C
IC105 SYNC SIG SW
SYNC SIG BUFF Q106
SYNC CHIP CLAMP Q191
CLAMP REF Q194
SYNC CHIP CLAMP2 Q193
SLICER Q208
CLAMPBUFF-1 Q192
CLAMPBUFF-2 Q195
AMP1,2 Q196,197
BUFF Q198
D341
IC107 (6/6)
+12V
D107
L252
SYNC SEP Q199
IC107(2/6)
SYNC BUFF Q112
L102
V SYNC SEP Q113,114
D106 LEVEL SHIFT
D128 PULSE SW
D113
IC109(3/4)
IC108
IC108
D161
MUTE SW Q190
IC120
+12V
D160
D123
COMP SYNC
TP105 COMP SYNC
IC120(1/2)
IC122(1/2)
IC121(1/2)
Y/G BUFF Q143
Y/G
B-Y/B
R-Y/R
RV123 MATRIX R-Y LEVEL
Y BUFF Q204
B-Y BUFF Q205
R-Y BUFF Q206
G BUFF Q202
B BUFF Q201
R BUFF Q203
VCA
IC124 RGB MATRIX
MATRIX
COMP/RGB SW
OSD
R GAIN CONT
G GAIN CONT
B GAIN CONT
R C/O CONT
G C/O CON
B C/O CONT
R BUFF Q165
G BUFF Q166
B BUFF Q167
B BUFF Q168
TP104
D133 D134 D135 SLICER
BLUE ONLY SW Q212
BLACK SLISE RER Q153
D162
SECAM
SECAM R-Y
SECAM B-Y
LINE/RGB
IC107(3/6)
D115
D116
A/B SW Q116
IC117
IC118
B-Y/B BUFF Q136
R-Y/R BUFF Q137
IC120(2/2)
IC123(2/2) HOLD
IC122(2/2) HOLD
IC121(2/2)
B-Y/B BUFF Q141
R-Y/R BUFF Q142
B/W
B/W SW Q144
MODE SW Q145
D289
COL
MODE SELECT
PIX ABL Q162
D393 U/S SW
BRT ABL Q163
D127 SW
D125 HV DL SW
HV DL SW D126
D143
D142
RV205 SUB SHARP
RV116 SUB COL
RV118 SUB BRT
RV115 SUB HUE
RV117 SUB PIX
IC113 CHROMA DEMODULATION
B-Y DEMOD
R-Y DEMOD
B-Y BUFF Q128
R-Y BUFF Q127
R-Y BUFF Q130
B-Y
R-Y
RV106 443NT COL(R-Y)
RV107 358NT COL(R-Y)
RV105 358NT COL(R-Y)
IC114 SYSTEM SW
RV109 BGP WHDTH
SYNC SEP
BURST GETE PULSE GEN
ACC
FF
H PULSE
TINF CONT
VXO
APC
COLOR CONT
ID KILLER FILT
BLK IN
D137 PROTECT
TP101
IC110(1/2)
PAL R-Y BURR Q117
443NT R-Y BUFF Q119
358NT R-Y BUFF Q122
B-Y BUFF Q124
RV103 443NT SHIFT
RV104 358NT SHIFT
IC110(2/2)
443/358
PAL/NT SW Q126
PAL 60 ID2 IC128
PAL/NT
B/W
D120
B/W SW
B/W SW Q125
D129 B/W SW3
PAL/NT BGP 443/358
VXO BUFF Q131
CV101 358F0
X101 14.3MHz
Q133
14.3 SW
SYSTEM SW Q134
CV102 443F0
X102 17.7MHz
Q135
17.7 SW
H BLK
INSERT PULSE SW Q132
PULSE SW Q109
TP110 H-BLK
H DL
IC107(4/6)
D170
RV102 PULSE POST ADJ
HV DL SW Q129
IC106
IC106 H PULSE GEN
IC107(5/6)
IC109(4/4)
R GAIN
G GAIN
B GAIN
R BIAS
G BIAS
B BIAS
NOR/BL-ONLY
VP PIX
BRT
CLP
HP
MUTE
IK F.B
V BLK
RV120 G GAIN
RV122 B GAIN
RV119 G C/O
RV121 B C/O
OFF MUTE SW Q299
D151
D152
IC129 ON/OFF MUTE
Y/C-C/BL-ONLY
TP107 V. P
S002 A/B
S001 LINE/RGB
S006 SYNC INT/EXT
S004 BLUE ONLY
S005 U/S
S003 H/V DELAY
LINE/RGB
NOR/DELAY
NOR/BL-ONLY
NOR/UNDER
NOR/EXT
A/B
X (TALLY LAMP)
HA (USER CONTROL, WHITE
LINE/RGB
NOR/EXT
PHASE
A/B
H BLK
NOR/DELAY
VOL
POWER LED
COMP SYNC
ABL
NOR/UNDER
CHROMA
APT
VP
CONTRAST
TALLY


IC124 RGB MATRIX
VCA
IC126
IC125 BLACK SAMPLING
IC127 HOLD
RV124 BL ONLY W/B-R
RV125 BL ONLY W/B-G
IC116 H BLK SW
R BUFF Q165
G BUFF Q166
B BUFF Q167
B BUFF Q168
R BUFF Q173
G BUFF Q174
B BUFF Q175
R DRIVE Q157
G DRIVE Q158
B DRIVE Q159
R REF PULSE SW Q148
G REF PULSE SW Q151
B REF PULSE SW Q154
R-E.F Q149,209
G-E.F Q152,210
B-E.F Q155,211
V901 PICTURER TUBE
CV RV701 H STAT
FOCUS
SCREEN
H1-H2
HV
CA (CRT SOCKET)
BLUE ONLY SW Q212
BLACK SLISE RER Q153
D133 D134 D135 SLICER
D162
BLUE-L
H BLK
V GATE SW Q146,147
D145
D146
TP104
TP105 COMP SYNC
IC120
+12V
D123
IC122(1/2)
IC121(1/2)
Y/G BUFF Q143
Y/G
B-Y/B
R-Y/R
RV123 MATRIX R-Y LEVEL
Y BUFF Q204
B-Y BUFF Q205
R-Y BUFF Q206
G BUFF Q202
B BUFF Q201
R BUFF Q203
MATRIX
COMP/RGB SW
OSD
B/W
B/W SW Q144
MODE SW Q145
D289
COL
MODE SELECT
IC123(2/2)
IC121(2/2)
B-Y/B BUFF Q141
R-Y/R BUFF Q142
IC122(2/2) BLD
INSERT PULSE SW Q132
PIX ABL Q162
BRT ABL Q163
D393 U/S SW
D127 SW
D125 HV DL SW
D126
D143
D142
D153
D152
D151
IC129 ON/OFF MUTE
OFF MUTE SW Q299
RV122 B GAIN
RV119 G C/O
RV121 B C/O
RV120 G GAIN
RV205 SUB SHARP
RV116 SUB COL
RV118 SUB BRT
RV115 SUB HUE
RV117 SUB PIX
V BLK SW Q164
V BLK SW Q179
BLKNKING Q177
REF PULSE BUFF Q161
REF PULSE SW Q160
Y/C-C/ BL-ONLY
TP110 H-BLK
IC107(4/6)
IC107(5/6)
IC109(4/4)
HV DL SW Q129
IC106
IC106 PULSE GEN
TP107 V.P
R GAIN
G GAIN
B GAIN
R BIAS
G BIAS
B BIAS
NOR/BL-ONLY
VP PIX
BRT
CLP
HP
IK F.B
V BLK
MUTE
ABL
U/S
POWER LED
COMP SYNC
NOR/UNDER
CHROMA
APT
VP
CONTRAST
NOR/DELAY
TALLY
X (TALLY LAMP)
HA (USER CONTROL, WHITE BALANSE)
LINE/RGB
NOR/DELAY
NOR/BL ONLY
NOR/UNDER
NOR/EXT
A/B
S002 A/B
S001 LINE/RGB
S006 SYNC INT/EXT
S004 BLUE ONLY
S005 U/S
S003 H/V DELAY
BIAS
GAIN
APERTURE
BRT
CHROMA
PHASE
CONTRAST
VOL
RV006 APT
RV004 CHROMA
RV002 CONTR
RV005 BRT
RV003 PHASE
RV001 VOL
D001 POWER
B (SIGNAL PROCESS)
DY
P (H OUT, FBT)
V(+)
V(-)
CS
PIN
H DRV
D.DCON
HP
△HV
ABL
T801 HDT
H DRIVE Q801
H OUT Q802
H(+)
H(-)
HV
120V REG D802
15V REG D803, 813
24V REG D801
120V
B+
15V
24V
T802 FBT
FOCUS
SCREEN
+120V
DEGAUS D807 D808 D809
DGC SW
DGC
H1
H2

6-4. CIRCUIT BOARDS LOCATION



6-5. PRINTED WIRING BOARDS AND SCHEMATIC DIAGRAMS

Note:

- All capacitors are in µF unless otherwise noted. pF: µµF 50WV or less are not indicated except for electrolytics.
- Indication of resistance, which does not have one for rating electrical power, is as follows.

  Pitch: 5 mm
  Rating electrical power 1/4W
- All resistors are in ohms.
- ▭: nonflammable resistor.
- ▭: fusible resistor.
- △: internal component.
- ▭: panel designation.
- All variable and adjustable resistors have characteristic curve B, unless otherwise noted.
- The components identified by ⊠ in this basic schematic diagram have been carefully factory-selected for each set in order to satisfy regulations regarding X-ray radiation. Should replacement be required, replace only with the value originally used.
- When replacing components identified by ◪, make the necessary adjustments indicated. If results do not meet the specified value, change the component identified by ⊠ and repeat the adjustment until the specified value is achieved. (Refer to RV651,RV1603, and RV833 adjust on page 18 and 19.)
- When replacing the part in below table be sure to parform the related adjustment.

Part replaced (◪)	Adjustment (⊠)
IC601, IC651, PH601, C654, R653, R655,R656,R657,RV651	RV651 (B+ MAX)
Q1601, Q1602, Q1603, D1601, D1602, D1603, D1604, D1605, C1601, C1602, R1601, R1602, R1603, R1604, R1605, R1606, R1607, R1608, R1628, R1629, R1630, RV1601, RV1603	RV1603 (B+MAX IN DC POWER INPUT MODE)
IC502, Q833, Q834, Q835, Q836, D835, D836, C519, C814, C843, C844, C845, C846, C847, C848, RV833, R523, R850, R851,R852, R853, R854, R855, R856, R857, R858, R859, R861, R862, R863, NL801	RV833 (HOLD-DOWN)

- All voltages are in V.
- Voltage are dc with respect to ground unless otherwise noted.
- Readings are taken with a color-bar signal input.
- Readings are taken with a PAL color-bar signal input.
- ▭: adjustment for repair.
- Voltage variations may be noted due to normal production tolerance.
- ▬▬ : B+ bus.
- ■ ■ ■ : B- bus.
- ▒▒▒ : signal path.
- No mark : with PAL coior-bar signal received or common voltage.
- ( ) : with SECAM color-bar signal received.
- < > : with NTSC 3.58 color-bar signal received.
- (( )) : with NTSC 4.43 color-bar signal received.
- [ ] : with S (Y/C) color-bar signal received.
- { } : with analog RGB color-bar signal received.
- << >> : with component color-bar signal received.
- ※ : measurement impossibility.

Reference information

RESISTOR	: RN	METAL FILM
	: RC	SOLID
	: FPRD	NONFLAMMABLE CARBON
	: FUSE	NONFLAMMABLE FUSIBLE
	: RS	NONFLAMMABLEWIREWOUND
	: RB	NONFLAMMABLE CEMENT
COIL	: LF-8L	MICRO INDUCTOR
CAPACITOR	: TA	TANTALUM
	: PS	STYROL
	: PP	POLYPROPYLENE
	: PT	MYLAR
	: MPS	METALIZED POLYESTER
	: MPP	METALIZED POLYPROPYLENE
	: ALB	BIPOLAR
	: ALT	HIGH TEMPERATURE
	: ALR	HIGH RIPPLE

P [H OUT, FBT] **G** [SWITCHING REGULATOR]

— P Board —



— G Board —



— X Board —



— S Board — — Component side —



• ▒▒▒ : Pattern from the side which enables see
• ▒▒▒ : Pattern of the rear side.

:C LATOR]

X [TALLY LAMP] **S** [SECAM DEMODULATION] **FA** [AC/ DC]





— FA Board —



— S Board — — Component side —



• : Pattern from the side which enables seeing.
• : Pattern of the rear side.

— S Board — — Conductor side —



• : Pattern from the side which enables seeing.
• : Pattern of the rear side.

QA Board

IC		TRANSISTOR		DIODE	
IC401	B-4	Q401	C-8	D401	D-2
IC402	D-4	Q402	C-6	D402	D-3
IC403	H-4	Q403	C-4	D403	F-3
		Q404	B-9		
		Q405	B-10		
		Q406	E-9		
		Q407	E-7		
		Q408	B-10		
		Q409	E-5		
		Q410	E-3		
		Q411	D-2		
		Q412	C-7		
		Q413	C-4		
		Q414	E-4		
		Q416	G-3		
		Q417	D-1		
		Q418	C-1		
		Q419	B-2		
		Q420	B-2		
		Q421	B-2		
		Q422	B-2		
		Q423	C-1		
		Q424	B-3		

		VARIABLE RESISTOR	
D404	C-8		
D405	C-8		
D406	C-6		
D407	C-6		
D408	C-9		
D409	C-9		
D410	D-1		
D411	D-2		
D412	C-1		
D413	C-2		
D414	C-11		
D415	C-11		
D416	E-9		
D417	E-9		
D418	E-8		
D419	E-8		
D420	F-5		
D421	E-5		
D422	E-3		
D423	E-4		
D424	B-2		
D425	B-1		
D426	B-2		
D427	B-2		
D428	C-1		
D429	C-1		
D430	B-2		
D431	B-2		
		RV401	F-7

QA [INPUT SIGNAL SELECTOR]

— QA Board —



FA [AC/ DC]

— A Board —



— Conductor side —



QA [INPUT SIGNAL SELECTOR]

— QA Board —



QA Board

IC		D404	C-8
IC401	B-4	D405	C-8
IC402	D-4	D406	C-6
IC403	H-4	D407	C-6
		D408	C-9
TRANSISTOR		D409	C-9
		D410	D-1
Q401	C-8	D411	D-2
Q402	C-6	D412	C-1
Q403	C-4	D413	C-2
Q404	B-9	D414	C-11
Q405	B-10	D415	C-11
Q406	E-9	D416	E-9
Q407	E-7	D417	E-9
Q408	B-10	D418	E-8
Q409	E-5	D419	E-8
Q410	E-3	D420	F-5
Q411	D-2	D421	E-5
Q412	C-7	D422	E-3
Q413	C-4	D423	E-4
Q414	E-4	D424	B-2
Q416	G-3	D425	B-1
Q417	D-1	D426	B-2
Q418	C-1	D427	B-2
Q419	B-2	D428	C-1
Q420	B-2	D429	C-1
Q421	B-2	D430	B-2
Q422	B-2	D431	B-2
Q423	C-1		
Q424	B-3	VARIABLE RESISTOR	
		RV401	F-7
DIODE			
D401	D-2		
D402	D-3		
D403	F-3		

• : Pattern from the side which enables seeing.
• : Pattern of the rear side.


Q A (INPUT SIGNAL SELECTOR)
IC401 MM1149XF (VIDEO SW)
Q401 2SC2412K (V.A BUFFER)
Q402 2SC2412K (V.B BUFFER)
Q403 2SA1037-K (Y.BUFFER-2)
Q404 2SC2412K (Y.BUFFER-1)
Q405 2SC2412K (C.BUFFER)
Q406 2SC2412K (R.BUFFER)
Q407 2SC7412K (G.BUFFER)
Q408 2SC2412K (Y/C SW)
Q409 2SC2412K (B.BUFFER)
Q410 2SC2412K (S.BUFFER)
Q411 2SA1037K (TALLY SW)
Q412 2SA1037K (A.A.BUFFER)
Q413 2SA1037K (A.B.BUFFER)
Q414 2SA1037K (A.RGB.BUFFER)
Q416 2SC3736 (10V REG.)
Q417 DTA144EK (DELAY SW)
Q418 DTA144EK (SYNC SW)
Q419 DTA144EK (B.ONLY SW1)
Q420 DTC144EK (B.ONLY SW2)
Q421 DTA144EK (RGB SW1)
Q422 DTC144EK (RGB SW2)
Q423 DTA144EK (U/S SW)
Q424 DTA144EK (RGB/LINE)
IC402 MM1149XF (AUDIO SW)
IC403 AN5265 (AUDIO OUT)
IC404 MM1149XF (TALLY SW)
D404 MA110 (INPUT PROT-1)
D405 MA110 (INPUT PROT-2)
D406 MA110 (INPUT PROT-3)
D407 MA110 (INPUT PROT-4)
D408 MA110 (INPUT PROT-5)
D409 MA110 (INPUT PROT-6)
D410 MA110 (INPUT PROT-7)
D411 MA110 (INPUT PROT-8)
D412 MA110 (INPUT PROT-9)
D413 MA110 (INPUT PROT-10)
D414 MA110 (INPUT PROT-11)
D415 MA110 (INPUT PROT-12)
D416 MA110 (INPUT PROT-15)
D417 MA110 (INPUT PROT-16)
D418 MA110 (INPUT PROT-17)
D419 MA110 (INPUT PROT-18)
D420 MA110 (INPUT PROT-19)
D421 MA110 (INPUT PROT-20)
D422 MA110 (INPUT PROT-27)
D423 MA110 (INPUT PROT-28)
D424 MA110 (INPUT PROT-24)
D425 MA110 (INPUT PROT-14)
D426 MA110 (INPUT PROT-21)
D427 MA110 (INPUT PROT-22)
D428 MA110 (INPUT PROT-23)
D429 MA110 (INPUT PROT-24)
D430 MA110 (INPUT PROT-25)
D431 MA110 (INPUT PROT-26)
D401 MA110 (INPUT PTOR-29)
D402 MA110 (INPUT PROT-30)
D403 2ES3 (10V REF.)
IN LINE A
IN LINE B
Y/C IN
R/R-Y IN
G/Y IN
B/B-Y IN
EXT SYNC
RGB
AC IN 100-240V 50/60Hz
OUT
TALLY
(RGB/LINE)
(RGB/COMP.A/B)
(U/S)
(GND)
(SYNC)
(B.ONLY)
(H/V.DELAY)
(TALLY)
VIDEO
S-Y
Y/VIDEO
S-C
R-Y/R
B-Y/B
Y/G
AUDIO
12V
15V
CN401 15P WHT-L :S-MICRO
15 EXT SYNC
14 HV DL
13 Y/COMPOSITE
12 GND
11 12V
10 VDL
9 B/B-Y
8 RGB/LINE
7 G/G-Y
6 A/E
5 R/R-Y
4 TALLY
3 SYNC
2 Y/C-C-OUT, B DLY
1 Y/C-H
TO B BOARD CN101
CN404 4P WHT-L :S-MICRO
1 U/S
2 15V
3 V.HOLD
4 E
TO B BOARD CN504
CN402 3P WHT-L :S-MICRO
1 SP
2 GND (SP)
3 GND
TO SP
CN403 4P WHT (L) :VH
1 AC SW
2
3
4 AC SW
CN601 4P :VH
AC SW
FA (AC/DC SW)
CN602 3P :MINI
AC OUT
DC SW 1
DC SW 2
DC SW 3
TO B BOARD CN505
CN603 4P WHT :S-MICRO
CN610 3P :MINI
AC OUT
CN21 3P WHT (-L) :S-MICRO
TALLY
GND
TO B BOARD CN108
D23 SEL3810D (TALLY3)
D21 SEL3810D (TALLY1)
D22 SEL3810D (TALLY2)
X (TALLY LAMP)
RV651: See Page 18,19
G (SWITCHING REGULATOR)
IC601 CH-1018
PH601 TLP732GR
IC651 TL431CLP
F601 3.15A 250V
D601 D3SB60
Q601 2SK1402A
D602 RS119
D603 ERA38
D604 ERA38
D605 RB28
D651 ESAC39M

15 | 16 | 17 | 18 | 19 | 20 | 21 | 22 | 23 | 24 | 25 | 26 | 27 | 28 | 29 | 30

S BOARD IC1101 CXA1214P



QA BOARD IC403 AN5265



P BOARD WAVEFORMS

201 2.5Vp – p (H)	202  80Vp – p (H)	203 46Vp – p (H)
204  22Vp – p (H)	205 320Vp – p (H)	

S BOARD WAVEFORMS

301  SECAM 0.8Vp – p (H)	302  SECAM 0.7Vp – p (H)	303  SECAM 0.1Vp – p (H)	304  SECAM 3Vp – p (H)
305  SECAM 0.6Vp – p (H)	306  SECAM 0.7Vp – p (H)	307  SECAM 3.4Vp – p (H)	308  SECAM 6Vp – p (H)

51: See Page 18,19







D BOARD WAVEFORMS

(101) 11Vp-p (V)	(102) 11Vp-p (H)	(103) 0.25Vp-p (V)	(104) 10.5Vp-p (V)
(105) 3.5Vp-p (V)	(106) 3Vp-p (V)	(107) 5.5Vp-p (V)	(108) 1.5Vp-p (V)
(109) 1.3Vp-p (V)	(110) 10Vp-p (V)	(111) 6Vp-p (H)	(112) 4.4Vp-p (H)
(113) 1.1Vp-p (H)	(114) 6.4Vp-p (H)	(115) 36Vp-p (H)	(116) 2.2Vp-p (V)
(117) 1Vp-p (V)	(118) 1Vp-p (V)	(119) 46Vp-p (V)	(120) 1.6Vp-p (V)
(121) 12Vp-p (V)	(122) 12Vp-p (V)	(123) 12Vp-p (H)	(124) 12Vp-p (H)
(125) 12Vp-p (H)	(126) 32Vp-p (H)	(127) 12Vp-p (H)	(128) 0.5Vp-p (V)
(129) 2.2Vp-p (V)	(130) 0.32Vp-p (H)	(131) 0.6Vp-p (V)	(132) 12Vp-p (V)
(133) 12Vp-p (V)	(134) 12Vp-p (V)	(135) 12Vp-p (H)	(136) 12Vp-p (V)



15 16 17 18 19 20 21 22 23 24 25 26 27 28 29 30


D (DEFLECTION SYSTEM)
CN503 14P WHT BOARD-IN TO P BOARD CN801
1 GND
2 +15V
3 +24V
4 0.8 CON
5 H.DRV
6 ΔHV
7 +B
8 ABL
9 PIN
10 V (+)
11 V (-)
12 CS
13 HP
14 +120V
IC503 LA7830 V-OUT
Q506 DTC144EK PIN.AMP-SW
Q507 DTC144EK PIN.AMP-SW2
Q517 DTC144EK V.CENT-SW
Q513 2SA1037K PIN-COM1
Q514 2SA1037K PIN-COM2
Q515 2SB1134 PIN-OUT
Q516 DTC144EK V.H.SIZE-SW
Q507 MA110 PIN.AMP
Q512 2SC2412K V.ZOOMING
Q518 2SC2412K V.ANG
IC504 MC7812CT +12V-REG
Q834 2SC2412K CURR-LIM1
Q833 2SA1037K CURR-LIM2
Q836 2SC1890A HV-BUFF1
Q835 2SC2412K HV-BUFF2
Q832 DTZ22.4B HV.PROTECT2
D835 RD5.1ES275 HV.PROTECT1
Q1602 2SC2412K COMPARATOR2
Q1603 2SC2412K COMPARATOR1
Q1604 2SA1037K ABL-CONT
Q1606 2SC3324 CHOPPER-OUT
Q1607 2SC2412K RELAY-SW
Q1608 2SC2412K BIAS3
Q1609 2SC2412K CLEG-DRIVE
Q1610 2SC2688-L SPEED-UP
Q1611 MA111 UNBLANKING
Q1612 MA110 DISCHARGER
Q1615 MA110 PROTECT12
Q1616 MA110 PROTECT13
Q1617 2SA1037K V-TRIGGER
Q1618 MA110 PROTECT14
Q1619 MA110 PROTECT15
Q1620 MA110 PROTECT16
Q1621 MA110 PROTECT17
Q1622 MA110 PROTECT18
Q1623 MA110 PROTECT19
Q1624 MA110 DISCHARGE
Q1625 MA110 DISCHARGE
D1601 DTZ6.2A BIAS1
D1602 DTZ6.2A BIAS2
D1603 DTZ6.2A STOPPER
D1604 DTZ6.2A LIMIT-SW
D1605 MA110 PROTECT8
D1606 MA110 PROTECT9
D1607 10
D1608 22
D1609 MA110 PROTECT10
D1610 MA110 PROTECT11
D1611 MA110 PROTECT15
D1612 MA110 DISCHARGER
D1613 MA110 PROTECT14
D1614 MA110 PROTECT13
D1615 MA110 PROTECT12
D1616 MA110 PROTECT16
D1617 MA110 PROTECT17
D1618 MA110 PROTECT18
D1619 MA110 PROTECT19
D1620 MA110 PROTECT10
D1621 MA110 PROTECT11
D1622 MA110 PROTECT15
D1623 MA110 DISCHARGER
D1624 MA110 PROTECT14
D1625 MA110 PROTECT13
D1626 MA110 PROTECT12
D1627 MA110 PROTECT16
D1628 MA110 PROTECT17
D1629 MA110 PROTECT18
D1630 MA110 PROTECT19
D1631 MA110 PROTECT10
D1632 MA110 PROTECT11
D1633 MA110 PROTECT15
D1634 MA110 PROTECT14
D1635 MA110 PROTECT13
D1636 MA110 PROTECT12
D1637 MA110 PROTECT16
D1638 MA110 PROTECT17
D1639 MA110 PROTECT18
D1640 MA110 PROTECT19
D1641 MA110 PROTECT10
D1642 MA110 PROTECT11
D1643 MA110 PROTECT15
D1644 MA110 PROTECT14
D1645 MA110 PROTECT13
D1646 MA110 PROTECT12
D1647 MA110 PROTECT16
D1648 MA110 PROTECT17
D1649 MA110 PROTECT18
D1650 MA110 PROTECT19
D1651 MA110 PROTECT10
D1652 MA110 PROTECT11
D1653 MA110 PROTECT15

D [DEFLECTION SYSTEM]

— D Board — — Component side —



D Board (Component S

IC		DIOI
IC501	C-1	D505
IC505	B-7	D508
IC831	D-9	D509
IC832	B-8	D510
IC833	C-8	D512
IC1601	F-11	D514
TRANSISTOR		D833
		D834
Q505	E-11	D836
Q508	E-11	D837
Q509	D-11	D838
Q512	D-3	D1609
Q525	A-6	D1610
Q532	B-6	D1616
Q533	A-6	D1621
Q1607	F-11	D1625
Q1610	E-12	D1626
Q1611	F-12	D1627
Q1612	D-12	D1628
Q1613	E-13	
Q1614	E-12	
Q1615	D-12	
Q1616	D-12	
Q1617	D-12	
Q1618	D-11	

• : Pattern from the side which enables seeing.
• : Pattern of the rear side.

D Board (Component Side)

IC		DIODE	
IC501	C-1	D505	E-11
IC505	B-7	D508	A-6
IC831	D-9	D509	C-1
IC832	B-8	D510	C-2
IC833	C-8	D512	B-6
IC1601	F-11	D514	A-7
		D833	A-7
TRANSISTOR		D834	A-8
		D836	C-4
Q505	E-11	D837	D-9
Q508	E-11	D838	D-9
Q509	D-11	D1609	F-11
Q512	D-3	D1610	F-11
Q525	A-6	D1616	E-11
Q532	B-6	D1621	A-13
Q533	A-6	D1625	D-12
Q1607	F-11	D1626	E-12
Q1610	E-12	D1627	E-12
Q1611	F-12	D1628	E-12
Q1612	D-12		
Q1613	E-13		
Q1614	E-12		
Q1615	D-12		
Q1616	D-12		
Q1617	D-12		
Q1618	D-11		



— D Board — — Conductor side —



• : Pattern from the side which enables seeing.
• : Pattern of the rear side.

ductor side —



D Board (Conductor Side)

IC		DIODE		FUSE	
IC502	B-12	D501	A-12	F1601	F-5
IC503	E-7	D502	B-11	VARIABLE RESISTOR	
IC504	C-8	D503	B-11		
		D504	C-13	RV501	A-11
TRANSISTOR		D506	E-7	RV502	F-10
		D507	F-14	RV503	D-12
Q501	C-14	D511	C-8	RV504	E-9
Q502	C-14	D599	E-8	RV505	E-11
Q503	A-11	D831	C-6	RV506	F-11
Q504	C-12	D832	B-7	RV507	F-10
Q506	E-13	D835	C-11	RV508	F-11
Q507	E-13	D1601	D-4	RV509	F-11
Q510	E-9	D1602	D-3	RV511	E-12
Q511	F-11	D1603	D-4	RV512	F-11
Q513	F-13	D1604	D-3	RV514	E-10
Q514	G-11	D1605	D-3	RV515	E-10
Q515	F-14	D1606	C-3	RV516	A-10
Q516	F-12	D1607	B-3	RV831	A-6
Q517	F-10	D1608	G-2	RV832	A-6
Q518	E-11	D1611	F-2	RV833	B-11
Q519	D-10	D1612	E-5	RV1601	F-3
Q833	C-11	D1613	B-5	RV1602	F-3
Q834	C-10	D1614	B-5	RV1603	F-3
Q835	B-11	D1615	G-2		
Q836	C-10	D1617	B-4		
Q1601	E-3	D1618	B-4		
Q1602	E-3	D1619	D-3		
Q1603	E-2	D1621	A-2		
Q1604	E-2	D1635	F-4		
Q1605	B-4	D1699	F-2		
Q1606	A-3				
Q1608	E-5				
Q1609	G-4				

• : Pattern from the side which enables seeing.
• : Pattern of the rear side.

PVM-9041QM/9044QM PVM-9041QM/9044QM

B [SIGNAL PROCESS]

— B Board — — Component side —



B Board (Component Side)

IC		Q141	C-5	D153	B-
IC101	E-7	Q145	C-7	D154	B-
IC102	F-8	Q149	A-13	D156	C
IC103	F-7	Q150	G-7	D157	A-
IC104	E-9	Q153	B-6	D162	A-
IC105	F-6	Q157	A-12	D342	D
IC106	F-1	Q164	A-11	D343	G
IC107	D-2	Q166	C-11	D344	F-
IC108	E-2	Q171	E-8	D345	A
IC109	C-2	Q176	E-8	D346	B
IC110	F-11	Q191	B-2	D347	C
IC111	D-11	Q193	B-1	D348	B
IC112	F-12	Q196	B-2	D349	B
IC113	F-14	Q197	B-2	D350	C
IC114	F-11	Q198	A-2	D393	F-
IC115	D-13	Q200	F-8	VARIAB	
IC116	B-10	Q204	B-8	RESIST	
IC117	E-5	Q205	A-8	RV101	F-
IC118	E-4	Q206	A-7	RV102	F-
IC119	E-4	Q207	B-6	RV103	E
IC120	C-4	Q208	B-2	RV104	E-
IC121	C-5	Q212	C-11	RV105	G
IC122	D-5	Q299	A-10	RV106	G
IC123	D-4	DIODE		RV107	G
IC124	A-9	D103	F-8	RV108	D
IC125	B-11	D107	D-2	RV109	E-
IC126	C-11	D114	C-1	RV110	E-
IC127	B-11	D118	B-1	RV111	D
IC128	D-12	D119	B-1	RV112	E-
IC129	B-4	D121	D-3	RV113	E-
TRANSISTOR		D122	D-3	RV114	E
Q101	F-6	D123	C-3	RV115	B
Q104	F-9	D128	E-1	RV116	B-
Q109	A-11	D130	B-12	RV118	B
Q115	C-1	D131	B-13	RV119	A
Q119	E-11	D132	C-13	RV120	A
Q121	E-11	D137	G-10	RV121	A-
Q124	E-10	D138	D-12	RV122	A
Q129	F-2	D139	B-12	RV123	A-
Q132	B-2	D142	C-8	RV124	B
Q136	E-6	D143	C-8	RV125	A
Q137	E-5	D146	C-12	RV205	B
Q138	F-4	D151	C-4		
		D152	B-4		

• : Pattern from the side which enables seeing.
• : Pattern of the rear side.



B Board (Component Side)

IC						TRANSISTOR						DIODE						VARIABLE RESISTOR	
IC101	E-7	Q141	C-5	D153	B-3	Q101	F-6	Q128	E-1	D103	F-8	D128	E-1	RV101	F-1
IC102	F-8	Q145	C-7	D154	B-12	Q104	F-9	Q130	B-12	D107	D-2	D130	B-12	RV102	F-2
IC103	F-7	Q149	A-13	D156	C-12	Q109	A-11	Q131	B-13	D114	C-1	D131	B-13	RV103	E-11
IC104	E-9	Q150	G-7	D157	A-12	Q115	C-1	Q132	C-13	D118	B-1	D132	C-13	RV104	E-12
IC105	F-6	Q153	B-6	D162	A-10	Q119	E-11	Q137	G-10	D119	B-1	D137	G-10	RV105	G-11
IC106	F-1	Q157	A-12	D342	D-11	Q121	E-11	Q138	D-12	D121	D-3	D138	D-12	RV106	G-11
IC107	D-2	Q164	A-11	D343	G-2	Q124	E-10	Q139	B-12	D122	D-3	D139	B-12	RV107	G-11
IC108	E-2	Q166	C-11	D344	F-8	Q129	F-2	Q142	C-8	D123	C-3	D142	C-8	RV108	D-13
IC109	C-2	Q171	E-8	D345	A-13	Q132	B-2	Q143	C-8	D128	E-1	D143	C-8	RV109	E-14
IC110	F-11	Q176	E-8	D346	B-13	Q136	E-6	Q146	C-12	D130	B-12	D146	C-12	RV110	E-14
IC111	D-11	Q191	B-2	D347	C-14	Q137	E-5	Q151	C-4	D131	B-13	D151	C-4	RV111	D-13
IC112	F-12	Q193	B-1	D348	B-13	Q138	F-4	Q152	B-4	D132	C-13	D152	B-4	RV112	E-13
IC113	F-14	Q196	B-2	D349	B-13	D137	G-10	RV113	E-12
IC114	F-11	Q197	B-2	D350	C-13	D138	D-12	RV114	E-13
IC115	D-13	Q198	A-2	D393	F-3	D139	B-12	RV115	B-5
IC116	B-10	Q200	F-8	D142	C-8	RV116	B-5
IC117	E-5	Q204	B-8	D143	C-8	RV118	B-4
IC118	E-4	Q205	A-8	D146	C-12	RV119	A-4
IC119	E-4	Q206	A-7	D151	C-4	RV120	A-5
IC120	C-4	Q207	B-6	D152	B-4	RV121	A-4
IC121	C-5	Q208	B-2	RV122	A-5
IC122	D-5	Q212	C-11	RV123	A-8
IC123	D-4	Q299	A-10	RV124	B-10
IC124	A-9	RV125	A-10
IC125	B-11	RV205	B-4
IC126	C-11
IC127	B-11
IC128	D-12
IC129	B-4

— B Board — — Conductor side —



• : Pattern from the side which enables seeing.
• : Pattern of the rear side.

onductor side —



B Board (Conductor Side)

TRANSISTOR					
Q102	F-9	Q158	B-3	D109	D-13
Q103	D-8	Q159	C-2	D110	E-13
Q105	F-8	Q160	A-3	D111	E-14
Q106	F-9	Q161	C-3	D112	C-14
Q107	D-6	Q162	F-12	D113	C-13
Q108	E-6	Q163	F-11	D115	E-13
Q112	D-13	Q165	D-4	D116	D-13
Q114	D-14	Q167	C-4	D117	D-13
Q116	E-14	Q168	B-5	D120	G-2
Q117	F-3	Q170	C-4	D124	D-10
Q118	E-4	Q172	B-4	D125	A-9
Q120	E-4	Q173	C-4	D126	B-9
Q122	E-4	Q174	C-3	D127	F-12
Q123	E-5	Q175	C-4	D129	G-2
Q125	G-2	Q177	A-4	D133	B-6
Q126	G-2	Q178	G-8	D134	B-6
Q127	G-3	Q179	A-4	D135	C-6
Q128	G-3	Q190	C-11	D136	D-3
Q130	F-4	Q192	B-13	D144	D-3
Q131	F-2	Q194	B-14	D145	D-3
Q133	F-2	Q195	B-13	D147	A-5
Q134	E-3	Q199	A-14	D148	B-3
Q135	F-3	Q201	C-7	D149	B-2
Q139	E-11	Q202	B-7	D150	C-2
Q140	D-10	Q203	B-7	D155	B-2
Q142	C-9	Q209	A-2	D158	B-2
Q143	C-10	Q210	B-1	D159	C-2
Q144	A-6	Q211	C-1	D160	C-11
Q146	B-3	DIODE		D161	C-11
Q147	D-2	D101	F-7	D170	F-12
Q148	A-2	D102	F-7	D171	F-13
Q151	B-2	D104	E-7	D172	F-13
Q152	B-2	D105	G-7	D284	D-10
Q154	C-2	D106	D-13	D285	D-10
Q155	C-2	D108	D-13	D289	B-8
				D341	B-13

- : Pattern from the side which enables seeing.
- : Pattern of the rear side.

HA [USER CONTROL, WHITE BALANSE] CA [CRT SOCKET]

— HA Board —



— CA Board —



B BOARD WAVEF





B BOARD WAVEFORMS





PVM-9041QM/9044QM

RGB 1Vp-p (H)
COMPONENT 1Vp-p (H)
(Y/C) 1Vp-p (H)
⑥ PAL 0.9Vp-p (H)
S (Y/C) 0.5Vp-p (H)
⑧ SECAM 1Vp-p (H)
PAL 0.75Vp-p (H)
SECAM 0.75Vp-p (H)
NTSC3.58 1Vp-p (H)
NTSC4.43 0.15Vp-p (H)
⑪ PAL 0.3Vp-p (H)
AL 0.9Vp-p (H)
ECAM 0.9Vp-p (H)
NTSC3.58 1Vp-p (H)
NTSC4.43 1Vp-p (H)
S (Y/C) 1Vp-p (H)
⑮ 12Vp-p (H)
⑯ 12Vp-p (H)
ECAM 0.6Vp-p (H)
㉑ SECAM 0.5Vp-p (H)
⑬ 12Vp-p (H)
㉔ 12Vp-p (H)

㉕ 12Vp-p (H)
㉖ PAL 1.2Vp-p (H)
SECAM 1.2Vp-p (H)
NTSC3.58 1.2Vp-p (H)
NTSC4.43 1.2Vp-p (H)
S (Y/C) 1.2Vp-p (H)
㉖ RGB 1.4Vp-p (H)
COMPONENT 1.4Vp-p (H)
㉗ PAL 1.3Vp-p (H)
SECAM 1.2Vp-p (H)
NTSC3.58 1.3Vp-p (H)
NTSC4.43 1.3Vp-p (H)
S (Y/C) 1.3Vp-p (H)
㉗ RGB 1.4Vp-p (H)
COMPONENT 1.4Vp-p (H)
㉘ PAL 1.2Vp-p (H)
SECAM 1.2Vp-p (H)
COMPONENT 1.4Vp-p (H)
NTSC3.58 1.5Vp-p (H)
NTSC4.43 1.5Vp-p (H)
S (Y/C) 1.5Vp-p (H)
RGB 1.4Vp-p (H)
㉙ PAL 1Vp-p (H)
SECAM 1Vp-p (H)
NTSC3.58 1Vp-p (H)
NTSC4.43 1Vp-p (H)
S (Y/C) 1Vp-p (H)
㉚ PAL 1Vp-p (H)
SECAM 1Vp-p (H)
NTSC3.58 1Vp-p (H)
NTSC4.43 1Vp-p (H)
S (Y/C) 1Vp-p (H)
㉛ PAL 0.36Vp-p (H)
NTSC3.58 0.3Vp-p (H)
NTSC4.43 0.3Vp-p (H)
S (Y/C) 0.32Vp-p (H)
㉜ PAL 0.2Vp-p (H)
㉜ SECAM 1Vp-p (H)
㉝ PAL 0.7Vp-p (H)
SECAM 1.1Vp-p (H)
NTSC3.58 1.0Vp-p (H) (3.58MHz)
NTSC4.43 0.6Vp-p (H) (4.43MHz)
S (Y/C) 1.0Vp-p (H) (3.58MHz)
㉞ PAL 1.2Vp-p (H)
㉞ NTSC3.58 1.2Vp-p (H)
NTSC4.43 1.2Vp-p (H)
S (Y/C) 1.2Vp-p (H)
㉟ PAL 0.5Vp-p (H)
NTSC3.58 1.2Vp-p (H)
NTSC4.43 0.6Vp-p (H)
S (Y/C) 1.2Vp-p (H)
㊱ PAL 0.4Vp-p (H)
SECAM 0.1Vp-p (H)
㊱ NTSC3.58 0.3Vp-p (H)
NTSC4.43 0.45Vp-p (H)
S (Y/C) 0.35Vp-p (H)
㊲ PAL 0.55Vp-p (H)
SECAM 0.1Vp-p (H)
NTSC3.58 0.4Vp-p (H)
S (Y/C) 0.4Vp-p (H)
㊳ PAL 0.4Vp-p (H)
SECAM 1Vp-p (H)
RGB 0.4Vp-p (H)
COMPONENT 0.4Vp-p (H)
㊳ NTSC3.58 0.4Vp-p (H)
NTSC4.43 0.4Vp-p (H)
S (Y/C) 0.4Vp-p (H)
㊴ 12Vp-p (H)
㊵ PAL 11Vp-p (H)
㊶ PAL 1.8Vp-p (H)
㊷ PAL 0.5Vp-p (H)
SECAM 1Vp-p (H)
NTSC3.58 1Vp-p (H)
NTSC4.43 1Vp-p (H)
S (Y/C) 1Vp-p (H)
RGB 0.5Vp-p (H)
COMPONENT 0.5Vp-p (H)
㊸ PAL 0.35Vp-p (H)
㊸ SECAM 0.35Vp-p (H)
㊸ NTSC3.58 0.35Vp-p (H)
NTSC4.43 0.32Vp-p (H)
S (Y/C) 0.35Vp-p (H)
COMPONENT 0.28Vp-p (H)
㊹ PAL 0.45Vp-p (H)
㊹ SECAM 0.45Vp-p (H)
NTSC3.58 0.45Vp-p (H)
NTSC4.43 0.4Vp-p (H)
S (Y/C) 0.33Vp-p (H)
COMPONENT 0.35Vp-p (H)
㊺ PAL 0.5Vp-p (H)
SECAM 0.5Vp-p (H)
COMPONENT 0.6Vp-p (H)
NTSC3.58 0.8Vp-p (H)
NTSC4.43 0.8Vp-p (H)
S (Y/C) 0.6Vp-p (H)

㊻ PAL 0.36Vp-p (H)
SECAM 0.35Vp-p (H)
NTSC3.58 0.8Vp-p (H)
NTSC4.43 0.6Vp-p (H)
S (Y/C) 0.8Vp-p (H)
㊻ COMPONENT 0.3Vp-p (H)
㊼ 4.5Vp-p (V)
㊽ 10.4Vp-p (V)
㊾ 3.5Vp-p (V)
㊿ 3.5Vp-p (H)
(51) PAL 2.6Vp-p (H)
SECAM 3Vp-p (H)
NTSC3.58 3.2Vp-p (H)
NTSC4.43 3.2Vp-p (H)
S (Y/C) 3.2Vp-p (H)
COMPONENT 3Vp-p (H)
RGB 2.7Vp-p (H)
(52) PAL 2.6Vp-p (H)
SECAM 2.6Vp-p (H)
NTSC3.58 3.4Vp-p (H)
NTSC4.43 3.4Vp-p (H)
S (Y/C) 3.4Vp-p (H)
RGB 2.7Vp-p (H)
COMPONENT 3Vp-p (H)
(53) PAL 2.5Vp-p (H)
SECAM 2.6Vp-p (H)
NTSC3.58 3.1Vp-p (H)
NTSC4.43 3.1Vp-p (H)
S (Y/C) 3.1Vp-p (H)
RGB 2.6Vp-p (H)
COMPONENT 2.8Vp-p (H)
(54) PAL 0.6Vp-p (V)
SECAM 0.6Vp-p (V)
RGB 0.6Vp-p (V)
COMPONENT 0.6Vp-p (V)
NTSC3.58 0.9Vp-p (V)
NTSC4.43 1Vp-p (H)
S (Y/C) 0.7Vp-p (V)
(55) 11Vp-p (H)
(56) 10Vp-p (H)
(57) 2.4Vp-p (H)
(58) PAL 72Vp-p (H)
SECAM 80Vp-p (H)
NTSC3.58 86Vp-p (H)
NTSC4.43 90Vp-p (H)
S (Y/C) 86Vp-p (H)
RGB 70Vp-p (H)
COMPONENT 80Vp-p (H)
(59) PAL 76Vp-p (H)
SECAM 72Vp-p (H)
NTSC3.58 72Vp-p (H)
NTSC4.43 90Vp-p (H)
S (Y/C) 86Vp-p (H)
RGB 70Vp-p (H)
COMPONENT 80Vp-p (H)
(60) PAL 66Vp-p (H)
SECAM 64Vp-p (H)
NTSC3.58 80Vp-p (H)
NTSC4.43 90Vp-p (H)
S (Y/C) 80Vp-p (H)
RGB 70Vp-p (H)
COMPONENT 80Vp-p (H)

ONY SP-00151/ DRUCK23

PVM-9041QM/9044QM




IC105 MMI148XF SYNC-SIG-SW
IC107 XRU4584BF NOT-GATE
IC109 XRU4070BF EX-OR
IC111 XRU4053BF SYSTEM-SW2
IC112 LM7805CT 5V-REG
IC114 XRU4052BF SYSTEM-SW
IC117 NJM2245M B/B-Y-SW
IC118 NJM2245M R/R-Y-SW
IC119 NJM2245M G/Y-SW
IC120 XRU4064BF SAMPLE
IC121 XRU4053BF BLACK-INSERT
IC123 LM358BR HOLD-KILLER-16
IC124 LM358BR HOLD1
IC126 LM358BR CLAMP-PULSE-SW
IC128 MA151WK PULSE-SW
IC129 MA110 SW1
IC130 MA110 SW2
IC131 MA110 SW3
IC132 MA110 SW4
IC133 MA110 SW5
IC134 MA110 SW6
IC135 MA110 SW7
IC136 MA110 SW8
IC137 MA110 SW9
IC138 MA110 SW10
IC139 MA110 SW11
IC140 MA110 SW12
IC141 MA110 SW13

14 15 16 17 18 19 20 21 22 23 24 25 26 27 28 29




VOL
A/B
LINE/RGB
CLP-2
EXH-H
NOR/BIG
PULSE-2
RGB-H
B-Y/B
R-Y/R
Y/G
MUTE
UNDER-H
P-LED
12V
S/W
HV-BL-L
CLP-1
HV-BL-H
HVE
V.P.
ABL
V-BLK
H-BLK
120V
CN107 13P
TO HA BOARD CN001
TO HA BOARD CN002
TO CA BOARD CN701
CN105 6P
B (2/2)
(SIGNAL PROCESS)


HA
(USER CONTROL WHITE BALANSE)
CN001 13P WHT
CN002 8P


KG KB G2
PICTURE TUBE
CV KR G1 G4 HV
TO FBT
CN701 6P WHT
TO B BOARD CN105
TO CRT-GND
TO FBT FOCUS
TO FBT SCREEN
CA
(CRT SOCKET)
CN803 5P WHT
TO P BOARD CN803

7 | 8 | 9 | 10 | 11 | 12 | 13 | 14 | 15 | 16 | 17 | 18 | 19 | 20 | 21 | 22 | 23







— B Board —

X

< TRANSISTOR >

		PAL	SECAM	NTSC 3.58	NTSC 4.43	S (Y/C)	ANALOG RGB	COMPO-NENT
Q113	E	0.5	0.5	0.4	0.4	0.5	0.5	0.5
	B	1.0	1.0	0.9	0.9	0.9	0.9	1.0
Q115	E	11.2	9.3	0.0	10.6	0.0	0.0	0.0
	B	2.8	2.2	0.1	2.4	0.1	0.1	0.0
Q118	E	0.0	0.0	1.7	1.7	1.7	1.7	1.7
Q119	B	0.1	0.0	1.7	1.7	1.7	1.7	1.7
Q121	E	0.0	0.0	1.7	1.7	1.7	1.7	1.7
Q122	B	0.0	0.0	1.7	1.7	1.7	1.7	1.7
Q130	E	4.3	4.3	4.4	4.4	4.5	4.4	4.4
	B	3.7	3.7	3.8	3.8	3.9	3.8	3.8
Q132	E	2.3	2.3	2.4	2.3	2.4	2.4	2.4
	C	1.8	1.7	1.7	1.7	1.7	1.8	1.8
	B	2.7	2.6	2.6	2.7	2.8	2.7	2.8
Q146	C	116.7	114.4	110.4	113.2	113.7	114.3	114.1
Q147	E	117.9	115.6	111.6	114.5	115.0	115.5	115.4
	C	126.0	123.5	120.3	123.4	123.8	124.6	124.4
	B	119.8	119.5	110.5	118.4	118.2	114.2	114.2
Q148	C	86.1	84.9	91.2	83.4	82.6	82.5	82.2
	B	94.0	93.3	86.3	92.4	92.1	94.2	90.6
Q149	E	1.6	1.6	1.4	1.7	1.7	1.7	1.7
	C	86.1	84.9	91.2	83.4	82.7	82.5	82.5
Q151	E	90.7	91.4	98.0	87.9	87.0	86.5	86.4
	C	89.2	89.8	96.5	86.4	85.3	84.9	84.7
	B	92.1	92.7	100.2	89.5	92.4	90.5	88.9
Q152	E	86.1	86.0	92.6	82.6	82.9	82.6	82.7
	C	10.8	10.5	9.7	10.9	10.9	10.9	11.0
Q154	B	92.5	92.9	99.8	90.1	88.7	90.4	89.2
Q155	B	88.3	88.5	95.7	85.7	83.9	84.6	83.9
Q157	E	82.4	81.1	87.5	79.9	79.9	80.8	79.4
	B	86.0	84.8	91.2	84.4	82.7	82.5	82.1
Q158	E	1.6	1.5	1.3	1.6	1.6	1.7	1.7
	B	2.1	2.0	1.8	2.1	2.2	2.2	2.2
Q159	E	1.6	1.6	1.3	1.6	1.7	1.7	1.7
	B	2.2	2.1	1.5	2.1	2.2	2.2	2.2
Q163	E	0.2	0.6	2.7	0.5	−0.5	−0.7	−0.6
Q166	B	0.9	0.9	0.6	1.0	1.0	1.0	1.0
Q168	C	2.1	2.0	1.6	2.1	2.2	2.1	2.2
Q170	B	2.3	2.3	2.1	2.4	2.4	2.4	2.4
Q172	B	2.2	2.1	1.9	2.2	2.3	2.2	2.3
Q173	B	1.7	1.6	1.4	1.7	1.7	1.7	1.7
Q174	E	2.1	2.0	1.8	2.1	2.2	2.2	2.2
	B	1.6	1.5	1.3	1.6	1.6	1.7	1.7
Q178	B	6.2	6.3	6.2	6.3	6.1	6.2	6.2
Q209	E	83.4	81.5	87.9	80.3	80.4	80.4	79.8
	C	115.8	113.2	110.7	113.2	113.8	114.5	114.2
	B	87.8	86.4	92.8	85.0	84.3	84.2	83.8
Q210	E	86.5	86.3	93.1	83.0	83.3	83.0	82.8
	C	116.5	114.2	111.5	113.9	114.5	115.1	114.9
Q211	C	115.9	113.6	111.7	113.3	113.8	114.5	114.3

< IC >

		PAL	SECAM	NTSC 3.58	NTSC 4.43	S (Y/C)	ANALOG RGB	COMPO-NENT
IC102	②	6.6	6.6	0.0	6.6	0.0	0.0	0.0
IC106	②	0.2	0.1	0.1	0.1	0.1	0.1	0.2
	④	1.8	1.7	1.7	1.7	1.7	1.8	1.8
IC107	②	10.7	10.7	10.6	10.6	10.6	10.6	10.6
	⑪	1.2	10.7	0.0	0.0	0.0	0.0	0.0
IC108	⑪	9.7	0.4	9.7	9.6	9.6	1.1	9.6
IC109	②	11.3	11.3	0.0	10.6	0.0	0.0	0.0
	③	11.3	11.4	0.0	11.3	0.0	0.0	0.0
	④	11.7	0.0	0.0	11.7	0.0	0.0	0.0
	⑤	11.0	11.1	0.0	11.0	0.0	0.0	0.0
IC110	④	2.1	2.2	2.5	2.5	2.5	2.5	2.5
	⑩	11.3	11.3	0.0	11.3	0.0	0.0	0.0
	⑪	11.3	11.3	0.0	0.0	0.0	0.0	0.0
	⑫	0.8	0.8	2.5	2.5	2.5	2.5	2.5
	⑭	1.7	1.7	2.5	2.6	2.5	2.5	2.5
IC113	④	2.7	1.1	2.6	2.6	2.6	1.1	1.1
	⑦	4.2	4.3	4.2	4.3	4.3	4.8	4.8
	⑪	3.0	2.9	2.8	3.0	2.8	2.9	2.9
	㉕	2.2	2.5	2.9	2.2	1.9	2.8	2.8
IC114	⑩	11.4	11.3	0.0	0.0	0.0	0.0	0.0
	⑬	3.7	3.7	3.8	3.8	3.8	3.9	3.9
IC115	③	1.2	1.1	0.6	0.7	0.7	0.6	0.6
	⑬	3.5	3.5	3.4	2.8	3.4	3.4	3.4
IC116	②	0.0	0.0	1.0	1.1	1.1	1.3	1.1
IC120	③	5.5	5.6	5.6	5.6	5.6	5.6	5.6
	④	5.5	5.6	5.6	5.6	5.6	5.0	5.6
IC121	⑬	5.3	5.3	5.4	5.2	5.2	5.1	5.1
	⑭	5.6	5.7	5.6	5.6	5.7	5.7	5.7
	⑱	5.6	5.7	5.6	5.6	5.7	5.7	5.6
IC122	②	5.3	5.3	5.4	5.2	5.2	5.1	5.1
	③	5.3	5.3	5.4	5.2	5.2	5.1	5.1
IC124	⑱	0.1	0.1	0.2	0.2	0.2	0.2	0.2
IC125	④	1.4	1.4	1.3	1.4	1.5	1.5	1.5
IC126	②	1.6	1.5	1.3	1.6	1.6	1.7	1.6
	⑤	1.6	1.5	1.3	1.6	1.6	1.6	1.7
	⑭	1.7	1.6	1.4	1.7	1.7	1.6	1.7
IC127	①	3.0	2.9	2.6	3.0	3.1	3.0	3.0
	②	1.4	1.4	1.3	1.5	1.5	1.5	1.5
	⑦	2.1	2.7	2.4	2.8	2.8	2.8	2.8

CA BOARD WAVEFORM



6-6. SEMICONDUCTORS

AN5265



CXA1214P



CXA1478S

CX23025



LA7830



LM7805CT
LM7812CT
MC7812CT



LM358D
LM358DR
MM1148XFF
MM1149XF
NJM2245M
XRA10393F



MC14538BF



M51279FP



µPC1377C



XRU4011BF
XRU4070BF



XRU4052BF
XRU4053BF
XRU4066BF



XRU4584BF



DTA144EK
DTC144EK
2SA1037K
2SA1162-G
2SC2412K

IMX1
IMX1T110



2SA1091-0
2SC1890-A
2SC2551-0
2SC2551R

2SC2334-L
2SD1134



2SC2611
2SC2688



2SC3736

2SK94

DTZ15B
DTZ20B
DTZ24B
DTZ5.6A
DTZ6.2-TT11
DTZ6.2B
DTZ8.2B
RD15SB1



D10SC4M



ERC81-004



GP08DPK23
HSM83-TL
RD5.6EBZ7STN
1SS83
1SS83TD



MA110

MA151WA
1S2836



MA151WK
MA152WK



MA157
1SS226



N13T1



RD3.6ESB1
RD5.6ESB2
RD8.2ESB3



SEL3810DLC05
SLP281C-50
TLG123A

U05G

NOTE:
- Items with not stocke routine ser
- The constr indicated v column.

7-1. CHA

● : BVTP3
▲ : BVTP3



REF. NO.	PART
1	X-40
1	X-40
2	4-03
3	*4-03
4	*4-03
5	*4-03
6	*1-64
7	1-54
8	*A-11
9	*A-13
10	⚠1-41
11	A-13
12	⚠1-57
13	*A-11
14	⚠1-43

MA157
1SS226



STN

N13T1



RD3.6ESB1
RD5.6ESB2
RD8.2ESB3



SEL3810DLC05
SLP281C-50
TLG123A



U05G

SECTION 7
EXPLODED VIEWS

NOTE:
- Items with no part number and no description are not stocked because they are seldom required for routine service.
- The construction parts of an assembled part are indicated with a collation number in the remark column.
- Items marked "*" are not stocked since they are seldom required for routine service. Some delay should be anticipated when ordering these items.

The components identified by shading and mark ⚠ are critical for safety.
Replace only with part number specified.

7-1. CHASSIS

● : BVTP3x8 7-685-646-79
▲ : BVTP3x12 7-685-648-79



REF. NO.	PART NO.	DESCRIPTION	REMARK
1	X-4030-164-6	BEZEL ASSY (PVM-9041QM only)	
1	X-4030-278-1	BEZEL ASSY (PVM-9044QM only)	
2	4-034-844-01	HANDLE, PROTECTOR	
3	*4-034-845-01	BRACKET (L), BEZEL	
4	*4-034-846-01	BRACKET (U), BEZEL	
5	*4-035-388-01	PLATE, LIGHT INTERCEPTION	
6	*1-641-724-11	PC BOARD, X	
7	1-544-252-11	SPEAKER	
8	*A-1135-716-A	B BOARD, COMPLETE	
9	*A-1394-368-A	S BOARD, COMPLETE	
10	⚠1-413-720-21	SWITCHING REGULATOR	
11	A-1346-018-A	D BOARD, COMPLETE	
12	⚠1-576-232-11	FUSE (H.B.C.) (5A 250V)	
13	*A-1195-048-A	P BOARD, COMPLETE	
14	⚠1-439-526-11	TRANSFORMER ASSY, FLYBACK	
15	4-034-847-01	HANDLE (BASE)	
16	3-419-372-31	HANDLE	
17	*4-034-867-01	CABINET	
18	*X-4030-273-1	REINFORCEMENT ASSY, HANDLE	
19	4-035-452-01	SCREW (M4X10)	
20	4-034-834-01	SCREW (CLAW) (4X6)	
21	A-1275-099-A	QA BOARD, COMPLETE	
22	*4-034-864-01	CHASSIS, R	
23	4-035-802-01	SCREW (M2.6X6)	
24	*4-034-870-02	CABINET, BOTTOM	
25	*4-035-691-01	CLOTH, VIBRATION PROOF	
26	4-389-025-01	SCREW (M4X8) (EXT TOOTH WASHER)	
27	*4-036-058-01	SPONGE	
28	1-543-925-11	CORE, FERRITE	

7-2. PICTURE TUBE

▲ : BVTP3x12 7-685-648-79



The components identified by shading and mark ⚠ are critical for safety.
Replace only with part number specified.

REF. NO.	PART NO.	DESCRIPTION	REMARK
51	4-304-511-00	FLANGE NUT, 5MM	
52 ⚠	8-737-151-05	CRT A20JKU10X (PVM-9041QM only)	
52 ⚠	8-737-651-05	CRT A20JMP10X (PVM-9044QM only)	
53	4-035-332-01	CLOTH, PROTECTION	
54	*4-034-856-01	HOLDER, HV CABLE	
55	4-309-369-00	SPACER, DEFLECTION YOKE	
56 ⚠	1-451-319-22	DEFLECTION YOKE (Y9FXC)	
57	*1-641-720-11	CA BOARD	
58	*4-376-133-11	COVER (MAIN), CV VOL	
59	*4-376-132-11	COVER (REAR LID), CV VOL	
60 ⚠	1-426-043-00	COIL, DEGAUSSING	
61	4-380-534-01	CAP, DGC	
62	*4-034-850-01	INSULATOR	
63	*A-1371-782-A	HA BOARD, MOUNTED	
64	4-034-849-01	SWITCH (SMALL), PUSH	
65	X-4030-162-1	KNOB ASSY, CONTROL	
66	*1-641-723-11	FA BOARD	
67	⚠1-692-050-11	SWITCH, PUSH (AC POWER) (1 KEY)	
68	4-034-841-01	SWITCH, POWER	
69	*X-4030-166-1	CHASSIS ASSY, BOTTOM	
70	4-034-840-01	RUBBER, FOOT	
71	*X-4030-163-1	GUIDE ASSY, BATTERY	
72	4-034-861-01	KNOB, BATTERY	
73	4-876-347-01	SPRING, COMPRESSION	
74	3-669-594-00	SPRING, COMPRESSION	
75	4-308-870-00	CLIP, LEAD WIRE	
76	1-452-126-11	MAGNET	
77	1-452-094-00	MAGNET, ROTATABLE DISK; 15 MM ϕ	
78	X-4308-815-0	PERMALLOY ASSY, CONVERGENCE	
79	*4-036-047-02	RUBBER, VIBRATION PROOF	
80	3-839-640-00	CUSHION	
81	3-831-441-11	CUSHION (F)	
82	*4-035-691-01	CLOTH, VIBRATION PROOF	

B

SECTION 8
ELECTRICAL PARTS LIST

NOTE:

The components identified by shading and mark ⚠ are critical for safety.
Replace only with part number specified.

- Items marked "*" are not stocked since they are seldom required for routine service. Some delay should be anticipated when ordering these items.
- All variable and adjustable resistors have characteristic curve B, unless otherwise noted.

RESISTORS
- All resistors are in ohms
- F: nonflammable

When indicating parts by reference number, please include the board name.

CAPACITORS
- MF: μF, PF: μμF

COILS
- MMH: mH, UH: μH

- The components identified by ⊠ in this manual have been carefully factory-selected for each set in order to satisfy regulations regarding X-ray radiation.
Should replacement be required, replace only with the value originally used.

REF.NO.	PART NO.	DESCRIPTION			REMARK
	*A-1135-716-A	B BOARD, COMPLETE			
		**********			
	3-710-578-01	COVER, VOLUME, 6 MOLD			
		<FILTER>			
BPF101	1-236-363-11	FILTER, BAND PASS			
BPF102	1-236-364-11	FILTER, BAND PASS			
		<CAPACITOR>			
C101	1-124-589-11	ELECT	47MF	20%	16V
C102	1-163-031-11	CERAMIC CHIP	0.01MF		50V
C103	1-126-157-11	ELECT	10MF	20%	16V
C104	1-163-031-11	CERAMIC CHIP	0.01MF		50V
C105	1-163-031-11	CERAMIC CHIP	0.01MF		50V
C106	1-124-477-11	ELECT	47MF	20%	16V
C107	1-163-031-11	CERAMIC CHIP	0.01MF		50V
C108	1-124-477-11	ELECT	47MF	20%	16V
C109	1-124-477-11	ELECT	47MF	20%	16V
C110	1-124-120-11	ELECT	220MF	20%	16V
C111	1-163-031-11	CERAMIC CHIP	0.01MF		50V
C112	1-163-031-11	CERAMIC CHIP	0.01MF		50V
C113	1-163-031-11	CERAMIC CHIP	0.01MF		50V
C114	1-124-477-11	ELECT	47MF	20%	16V
C115	1-163-031-11	CERAMIC CHIP	0.01MF		50V
C116	1-124-589-11	ELECT	47MF	20%	16V
C117	1-126-154-11	ELECT	47MF	20%	6.3V
C118	1-126-154-11	ELECT	47MF	20%	6.3V
C119	1-163-031-11	CERAMIC CHIP	0.01MF		50V
C120	1-126-154-11	ELECT	47MF	20%	6.3V
C121	1-124-477-11	ELECT	47MF	20%	16V
C122	1-124-477-11	ELECT	47MF	20%	16V
C123	1-163-031-11	CERAMIC CHIP	0.01MF		50V
C124	1-163-031-11	CERAMIC CHIP	0.01MF		50V
C125	1-126-154-11	ELECT	47MF	20%	6.3V
C126	1-163-031-11	CERAMIC CHIP	0.01MF		50V
C127	1-126-154-11	ELECT	47MF	20%	6.3V
C128	1-126-154-11	ELECT	47MF	20%	6.3V
C129	1-163-031-11	CERAMIC CHIP	0.01MF		50V
C130	1-163-031-11	CERAMIC CHIP	0.01MF		50V
C131	1-163-031-11	CERAMIC CHIP	0.01MF		50V
C132	1-124-589-11	ELECT	47MF	20%	16V
C133	1-124-589-11	ELECT	47MF	20%	16V
C134	1-163-275-11	CERAMIC CHIP	0.001MF	5%	50V
C135	1-163-113-00	CERAMIC CHIP	68PF	5%	50V
C137	1-163-115-00	CERAMIC CHIP	82PF	5%	50V
C138	1-124-589-11	ELECT	47MF	20%	16V
C139	1-163-031-11	CERAMIC CHIP	0.01MF		50V
C140	1-163-205-00	CERAMIC CHIP	0.001MF	5%	50V
C141	1-163-141-00	CERAMIC CHIP	0.001MF	5%	50V
C142	1-163-031-11	CERAMIC CHIP	0.01MF		50V
C143	1-163-121-00	CERAMIC CHIP	150PF	5%	50V
C144	1-163-101-00	CERAMIC CHIP	22PF	5%	50V
C145	1-163-131-00	CERAMIC CHIP	390PF	5%	50V
C146	1-126-157-11	ELECT	10MF	20%	16V
C147	1-164-232-11	CERAMIC CHIP	0.01MF	10%	50V
C148	1-126-160-11	ELECT	1MF	20%	50V
C149	1-163-022-00	CERAMIC CHIP	0.012MF	10%	50V
C150	1-124-589-11	ELECT	47MF	20%	16V
C151	1-163-131-00	CERAMIC CHIP	390PF	5%	50V
C152	1-163-101-00	CERAMIC CHIP	22PF	5%	50V
C153	1-163-125-00	CERAMIC CHIP	220PF	5%	50V
C154	1-163-031-11	CERAMIC CHIP	0.01MF		50V
C155	1-163-133-00	CERAMIC CHIP	470PF	5%	50V
C156	1-164-299-11	CERAMIC CHIP	0.22MF	10%	25V
C157	1-163-229-11	CERAMIC CHIP	12PF	5%	50V
C158	1-124-477-11	ELECT	47MF	20%	16V
C159	1-163-229-11	CERAMIC CHIP	12PF	5%	50V
C160	1-163-229-11	CERAMIC CHIP	12PF	5%	50V
C161	1-124-902-00	ELECT	0.47MF	20%	50V
C162	1-124-903-11	ELECT	1MF	20%	50V
C163	1-163-809-11	CERAMIC CHIP	0.047MF	10%	25V
C164	1-163-809-11	CERAMIC CHIP	0.047MF	10%	25V
C165	1-163-009-11	CERAMIC CHIP	0.001MF	10%	50V
C166	1-163-031-11	CERAMIC CHIP	0.01MF		50V
C167	1-124-477-11	ELECT	47MF	20%	16V
C168	1-163-031-11	CERAMIC CHIP	0.01MF		50V
C169	1-163-243-11	CERAMIC CHIP	47PF	5%	50V
C170	1-163-129-00	CERAMIC CHIP	330PF	5%	50V
C171	1-163-243-11	CERAMIC CHIP	47PF	5%	50V
C172	1-163-129-00	CERAMIC CHIP	330PF	5%	50V
C173	1-124-589-11	ELECT	47MF	20%	16V
C174	1-124-477-11	ELECT	47MF	20%	16V
C175	1-108-792-11	MYLAR	0.001MF	5%	50V
C176	1-163-031-11	CERAMIC CHIP	0.01MF		50V
C177	1-163-031-11	CERAMIC CHIP	0.01MF		50V
C178	1-163-031-11	CERAMIC CHIP	0.01MF		50V
C179	1-126-160-11	ELECT	1MF	20%	50V
C180	1-163-031-11	CERAMIC CHIP	0.01MF		50V
C181	1-126-154-11	ELECT	47MF	20%	6.3V
C182	1-126-163-11	ELECT	4.7MF	20%	16V
C183	1-164-232-11	CERAMIC CHIP	0.01MF	10%	50V
C184	1-163-031-11	CERAMIC CHIP	0.01MF		50V
C185	1-163-031-11	CERAMIC CHIP	0.01MF		50V
C186	1-163-099-00	CERAMIC CHIP	18PF	5%	50V
C187	1-163-031-11	CERAMIC CHIP	0.01MF		50V
C188	1-163-031-11	CERAMIC CHIP	0.01MF		50V
C189	1-163-035-00	CERAMIC CHIP	0.047MF		50V
C190	1-163-121-00	CERAMIC CHIP	150PF	5%	50V
C191	1-163-031-11	CERAMIC CHIP	0.01MF		50V

REF.NO.	PART NO.	DESCRIPTION		REMARK
C192	1-163-031-11	CERAMIC CHIP 0.01MF		50V
C193	1-124-589-11	ELECT 47MF	20%	16V
C194	1-124-589-11	ELECT 47MF	20%	16V
C195	1-124-589-11	ELECT 47MF	20%	16V
C196	1-124-589-11	ELECT 47MF	20%	16V
C197	1-124-589-11	ELECT 47MF	20%	16V
C198	1-124-589-11	ELECT 47MF	20%	16V
C199	1-124-589-11	ELECT 47MF	20%	16V
C202	1-124-589-11	ELECT 47MF	20%	16V
C203	1-124-589-11	ELECT 47MF	20%	16V
C204	1-124-589-11	ELECT 47MF	20%	16V
C205	1-163-101-00	CERAMIC CHIP 22PF	5%	50V
C206	1-164-298-11	CERAMIC CHIP 0.15MF	10%	25V
C207	1-164-298-11	CERAMIC CHIP 0.15MF	10%	25V
C208	1-163-101-00	CERAMIC CHIP 22PF	5%	50V
C209	1-164-004-11	CERAMIC CHIP 0.1MF	10%	25V
C210	1-124-589-11	ELECT 47MF	20%	16V
C211	1-124-589-11	ELECT 47MF	20%	16V
C212	1-124-589-11	ELECT 47MF	20%	16V
C213	1-124-589-11	ELECT 47MF	20%	16V
C214	1-126-157-11	ELECT 10MF	20%	16V
C215	1-126-157-11	ELECT 10MF	20%	16V
C216	1-126-157-11	ELECT 10MF	20%	16V
C217	1-163-031-11	CERAMIC CHIP 0.01MF		50V
C218	1-164-298-11	CERAMIC CHIP 0.15MF	10%	25V
C219	1-163-009-11	CERAMIC CHIP 0.001MF	10%	50V
C220	1-163-031-11	CERAMIC CHIP 0.01MF		50V
C221	1-124-903-11	ELECT 1MF	20%	50V
C222	1-163-093-00	CERAMIC CHIP 10PF	5%	50V
C223	1-163-031-11	CERAMIC CHIP 0.01MF		50V
C225	1-124-477-11	ELECT 47MF	20%	16V
C226	1-163-031-11	CERAMIC CHIP 0.01MF		50V
C227	1-163-038-00	CERAMIC CHIP 0.1MF		25V
C228	1-163-986-00	CERAMIC CHIP 0.027MF	10%	25V
C229	1-163-031-11	CERAMIC CHIP 0.01MF		50V
C230	1-163-038-00	CERAMIC CHIP 0.1MF		25V
C231	1-163-986-00	CERAMIC CHIP 0.027MF	10%	25V
C232	1-163-031-11	CERAMIC CHIP 0.01MF		50V
C233	1-163-031-11	CERAMIC CHIP 0.01MF		50V
C234	1-163-038-00	CERAMIC CHIP 0.1MF		25V
C235	1-163-986-00	CERAMIC CHIP 0.027MF	10%	25V
C236	1-163-031-11	CERAMIC CHIP 0.01MF		50V
C237	1-163-031-11	CERAMIC CHIP 0.01MF		50V
C238	1-164-299-11	CERAMIC CHIP 0.22MF	10%	25V
C239	1-163-809-11	CERAMIC CHIP 0.047MF	10%	25V
C240	1-163-809-11	CERAMIC CHIP 0.047MF	10%	25V
C241	1-163-809-11	CERAMIC CHIP 0.047MF	10%	25V
C242	1-163-113-00	CERAMIC CHIP 68PF	5%	50V
C243	1-163-031-11	CERAMIC CHIP 0.01MF		50V
C244	1-163-103-00	CERAMIC CHIP 27PF	5%	50V
C245	1-163-105-00	CERAMIC CHIP 33PF	5%	50V
C246	1-163-809-11	CERAMIC CHIP 0.047MF	10%	25V
C247	1-163-809-11	CERAMIC CHIP 0.047MF	10%	25V
C248	1-163-809-11	CERAMIC CHIP 0.047MF	10%	25V
C249	1-126-101-11	ELECT 100MF	20%	16V
C250	1-163-017-00	CERAMIC CHIP 0.0047MF	10%	50V
C251	1-110-364-11	MYLAR 0.1MF	10%	200V
C252	1-123-935-00	ELECT 33MF	20%	160V
C253	1-124-477-11	ELECT 47MF	20%	16V
C254	1-163-031-11	CERAMIC CHIP 0.01MF		50V
C255	1-124-477-11	ELECT 47MF	20%	16V
C256	1-163-129-00	CERAMIC CHIP 330PF	5%	50V
C257	1-163-129-00	CERAMIC CHIP 330PF	5%	50V
C258	1-163-129-00	CERAMIC CHIP 330PF	5%	50V

REF.NO.	PART NO.	DESCRIPTION		REMARK
C259	1-163-031-11	CERAMIC CHIP 0.01MF		50V
C260	1-124-465-00	ELECT 0.47MF	20%	50V
C261	1-137-193-11	FILM 0.39MF	5%	50V
C262	1-124-465-00	ELECT 0.47MF	20%	50V
C264	1-163-123-00	CERAMIC CHIP 180PF	5%	50V
C265	1-163-129-00	CERAMIC CHIP 330PF	5%	50V
C266	1-126-320-11	ELECT 10MF	20%	16V
C267	1-126-320-11	ELECT 10MF	20%	16V
C268	1-124-477-11	ELECT 47MF	20%	16V
C269	1-164-004-11	CERAMIC CHIP 0.1MF	10%	25V
C270	1-164-004-11	CERAMIC CHIP 0.1MF	10%	25V
C271	1-163-809-11	CERAMIC CHIP 0.047MF	10%	25V
C272	1-163-129-00	CERAMIC CHIP 330PF	5%	50V
C273	1-163-129-00	CERAMIC CHIP 330PF	5%	50V
C274	1-124-477-11	ELECT 47MF	20%	16V
C275	1-163-119-00	CERAMIC CHIP 120PF	5%	50V
C277	1-163-097-00	CERAMIC CHIP 15PF	5%	50V
C278	1-163-809-11	CERAMIC CHIP 0.047MF	10%	25V
C279	1-126-157-11	ELECT 10MF	20%	16V
C280	1-163-117-00	CERAMIC CHIP 100PF	5%	50V
C281	1-163-031-11	CERAMIC CHIP 0.01MF		50V
C282	1-163-031-11	CERAMIC CHIP 0.01MF		50V
C283	1-163-031-11	CERAMIC CHIP 0.01MF		50V
C299	1-163-031-11	CERAMIC CHIP 0.01MF		50V
C300	1-126-157-11	ELECT 10MF	20%	16V
C301	1-163-809-11	CERAMIC CHIP 0.047MF	10%	25V
C302	1-124-589-11	ELECT 47MF	20%	16V
C303	1-126-157-11	ELECT 10MF	20%	16V
C304	1-163-125-00	CERAMIC CHIP 220PF	5%	50V
C305	1-124-257-00	ELECT 2.2MF	20%	50V
C306	1-163-115-00	CERAMIC CHIP 82PF	5%	50V
C307	1-163-145-00	CERAMIC CHIP 0.0015MF	5%	50V
C308	1-164-004-11	CERAMIC CHIP 0.1MF	10%	25V
C309	1-164-004-11	CERAMIC CHIP 0.1MF	10%	25V
C310	1-164-004-11	CERAMIC CHIP 0.1MF	10%	25V
C312	1-163-031-11	CERAMIC CHIP 0.01MF		50V
C313	1-163-115-00	CERAMIC CHIP 82PF	5%	50V
C314	1-126-157-11	ELECT 10MF	20%	16V
C315	1-164-299-11	CERAMIC CHIP 0.22MF	10%	25V
C316	1-126-157-11	ELECT 10MF	20%	16V
C317	1-163-031-11	CERAMIC CHIP 0.01MF		50V
C318	1-163-095-00	CERAMIC CHIP 12PF	5%	50V
C319	1-163-095-00	CERAMIC CHIP 12PF	5%	50V
C320	1-163-095-00	CERAMIC CHIP 12PF	5%	50V
C321	1-163-121-00	CERAMIC CHIP 150PF	5%	50V
C322	1-163-121-00	CERAMIC CHIP 150PF	5%	50V
C324	1-163-121-00	CERAMIC CHIP 150PF	5%	50V
C340	1-163-205-00	CERAMIC CHIP 0.001MF	5%	50V
C344	1-163-092-00	CERAMIC CHIP 9PF	0.25PF	50V
C345	1-163-109-00	CERAMIC CHIP 47PF	5%	50V
C346	1-163-109-00	CERAMIC CHIP 47PF	5%	50V
C347	1-163-109-00	CERAMIC CHIP 47PF	5%	50V
C1293	1-163-119-00	CERAMIC CHIP 120PF	5%	50V
C1294	1-163-119-00	CERAMIC CHIP 120PF	5%	50V
C1295	1-163-119-00	CERAMIC CHIP 120PF	5%	50V
C1296	1-163-115-00	CERAMIC CHIP 82PF	5%	50V
C1297	1-163-103-00	CERAMIC CHIP 27PF	5%	50V
C1298	1-163-113-00	CERAMIC CHIP 68PF	5%	50V
C1299	1-163-093-00	CERAMIC CHIP 10PF	5%	50V
C1300	1-126-160-11	ELECT 1MF	20%	50V
C1301	1-126-160-11	ELECT 1MF	20%	50V
C1302	1-126-160-11	ELECT 1MF	20%	50V

B

REF.NO.	PART NO.	DESCRIPTION	REMARK
C1303	1-126-160-11	ELECT 1MF 20% 50V	
		<FILTER BLOCK>	
CFM101	1-464-880-11	FILTER BLOCK, COM (CFB-2)	
		<CONNECTOR>	
CN101	1-506-480-11	PIN, CONNECTOR 15P	
CN102	*1-564-506-11	PLUG, CONNECTOR 3P	
CN103	*1-565-503-11	CONNECTOR, BOARD TO BOARD 12P	
CN104	1-506-477-11	PIN, CONNECTOR 12P	
CN105	*1-564-509-11	PLUG, CONNECTOR 6P	
CN106	1-506-473-11	PIN, CONNECTOR 8P	
CN107	1-506-478-11	PIN, CONNECTOR 13P	
CN108	*1-564-506-11	PLUG, CONNECTOR 3P	
		<TRAP MODULE>	
CTR101	1-236-366-11	MODULE, TRAP	
CTR102	1-236-365-11	MODULE, TRAP	
		<TRIMMER>	
CV101	1-141-245-00	CAP, TRIMMER	
CV102	1-141-245-00	CAP, TRIMMER	
		<DIODE>	
D101	8-719-404-46	DIODE MA110	
D102	8-719-404-46	DIODE MA110	
D103	8-719-404-46	DIODE MA110	
D104	8-719-404-46	DIODE MA110	
D105	8-719-404-46	DIODE MA110	
D106	8-719-404-46	DIODE MA110	
D107	8-719-404-46	DIODE MA110	
D108	8-719-404-46	DIODE MA110	
D109	8-719-404-46	DIODE MA110	
D110	8-719-404-46	DIODE MA110	
D111	8-719-404-46	DIODE MA110	
D112	8-719-404-46	DIODE MA110	
D113	8-719-404-46	DIODE MA110	
D114	8-719-404-46	DIODE MA110	
D115	8-719-404-46	DIODE MA110	
D116	8-719-404-46	DIODE MA110	
D117	8-719-404-46	DIODE MA110	
D118	8-719-404-46	DIODE MA110	
D119	8-719-404-46	DIODE MA110	
D120	8-719-404-46	DIODE MA110	
D121	8-719-404-46	DIODE MA110	
D122	8-719-404-46	DIODE MA110	
D123	8-719-404-46	DIODE MA110	
D125	8-719-404-46	DIODE MA110	
D126	8-719-404-46	DIODE MA110	
D127	8-719-404-46	DIODE MA110	
D128	8-719-400-18	DIODE MA152WK	
D129	8-719-404-46	DIODE MA110	
D130	8-719-800-76	DIODE 1SS226	
D131	8-719-800-76	DIODE 1SS226	
D132	8-719-800-76	DIODE 1SS226	
D133	8-719-404-46	DIODE MA110	
D134	8-719-404-46	DIODE MA110	
D135	8-719-404-46	DIODE MA110	
D136	8-719-404-46	DIODE MA110	
D137	8-719-404-46	DIODE MA110	
D138	8-719-404-46	DIODE MA110	
D139	8-719-404-46	DIODE MA110	
D142	8-719-404-46	DIODE MA110	
D143	8-719-404-46	DIODE MA110	
D144	8-719-404-46	DIODE MA110	
D145	8-719-404-46	DIODE MA110	
D146	8-719-404-46	DIODE MA110	
D147	8-719-404-46	DIODE MA110	
D148	8-719-404-46	DIODE MA110	
D149	8-719-404-46	DIODE MA110	
D150	8-719-404-46	DIODE MA110	
D151	8-719-404-46	DIODE MA110	
D152	8-719-404-46	DIODE MA110	
D153	8-719-977-20	DIODE DTZ8.2B	
D154	8-719-404-46	DIODE MA110	
D155	8-719-404-46	DIODE MA110	
D156	8-719-404-46	DIODE MA110	
D157	8-719-901-83	DIODE 1SS83	
D158	8-719-901-83	DIODE 1SS83	
D159	8-719-901-83	DIODE 1SS83	
D160	8-719-404-46	DIODE MA110	
D161	8-719-404-46	DIODE MA110	
D162	8-719-404-46	DIODE MA110	
D170	8-719-404-46	DIODE MA110	
D171	8-719-404-46	DIODE MA110	
D172	8-719-404-46	DIODE MA110	
D285	8-719-404-46	DIODE MA110	
D289	8-719-404-46	DIODE MA110	
D341	8-719-404-46	DIODE MA110	
D342	8-719-104-34	DIODE 1S2836	
D343	8-719-800-76	DIODE 1SS226	
D344	8-719-105-XX	DIODE RD6.2M-B1	
D345	8-719-901-83	DIODE 1SS83	
D346	8-719-901-83	DIODE 1SS83	
D347	8-719-901-83	DIODE 1SS83	
D348	8-719-800-76	DIODE 1SS226	
D349	8-719-800-76	DIODE 1SS226	
D350	8-719-800-76	DIODE 1SS226	
D393	8-719-404-46	DIODE MA110	
		<DELAY LINE>	
DL101	1-415-632-11	DELAY LINE, Y	
DL102	1-415-633-11	DELAY LINE, Y	
		<IC>	
IC101	8-759-048-09	IC MM1148XF	
IC102	8-759-501-21	IC MM1149XF	
IC103	8-759-501-21	IC MM1149XF	
IC104	8-759-501-21	IC MM1149XF	
IC105	8-759-048-09	IC MM1148XF	
IC106	8-759-009-51	IC MC14538BF	
IC107	8-759-509-57	IC XRU4584BF	
IC108	8-759-509-17	IC XRU4053BF	
IC109	8-759-509-37	IC XRU4070BF	
IC110	8-759-509-17	IC XRU4053BF	
IC111	8-759-509-17	IC XRU4053BF	
IC112	8-759-924-12	IC LM7805CT	

REF.NO.	PART NO.	DESCRIPTION	REMARK
IC113	8-759-631-08	IC M51279FP	
IC114	8-759-509-13	IC XRU4052BF	
IC115	8-759-509-13	IC XRU4052BF	
IC116	8-759-509-05	IC XRU4066BF	
IC117	8-759-711-32	IC NJM2245M	
IC118	8-759-711-32	IC NJM2245M	
IC119	8-759-711-32	IC NJM2245M	
IC120	8-759-509-05	IC XRU4066BF	
IC121	8-759-509-17	IC XRU4053BF	
IC122	8-759-998-98	IC LM358D	
IC123	8-759-998-98	IC LM358D	
IC124	8-752-052-62	IC CXA1478S	
IC125	8-759-509-05	IC XRU4066BF	
IC126	8-759-509-17	IC XRU4053BF	
IC127	8-759-998-98	IC LM358D	
IC128	8-759-998-98	IC LM358D	
IC129	8-759-998-98	IC LM358D	
		<COIL>	
L101	1-410-470-11	INDUCTOR 10UH	
L102	1-410-090-41	INDUCTOR 18MMH	
L103	1-412-002-31	INDUCTOR CHIP 4.7UH	
L104	1-412-002-31	INDUCTOR CHIP 4.7UH	
L105	1-412-002-31	INDUCTOR CHIP 4.7UH	
L106	1-410-470-11	INDUCTOR 10UH	
L107	1-410-470-11	INDUCTOR 10UH	
L108	1-408-418-00	INDUCTOR 56UH	
L109	1-408-418-00	INDUCTOR 56UH	
L110	1-408-418-00	INDUCTOR 56UH	
L112	1-408-419-00	INDUCTOR 68UH	
L113	1-410-947-31	INDUCTOR CHIP 33UH	
L114	1-410-947-31	INDUCTOR CHIP 33UH	
L115	1-410-947-31	INDUCTOR CHIP 33UH	
L116	1-412-011-31	INDUCTOR CHIP 27UH	
L117	1-412-011-31	INDUCTOR CHIP 27UH	
L118	1-412-011-31	INDUCTOR CHIP 27UH	
L250	1-410-997-31	INDUCTOR CHIP 2.2UH	
L251	1-410-999-11	INDUCTOR CHIP 3.3UH	
L252	1-410-478-11	INDUCTOR 47UH	
L300	1-410-482-31	INDUCTOR 100UH	
		<TRANSISTOR>	
Q101	8-729-920-74	TRANSISTOR 2SC2412K-QR	
Q102	8-729-920-74	TRANSISTOR 2SC2412K-QR	
Q103	8-729-920-74	TRANSISTOR 2SC2412K-QR	
Q104	8-729-920-74	TRANSISTOR 2SC2412K-QR	
Q105	8-729-920-74	TRANSISTOR 2SC2412K-QR	
Q106	8-729-920-74	TRANSISTOR 2SC2412K-QR	
Q107	8-729-920-74	TRANSISTOR 2SC2412K-QR	
Q108	8-729-216-22	TRANSISTOR 2SA1162-G	
Q109	8-729-901-01	TRANSISTOR DTC144EK	
Q112	8-729-920-74	TRANSISTOR 2SC2412K-QR	
Q113	8-729-920-74	TRANSISTOR 2SC2412K-QR	
Q114	8-729-216-22	TRANSISTOR 2SA1162-G	
Q115	8-729-920-74	TRANSISTOR 2SC2412K-QR	
Q116	8-729-920-74	TRANSISTOR 2SC2412K-QR	
Q117	8-729-216-22	TRANSISTOR 2SA1162-G	
Q118	8-729-920-74	TRANSISTOR 2SC2412K-QR	
Q119	8-729-216-22	TRANSISTOR 2SA1162-G	
Q120	8-729-216-22	TRANSISTOR 2SA1162-G	
Q121	8-729-920-74	TRANSISTOR 2SC2412K-QR	
Q122	8-729-216-22	TRANSISTOR 2SA1162-G	
Q123	8-729-920-74	TRANSISTOR 2SC2412K-QR	
Q124	8-729-216-22	TRANSISTOR 2SA1162-G	
Q125	8-729-920-74	TRANSISTOR 2SC2412K-QR	
Q126	8-729-901-01	TRANSISTOR DTC144EK	
Q127	8-729-216-22	TRANSISTOR 2SA1162-G	
Q128	8-729-216-22	TRANSISTOR 2SA1162-G	
Q129	8-729-901-01	TRANSISTOR DTC144EK	
Q130	8-729-216-22	TRANSISTOR 2SA1162-G	
Q131	8-729-920-74	TRANSISTOR 2SC2412K-QR	
Q132	8-729-216-22	TRANSISTOR 2SA1162-G	
Q133	8-729-920-74	TRANSISTOR 2SC2412K-QR	
Q134	8-729-901-01	TRANSISTOR DTC144EK	
Q135	8-729-920-74	TRANSISTOR 2SC2412K-QR	
Q136	8-729-907-26	TRANSISTOR IMX1	
Q137	8-729-907-26	TRANSISTOR IMX1	
Q138	8-729-907-26	TRANSISTOR IMX1	
Q139	8-729-216-22	TRANSISTOR 2SA1162-G	
Q140	8-729-920-74	TRANSISTOR 2SC2412K-QR	
Q141	8-729-920-74	TRANSISTOR 2SC2412K-QR	
Q142	8-729-920-74	TRANSISTOR 2SC2412K-QR	
Q143	8-729-920-74	TRANSISTOR 2SC2412K-QR	
Q144	8-729-920-74	TRANSISTOR 2SC2412K-QR	
Q145	8-729-920-74	TRANSISTOR 2SC2412K-QR	
Q146	8-729-255-12	TRANSISTOR 2SC2551-O	
Q147	8-729-255-12	TRANSISTOR 2SC2551-O	
Q148	8-729-216-22	TRANSISTOR 2SA1162-G	
Q149	8-729-200-17	TRANSISTOR 2SA1091-O2	
Q150	8-729-920-74	TRANSISTOR 2SC2412K-QR	
Q151	8-729-216-22	TRANSISTOR 2SA1162-G	
Q152	8-729-200-17	TRANSISTOR 2SA1091-O2	
Q153	8-729-920-74	TRANSISTOR 2SC2412K-QR	
Q154	8-729-216-22	TRANSISTOR 2SA1162-G	
Q155	8-729-200-17	TRANSISTOR 2SA1091-O2	
Q157	8-729-326-11	TRANSISTOR 2SC2611	
Q158	8-729-326-11	TRANSISTOR 2SC2611	
Q159	8-729-326-11	TRANSISTOR 2SC2611	
Q160	8-729-920-74	TRANSISTOR 2SC2412K-QR	
Q161	8-729-216-22	TRANSISTOR 2SA1162-G	
Q162	8-729-920-74	TRANSISTOR 2SC2412K-QR	
Q163	8-729-920-74	TRANSISTOR 2SC2412K-QR	
Q164	8-729-901-01	TRANSISTOR DTC144EK	
Q165	8-729-216-22	TRANSISTOR 2SA1162-G	
Q166	8-729-216-22	TRANSISTOR 2SA1162-G	
Q167	8-729-216-22	TRANSISTOR 2SA1162-G	
Q168	8-729-216-22	TRANSISTOR 2SA1162-G	
Q170	8-729-920-74	TRANSISTOR 2SC2412K-QR	
Q171	8-729-920-74	TRANSISTOR 2SC2412K-QR	
Q172	8-729-920-74	TRANSISTOR 2SC2412K-QR	
Q173	8-729-216-22	TRANSISTOR 2SA1162-G	
Q174	8-729-216-22	TRANSISTOR 2SA1162-G	
Q175	8-729-216-22	TRANSISTOR 2SA1162-G	
Q176	8-729-216-22	TRANSISTOR 2SA1162-G	
Q177	8-729-920-74	TRANSISTOR 2SC2412K-QR	
Q178	8-729-920-74	TRANSISTOR 2SC2412K-QR	
Q179	8-729-901-01	TRANSISTOR DTC144EK	
Q190	8-729-216-22	TRANSISTOR 2SA1162-G	
Q191	8-729-920-74	TRANSISTOR 2SC2412K-QR	
Q192	8-729-920-74	TRANSISTOR 2SC2412K-QR	
Q193	8-729-920-74	TRANSISTOR 2SC2412K-QR	
Q194	8-729-920-74	TRANSISTOR 2SC2412K-QR	
Q195	8-729-216-22	TRANSISTOR 2SA1162-G	
Q196	8-729-920-74	TRANSISTOR 2SC2412K-QR	
Q197	8-729-216-22	TRANSISTOR 2SA1162-G	

B

REF.NO.	PART NO.	DESCRIPTION	REMARK
Q198	8-729-216-22	TRANSISTOR 2SA1162-G	
Q199	8-729-216-22	TRANSISTOR 2SA1162-G	
Q200	8-729-901-06	TRANSISTOR DTA144EK	
Q201	8-729-216-22	TRANSISTOR 2SA1162-G	
Q202	8-729-216-22	TRANSISTOR 2SA1162-G	
Q203	8-729-216-22	TRANSISTOR 2SA1162-G	
Q204	8-729-216-22	TRANSISTOR 2SA1162-G	
Q205	8-729-216-22	TRANSISTOR 2SA1162-G	
Q206	8-729-216-22	TRANSISTOR 2SA1162-G	
Q208	8-729-216-22	TRANSISTOR 2SA1162-G	
Q209	8-729-255-12	TRANSISTOR 2SC2551-O	
Q210	8-729-255-12	TRANSISTOR 2SC2551-O	
Q211	8-729-255-12	TRANSISTOR 2SC2551-O	
Q212	8-729-109-44	TRANSISTOR 2SK94-X4	
Q299	8-729-920-74	TRANSISTOR 2SC2412K-QR	
		<RESISTOR>	
JR105	1-216-295-00	METAL GLAZE 0 5% 1/10W	
JR110	1-216-295-00	METAL GLAZE 0 5% 1/10W	
JR118	1-216-295-00	METAL GLAZE 0 5% 1/10W	
JR133	1-216-295-00	METAL GLAZE 0 5% 1/10W	
JR138	1-216-295-00	METAL GLAZE 0 5% 1/10W	
JR178	1-216-295-00	METAL GLAZE 0 5% 1/10W	
R101	1-216-089-00	METAL GLAZE 47K 5% 1/10W	
R102	1-216-025-00	METAL GLAZE 100 5% 1/10W	
R103	1-216-091-00	METAL GLAZE 56K 5% 1/10W	
R104	1-216-061-00	METAL GLAZE 3.3K 5% 1/10W	
R105	1-216-025-00	METAL GLAZE 100 5% 1/10W	
R106	1-216-065-00	METAL GLAZE 4.7K 5% 1/10W	
R107	1-216-025-00	METAL GLAZE 100 5% 1/10W	
R108	1-216-113-00	METAL GLAZE 470K 5% 1/10W	
R109	1-216-065-00	METAL GLAZE 4.7K 5% 1/10W	
R110	1-216-049-00	METAL GLAZE 1K 5% 1/10W	
R111	1-216-063-00	METAL GLAZE 3.9K 5% 1/10W	
R112	1-216-049-00	METAL GLAZE 1K 5% 1/10W	
R113	1-249-401-11	CARBON 47 5% 1/4W	F
R114	1-216-045-00	METAL GLAZE 680 5% 1/10W	
R115	1-216-061-00	METAL GLAZE 3.3K 5% 1/10W	
R117	1-216-073-00	METAL GLAZE 10K 5% 1/10W	
R118	1-216-025-00	METAL GLAZE 100 5% 1/10W	
R119	1-216-647-11	METAL CHIP 680 0.50% 1/10W	
R120	1-216-647-11	METAL CHIP 680 0.50% 1/10W	
R121	1-216-025-00	METAL GLAZE 100 5% 1/10W	
R122	1-216-083-00	METAL GLAZE 27K 5% 1/10W	
R123	1-216-073-00	METAL GLAZE 10K 5% 1/10W	
R124	1-216-073-00	METAL GLAZE 10K 5% 1/10W	
R125	1-216-083-00	METAL GLAZE 27K 5% 1/10W	
R126	1-216-093-00	METAL GLAZE 68K 5% 1/10W	
R127	1-216-037-00	METAL GLAZE 330 5% 1/10W	
R128	1-216-083-00	METAL GLAZE 27K 5% 1/10W	
R129	1-216-067-00	METAL GLAZE 5.6K 5% 1/10W	
R130	1-216-097-00	METAL GLAZE 100K 5% 1/10W	
R131	1-216-089-00	METAL GLAZE 47K 5% 1/10W	
R132	1-216-057-00	METAL GLAZE 2.2K 5% 1/10W	
R133	1-216-079-00	METAL GLAZE 18K 5% 1/10W	
R134	1-216-645-11	METAL CHIP 560 0.50% 1/10W	
R135	1-216-645-11	METAL CHIP 560 0.50% 1/10W	
R136	1-216-091-00	METAL GLAZE 56K 5% 1/10W	
R137	1-216-045-00	METAL GLAZE 680 5% 1/10W	
R138	1-216-657-11	METAL CHIP 1.8K 0.50% 1/10W	
R139	1-216-079-00	METAL GLAZE 18K 5% 1/10W	
R140	1-216-653-11	METAL CHIP 1.2K 0.50% 1/10W	
R141	1-216-063-00	METAL GLAZE 3.9K 5% 1/10W	
R142	1-216-073-00	METAL GLAZE 10K 5% 1/10W	
R143	1-216-085-00	METAL GLAZE 33K 5% 1/10W	
R145	1-216-065-00	METAL GLAZE 4.7K 5% 1/10W	
R146	1-216-037-00	METAL GLAZE 330 5% 1/10W	
R147	1-216-089-00	METAL GLAZE 47K 5% 1/10W	
R148	1-216-671-11	METAL CHIP 6.8K 0.50% 1/10W	
R155	1-216-655-11	METAL CHIP 1.5K 0.50% 1/10W	
R157	1-216-679-11	METAL CHIP 15K 0.50% 1/10W	
R158	1-216-677-11	METAL CHIP 12K 0.50% 1/10W	
R160	1-216-065-00	METAL GLAZE 4.7K 5% 1/10W	
R161	1-216-089-00	METAL GLAZE 47K 5% 1/10W	
R163	1-216-073-00	METAL GLAZE 10K 5% 1/10W	
R164	1-216-677-11	METAL CHIP 12K 0.50% 1/10W	
R165	1-216-107-00	METAL GLAZE 270K 5% 1/10W	
R166	1-216-681-11	METAL CHIP 18K 0.50% 1/10W	
R167	1-216-635-11	METAL CHIP 220 0.50% 1/10W	
R168	1-216-103-00	METAL GLAZE 180K 5% 1/10W	
R169	1-216-033-00	METAL GLAZE 220 5% 1/10W	
R170	1-216-089-00	METAL GLAZE 47K 5% 1/10W	
R171	1-216-053-00	METAL GLAZE 1.5K 5% 1/10W	
R172	1-216-043-00	METAL GLAZE 560 5% 1/10W	
R173	1-216-093-00	METAL GLAZE 68K 5% 1/10W	
R174	1-216-069-00	METAL GLAZE 6.8K 5% 1/10W	
R175	1-216-057-00	METAL GLAZE 2.2K 5% 1/10W	
R176	1-216-065-00	METAL GLAZE 4.7K 5% 1/10W	
R177	1-216-073-00	METAL GLAZE 10K 5% 1/10W	
R178	1-216-089-00	METAL GLAZE 47K 5% 1/10W	
R179	1-216-081-00	METAL GLAZE 22K 5% 1/10W	
R180	1-216-679-11	METAL CHIP 15K 0.50% 1/10W	
R181	1-216-071-00	METAL GLAZE 8.2K 5% 1/10W	
R182	1-216-683-11	METAL CHIP 22K 0.50% 1/10W	
R183	1-216-691-11	METAL CHIP 47K 0.50% 1/10W	
R184	1-216-699-11	METAL CHIP 100K 0.50% 1/10W	
R185	1-216-073-00	METAL GLAZE 10K 5% 1/10W	
R186	1-216-113-00	METAL GLAZE 470K 5% 1/10W	
R187	1-216-073-00	METAL GLAZE 10K 5% 1/10W	
R188	1-216-113-00	METAL GLAZE 470K 5% 1/10W	
R189	1-216-103-00	METAL GLAZE 180K 5% 1/10W	
R190	1-216-107-00	METAL GLAZE 270K 5% 1/10W	
R191	1-216-097-00	METAL GLAZE 100K 5% 1/10W	
R192	1-216-103-00	METAL GLAZE 180K 5% 1/10W	
R193	1-216-105-00	METAL GLAZE 220K 5% 1/10W	
R194	1-216-089-00	METAL GLAZE 47K 5% 1/10W	
R195	1-216-113-00	METAL GLAZE 470K 5% 1/10W	
R196	1-216-073-00	METAL GLAZE 10K 5% 1/10W	
R197	1-216-671-11	METAL CHIP 6.8K 0.50% 1/10W	
R198	1-216-049-00	METAL GLAZE 1K 5% 1/10W	
R199	1-216-065-00	METAL GLAZE 4.7K 5% 1/10W	
R200	1-216-065-00	METAL GLAZE 4.7K 5% 1/10W	
R201	1-216-043-00	METAL GLAZE 560 5% 1/10W	
R202	1-216-033-00	METAL GLAZE 220 5% 1/10W	
R203	1-216-045-00	METAL GLAZE 680 5% 1/10W	
R204	1-216-073-00	METAL GLAZE 10K 5% 1/10W	
R205	1-216-073-00	METAL GLAZE 10K 5% 1/10W	
R206	1-216-043-00	METAL GLAZE 560 5% 1/10W	
R207	1-216-045-00	METAL GLAZE 680 5% 1/10W	
R208	1-216-671-11	METAL CHIP 6.8K 0.50% 1/10W	
R209	1-216-043-00	METAL GLAZE 560 5% 1/10W	
R210	1-216-033-00	METAL GLAZE 220 5% 1/10W	
R211	1-216-099-00	METAL GLAZE 120K 5% 1/10W	
R212	1-216-065-00	METAL GLAZE 4.7K 5% 1/10W	
R213	1-216-043-00	METAL GLAZE 560 5% 1/10W	

REF.NO.	PART NO.	DESCRIPTION				REMARK
R214	1-216-043-00	METAL GLAZE	560	5%	1/10W	
R215	1-216-125-00	METAL GLAZE	1.5M	5%	1/10W	
R216	1-216-043-00	METAL GLAZE	560	5%	1/10W	
R217	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R218	1-216-295-00	METAL GLAZE	0	5%	1/10W	
R219	1-216-043-00	METAL GLAZE	560	5%	1/10W	
R220	1-216-043-00	METAL GLAZE	560	5%	1/10W	
R221	1-216-035-00	METAL GLAZE	270	5%	1/10W	
R222	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R223	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R224	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R225	1-216-095-00	METAL GLAZE	82K	5%	1/10W	
R226	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R227	1-216-035-00	METAL GLAZE	270	5%	1/10W	
R228	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R229	1-216-113-00	METAL GLAZE	470K	5%	1/10W	
R230	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R231	1-216-113-00	METAL GLAZE	470K	5%	1/10W	
R232	1-216-105-00	METAL GLAZE	220K	5%	1/10W	
R233	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R234	1-216-041-00	METAL GLAZE	470	5%	1/10W	
R235	1-216-041-00	METAL GLAZE	470	5%	1/10W	
R236	1-216-077-00	METAL GLAZE	15K	5%	1/10W	
R237	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R238	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R239	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R240	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R241	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R242	1-216-051-00	METAL GLAZE	1.2K	5%	1/10W	
R243	1-216-113-00	METAL GLAZE	470K	5%	1/10W	
R244	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R245	1-216-679-11	METAL CHIP	15K	0.50%	1/10W	
R246	1-216-103-00	METAL GLAZE	180K	5%	1/10W	
R247	1-216-093-00	METAL GLAZE	68K	5%	1/10W	
R248	1-216-095-00	METAL GLAZE	82K	5%	1/10W	
R249	1-216-109-00	METAL GLAZE	330K	5%	1/10W	
R250	1-216-101-00	METAL GLAZE	150K	5%	1/10W	
R251	1-216-105-00	METAL GLAZE	220K	5%	1/10W	
R252	1-216-101-00	METAL GLAZE	150K	5%	1/10W	
R253	1-216-101-00	METAL GLAZE	150K	5%	1/10W	
R254	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R255	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R256	1-216-107-00	METAL GLAZE	270K	5%	1/10W	
R258	1-216-041-00	METAL GLAZE	470	5%	1/10W	
R259	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R260	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R261	1-216-035-00	METAL GLAZE	270	5%	1/10W	
R262	1-216-097-00	METAL GLAZE	100K	5%	1/10W	
R263	1-216-029-00	METAL GLAZE	150	5%	1/10W	
R264	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R265	1-216-067-00	METAL GLAZE	5.6K	5%	1/10W	
R266	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R267	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R268	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R269	1-216-101-00	METAL GLAZE	150K	5%	1/10W	
R270	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R271	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R272	1-216-101-00	METAL GLAZE	150K	5%	1/10W	
R273	1-216-113-00	METAL GLAZE	470K	5%	1/10W	
R275	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R276	1-216-037-00	METAL GLAZE	330	5%	1/10W	
R277	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R278	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W	
R279	1-216-037-00	METAL GLAZE	330	5%	1/10W	
R280	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R281	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R282	1-216-037-00	METAL GLAZE	330	5%	1/10W	
R283	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R284	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W	
R285	1-216-037-00	METAL GLAZE	330	5%	1/10W	
R286	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R287	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R288	1-216-037-00	METAL GLAZE	330	5%	1/10W	
R289	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R290	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W	
R291	1-216-037-00	METAL GLAZE	330	5%	1/10W	
R292	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R293	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R295	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W	
R296	1-216-659-11	METAL CHIP	2.2K	0.50%	1/10W	
R297	1-216-659-11	METAL CHIP	2.2K	0.50%	1/10W	
R298	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R300	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R301	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R302	1-216-113-00	METAL GLAZE	470K	5%	1/10W	
R303	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R304	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R305	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R306	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R307	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R308	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R309	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R310	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R311	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R312	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R313	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R314	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R315	1-216-113-00	METAL GLAZE	470K	5%	1/10W	
R316	1-216-105-00	METAL GLAZE	220K	5%	1/10W	
R317	1-216-109-00	METAL GLAZE	330K	5%	1/10W	
R318	1-216-105-00	METAL GLAZE	220K	5%	1/10W	
R319	1-216-099-00	METAL GLAZE	120K	5%	1/10W	
R320	1-216-099-00	METAL GLAZE	120K	5%	1/10W	
R321	1-216-043-00	METAL GLAZE	560	5%	1/10W	
R322	1-216-109-00	METAL GLAZE	330K	5%	1/10W	
R323	1-216-109-00	METAL GLAZE	330K	5%	1/10W	
R324	1-216-109-00	METAL GLAZE	330K	5%	1/10W	
R325	1-216-097-00	METAL GLAZE	100K	5%	1/10W	
R326	1-216-113-00	METAL GLAZE	470K	5%	1/10W	
R328	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R329	1-216-107-00	METAL GLAZE	270K	5%	1/10W	
R330	1-216-105-00	METAL GLAZE	220K	5%	1/10W	
R331	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R332	1-216-097-00	METAL GLAZE	100K	5%	1/10W	
R333	1-216-097-00	METAL GLAZE	100K	5%	1/10W	
R334	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R335	1-216-099-00	METAL GLAZE	120K	5%	1/10W	
R336	1-216-095-00	METAL GLAZE	82K	5%	1/10W	
R337	1-216-105-00	METAL GLAZE	220K	5%	1/10W	
R338	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R339	1-216-099-00	METAL GLAZE	120K	5%	1/10W	
R340	1-216-095-00	METAL GLAZE	82K	5%	1/10W	
R341	1-216-105-00	METAL GLAZE	220K	5%	1/10W	
R342	1-216-047-00	METAL GLAZE	820	5%	1/10W	
R343	1-216-053-00	METAL GLAZE	1.5K	5%	1/10W	

B

REF.NO.	PART NO.	DESCRIPTION				REMARK
R344	1-216-664-11	METAL CHIP	3.6K	0.50%	1/10W	
R345	1-216-661-11	METAL CHIP	2.7K	0.50%	1/10W	
R346	1-216-105-00	METAL GLAZE	220K	5%	1/10W	
R348	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R349	1-216-650-11	METAL CHIP	910	0.50%	1/10W	
R350	1-216-653-11	METAL CHIP	1.2K	0.50%	1/10W	
R351	1-216-650-11	METAL CHIP	910	0.50%	1/10W	
R352	1-216-653-11	METAL CHIP	1.2K	0.50%	1/10W	
R353	1-216-650-11	METAL CHIP	910	0.50%	1/10W	
R354	1-216-653-11	METAL CHIP	1.2K	0.50%	1/10W	
R355	1-216-113-00	METAL GLAZE	470K	5%	1/10W	
R356	1-216-113-00	METAL GLAZE	470K	5%	1/10W	
R357	1-216-095-00	METAL GLAZE	82K	5%	1/10W	
R358	1-216-113-00	METAL GLAZE	470K	5%	1/10W	
R359	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R360	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R363	1-216-069-00	METAL GLAZE	6.8K	5%	1/10W	
R364	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R365	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R366	1-216-244-00	METAL GLAZE	82K	5%	1/8W	
R367	1-216-244-00	METAL GLAZE	82K	5%	1/8W	
R368	1-216-055-00	METAL GLAZE	1.8K	5%	1/10W	
R369	1-216-248-00	METAL GLAZE	120K	5%	1/8W	
R370	1-216-115-00	METAL GLAZE	560K	5%	1/10W	
R371	1-216-067-00	METAL GLAZE	5.6K	5%	1/10W	
R372	1-216-115-00	METAL GLAZE	560K	5%	1/10W	
R374	1-216-115-00	METAL GLAZE	560K	5%	1/10W	
R375	1-216-683-11	METAL CHIP	22K	0.50%	1/10W	
R376	1-216-663-11	METAL CHIP	3.3K	0.50%	1/10W	
R378	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R379	1-216-641-11	METAL CHIP	390	0.50%	1/10W	
R380	1-216-668-11	METAL CHIP	5.1K	0.50%	1/10W	
R381	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R382	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R383	1-216-641-11	METAL CHIP	390	0.50%	1/10W	
R384	1-216-668-11	METAL CHIP	5.1K	0.50%	1/10W	
R385	1-216-117-00	METAL GLAZE	680K	5%	1/10W	
R386	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R387	1-216-641-11	METAL CHIP	390	0.50%	1/10W	
R388	1-216-668-11	METAL CHIP	5.1K	0.50%	1/10W	
R390	1-216-105-00	METAL GLAZE	220K	5%	1/10W	
R391	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R392	1-216-113-00	METAL GLAZE	470K	5%	1/10W	
R393	1-216-085-00	METAL GLAZE	33K	5%	1/10W	
R394	1-216-113-00	METAL GLAZE	470K	5%	1/10W	
R397	1-249-437-11	CARBON	47K	5%	1/4W	F
R398	1-249-434-11	CARBON	27K	5%	1/4W	F
R399	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1001	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1002	1-216-047-00	METAL GLAZE	820	5%	1/10W	
R1003	1-216-055-00	METAL GLAZE	1.8K	5%	1/10W	
R1004	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R1005	1-216-047-00	METAL GLAZE	820	5%	1/10W	
R1006	1-216-055-00	METAL GLAZE	1.8K	5%	1/10W	
R1007	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R1008	1-216-047-00	METAL GLAZE	820	5%	1/10W	
R1009	1-216-055-00	METAL GLAZE	1.8K	5%	1/10W	
R1010	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R1011	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R1012	1-216-051-00	METAL GLAZE	1.2K	5%	1/10W	
R1013	1-216-051-00	METAL GLAZE	1.2K	5%	1/10W	
R1014	1-216-246-00	METAL GLAZE	100K	5%	1/8W	
R1015	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R1016	1-216-089-00	METAL GLAZE	47K	5%	1/10W	

REF.NO.	PART NO.	DESCRIPTION				REMARK
R1017	1-216-045-00	METAL GLAZE	680	5%	1/10W	
R1018	1-216-043-00	METAL GLAZE	560	5%	1/10W	
R1019	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R1020	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R1021	1-216-045-00	METAL GLAZE	680	5%	1/10W	
R1022	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R1023	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1024	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R1025	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R1026	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R1027	1-216-101-00	METAL GLAZE	150K	5%	1/10W	
R1028	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R1029	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R1030	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R1031	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R1032	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R1033	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R1035	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1036	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R1038	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R1040	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R1042	1-216-047-00	METAL GLAZE	820	5%	1/10W	
R1043	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W	
R1044	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R1045	1-216-125-00	METAL GLAZE	1.5M	5%	1/10W	
R1046	1-216-689-11	METAL CHIP	39K	0.50%	1/10W	
R1047	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R1048	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R1049	1-216-085-00	METAL GLAZE	33K	5%	1/10W	
R1050	1-216-059-00	METAL GLAZE	2.7K	5%	1/10W	
R1051	1-216-105-00	METAL GLAZE	220K	5%	1/10W	
R1053	1-216-091-00	METAL GLAZE	56K	5%	1/10W	
R1054	1-216-093-00	METAL GLAZE	68K	5%	1/10W	
R1055	1-216-097-00	METAL GLAZE	100K	5%	1/10W	
R1056	1-216-037-00	METAL GLAZE	330	5%	1/10W	
R1057	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R1058	1-216-109-00	METAL GLAZE	330K	5%	1/10W	
R1059	1-216-109-00	METAL GLAZE	330K	5%	1/10W	
R1060	1-216-109-00	METAL GLAZE	330K	5%	1/10W	
R1061	1-216-109-00	METAL GLAZE	330K	5%	1/10W	
R1062	1-216-103-00	METAL GLAZE	180K	5%	1/10W	
R1063	1-216-103-00	METAL GLAZE	180K	5%	1/10W	
R1064	1-216-103-00	METAL GLAZE	180K	5%	1/10W	
R1065	1-216-103-00	METAL GLAZE	180K	5%	1/10W	
R1066	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1067	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1068	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R1069	1-216-133-00	METAL GLAZE	3.3M	5%	1/10W	
R1070	1-216-085-00	METAL GLAZE	33K	5%	1/10W	
R1071	1-216-113-00	METAL GLAZE	470K	5%	1/10W	
R1072	1-216-099-00	METAL GLAZE	120K	5%	1/10W	
R1073	1-216-131-11	METAL GLAZE	2.7M	5%	1/10W	
R1075	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R1076	1-216-101-00	METAL GLAZE	150K	5%	1/10W	
R1077	1-216-103-00	METAL GLAZE	180K	5%	1/10W	
R1079	1-216-131-11	METAL GLAZE	2.7M	5%	1/10W	
R1080	1-216-097-00	METAL GLAZE	100K	5%	1/10W	
R1081	1-216-097-00	METAL GLAZE	100K	5%	1/10W	
R1082	1-216-105-00	METAL GLAZE	220K	5%	1/10W	
R1083	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R1084	1-216-063-00	METAL GLAZE	3.9K	5%	1/10W	
R1086	1-216-073-00	METAL GLAZE	10K	5%	1/10W	

REF.NO.	PART NO.	DESCRIPTION				REMARK
R1087	1-216-121-00	METAL GLAZE	1M	5%	1/10W	
R1088	1-216-047-00	METAL GLAZE	820	5%	1/10W	
R1090	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R1091	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R1092	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R1093	1-216-121-00	METAL GLAZE	1M	5%	1/10W	
R1094	1-216-075-00	METAL GLAZE	12K	5%	1/10W	
R1095	1-216-075-00	METAL GLAZE	12K	5%	1/10W	
R1096	1-216-075-00	METAL GLAZE	12K	5%	1/10W	
R1200	1-216-699-11	METAL CHIP	100K	0.50%	1/10W	
R1201	1-218-754-11	METAL CHIP	120K	0.50%	1/10W	
R1207	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R1208	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R1220	1-216-055-00	METAL GLAZE	1.8K	5%	1/10W	
R1221	1-216-055-00	METAL GLAZE	1.8K	5%	1/10W	
R1222	1-216-055-00	METAL GLAZE	1.8K	5%	1/10W	
R1223	1-216-087-11	METAL GLAZE	39K	5%	1/10W	
R1225	1-215-876-00	METAL OXIDE	15K	5%	1W	F
R1226	1-215-876-00	METAL OXIDE	15K	5%	1W	F
R1227	1-215-876-00	METAL OXIDE	15K	5%	1W	F
R1228	1-249-421-11	CARBON	2.2K	5%	1/4W	F
R1229	1-249-421-11	CARBON	2.2K	5%	1/4W	F
R1230	1-249-421-11	CARBON	2.2K	5%	1/4W	F
R1231	1-216-029-00	METAL GLAZE	150	5%	1/10W	
R1232	1-216-029-00	METAL GLAZE	150	5%	1/10W	
R1233	1-216-029-00	METAL GLAZE	150	5%	1/10W	
R1234	1-216-029-00	METAL GLAZE	150	5%	1/10W	
R1235	1-216-029-00	METAL GLAZE	150	5%	1/10W	
R1236	1-216-029-00	METAL GLAZE	150	5%	1/10W	
R1237	1-249-419-11	CARBON	1.5K	5%	1/4W	F
R1238	1-249-419-11	CARBON	1.5K	5%	1/4W	F
R1239	1-249-419-11	CARBON	1.5K	5%	1/4W	F
R1270	1-216-079-00	METAL GLAZE	18K	5%	1/10W	
R1271	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W	
R1280	1-216-109-00	METAL GLAZE	330K	5%	1/10W	
R1290	1-216-071-00	METAL GLAZE	8.2K	5%	1/10W	
R1291	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R1294	1-216-069-00	METAL GLAZE	6.8K	5%	1/10W	
R1295	1-216-109-00	METAL GLAZE	330K	5%	1/10W	
R1296	1-216-095-00	METAL GLAZE	82K	5%	1/10W	
R1297	1-216-071-00	METAL GLAZE	8.2K	5%	1/10W	
R1298	1-216-071-00	METAL GLAZE	8.2K	5%	1/10W	
R1299	1-216-071-00	METAL GLAZE	8.2K	5%	1/10W	
R1300	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R1301	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R1302	1-216-113-00	METAL GLAZE	470K	5%	1/10W	
R1303	1-216-113-00	METAL GLAZE	470K	5%	1/10W	
R1304	1-216-091-00	METAL GLAZE	56K	5%	1/10W	
R1305	1-216-093-00	METAL GLAZE	68K	5%	1/10W	
R1306	1-216-063-00	METAL GLAZE	3.9K	5%	1/10W	
R1307	1-216-041-00	METAL GLAZE	470	5%	1/10W	
R1308	1-216-041-00	METAL GLAZE	470	5%	1/10W	
R1309	1-216-063-00	METAL GLAZE	3.9K	5%	1/10W	
R1310	1-216-119-00	METAL GLAZE	820K	5%	1/10W	
R1313	1-216-101-00	METAL GLAZE	150K	5%	1/10W	
R1314	1-216-053-00	METAL GLAZE	1.5K	5%	1/10W	
R1315	1-216-077-00	METAL GLAZE	15K	5%	1/10W	
R1320	1-216-083-00	METAL GLAZE	27K	5%	1/10W	
R1321	1-216-093-00	METAL GLAZE	68K	5%	1/10W	
R1322	1-216-037-00	METAL GLAZE	330	5%	1/10W	
R1323	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W	
R1324	1-216-121-00	METAL GLAZE	1M	5%	1/10W	
R1325	1-216-085-00	METAL GLAZE	33K	5%	1/10W	
R1326	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R1327	1-216-099-00	METAL GLAZE	120K	5%	1/10W	
R1328	1-216-099-00	METAL GLAZE	120K	5%	1/10W	
R1329	1-216-093-00	METAL GLAZE	68K	5%	1/10W	
R1330	1-216-063-00	METAL GLAZE	3.9K	5%	1/10W	
R1331	1-216-051-00	METAL GLAZE	1.2K	5%	1/10W	
R1332	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W	
R1333	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W	
R1334	1-216-055-00	METAL GLAZE	1.8K	5%	1/10W	
R1335	1-216-035-00	METAL GLAZE	270	5%	1/10W	
R1336	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R1337	1-216-113-00	METAL GLAZE	470K	5%	1/10W	
R1338	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R1339	1-216-097-00	METAL GLAZE	100K	5%	1/10W	
R1340	1-216-097-00	METAL GLAZE	100K	5%	1/10W	
R1341	1-216-111-00	METAL GLAZE	390K	5%	1/10W	
R1342	1-216-694-11	METAL CHIP	62K	0.50%	1/10W	
R1343	1-216-121-00	METAL GLAZE	1M	5%	1/10W	
R1344	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1345	1-216-055-00	METAL GLAZE	1.8K	5%	1/10W	
R1346	1-216-047-00	METAL GLAZE	820	5%	1/10W	
R1347	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1348	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1349	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1350	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1351	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1352	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1353	1-216-115-00	METAL GLAZE	560K	5%	1/10W	
R1371	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W	
R1372	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W	
R1373	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W	
R1392	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R1393	1-216-095-00	METAL GLAZE	82K	5%	1/10W	

<VARIABLE RESISTOR>

RV101	1-241-763-11	RES, ADJ, CERMET 4.7K
RV102	1-241-763-11	RES, ADJ, CERMET 4.7K
RV103	1-238-009-11	RES, ADJ, CARBON 220
RV104	1-238-009-11	RES, ADJ, CARBON 220
RV105	1-238-012-11	RES, ADJ, CARBON 1K
RV106	1-238-012-11	RES, ADJ, CARBON 1K
RV107	1-238-012-11	RES, ADJ, CARBON 1K
RV108	1-238-016-11	RES, ADJ, CARBON 10K
RV109	1-241-703-11	RES, ADJ, CERMET 22K
RV110	1-238-016-11	RES, ADJ, CARBON 10K
RV111	1-238-016-11	RES, ADJ, CARBON 10K
RV112	1-238-019-11	RES, ADJ, CARBON 47K
RV113	1-238-019-11	RES, ADJ, CARBON 47K
RV114	1-238-019-11	RES, ADJ, CARBON 47K
RV115	1-238-017-11	RES, ADJ, CARBON 22K
RV116	1-238-017-11	RES, ADJ, CARBON 22K
RV118	1-238-017-11	RES, ADJ, CARBON 22K
RV119	1-238-017-11	RES, ADJ, CARBON 22K
RV120	1-238-017-11	RES, ADJ, CARBON 22K
RV121	1-238-017-11	RES, ADJ, CARBON 22K
RV122	1-238-017-11	RES, ADJ, CARBON 22K
RV123	1-238-013-11	RES, ADJ, CARBON 2.2K
RV124	1-238-012-11	RES, ADJ, CARBON 1K
RV125	1-238-012-11	RES, ADJ, CARBON 1K
RV205	1-238-017-11	RES, ADJ, CARBON 22K

B P FA

The components identified by shading and mark ⚠ are critical for safety.
Replace only with part number specified.

REF.NO.	PART NO.	DESCRIPTION				REMARK
		<MODULE>				
SEP101	1-808-654-11	MODULE				
		<CRYSTAL>				
X101	1-527-722-00	OSCILLATOR, CRYSTAL				
X102	1-577-259-11	VIBRATOR, CRYSTAL				
**********						
	*A-1195-048-A	P BOARD, COMPLETE				
		**********				
		<CAPACITOR>				
C801	1-126-104-11	ELECT	470MF	20%	35V	
C802	1-162-318-11	CERAMIC	0.001MF	10%	500V	
C803	1-102-228-00	CERAMIC	470PF	10%	500V	
C804	1-123-935-00	ELECT	33MF	20%	160V	
C805	1-101-004-00	CERAMIC	0.01MF		50V	
C806	1-124-480-11	ELECT	470MF	20%	25V	
C807	1-102-228-00	CERAMIC	470PF	10%	500V	
C808	1-106-367-00	MYLAR	0.01MF	10%	100V	
C809	1-106-375-12	MYLAR	0.022MF	10%	100V	
C810	1-162-318-11	CERAMIC	0.001MF	10%	500V	
C811 ⚠	1-137-544-11	FILM	0.01MF	3%	600V	
C812 ⚠	1-137-545-11	FILM	0.013MF	3%	600V	
C813	1-106-385-00	MYLAR	0.056MF	5%	200V	
C814	1-106-383-00	MYLAR	0.047MF	10%	100V	
C815	1-126-233-11	ELECT	22MF	20%	50V	
C816	1-124-798-11	ELECT	1MF	20%	160V	
C817	1-130-800-00	FILM	2.2MF	10%	250V	
C818	1-102-228-00	CERAMIC	470PF	10%	500V	
C819	1-162-116-00	CERAMIC	680PF	10%	2KV	
C820	1-162-116-00	CERAMIC	680PF	10%	2KV	
		<CONNECTOR>				
CN801	*1-564-595-11	PLUG, CONNECTOR 14P				
CN802	*1-508-766-00	PIN, CONNECTOR (5MM PITCH) 4P				
CN803	*1-564-508-11	PLUG, CONNECTOR 5P				
CN805	*1-560-123-00	PLUG, CONNECTOR (2.5MM) 3P				
		<DIODE>				
D801	8-719-300-33	DIODE RU-3AM				
D802	8-719-300-33	DIODE RU-3AM				
D803	8-719-300-33	DIODE RU-3AM				
D804	8-719-979-85	DIODE EGP-20G				
D805	8-719-300-33	DIODE RU-3AM				
D806	8-719-300-33	DIODE RU-3AM				
D807	8-719-105-XX	DIODE RD6.2M-B1				
D808	8-719-008-28	THYRISTOR CR02AM-4TB				
D809	8-719-911-55	DIODE U05G				
D810	8-719-911-55	DIODE U05G				
D811	8-719-911-55	DIODE U05G				
D813	8-719-300-33	DIODE RU-3AM				
		<COIL>				
L802	1-459-442-00	COIL (WITH CORE)				
L803	1-422-613-11	COIL, AIR CORE				
L804	1-459-109-00	COIL,DUST CORE				
L805 ⚠	1-460-225-11	COIL, HORIZONTAL LINEARITY				
L806	1-407-500-00	INDUCTOR	4.7MMH			
L807	1-407-500-00	INDUCTOR	4.7MMH			
		<NEON LAMP>				
NL801	1-519-108-XX	LAMP, NEON				
		<TRANSISTOR>				
Q801	8-729-195-82	TRANSISTOR 2SC2958				
Q802	8-729-201-62	TRANSISTOR 2SC2555				
	*4-363-404-00	HOLDER, IC; Q802				
	4-382-854-01	SCREW (M3X8), P, SW (+); Q802				
	4-879-937-00	SHEET, MICA; Q802				
Q803	8-729-906-24	TRANSISTOR 2SD835				
		<RESISTOR>				
R801	1-249-383-11	CARBON	1.5	5%	1/4W	F
R802	1-249-377-11	CARBON	0.47	5%	1/4W	F
R803	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R804	1-249-419-11	CARBON	1.5K	5%	1/4W	F
R805	1-215-892-11	METAL OXIDE	1K	5%	2W	F
R807	1-216-425-11	METAL OXIDE	56	5%	1W	F
R808	1-202-846-00	SOLID	470K	20%	1/2W	
R809	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R810	1-249-421-11	CARBON	2.2K	5%	1/4W	F
R811	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R812	1-249-439-11	CARBON	68K	5%	1/4W	F
R813	1-249-414-11	CARBON	560	5%	1/4W	F
R814	1-249-377-11	CARBON	0.47	5%	1/4W	F
		<VARIABLE RESISTOR>				
RV801	1-223-102-00	RES, ADJ, WIREWOUND 120				
		<TRANSFORMER>				
T801	1-437-082-31	HDT				
T802 ⚠	1-439-526-11	TRANSFORMER ASSY, FLYBACK				
**********						
	*1-641-723-11	FA BOARD				
		********				
	1-533-223-11	CLIP, FUSE				
	*4-341-751-01	EYELET	EY6, EY7			
	*4-341-752-01	EYELET	EY1, EY3, EY8, EY9			
		<CONNECTOR>				
CN601	*1-580-689-11	PIN, CONNECTOR (PC BOARD) 4P				
CN602	*1-508-765-00	PIN, CONNECTOR (5MM PITCH) 3P				
CN603	1-564-507-11	PLUG, CONNECTOR 4P				
		<FUSE>				
F601 ⚠	1-576-230-11	FUSE (H.B.C.) (3.15A/250V)				
		<RESISTOR>				
R602	1-202-721-00	SOLID	1.5M	20%	1/2W	
		<SWITCH>				
S601 ⚠	1-692-050-11	SWITCH, PUSH (AC POWER) (1KEY)				
**********						

QA

The components identified by shading and mark ⚠ are critical for safety.
Replace only with part number specified.

REF.NO.	PART NO.	DESCRIPTION			REMARK
	A-1275-099-A	QA BOARD, COMPLETE			
		**********			
	1-537-408-11	TERMINAL BOARD, IN/OUT (LINE B)			
⚠	1-537-410-11	TERMINAL BOARD, IN/OUT (LINE A)& AC INLET			
	*4-341-752-01	EYELET EY10, EY11			
		<CAPACITOR>			
C401	1-124-234-00	ELECT	22MF	20%	16V
C402	1-124-234-00	ELECT	22MF	20%	16V
C403	1-124-234-00	ELECT	22MF	20%	16V
C404	1-124-234-00	ELECT	22MF	20%	16V
C405	1-124-234-00	ELECT	22MF	20%	16V
C406	1-124-234-00	ELECT	22MF	20%	16V
C407	1-124-234-00	ELECT	22MF	20%	16V
C408	1-124-463-00	ELECT	0.1MF	20%	50V
C409	1-124-234-00	ELECT	22MF	20%	16V
C410	1-124-234-00	ELECT	22MF	20%	16V
C411	1-124-234-00	ELECT	22MF	20%	16V
C412	1-124-234-00	ELECT	22MF	20%	16V
C413	1-124-234-00	ELECT	22MF	20%	16V
C414	1-126-157-11	ELECT	10MF	20%	16V
C415	1-126-157-11	ELECT	10MF	20%	16V
C416	1-126-157-11	ELECT	10MF	20%	16V
C417	1-126-157-11	ELECT	10MF	20%	16V
C418	1-126-157-11	ELECT	10MF	20%	16V
C419	1-126-157-11	ELECT	10MF	20%	16V
C420	1-126-157-11	ELECT	10MF	20%	16V
C421	1-102-125-00	CERAMIC	0.0047MF	10%	50V
C422	1-124-464-11	ELECT	0.22MF	20%	50V
C423	1-126-157-11	ELECT	10MF	20%	16V
C424	1-126-157-11	ELECT	10MF	20%	16V
C425	1-108-634-11	MYLAR	0.047MF	10%	100V
C426	1-128-499-11	ELECT	220MF	20%	16V
C427	1-128-499-11	ELECT	220MF	20%	16V
C428	1-124-589-11	ELECT	47MF	20%	16V
C429	1-124-234-00	ELECT	22MF	20%	16V
C430	1-163-033-00	CERAMIC CHIP	0.022MF		50V
C431	1-124-234-00	ELECT	22MF	20%	16V
C432	1-163-033-00	CERAMIC CHIP	0.022MF		50V
C433	1-124-234-00	ELECT	22MF	20%	16V
C434	1-163-033-00	CERAMIC CHIP	0.022MF		50V
C435	1-124-234-00	ELECT	22MF	20%	16V
C436	1-163-033-00	CERAMIC CHIP	0.022MF		50V
C437	1-163-033-00	CERAMIC CHIP	0.022MF		50V
C438	1-124-234-00	ELECT	22MF	20%	16V
C439	1-163-033-00	CERAMIC CHIP	0.022MF		50V
C440	1-163-033-00	CERAMIC CHIP	0.022MF		50V
C441	1-124-234-00	ELECT	22MF	20%	16V
C442	1-163-033-00	CERAMIC CHIP	0.022MF		50V
C443	1-163-033-00	CERAMIC CHIP	0.022MF		50V
C444	1-163-033-00	CERAMIC CHIP	0.022MF		50V
C445	1-163-031-11	CERAMIC CHIP	0.01MF		50V
C446	1-163-031-11	CERAMIC CHIP	0.01MF		50V
C447	1-126-301-11	ELECT	1MF	20%	50V
C448	1-124-234-00	ELECT	22MF	20%	16V
C449	1-163-031-11	CERAMIC CHIP	0.01MF		50V
C450	1-124-234-00	ELECT	22MF	20%	16V
C451	1-163-033-00	CERAMIC CHIP	0.022MF		50V
C452	1-128-499-11	ELECT	220MF	20%	16V
C453	1-124-234-00	ELECT	22MF	20%	16V
C454	1-128-499-11	ELECT	220MF	20%	16V
C460	1-126-301-11	ELECT	1MF	20%	50V
C461	1-126-301-11	ELECT	1MF	20%	50V
C462	1-126-301-11	ELECT	1MF	20%	50V
C464	1-163-031-11	CERAMIC CHIP	0.01MF		50V
C465	1-163-031-11	CERAMIC CHIP	0.01MF		50V
C466	1-163-031-11	CERAMIC CHIP	0.01MF		50V
C467	1-163-031-11	CERAMIC CHIP	0.01MF		50V
		<CONNECTOR>			
CN401	1-506-494-11	PIN, CONNECTOR 15P			
CN402	*1-564-518-11	PLUG, CONNECTOR 3P			
CN403	*1-580-690-11	PIN, CONNECTOR (PC BOARD) 4P			
CN404	*1-564-519-11	PLUG, CONNECTOR 4P			
		<DIODE>			
D401	8-719-404-46	DIODE MA110			
D402	8-719-404-46	DIODE MA110			
D403	8-719-110-09	DIODE RD8.2ES-B3			
D404	8-719-404-46	DIODE MA110			
D405	8-719-404-46	DIODE MA110			
D406	8-719-404-46	DIODE MA110			
D407	8-719-404-46	DIODE MA110			
D408	8-719-404-46	DIODE MA110			
D409	8-719-404-46	DIODE MA110			
D410	8-719-404-46	DIODE MA110			
D411	8-719-404-46	DIODE MA110			
D412	8-719-404-46	DIODE MA110			
D413	8-719-404-46	DIODE MA110			
D414	8-719-404-46	DIODE MA110			
D415	8-719-404-46	DIODE MA110			
D416	8-719-404-46	DIODE MA110			
D417	8-719-404-46	DIODE MA110			
D418	8-719-404-46	DIODE MA110			
D419	8-719-404-46	DIODE MA110			
D420	8-719-404-46	DIODE MA110			
D421	8-719-404-46	DIODE MA110			
D422	8-719-404-46	DIODE MA110			
D423	8-719-404-46	DIODE MA110			
D424	8-719-404-46	DIODE MA110			
D425	8-719-404-46	DIODE MA110			
D426	8-719-404-46	DIODE MA110			
D427	8-719-404-46	DIODE MA110			
D428	8-719-404-46	DIODE MA110			
D429	8-719-404-46	DIODE MA110			
D430	8-719-404-46	DIODE MA110			
D431	8-719-404-46	DIODE MA110			
		<IC>			
IC401	8-759-501-21	IC MM1149XF			
IC402	8-759-501-21	IC MM1149XF			
IC403	8-759-420-04	IC AN5265			
		<COIL>			
L401	1-410-682-31	INDUCTOR	470UH		
L402	1-410-682-31	INDUCTOR	470UH		

QA

<TRANSISTOR>

REF.NO.	PART NO.	DESCRIPTION	REMARK
Q401	8-729-920-74	TRANSISTOR 2SC2412K-QR	
Q402	8-729-920-74	TRANSISTOR 2SC2412K-QR	
Q403	8-729-216-22	TRANSISTOR 2SA1162-G	
Q404	8-729-920-74	TRANSISTOR 2SC2412K-QR	
Q405	8-729-920-74	TRANSISTOR 2SC2412K-QR	
Q406	8-729-920-74	TRANSISTOR 2SC2412K-QR	
Q407	8-729-920-74	TRANSISTOR 2SC2412K-QR	
Q408	8-729-920-74	TRANSISTOR 2SC2412K-QR	
Q409	8-729-920-74	TRANSISTOR 2SC2412K-QR	
Q410	8-729-920-74	TRANSISTOR 2SC2412K-QR	
Q411	8-729-216-22	TRANSISTOR 2SA1162-G	
Q412	8-729-216-22	TRANSISTOR 2SA1162-G	
Q413	8-729-216-22	TRANSISTOR 2SA1162-G	
Q414	8-729-216-22	TRANSISTOR 2SA1162-G	
Q416	8-729-145-18	TRANSISTOR 2SC3736	
Q417	8-729-901-06	TRANSISTOR DTA144EK	
Q418	8-729-901-06	TRANSISTOR DTA144EK	
Q419	8-729-901-06	TRANSISTOR DTA144EK	
Q420	8-729-901-01	TRANSISTOR DTC144EK	
Q421	8-729-901-06	TRANSISTOR DTA144EK	
Q422	8-729-901-01	TRANSISTOR DTC144EK	
Q423	8-729-901-06	TRANSISTOR DTA144EK	
Q424	8-729-901-06	TRANSISTOR DTA144EK	

<RESISTOR>

REF.NO.	PART NO.	DESCRIPTION				REMARK
R401	1-214-702-00	METAL	75	1%	1/4W	
R402	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R403	1-216-093-00	METAL GLAZE	68K	5%	1/10W	
R404	1-216-091-00	METAL GLAZE	56K	5%	1/10W	
R405	1-216-063-00	METAL GLAZE	3.9K	5%	1/10W	
R406	1-216-037-00	METAL GLAZE	330	5%	1/10W	
R407	1-216-087-11	METAL GLAZE	39K	5%	1/10W	
R408	1-216-085-00	METAL GLAZE	33K	5%	1/10W	
R409	1-214-702-00	METAL	75	1%	1/4W	
R410	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R411	1-216-093-00	METAL GLAZE	68K	5%	1/10W	
R412	1-216-091-00	METAL GLAZE	56K	5%	1/10W	
R413	1-216-063-00	METAL GLAZE	3.9K	5%	1/10W	
R414	1-216-037-00	METAL GLAZE	330	5%	1/10W	
R415	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R416	1-216-023-00	METAL GLAZE	82	5%	1/10W	
R417	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R418	1-216-093-00	METAL GLAZE	68K	5%	1/10W	
R419	1-216-091-00	METAL GLAZE	56K	5%	1/10W	
R420	1-216-063-00	METAL GLAZE	3.9K	5%	1/10W	
R421	1-216-027-00	METAL GLAZE	120	5%	1/10W	
R422	1-214-702-00	METAL	75	1%	1/4W	
R423	1-214-702-00	METAL	75	1%	1/4W	
R424	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R425	1-216-093-00	METAL GLAZE	68K	5%	1/10W	
R426	1-216-091-00	METAL GLAZE	56K	5%	1/10W	
R427	1-216-063-00	METAL GLAZE	3.9K	5%	1/10W	
R428	1-216-037-00	METAL GLAZE	330	5%	1/10W	
R429	1-214-702-00	METAL	75	1%	1/4W	
R430	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R431	1-216-093-00	METAL GLAZE	68K	5%	1/10W	
R432	1-216-091-00	METAL GLAZE	56K	5%	1/10W	
R433	1-216-063-00	METAL GLAZE	3.9K	5%	1/10W	
R434	1-216-027-00	METAL GLAZE	120	5%	1/10W	
R435	1-214-702-00	METAL	75	1%	1/4W	
R436	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R437	1-216-093-00	METAL GLAZE	68K	5%	1/10W	
R438	1-216-091-00	METAL GLAZE	56K	5%	1/10W	
R439	1-216-063-00	METAL GLAZE	3.9K	5%	1/10W	
R440	1-216-027-00	METAL GLAZE	120	5%	1/10W	
R441	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R442	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R443	1-216-087-11	METAL GLAZE	39K	5%	1/10W	
R444	1-214-702-00	METAL	75	1%	1/4W	
R445	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R446	1-216-093-00	METAL GLAZE	68K	5%	1/10W	
R447	1-216-091-00	METAL GLAZE	56K	5%	1/10W	
R448	1-216-063-00	METAL GLAZE	3.9K	5%	1/10W	
R449	1-216-027-00	METAL GLAZE	120	5%	1/10W	
R450	1-214-702-00	METAL	75	1%	1/4W	
R451	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R452	1-216-091-00	METAL GLAZE	56K	5%	1/10W	
R453	1-216-093-00	METAL GLAZE	68K	5%	1/10W	
R454	1-216-063-00	METAL GLAZE	3.9K	5%	1/10W	
R455	1-216-037-00	METAL GLAZE	330	5%	1/10W	
R456	1-216-085-00	METAL GLAZE	33K	5%	1/10W	
R457	1-216-085-00	METAL GLAZE	33K	5%	1/10W	
R458	1-247-707-11	CARBON	390	5%	1/4W	
R459	1-216-087-11	METAL GLAZE	39K	5%	1/10W	
R460	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R461	1-216-097-00	METAL GLAZE	100K	5%	1/10W	
R462	1-216-115-00	METAL GLAZE	560K	5%	1/10W	
R463	1-216-105-00	METAL GLAZE	220K	5%	1/10W	
R464	1-216-077-00	METAL GLAZE	15K	5%	1/10W	
R465	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R466	1-216-097-00	METAL GLAZE	100K	5%	1/10W	
R467	1-216-115-00	METAL GLAZE	560K	5%	1/10W	
R468	1-216-105-00	METAL GLAZE	220K	5%	1/10W	
R469	1-216-077-00	METAL GLAZE	15K	5%	1/10W	
R470	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R471	1-216-097-00	METAL GLAZE	100K	5%	1/10W	
R472	1-216-115-00	METAL GLAZE	560K	5%	1/10W	
R473	1-216-105-00	METAL GLAZE	220K	5%	1/10W	
R474	1-216-077-00	METAL GLAZE	15K	5%	1/10W	
R475	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R477	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R479	1-216-085-00	METAL GLAZE	33K	5%	1/10W	
R480	1-247-711-11	CARBON	680	5%	1/4W	
R481	1-247-720-11	CARBON	3.9K	5%	1/4W	
R482	1-249-455-11	CARBON	4.7	5%	1/4W	
R483	1-249-389-11	CARBON	4.7	5%	1/4W	F
R484	1-216-041-00	METAL GLAZE	470	5%	1/10W	
R485	1-247-688-11	CARBON	10	5%	1/4W	F
R486	1-216-037-00	METAL GLAZE	330	5%	1/10W	
R487	1-249-468-11	CARBON	82K	5%	1/4W	
R488	1-249-468-11	CARBON	82K	5%	1/4W	
R489	1-249-468-11	CARBON	82K	5%	1/4W	
R490	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W	
R491	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R492	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R493	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R494	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R495	1-216-295-00	METAL GLAZE	0	5%	1/10W	
R496	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W	
R497	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R498	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R499	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R1401	1-216-097-00	METAL GLAZE	100K	5%	1/10W	
R1403	1-216-295-00	METAL GLAZE	0	5%	1/10W	
R1404	1-216-097-00	METAL GLAZE	100K	5%	1/10W	

QA CA D

REF.NO.	PART NO.	DESCRIPTION			REMARK
		<VARIABLE RESISTOR>			
RV401	1-230-481-11	RES, VAR, CARBON 20K			
		**********			
	*1-641-720-11	CA BOARD			
		********			
	1-526-958-41	SOCKET, PICTURE TUBE			
		<CAPACITOR>			
C701	1-162-114-00	CERAMIC	0.0047MF	10%	2KV
C702	1-102-050-00	CERAMIC	0.01MF	99%	500V
C710	1-161-830-00	CERAMIC	0.0047MF	99%	500V
		<CONNECTOR>			
CN701	*1-564-509-11	PLUG, CONNECTOR 6P			
CN702	*1-508-784-00	PIN, CONNECTOR (5MM PITCH) 1P			
CN703	*1-564-508-11	PLUG, CONNECTOR 5P			
		<COIL>			
L701	1-410-668-11	INDUCTOR	27UH		
		<RESISTOR>			
R701	1-202-822-00	SOLID	2.2K	20%	1/2W
R702	1-202-822-00	SOLID	2.2K	20%	1/2W
R703	1-202-822-00	SOLID	2.2K	20%	1/2W
R704	1-202-838-00	SOLID	100K	20%	1/2W
R705	1-202-719-00	SOLID	1M	20%	1/2W
R706	1-202-842-11	SOLID	220K	20%	1/2W
		<VARIABLE RESISTOR>			
RV701	1-230-164-00	RES, ADJ, METAL GLAZE 55M			
	*4-376-132-11	COVER (REAR LID), CV VOL; RV701			
	*4-376-133-11	COVER (MAIN), CV VOL; RV701			
		**********			
	A-1346-018-A	D BOARD, COMPLETE			
		**********			
	1-533-189-11	HOLDER, FUSE			
	3-710-578-01	COVER, VOLUME, 6 MOLD			
	*3-738-015-01	COVER, (DIA. 6) CARBON VR			
	4-382-854-01	SCREW (M3X8), P, SW (+)			
	4-382-854-11	SCREW (M3X10), P, SW (+)			
		<CAPACITOR>			
C501	1-124-477-11	ELECT	47MF	20%	16V
C502	1-124-907-11	ELECT	10MF	20%	50V
C503	1-126-103-11	ELECT	470MF	20%	16V
C504	1-124-902-00	ELECT	0.47MF	20%	50V
C505	1-106-381-12	MYLAR	0.039MF	10%	100V
C506	1-124-903-11	ELECT	1MF	20%	50V
C507	1-106-367-00	MYLAR	0.01MF	10%	100V
C508	1-124-903-11	ELECT	1MF	20%	50V
C509	1-136-173-00	FILM	0.47MF	5%	50V
C510	1-136-161-00	FILM	0.047MF	5%	50V
C511	1-124-903-11	ELECT	1MF	20%	50V

REF.NO.	PART NO.	DESCRIPTION			REMARK
C512	1-106-375-12	MYLAR	0.022MF	10%	100V
C513	1-106-375-12	MYLAR	0.022MF	10%	100V
C514	1-106-371-00	MYLAR	0.015MF	10%	100V
C515	1-124-925-11	ELECT	2.2MF	20%	50V
C516	1-124-925-11	ELECT	2.2MF	20%	50V
C517	1-130-480-00	FILM	0.0056MF	5%	50V
C518	1-163-245-11	CERAMIC CHIP	56PF	5%	50V
C519	1-124-927-11	ELECT	4.7MF	20%	50V
C520	1-163-129-00	CERAMIC CHIP	330PF	5%	50V
C521	1-124-907-11	ELECT	10MF	20%	50V
C523	1-106-363-00	MYLAR	0.0068MF	10%	100V
C524	1-102-116-00	CERAMIC	680PF	10%	50V
C525	1-102-820-00	CERAMIC	330PF	5%	50V
C526	1-102-973-00	CERAMIC	100PF	5%	50V
C527	1-124-122-11	ELECT	100MF	20%	50V
C528	1-102-125-00	CERAMIC	0.0047MF	10%	50V
C529	1-124-910-11	ELECT	47MF	20%	50V
C530	1-163-097-00	CERAMIC CHIP	15PF	5%	50V
C531	1-131-370-00	TANTALUM	6.8MF	10%	16V
C532	1-124-557-11	ELECT	1000MF	20%	25V
C533	1-124-927-11	ELECT	4.7MF	20%	50V
C534	1-124-768-11	ELECT	4.7MF	20%	50V
C535	1-136-161-00	FILM	0.047MF	5%	50V
C536	1-124-927-11	ELECT	4.7MF	20%	50V
C537	1-124-484-11	ELECT	220MF	20%	35V
C538	1-124-910-11	ELECT	47MF	20%	50V
C539	1-136-113-00	FILM	2MF	5%	200V
C540	1-163-017-00	CERAMIC CHIP	0.0047MF	10%	50V
C541	1-163-035-00	CERAMIC CHIP	0.047MF		50V
C542	1-126-103-11	ELECT	470MF	20%	16V
C545	1-126-101-11	ELECT	100MF	20%	16V
C546	1-124-907-11	ELECT	10MF	20%	50V
C547	1-124-907-11	ELECT	10MF	20%	50V
C548	1-124-907-11	ELECT	10MF	20%	50V
C549	1-124-907-11	ELECT	10MF	20%	50V
C550	1-124-907-11	ELECT	10MF	20%	50V
C551	1-124-927-11	ELECT	4.7MF	20%	50V
C552	1-101-004-00	CERAMIC	0.01MF		50V
C553	1-126-103-11	ELECT	470MF	20%	16V
C563	1-106-383-00	MYLAR	0.047MF	10%	100V
C564	1-163-009-11	CERAMIC CHIP	0.001MF	10%	50V
C567	1-124-907-11	ELECT	10MF	20%	50V
C568	1-130-736-11	FILM	0.01MF	5%	50V
C569	1-130-471-00	FILM	0.001MF	5%	50V
C570	1-163-117-00	CERAMIC CHIP	100PF	5%	50V
C571	1-124-913-11	ELECT	470MF	20%	50V
C572	1-101-004-00	CERAMIC	0.01MF		50V
C574	1-106-351-00	MYLAR	0.0022MF	10%	100V
C575	1-106-351-00	MYLAR	0.0022MF	10%	100V
C831	1-124-907-11	ELECT	10MF	20%	50V
C832	1-124-907-11	ELECT	10MF	20%	50V
C833	1-163-009-11	CERAMIC CHIP	0.001MF	10%	50V
C834	1-163-121-00	CERAMIC CHIP	150PF	5%	50V
C835	1-163-209-00	CERAMIC CHIP	0.0015MF	5%	50V
C836	1-124-907-11	ELECT	10MF	20%	50V
C837	1-163-209-00	CERAMIC CHIP	0.0015MF	5%	50V
C838	1-136-163-00	FILM	0.068MF	5%	50V
C839	1-106-351-00	MYLAR	0.0022MF	10%	100V
C840	1-163-209-00	CERAMIC CHIP	0.0015MF	5%	50V
C841	1-163-209-00	CERAMIC CHIP	0.0015MF	5%	50V
C843	1-124-902-00	ELECT	0.47MF	20%	50V
C844	1-124-902-00	ELECT	0.47MF	20%	50V
C845	1-124-477-11	ELECT	47MF	20%	25V
C846	1-124-907-11	ELECT	10MF	20%	50V

D

The components identified by shading and mark ⚠ are critical for safety.
Replace only with part number specified.

REF.NO.	PART NO.	DESCRIPTION			REMARK
C847	1-126-233-11	ELECT	22MF	20%	50V
C848	1-131-351-00	TANTALUM	4.7MF	10%	35V
C849	1-164-182-11	CERAMIC CHIP	0.0033MF	10%	50V
C1601	1-124-907-11	ELECT	10MF	20%	50V
C1602	1-164-161-11	CERAMIC CHIP	0.0022MF	10%	50V
C1603	1-124-903-11	ELECT	1MF	20%	50V
C1604	1-128-500-51	ELECT	1000MF	20%	50V
C1605	1-124-922-11	ELECT	1000MF	20%	50V
C1606	1-102-074-00	CERAMIC	0.001MF	10%	50V
C1607	1-124-907-11	ELECT	10MF	20%	50V
C1608	1-126-233-11	ELECT	22MF	20%	50V
C1609	1-163-009-11	CERAMIC CHIP	0.001MF	10%	50V
C1610	1-124-927-11	ELECT	4.7MF	20%	50V
C1611	1-124-482-11	ELECT	33MF	20%	35V
C1612	1-136-257-00	FILM	0.0039MF	5%	50V
C1613	1-163-009-11	CERAMIC CHIP	0.001MF	10%	50V
C1614	1-164-232-11	CERAMIC CHIP	0.01MF	10%	50V
C1615	1-124-465-00	ELECT	0.47MF	20%	50V
C1620	1-163-133-00	CERAMIC CHIP	470PF	5%	50V
C1621	1-163-117-00	CERAMIC CHIP	100PF	5%	50V

<CONNECTOR>

CN501	*1-564-506-11	PLUG, CONNECTOR 3P	
CN502	1-506-477-11	PIN, CONNECTOR 12P	
CN504	*1-564-507-11	PLUG, CONNECTOR 4P	
CN505	*1-564-509-11	PLUG, CONNECTOR 6P	
CN507	*1-564-511-11	PLUG, CONNECTOR 8P	
CN508	*1-564-104-00	PIN, CONNECTOR (B3P-VH) 3P	
CN509	*1-564-506-11	PLUG, CONNECTOR 3P	

<DIODE>

D501	8-719-404-46	DIODE MA110
D502	8-719-404-46	DIODE MA110
D503	8-719-404-46	DIODE MA110
D504	8-719-404-46	DIODE MA110
D505	8-719-404-46	DIODE MA110
D506	8-719-911-55	DIODE U05G
D507	8-719-404-46	DIODE MA110
D508	8-719-404-46	DIODE MA110
D509	8-719-404-46	DIODE MA110
D510	8-719-404-46	DIODE MA110
D511	8-719-404-46	DIODE MA110
D512	8-719-404-46	DIODE MA110
D514	8-719-404-46	DIODE MA110
D831	8-719-404-46	DIODE MA110
D832	8-719-404-46	DIODE MA110
D833	8-719-404-46	DIODE MA110
D834	8-719-404-46	DIODE MA110
D835	8-719-109-89	DIODE RD5.6ES-B2
D836	8-719-977-69	DIODE DTZ24B
D837	8-719-404-46	DIODE MA110
D838	8-719-404-46	DIODE MA110
D1601	8-719-105-XX	DIODE RD6.2M-B1
D1602	8-719-404-46	DIODE MA110
D1603	8-719-977-61	DIODE DTZ20B
D1604	8-719-404-46	DIODE MA110
D1605	8-719-404-46	DIODE MA110
D1606	8-719-981-00	DIODE ERC81-004
D1607	8-719-981-00	DIODE ERC81-004
D1608	8-719-977-02	DIODE DTZ5.6A
D1609	8-719-977-49	DIODE DTZ15B
D1610	8-719-404-46	DIODE MA110
D1611	8-729-101-31	TRANSISTOR N13T1
D1612	8-719-404-46	DIODE MA110
D1613	8-719-404-46	DIODE MA110
D1614	8-719-404-46	DIODE MA110
D1615	8-719-404-46	DIODE MA110
D1616	8-719-404-46	DIODE MA110
D1617	8-719-977-49	DIODE DTZ15B
D1618	8-719-977-49	DIODE DTZ15B
D1621	8-719-510-12	DIODE D10SC4M
D1625	8-719-404-46	DIODE MA110
D1626	8-719-404-46	DIODE MA110
D1627	8-719-404-46	DIODE MA110
D1628	8-719-404-46	DIODE MA110
D1635	8-719-404-46	DIODE MA110
D1699	8-719-404-46	DIODE MA110

<FUSE>

F1601 ⚠	1-532-777-21	FUSE, MICRO (SECONDARY) (1.25A/125V)
F1602 ⚠	1-576-232-11	FUSE (H.B.C.) (5.0A/250V)

<IC>

IC501	8-759-909-70	IC CX23025
IC502	8-759-100-60	IC UPC1377C
IC503	8-759-801-98	IC LA7830
IC504	8-759-929-62	IC MC7812CT
IC505	8-759-009-51	IC MC14538BF
IC831	8-759-509-29	IC XRU4011BF
IC832	8-759-509-37	IC XRU4070BF
IC833	8-759-009-51	IC MC14538BF
IC1601	8-759-509-91	IC XRA10393F

<COIL>

L501	1-410-093-11	INDUCTOR 33MMH
L502	1-410-665-31	INDUCTOR 15UH
L503	1-424-625-11	COIL, CHOKE (PMC) 381.4UH
L506	1-412-530-31	INDUCTOR 27UH
L1601	1-459-155-00	COIL (WITH CORE) 45UH
L1602	1-424-626-12	COIL, CHOKE 390UH
L1603	1-410-397-21	FERRITE BEAD INDUCTOR

<TRANSISTOR>

Q501	8-729-901-01	TRANSISTOR DTC144EK
Q502	8-729-901-01	TRANSISTOR DTC144EK
Q503	8-729-901-06	TRANSISTOR DTA144EK
Q504	8-729-901-01	TRANSISTOR DTC144EK
Q505	8-729-920-74	TRANSISTOR 2SC2412K-QR
Q506	8-729-901-01	TRANSISTOR DTC144EK
Q507	8-729-901-01	TRANSISTOR DTC144EK
Q508	8-729-920-74	TRANSISTOR 2SC2412K-QR
Q509	8-729-920-74	TRANSISTOR 2SC2412K-QR
Q510	8-729-901-06	TRANSISTOR DTA144EK
Q511	8-729-901-01	TRANSISTOR DTC144EK
Q512	8-729-920-74	TRANSISTOR 2SC2412K-QR
Q513	8-729-216-22	TRANSISTOR 2SA1162-G
Q514	8-729-216-22	TRANSISTOR 2SA1162-G
Q515	8-729-313-42	TRANSISTOR 2SD1134-C
Q516	8-729-901-01	TRANSISTOR DTC144EK
Q517	8-729-901-01	TRANSISTOR DTC144EK
Q518	8-729-920-74	TRANSISTOR 2SC2412K-QR
Q519	8-729-920-74	TRANSISTOR 2SC2412K-QR
Q525	8-729-920-74	TRANSISTOR 2SC2412K-QR

REF.NO.	PART NO.	DESCRIPTION				REMARK
Q532	8-729-920-74	TRANSISTOR 2SC2412K-QR				
Q533	8-729-920-74	TRANSISTOR 2SC2412K-QR				
Q833	8-729-216-22	TRANSISTOR 2SA1162-G				
Q834	8-729-920-74	TRANSISTOR 2SC2412K-QR				
Q835	8-729-920-74	TRANSISTOR 2SC2412K-QR				
Q836	8-729-309-08	TRANSISTOR 2SC1890A				
Q1601	8-729-920-74	TRANSISTOR 2SC2412K-QR				
Q1602	8-729-920-74	TRANSISTOR 2SC2412K-QR				
Q1603	8-729-920-74	TRANSISTOR 2SC2412K-QR				
Q1604	8-729-216-22	TRANSISTOR 2SA1162-G				
Q1605	8-729-119-80	TRANSISTOR 2SC2688-LK				
Q1606	8-729-133-42	TRANSISTOR 2SC2334-L				
Q1607	8-729-920-74	TRANSISTOR 2SC2412K-QR				
Q1608	8-729-920-74	TRANSISTOR 2SC2412K-QR				
Q1609	8-729-920-74	TRANSISTOR 2SC2412K-QR				
Q1610	8-729-920-74	TRANSISTOR 2SC2412K-QR				
Q1611	8-729-920-74	TRANSISTOR 2SC2412K-QR				
Q1612	8-729-920-74	TRANSISTOR 2SC2412K-QR				
Q1613	8-729-920-74	TRANSISTOR 2SC2412K-QR				
Q1614	8-729-920-74	TRANSISTOR 2SC2412K-QR				
Q1615	8-729-216-22	TRANSISTOR 2SA1162-G				
Q1616	8-729-216-22	TRANSISTOR 2SA1162-G				
Q1617	8-729-216-22	TRANSISTOR 2SA1162-G				
Q1618	8-729-216-22	TRANSISTOR 2SA1162-G				

<RESISTOR>

JR510	1-216-295-00	METAL GLAZE	0	5%	1/10W	
R501	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R502	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R503	1-249-437-11	CARBON	47K	5%	1/4W	F
R504	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R505	1-249-393-11	CARBON	10	5%	1/4W	F
R506	1-216-071-00	METAL GLAZE	8.2K	5%	1/10W	
R507	1-216-059-00	METAL GLAZE	2.7K	5%	1/10W	
R508	1-216-085-00	METAL GLAZE	33K	5%	1/10W	
R509	1-216-687-11	METAL CHIP	33K	0.50%	1/10W	
R510	1-216-683-11	METAL CHIP	22K	0.50%	1/10W	
R511	1-216-675-11	METAL CHIP	10K	0.50%	1/10W	
R512	1-218-761-11	METAL CHIP	240K	0.50%	1/10W	
R513	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R514	1-218-754-11	METAL CHIP	120K	0.50%	1/10W	
R515	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R516	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R517	1-216-107-00	METAL CHIP	270K	0.50%	1/10W	
R518	1-249-422-11	CARBON	2.7K	5%	1/4W	F
R519	1-216-085-00	METAL GLAZE	33K	5%	1/10W	
R520	1-216-677-11	METAL CHIP	12K	0.50%	1/10W	
R521	1-216-067-00	METAL GLAZE	5.6K	5%	1/10W	
R522	1-216-107-00	METAL GLAZE	270K	5%	1/10W	
R523	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R524	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R525	1-216-434-11	METAL OXIDE	1.8K	5%	1W	F
R526	1-216-079-00	METAL GLAZE	18K	5%	1/10W	
R527	1-249-437-11	CARBON	47K	5%	1/4W	F
R528	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R529	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R530	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R531	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R532	1-216-097-00	METAL GLAZE	100K	5%	1/10W	
R533	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R534	1-216-097-00	METAL GLAZE	100K	5%	1/10W	
R535	1-216-053-00	METAL GLAZE	1.5K	5%	1/10W	
R536	1-212-881-11	FUSIBLE	100	5%	1/4W	F

REF.NO.	PART NO.	DESCRIPTION				REMARK
R537	1-215-867-00	METAL OXIDE	470	5%	1W	F
R538	1-216-095-00	METAL GLAZE	82K	5%	1/10W	
R539	1-216-095-00	METAL GLAZE	82K	5%	1/10W	
R540	1-216-101-00	METAL GLAZE	150K	5%	1/10W	
R541	1-216-063-00	METAL GLAZE	3.9K	5%	1/10W	
R542	1-216-075-00	METAL GLAZE	12K	5%	1/10W	
R543	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R544	1-216-101-00	METAL GLAZE	150K	5%	1/10W	
R545	1-216-041-00	METAL GLAZE	470	5%	1/10W	
R546	1-216-091-00	METAL GLAZE	56K	5%	1/10W	
R547	1-216-121-00	METAL GLAZE	1M	5%	1/10W	
R548	1-216-107-00	METAL GLAZE	270K	5%	1/10W	
R549	1-216-101-00	METAL GLAZE	150K	5%	1/10W	
R550	1-216-356-00	METAL OXIDE	3.9	5%	1W	F
R552	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R553	1-216-087-11	METAL GLAZE	39K	5%	1/10W	
R554	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R555	1-216-077-00	METAL GLAZE	15K	5%	1/10W	
R557	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W	
R558	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R559	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R560	1-216-037-00	METAL GLAZE	330	5%	1/10W	
R561	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R562	1-216-053-00	METAL GLAZE	1.5K	5%	1/10W	
R563	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R564	1-249-415-11	CARBON	680	5%	1/4W	F
R565	1-216-059-00	METAL GLAZE	2.7K	5%	1/10W	
R566	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R567	1-216-095-00	METAL GLAZE	82K	5%	1/10W	
R568	1-216-063-00	METAL GLAZE	3.9K	5%	1/10W	
R569	1-216-063-00	METAL GLAZE	3.9K	5%	1/10W	
R570	1-216-093-00	METAL GLAZE	68K	5%	1/10W	
R571	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R572	1-216-095-00	METAL GLAZE	82K	5%	1/10W	
R573	1-216-063-00	METAL GLAZE	3.9K	5%	1/10W	
R574	1-216-063-00	METAL GLAZE	3.9K	5%	1/10W	
R575	1-216-105-00	METAL GLAZE	220K	5%	1/10W	
R576	1-216-109-00	METAL GLAZE	330K	5%	1/10W	
R577	1-216-105-00	METAL GLAZE	220K	5%	1/10W	
R578	1-249-457-11	CARBON	6.8	5%	1/4W	F
R579	1-249-457-11	CARBON	6.8	5%	1/4W	F
R591	1-216-063-00	METAL GLAZE	3.9K	5%	1/10W	
R592	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R831	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R832	1-216-075-00	METAL GLAZE	12K	5%	1/10W	
R833	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R834	1-216-059-00	METAL GLAZE	2.7K	5%	1/10W	
R835	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R836	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R837	1-216-075-00	METAL GLAZE	12K	5%	1/10W	
R838	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R839	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R840	1-216-097-00	METAL GLAZE	100K	5%	1/10W	
R841	1-216-093-00	METAL GLAZE	68K	5%	1/10W	
R842	1-216-093-00	METAL GLAZE	68K	5%	1/10W	
R843	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R844	1-216-077-00	METAL GLAZE	15K	5%	1/10W	
R847	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R850	1-216-085-00	METAL GLAZE	33K	5%	1/10W	
R851	1-216-669-11	METAL CHIP	5.6K	0.50%	1/10W	
R852	1-216-675-11	METAL CHIP	10K	0.50%	1/10W	
R853	1-216-105-00	METAL GLAZE	220K	5%	1/10W	
R854	1-218-754-11	METAL CHIP	120K	0.50%	1/10W	

D HA

- The components identified by ⊠ in this manual have been carefully factory-selected for each set in order to satisfy regulations regarding X-ray radiation.
  Should replacement be required, replace only with the value originally used.

The components identified by shading and mark ⚠ are critical for safety.
Replace only with part number specified.

REF.NO.	PART NO.	DESCRIPTION				REMARK
R855	1-216-697-11	METAL CHIP	82K	0.50%	1/10W	
R856	1-216-699-11	METAL CHIP	100K	0.50%	1/10W	
R857	1-216-686-11	METAL CHIP	30K	0.50%	1/10W	
R858	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R859	1-216-436-00	METAL OXIDE	3.9K	5%	1W	F
R860	1-216-675-11	METAL CHIP	10K	0.50%	1/10W	
R861	1-216-671-11	METAL CHIP	6.8K	0.50%	1/10W	
R862	1-216-675-11	METAL CHIP	10K	0.50%	1/10W	
R863	1-249-435-11	CARBON	33K	5%	1/4W	F
R1503	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R1504	1-216-695-11	METAL CHIP	68K	0.50%	1/10W	
R1505	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R1506	1-216-667-11	METAL CHIP	4.7K	0.50%	1/10W	
R1507	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R1508	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1509	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R1510	1-249-425-11	CARBON	4.7K	5%	1/4W	F
R1511	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R1512	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R1513	1-216-017-00	METAL GLAZE	47	5%	1/10W	
R1519	1-216-031-00	METAL GLAZE	180	5%	1/10W	
R1520	1-216-053-00	METAL GLAZE	1.5K	5%	1/10W	
R1601	1-216-685-11	METAL CHIP	27K	0.50%	1/10W	
R1602	1-216-681-11	METAL CHIP	18K	0.50%	1/10W	
R1603	1-216-671-11	METAL CHIP	6.8K	0.50%	1/10W	
R1604	1-249-433-11	CARBON	22K	5%	1/4W	F
R1605	1-216-070-00	METAL GLAZE	7.5K	5%	1/10W	
R1606	1-216-070-00	METAL GLAZE	7.5K	5%	1/10W	
R1607	1-216-071-00	METAL GLAZE	8.2K	5%	1/10W	
R1608	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R1609	1-216-069-00	METAL GLAZE	6.8K	5%	1/10W	
R1610	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W	
R1611	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W	
R1612	1-215-913-11	METAL OXIDE	220	5%	3W	F
R1613	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R1614	1-216-067-00	METAL GLAZE	5.6K	5%	1/10W	
R1615	1-216-657-11	METAL CHIP	1.8K	0.50%	1/10W	
R1616	1-216-629-11	METAL CHIP	120	0.50%	1/10W	
R1617	1-216-659-11	METAL CHIP	2.2K	0.50%	1/10W	
R1618	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1620	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R1621	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1622	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1623	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1624	1-216-246-00	METAL GLAZE	100K	5%	1/8W	
R1625	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R1626	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R1627	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R1628	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1629	1-216-683-11	METAL CHIP	22K	0.50%	1/10W	
R1630	1-216-683-11	METAL CHIP	22K	0.50%	1/10W	
R1631	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W	
R1632	1-216-042-00	METAL GLAZE	510	5%	1/10W	
R1633	1-216-109-00	METAL GLAZE	330K	5%	1/10W	
R1634	1-216-099-00	METAL GLAZE	120K	5%	1/10W	
R1635	1-216-097-00	METAL GLAZE	100K	5%	1/10W	
R1636	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1640	1-216-063-00	METAL GLAZE	3.9K	5%	1/10W	
R1641	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1642	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1643	1-216-069-00	METAL GLAZE	6.8K	5%	1/10W	
R1644	1-216-069-00	METAL GLAZE	6.8K	5%	1/10W	
R1645	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1646	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1647	1-216-685-11	METAL CHIP	27K	0.50%	1/10W	
R1648	1-216-069-00	METAL GLAZE	6.8K	5%	1/10W	
R1649	1-216-069-00	METAL GLAZE	6.8K	5%	1/10W	
R1650	1-216-069-00	METAL GLAZE	6.8K	5%	1/10W	
R1651	1-216-069-00	METAL GLAZE	6.8K	5%	1/10W	
R1652	1-216-069-00	METAL GLAZE	6.8K	5%	1/10W	
R1653	1-216-069-00	METAL GLAZE	6.8K	5%	1/10W	
R1654	1-216-681-11	METAL CHIP	18K	0.50%	1/10W	
R1655	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R1656	1-216-643-11	METAL CHIP	470	0.50%	1/10W	
R1657	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R1658	1-216-063-00	METAL GLAZE	3.9K	5%	1/10W	
R1659	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R1660	1-216-649-11	METAL CHIP	820	0.50%	1/10W	
R1661	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	

<VARIABLE RESISTOR>

RV501	1-238-019-11	RES, ADJ, CARBON 47K
RV502	1-238-017-11	RES, ADJ, CARBON 22K
RV503	1-241-763-11	RES, ADJ, CERMET 4.7K
RV504	1-224-250-XX	RES, ADJ, METAL GLAZE 2.2K
RV505	1-238-009-11	RES, ADJ, CARBON 220
RV506	1-238-012-11	RES, ADJ, CARBON 1K
RV507	1-238-013-11	RES, ADJ, CARBON 2.2K
RV508	1-238-012-11	RES, ADJ, CARBON 1K
RV509	1-238-021-11	RES, ADJ, CARBON 220K
RV511	1-238-015-11	RES, ADJ, CARBON 4.7K
RV512	1-238-015-11	RES, ADJ, CARBON 4.7K
RV514	1-238-019-11	RES, ADJ, CARBON 47K
RV515	1-238-021-11	RES, ADJ, CARBON 220K
RV516	1-241-763-11	RES, ADJ, CERMET 4.7K
RV831	1-228-997-00	RES, ADJ, METAL GLAZE 100K
RV832	1-241-764-11	RES, ADJ, CERMET 10K
⊠RV833⚠		RES, ADJ, CERMET
RV1601	1-241-700-11	RES, ADJ, CERMET 2.2K
RV1602	1-238-012-11	RES, ADJ, CARBON 1K
⊠RV1603⚠		RES, ADJ, CERMET

<RELAY>

RY1601	1-515-481-21	RELAY (G2R-212P-V)

<TRANSFORMER>

T1601	1-437-216-11	TRANSFORMER, DRIVE

****

	*A-1371-782-A	HA BOARD, COMPLETE
		**********
	*4-348-208-00	HOLDER, LED
	*4-341-751-01	EYELET EY5

<CONNECTOR>

CN001	1-506-478-11	PIN, CONNECTOR 13P
CN002	1-506-473-11	PIN, CONNECTOR 8P

<DIODE>

D001	8-719-920-05	DIODE SLP281C-50
D002	8-719-109-68	DIODE RD3.6ESB1

REF.NO.	PART NO.	DESCRIPTION			REMARK
		<RESISTOR>			
JW009	1-216-295-00	METAL GLAZE	0	5% 1/10W	
JW024	1-216-295-00	METAL GLAZE	0	5% 1/10W	
R001	1-247-713-11	CARBON	1K	5% 1/4W	
R002	1-216-295-00	METAL GLAZE	0	5% 1/10W	
R003	1-216-295-00	METAL GLAZE	0	5% 1/10W	
R004	1-216-081-00	METAL GLAZE	22K	5% 1/10W	
		<VARIABLE RESISTOR>			
RV001	1-241-846-11	RES, VAR, CARBON 20K			
RV002	1-241-846-11	RES, VAR, CARBON 20K			
RV003	1-241-845-11	RES, VAR, CARBON 20K			
RV004	1-241-845-11	RES, VAR, CARBON 20K			
RV005	1-241-845-11	RES, VAR, CARBON 20K			
RV006	1-241-845-11	RES, VAR, CARBON 20K			
RV007	1-226-773-11	RES, ADJ, METAL GLAZE 22K			
RV008	1-226-773-11	RES, ADJ, METAL GLAZE 22K			
RV009	1-226-773-11	RES, ADJ, METAL GLAZE 22K			
RV010	1-226-773-11	RES, ADJ, METAL GLAZE 22K			
RV011	1-226-773-11	RES, ADJ, METAL GLAZE 22K			
RV012	1-226-773-11	RES, ADJ, METAL GLAZE 22K			
		<SWITCH>			
S001	1-554-419-00	SWITCH, PUSH (1 KEY)			
S002	1-554-419-00	SWITCH, PUSH (1 KEY)			
S003	1-554-419-00	SWITCH, PUSH (1 KEY)			
S004	1-554-419-00	SWITCH, PUSH (1 KEY)			
S005	1-554-419-00	SWITCH, PUSH (1 KEY)			
S006	1-554-419-00	SWITCH, PUSH (1 KEY)			
**********					
*1-641-724-11		X BOARD			
		*******			
		<CONNECTOR>			
CN21	*1-564-518-11	PLUG, CONNECTOR 3P			
		<DIOE>			
D21	8-719-023-78	DIODE SEL3810DLC05			
D22	8-719-023-78	DIODE SEL3810DLC05			
D23	8-719-023-78	DIODE SEL3810DLC05			
**********					
*A-1394-368-A		S BOARD, COMPLETE			
		**********			
3-710-578-01		COVER, VOLUME, 6 MOLD			
		<CAPACITOR>			
C1101	1-163-119-00	CERAMIC CHIP	120PF	5% 50V	
C1102	1-164-004-11	CERAMIC CHIP	0.1MF	10% 25V	
C1103	1-124-589-11	ELECT	47MF	20% 16V	
C1104	1-163-031-11	CERAMIC CHIP	0.01MF	50V	
C1105	1-163-114-00	CERAMIC CHIP	75PF	5% 50V	
C1106	1-163-101-00	CERAMIC CHIP	22PF	5% 50V	
C1107	1-164-004-11	CERAMIC CHIP	0.1MF	10% 25V	
C1108	1-163-119-00	CERAMIC CHIP	120PF	5% 50V	
C1109	1-163-031-11	CERAMIC CHIP	0.01MF	50V	
C1110	1-163-117-00	CERAMIC CHIP	100PF	5% 50V	
C1111	1-163-018-00	CERAMIC CHIP	0.0056MF	10% 50V	
C1112	1-126-160-11	ELECT	1MF	20% 50V	
C1113	1-163-119-00	CERAMIC CHIP	120PF	5% 50V	
C1114	1-163-103-00	CERAMIC CHIP	27PF	5% 50V	
C1115	1-164-004-11	CERAMIC CHIP	0.1MF	10% 25V	
C1116	1-163-114-00	CERAMIC CHIP	75PF	5% 50V	
C1117	1-124-589-11	ELECT	47MF	20% 16V	
C1118	1-164-004-11	CERAMIC CHIP	0.1MF	10% 25V	
C1119	1-163-020-00	CERAMIC CHIP	0.0082MF	10% 50V	
C1120	1-163-097-00	CERAMIC CHIP	15PF	5% 50V	
C1121	1-163-097-00	CERAMIC CHIP	15PF	5% 50V	
C1122	1-163-222-11	CERAMIC CHIP	5PF	0.25PF 50V	
C1123	1-163-097-00	CERAMIC CHIP	15PF	5% 50V	
C1130	1-163-097-00	CERAMIC CHIP	15PF	5% 50V	
C1131	1-163-097-00	CERAMIC CHIP	15PF	5% 50V	
		<CONNECTOR>			
CN1101	*1-565-488-11	CONNECTOR, BOARD TO BOARD 12P			
		<DIODE>			
D1101	8-719-404-46	DIODE MA110			
D1102	8-719-404-46	DIODE MA110			
		<IC>			
IC1101	8-752-056-67	IC CXA1214P			
		<COIL>			
L1101	1-408-411-00	INDUCTOR	15UH		
L1102	1-404-496-00	COIL			
L1103	1-404-496-00	COIL			
L1104	1-408-411-00	INDUCTOR	15UH		
L1110	1-412-008-31	INDUCTOR CHIP	15UH		
L1111	1-412-008-31	INDUCTOR CHIP	15UH		
		<TRANSISTOR>			
Q1101	8-729-216-22	TRANSISTOR 2SA1162-G			
Q1102	8-729-920-74	TRANSISTOR 2SC2412K-QR			
Q1103	8-729-216-22	TRANSISTOR 2SA1162-G			
Q1104	8-729-216-22	TRANSISTOR 2SA1162-G			
Q1105	8-729-901-01	TRANSISTOR DTC144EK			
Q1106	8-729-901-01	TRANSISTOR DTC144EK			
Q1107	8-729-109-44	TRANSISTOR 2SK94-X4			
Q1108	8-729-920-74	TRANSISTOR 2SC2412K-QR			
		<RESISTOR>			
R1101	1-216-053-00	METAL GLAZE	1.5K	5% 1/10W	
R1102	1-216-067-00	METAL GLAZE	5.6K	5% 1/10W	
R1103	1-216-059-00	METAL GLAZE	2.7K	5% 1/10W	
R1104	1-216-073-00	METAL GLAZE	10K	5% 1/10W	
R1105	1-216-031-00	METAL GLAZE	180	5% 1/10W	
R1106	1-216-059-00	METAL GLAZE	2.7K	5% 1/10W	
R1107	1-216-071-00	METAL GLAZE	8.2K	5% 1/10W	
R1108	1-216-039-00	METAL GLAZE	390	5% 1/10W	
R1109	1-216-063-00	METAL GLAZE	3.9K	5% 1/10W	
R1110	1-216-069-00	METAL GLAZE	6.8K	5% 1/10W	

S G

- The components identified by ⊠ in this manual have been carefully factory-selected for each set in order to satisfy regulations regarding X-ray radiation.
  Should replacement be required, replace only with the value originally used.

The components identified by shading and mark ⚠ are critical for safety.
Replace only with part number specified.

REF.NO.	PART NO.	DESCRIPTION				REMARK
R1111	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R1112	1-216-063-00	METAL GLAZE	3.9K	5%	1/10W	
R1113	1-216-069-00	METAL GLAZE	6.8K	5%	1/10W	
R1114	1-216-055-00	METAL GLAZE	1.8K	5%	1/10W	
R1115	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R1116	1-216-069-00	METAL GLAZE	6.8K	5%	1/10W	
R1117	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R1118	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1119	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R1120	1-216-097-00	METAL GLAZE	100K	5%	1/10W	
R1121	1-216-121-00	METAL GLAZE	1M	5%	1/10W	
R1122	1-216-039-00	METAL GLAZE	390	5%	1/10W	
R1123	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R1124	1-216-029-00	METAL GLAZE	150	5%	1/10W	
R1125	1-216-029-00	METAL GLAZE	150	5%	1/10W	
R1126	1-216-053-00	METAL GLAZE	1.5K	5%	1/10W	
R1127	1-216-043-00	METAL GLAZE	560	5%	1/10W	
R1128	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R1129	1-216-091-00	METAL GLAZE	56K	5%	1/10W	
R1130	1-216-295-00	METAL GLAZE	0	5%	1/10W	
R1131	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1132	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1133	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1134	1-216-091-00	METAL GLAZE	56K	5%	1/10W	

<VARIABLE RESISTOR>

RV1101	1-238-015-11	RES, ADJ, CARBON 4.7K	
RV1102	1-238-013-11	RES, ADJ, CARBON 2.2K	

<TRANSISTOR>

T1101	1-404-584-11	COIL	

****

G BOARD (SOPS-1021)
****

⚠	4-812-134-11	RIVET NYLON, 3.5φ			

<CAPACITOR>

C601	⚠ 1-136-889-11	METALIZED FILM	0.22MF	20%	250V
C602	⚠ 1-136-889-11	METALIZED FILM	0.22MF	20%	250V
C603	⚠ 1-161-973-51	CERAMIC	220PF	10%	400V
C604	⚠ 1-161-973-51	CERAMIC	220PF	10%	400V
C605	⚠ 1-161-973-51	CERAMIC	220PF	10%	400V
C608	⚠ 1-161-742-51	CERAMIC	0.0022MF	20%	400V
C609	⚠ 1-161-742-51	CERAMIC	0.0022MF	20%	400V
C610	⚠ 1-125-724-11	ELECT	180MF	20%	400V
C611	⚠ 1-136-206-21	METALIZED FILM	0.033MF	10%	630V
C612	⚠ 1-124-910-51	ELECT	47MF	20%	50V
C613	⚠ 1-137-190-91	METALIZED FILM	0.22MF	5%	50V
C614	⚠ 1-137-190-91	METALIZED FILM	0.22MF	5%	50V
C615	⚠ 1-130-471-91	PE TEREPHTHALATE	0.001MF	5%	50V
C651	⚠ 1-161-925-11	CERAMIC	100PF B	10%	500V
C652	⚠ 1-128-486-51	ELECT	680MF	20%	50V
C653	⚠ 1-128-485-51	ELECT	220MF	20%	50V
C654	⚠ 1-130-483-91	PE TEREPHTHALATE	0.01MF	5%	50V

<CONNECTOR>

CN610	⚠* 1-560-436-11	HORIZONTAL PIN ASSY 3P	
CN651	⚠* 1-564-518-11	PLUG, CONNECTOR 3P	

REF.NO.	PART NO.	DESCRIPTION	REMARK

<DIODE>

D201	⚠ 8-719-971-08	DIODE ESAC39M 06C	
D601	⚠ 8-719-510-27	DIODE D3SB60	
D602	⚠ 8-719-921-20	DIODE 1SS119TD	
D603	⚠ 8-719-981-47	DIODE ERA38-06TP1	
D604	⚠ 8-719-981-47	DIODE ERA38-06TP1	
D605	⚠ 8-719-113-44	DIODE RD20ES-T1B3	
D651	⚠ 8-719-971-08	DIODE ESAC39M 06C	

<IC>

IC601	⚠ 1-809-086-12	HIC CH-1018	
IC651	⚠ 8-759-908-15	IC TL431CLP	
PH601	⚠ 8-759-045-81	IC TLP732GR-LF2	

<COIL>

L601	⚠ 1-424-616-11	TRANSFORMER, LINE FILTER	
L602	⚠ 1-424-574-11	L.F.T	
L651	⚠ 1-424-255-41	COIL, CHOKE (MOLDE) 10UH	
L652	⚠ 1-424-615-11	COIL, CHOKE	

<TRANSISTOR>

Q601	⚠ 8-729-322-18	TRANSISTOR 2SK1402A	

<RESISTOR>

R601	⚠ 1-205-940-51	CEMENT	1.5	5%	5W	F
R602	⚠ 1-205-940-51	CEMENT	1.5	5%	5W	F
R603	⚠ 1-215-904-11	METAL OXIDE	100K	5%	2W	F
R604	⚠ 1-215-904-11	METAL OXIDE	100K	5%	2W	F
R605	⚠ 1-212-865-61	FUSIBLE	22	5%	1/4W	F
R606	⚠ 1-247-805-91	CARBON	82	5%	1/4W	
R607	⚠ 1-260-128-91	CARBON	270K	5%	1/2W	
R608	⚠ 1-260-128-91	CARBON	270K	5%	1/2W	
R609	⚠ 1-215-904-51	METAL OXIDE	100K	5%	2W	F
R610	⚠ 1-207-455-11	WIRE	0.22	10%	1/2W	
R611	⚠ 1-247-789-91	CARBON	18	5%	1/4W	
R612	⚠ 1-247-795-91	CARBON	33	5%	1/4W	
R613	⚠ 1-215-904-51	METAL OXIDE	100K	5%	2W	F
R614	⚠ 1-247-815-91	CARBON	220	5%	1/4W	
R651	⚠ 1-215-886-51	METAL OXIDE	100	5%	2W	F
R652	⚠ 1-215-886-51	METAL OXIDE	100	5%	2W	F
R653	⚠ 1-260-107-91	CARBON	4.7K	5%	1/2W	
R654	⚠ 1-260-107-91	CARBON	4.7K	5%	1/2W	
R655	⚠ 1-247-867-91	CARBON	33K	5%	1/4W	
R656	⚠ 1-247-867-91	CARBON	33K	5%	1/4W	
R657	⚠ 1-247-837-91	CARBON	1.8K	5%	1/4W	

<VARIABLE RESISTOR>

⊠RV651	⚠ 1-237-443-11	RES, ADJ, CARBON 1K	

<TRANSFORMER>

T601	⚠ 1-450-760-11	TRANSFORMER, CONVERTER	

****

The components identified by shading and mark ⚠ are critical for safety.
Replace only with part number specified.

REF.NO.	PART NO.	DESCRIPTION	REMARK
		MISCELLANEOUS	
		**********	
	⚠.1-413-720-21	SWITCHING REGULATOR (SOPS-1021)	
	⚠.1-426-043-12	COIL, DEGAUSSING	
	⚠.1-451-319-22	DEFLECTION YOKE (Y9FXC)	
	1-452-126-11	MAGNET	
	1-543-925-11	CORE, FERRITE	
	1-544-252-11	SPEAKER	
	1-690-871-11	CABLE (MINI DIN) 8P	
V901	⚠.8-737-151-05	PICTURE TUBE (A20JKU10X) (PVM-9041QM)	
	⚠.8-737-651-05	PICTURE TUBE (M20JMP10X) (PVM-9044QM)	

****

ACCESSORIES & PACKING MATERIALS
****

PART NO.	DESCRIPTION	REMARK
⚠.1-590-910-11	CORD SET, POWER (10.0A/250V)	
1-690-871-11	CABLE (MINI DIN) 8P	
2-990-241-02	HOLDER (A), PLUG	
*3-170-078-01	HOLDER (B), PLUG	
*3-704-301-01	BAG (STANDARD), PROTECTION	
3-754-506-21	MANUAL, INSTRUCTION	
4-034-835-01	PLATE, TALLY	
*4-034-955-01	CUSHION (UPPER) (ASSY)	
*4-034-956-01	CUSHION (LOWER) (ASSY)	
*4-035-784-01	INDIVIDUAL CARTON	

Sony Corporation
Display Products Group

English
92EL0913-1
Printed in Japan
© 1992.5

9-978-259-01

PVM-9041QM/9044QM

SONY

SERVICE MANUAL

AEP Model

PVM-9041QM
Chassis No. SCC-F09B-A
PVM-9044QM
Chassis No. SCC-F09A-A

SUPPLEMENT-1

INTRODUCTION

- B board : The transistor is changed to the pair transistor (Q189).
  The diodes are changed to the three-terminal diodes.
  (D185, D186, D187, D188, D191, D390 and D1382)
- D board : The transistors are changed to the pair transistors.
  (Q569, Q576, Q579 and Q599)
  The diodes are changed to the three-terminal diodes.
  (D520, D521, D848, D1620, D1622 and D1623)
- S board : The pattern is modified.

Note)
Before using the circuit board, confirm that the parts number shown below and the parts number of the circuit board which is being used in your set are the same.

Board (Complete No.)	Board Part. No.
B (A-1135-716-A)	1-641-716-15
D (A-1346-018-A)	1-641-717-16
S (A-1394-368-A)	1-641-719-15

MICROFILM

TABLE OF CONTENTS

Section	*Title*	*Page*
1. DIAGRAMS		
1-1.	Circuit Boards Location	3
1-2.	Printed Wiring Boards and Schematic Diagrams	3
	S Board	4
	D Board	7
	B Board	16
2. ELECTRICAL PARTS LIST		31

(CAUTION)

SHORT CIRCUIT THE ANODE OF THE PICTURE TUBE AND THE ANODE CAP TO THE METAL CHASSIS, CRT SHIELD, OR CARBON PAINTED ON THE CRT, AFTER REMOVING THE ANODE.

WARNING!!

AN ISOLATION TRANSFORMER SHOULD BE USED DURING ANY SERVICE TO AVOID POSSIBLE SHOCK HAZARD, BECAUSE OF LIVE CHASSIS.
THE CHASSIS OF THIS RECEIVER IS DIRECTLY CONNECTED TO THE AC POWER LINE.

SAFETY-RELATED COMPONENT WARNING !!

COMPONENTS IDENTIFIED BY SHADING AND MARK ⚠ ON THE SCHEMATIC DIAGRAMS, EXPLODED VIEWS AND IN THE PARTS LIST ARE CRITICAL TO SAFE OPERATION. REPLACE THESE COMPONENTS WITH SONY PARTS WHOSE PART NUMBERS APPEAR AS SHOWN IN THIS MANUAL OR IN SUPPLEMENTS PUBLISHED BY SONY. CIRCUIT ADJUSTMENTS THAT ARE CRITICAL TO SAFE OPERATION ARE IDENTIFIED IN THIS MANUAL. FOLLOW THESE PROCEDURES WHENEVER CRITICAL COMPONENTS ARE REPLACED OR IMPROPER OPERATION IS SUSPECTED.

Super 1

SECTION 1
DIAGRAMS

1-1. CIRCUITS BOARDS LOCATION



Part replaced (◪)	Adjustment (⊠)
IC601, IC651, PH602, C655, R653, R655, R656, R657, RV651	RV651 (B+ MAX)
Q1601, Q1602, Q1603, D1601, D1603, D1622, D1623, C1601, C1602, R1601, R1602, R1603, R1604, R1605, R1606, R1607, R1608, R1628, R1629, R1630, RV1601, RV1603	RV1603 (B+ MAX IN DC POWER INPUT MODE)
IC502, Q833, Q834, Q835, Q836, D835, D836, C519, C843, C844, C845, C846, C847, C848, RV833, R523, R850, R851, R852, R853, R854, R855, R856, R857, R858, R859, R861, R862, R863, NL801	R833 (HOLD-DOWN)

1-2. PRINTED WIRING BOARDS AND SCHEMATIC DIAGRAMS

Note:

- All capacitors are in μF unless otherwise noted. pF: μμF 50 WV or less are not indicated except for electrolytic.
- Indication of resistance, which does not have one for rating electrical power, is as follows.

  Pitch: 5 mm
  Rating electrical power ¼ W
- All resistors are in ohms.
- : nonflammable resistor.
- : fusible resistor.
- △ : internal component.
- : panel designation.
- All variable and adjustable resistors have characteristic curve B, unless otherwise noted.
- The components identified by ⊠ in this basic schematic diagram have been carefully factory-selected for each set in order to satisfy regulations regarding X-ray radiation. Should replacement be required, replace only with the value originally used.
- When replacing components identified by ◪, make the necessary adjustments indicated. If results do not meet the specified value, change the component identified by ⊠ and repeat the adjustment until the specified value is achieved.
- When replacing the part in below table be sure to perform the related adjustment.

Reference information

RESISTOR	: RN	METAL FILM
	: RC	SOLID
	: FPRD	NONFLAMMABLE CARBON
	: FUSE	NONFLAMMABLE FUSIBLE
	: RS	NONFLAMMABLE WIREWOUND
	: RB	NONFLAMMABLE CEMENT
COIL	: LF-8L	MICRO INDUCTOR
CAPACITOR	: TA	TANTALUM
	: PS	STYROL
	: PP	POLYPROPYLENE
	: PT	MYLAR
	: MPS	METALIZED POLYESTER
	: MPP	METALIZED POLYPROPYLENE
	: ALB	BIPOLAR
	: ALT	HIGH TEMPERATURE
	: ALR	HIGH RIPPLE

S [SECAM DEMODULATION]

– S Board – – Component Side –



– S Board – – Conductor Side –



- ▒▒▒ : Pattern from the side which enables seeing.
- ▒▒▒ : Pattern of the rear side.

A B C D E F G H I J

ONY SP-00151/ DRUCK31



S Board IC1101 CXA1214P



• S BOARD WAVEFORMS

(301) SECAM 0.8Vp-p (H)	(302) SECAM 0.7Vp-p (H).	(303) SECAM 0.1Vp-p (H)	(304) SECAM 3Vp-p (H)
(305) SECAM 0.6Vp-p (H)	(306) SECAM 0.7Vp-p (H)	(307) SECAM 3.4Vp-p (H)	(308) SECAM 6Vp-p (H)

SONY SP-00151/ DRUCK32

• D BOARD WAVEFORMS

(101) 11Vp-p (V)	(102) 11Vp-p (H)	(103) 0.25Vp-p (V)	(104) 10.5Vp-p (V)
(105) 3.5Vp-p (V)	(106) 3Vp-p (V)	(107) 5.5Vp-p (V)	(108) 1.5Vp-p (V)
(109) 1.3Vp-p (V)	(110) 10Vp-p (V)	(111) 6Vp-p (H)	(112) 4.4Vp-p (H)
(113) 1.1Vp-p (H)	(114) 6.4Vp-p (H)	(115) 36Vp-p (H)	(116) 2.2Vp-p (V)
(117) 1Vp-p (V)	(118) 1Vp-p (V)	(119) 46Vp-p (V)	(120) 1.6Vp-p (V)
(121) 12Vp-p (V)	(122) 12Vp-p (V)	(123) 12Vp-p (H)	(124) 12Vp-p (H)
(125) 12Vp-p (H)	(126) 32Vp-p (H)	(127) 12Vp-p (H)	(128) 0.5Vp-p (V)
(129) 2.2Vp-p (V)	(130) 0.32Vp-p (H)	(131) 0.6Vp-p (V)	(132) 12Vp-p (V)
(133) 12Vp-p (V)	(134) 12Vp-p (V)	(135) 12Vp-p (H)	(136) 12Vp-p (V)





D BOARD IC501 CX23025



D BOARD IC503 LA7830



D [DEFLECTION SYSTEM]

– D Board – – Component Side –





D Board (Component Side)

IC	
IC505	C – 8
IC831	D – 10
IC832	B – 9
IC833	C – 9
IC1601	F – 12

TRANSISTOR	
Q505	F – 12
Q508	F – 12
Q509	E – 12
Q512	E – 4
Q532	B – 6
Q576	G – 5
Q579	G – 4
Q599	E – 2
Q1607	G – 12
Q1610	E – 13
Q1611	F – 13
Q1612	E – 13
Q1613	F – 13
Q1614	F – 13
Q1615	E – 13
Q1616	E – 13
Q1617	E – 13
Q1618	D – 12

DIODE	
D508	A – 6
D512	C – 6
D514	A – 7
D520	C – 2
D521	F – 12
D833	A – 8
D834	A – 9
D836	C – 5
D848	D – 10
D1609	G – 12
D1610	G – 10
D1626	F – 13
D1627	F – 13
D1628	F – 13

– D Board – – Conductor Side –



- ▒▒▒ : Pattern from the side which enables seeing.
- ▒▒▒ : Pattern of the rear side.

PVM-9041QM/9044QM

r Side –



PVM-9041QM/9044QM PVM-9041QM/9044QM

B [SIGNAL PROCESS]

– B Board – – Component Side –



B Board (Component Side)

IC		IC		IC	
IC102	G – 9	Q189	G – 4	D107	D – 2
IC103	G – 8	Q191	B – 2	D121	E – 4
IC104	E – 9	Q193	B – 1	D122	E – 4
IC105	G – 6	Q196	B – 2	D123	C – 4
IC106	F – 2	Q197	B – 2	D128	E – 1
IC107	E – 2	Q198	A – 3	D130	B – 13
IC108	E – 2	Q200	F – 8	D131	C – 14
IC109	C – 2	Q204	B – 9	D132	D – 14
IC110	F – 12	Q205	A – 9	D137	G – 11
IC111	E – 11	Q206	A – 8	D138	B – 13
IC113	G – 14	Q208	B – 3	D139	C – 13
IC114	G – 12	Q212	C – 11	D146	D – 12
IC115	E – 14	Q299	A – 11	D151	C – 5
IC116	D – 11	DIODE		D152	B – 4
IC117	F – 6			D153	B – 4
IC118	F – 5			D154	B – 13
IC119	F – 4			D156	C – 13
IC120	C – 4			D157	A – 13
IC121	D – 5			D162	B – 11
IC122	D – 5			D188	C – 9
IC123	D – 4			D191	C – 1
IC125	C – 12			D342	D – 12
IC126	C – 12			D343	H – 2
IC127	C – 12			D344	F – 8
IC128	E – 13			D345	A – 14
IC129	B – 4			D346	B – 14
TRANSISTOR				D347	C – 14
Q101	F – 6			D348	B – 14
Q104	G – 10			D349	C – 14
Q109	A – 12			D350	D – 14
Q115	C – 1			D390	D – 1
Q119	F – 12			D393	G – 3
Q121	E – 12				
Q124	F – 11				
Q129	G – 3				
Q132	C – 5				
Q136	F – 6				
Q137	F – 5				
Q138	F – 5				
Q141	C – 6				
Q150	G – 8				
Q164	B – 12				
Q166	D – 12				
Q171	F – 9				
Q176	F – 9				

- ▒▒▒ : Pattern from the side which enables seeing.
- ▒▒▒ : Pattern of the rear side.

SONY SP-00151/ DRUCK38

B Board (Component Side)



IC		Q189	G – 4
		Q191	B – 2
IC102	G – 9	Q193	B – 1
IC103	G – 8	Q196	B – 2
IC104	E – 9	Q197	B – 2
IC105	G – 6	Q198	A – 3
IC106	F – 2	Q200	F – 8
IC107	E – 2	Q204	B – 9
IC108	E – 2	Q205	A – 9
IC109	C – 2	Q206	A – 8
IC110	F – 12	Q208	B – 3
IC111	E – 11	Q212	C – 11
IC113	G – 14	Q299	A – 11
IC114	G – 12		
IC115	E – 14	DIODE	
IC116	D – 11		
IC117	F – 6	D107	D – 2
IC118	F – 5	D121	E – 4
IC119	F – 4	D122	E – 4
IC120	C – 4	D123	C – 4
IC121	D – 5	D128	E – 1
IC122	D – 5	D130	B – 13
IC123	D – 4	D131	C – 14
IC125	C – 12	D132	D – 14
IC126	C – 12	D137	G – 11
IC127	C – 12	D138	B – 13
IC128	E – 13	D139	C – 13
IC129	B – 4	D146	D – 12
		D151	C – 5
TRANSISTOR		D152	B – 4
		D153	B – 4
Q101	F – 6	D154	B – 13
Q104	G – 10	D156	C – 13
Q109	A – 12	D157	A – 13
Q115	C – 1	D162	B – 11
Q119	F – 12	D188	C – 9
Q121	E – 12	D191	C – 1
Q124	F – 11	D342	D – 12
Q129	G – 3	D343	H – 2
Q132	C – 5	D344	F – 8
Q136	F – 6	D345	A – 14
Q137	F – 5	D346	B – 14
Q138	F – 5	D347	C – 14
Q141	C – 6	D348	B – 14
Q150	G – 8	D349	C – 14
Q164	B – 12	D350	D – 14
Q166	D – 12	D390	D – 1
Q171	F – 9	D393	G – 3
Q176	F – 9		

– B Board – – Conductor Side –



- ▒▒▒ : Pattern from the side which enables seeing.
- ▒▒▒ : Pattern of the rear side.

r Side –



B Board (Conductor Side)

IC		Q174	C – 4	VARIABLE RESISTOR	
IC112	G – 3	Q175	C – 4	RV101	G – 15
IIC124	C – 7	Q177	A – 4	RV102	G – 14
		Q179	A – 4	RV103	E – 4
TRANSISTOR		Q190	C – 12	RV104	F – 4
		Q192	B – 14	RV105	H – 5
Q102	G – 10	Q194	B – 15	RV106	H – 4
Q103	E – 9	Q195	B – 14	RV107	G – 5
Q106	F – 10	Q199	A – 15	RV108	D – 2
Q107	E – 7	Q201	C – 7	RV109	F – 1
Q108	E – 7	Q202	C – 8	RV110	E – 1
Q112	D – 14	Q203	C – 8	RV111	D – 2
Q113	D – 14	Q210	B – 2	RV112	E – 2
Q114	D – 15	Q211	C – 2	RV113	F – 3
Q116	E – 15			RV114	E – 3
Q117	F – 15	DIODE		RV115	A – 10
Q118	E – 4			RV116	B – 11
Q120	F – 4	D104	F – 7	RV118	B – 12
Q122	F – 4	D105	G – 8	RV119	A – 12
Q123	F – 5	D106	D – 14	RV120	A – 11
Q125	H – 2	D108	E – 14	RV121	A – 11
Q126	G – 3	D109	E – 14	RV122	A – 10
Q127	H – 4	D110	F – 14	RV123	B – 8
Q128	H – 3	D111	F – 15	RV124	B – 5
Q130	G – 4	D112	C – 15	RV125	A – 5
Q131	G – 2	D113	C – 14	RV205	B – 11
Q133	G – 3	D117	E – 14		
Q134	F – 3	D120	H – 3		
Q135	F – 3	D125	A – 10		
Q139	F – 12	D126	B – 10		
Q140	E – 11	D127	F – 13		
Q142	C – 10	D129	H – 2		
Q143	C – 11	D133	B – 6		
Q144	A – 7	D134	C – 6		
Q145	C – 7	D135	C – 6		
Q146	B – 3	D136	D – 3		
Q147	D – 3	D144	D – 4		
Q148	A – 2	D145	D – 4		
Q149	B – 2	D147	A – 5		
Q151	B – 2	D148	B – 3		
Q152	B – 2	D149	B – 2		
Q153	C – 7	D150	D – 3		
Q154	C – 2	D155	B – 3		
Q155	C – 2	D158	B – 3		
Q157	B – 3	D159	C – 2		
Q158	B – 3	D160	D – 12		
Q159	C – 3	D161	D – 12		
Q160	A – 4	D170	G – 13		
Q161	C – 3	D185	E – 14		
Q165	D – 4	D186	F – 8		
Q167	C – 5	D187	G – 14		
Q168	C – 5	D285	E – 11		
Q170	C – 4	D289	B – 8		
Q172	C – 4	D341	B – 14		
Q173	D – 4	D1382	D – 12		

- ▒▒▒ : Pattern from the side which enables seeing.
- ▒▒▒ : Pattern of the rear side.


B (1/2)
(SIGNAL PROCESS)
CN102 3P WHT :S-MICRO
TO GND (REAR CHASSIS)
CN101 13P
TO QA BOARD CN401
Y/C-H
Y/C-C-IN
SYNC
EX-SYNC-H/TALLY
R
G
B
RGB/COMP
RGB/LINE
VOL
12V
GND
Y/VIDEO
HV-DLY
BL-ONLY/EXT-H
COMB FILTER
CFM101 CFB-2
IC101 MM1148XF SECAM-INPUT-SW
IC102 MM1149XF Y-SW
IC103 MM1149XF BPF-SW
IC104 MM1149XF Y-DLY-SW
IC105 MM1148XF SYNC-SIG-SW
IC106 MC14538BF H-BLK-GEN
IC107 XRU4538BF NOT-GATE
IC108 CLAMP-PULSE-SW
IC109 SECAM-SW
IC110 XRU4053BF SYSTEM-SW
IC111 SYSTEM-SW
IC112 LM7805CT 5V-REG
IC113 MSI279FP CHROMA-DEMOD
IC114 SYSTEM-SW
IC115 SYSTEM-SW
IC116 SYSTEM-SW
IC117 NJM2245M B/B-Y-SW
IC118 NJM2245M G/Y-SW
IC119 NJM2245M G/Y-SW
IC120 KRU4066BF SAMPLE
IC121 XRU4053BF BLACK-INSER
IC122 LM358BR HOLD
IC123 LM358BR HOLD-ERILER-10
CTR101 TRAP
CTR102 TRAP
BPF101 BPF3.58
BPF102 4.43 BPF
3.58 BPF
4.43 BPF
Q101 2SC2412K VIDEO-IN-BUFF-1
Q102 2SC2412K VIDEO-IN-BUFF-2
Q103 2SC2412K SY-REG
Q104 MA110 B/Y-SW
Q105 MA110 SLICER1
Q106 2SC2412K SYNC-SIG-BUFF
Q107 2SC2412K Y-AMP-1
Q108 2SA1037K Y-AMP-2
Q109 2SC2412K Y-AMP-3
Q110 2SC2412K Y-AMP-4
Q111 2SC2412K Y-AMP-5
Q112 2SC2412K SYNC-BUFF
Q113 2SA1037K V-SYNC-SEP-2
Q114 2SA1037K V-SYNC-SEP-1
Q115 2SC2412K V-SYNC-SEP-1
Q116 2SA1037K INSERT-PULSE-SW
Q117 2SA1037K PAL R-Y-BUFF
Q118 2SC2412K R-Y-EQ
Q119 2SA1037K R-Y-BUFF2
Q120 2SA1037K PAL B-Y-BUFF
Q121 2SC2412K B-Y-EQ
Q122 2SA1037K B-Y-BUFF2
Q123 2SC2412K B-Y-EQ
Q124 2SA1037K G-Y-BUFF2
Q125 2SC2412K G-Y-EQ
Q126 BTC144EK PAL/M-SW
Q127 2SA1037K R-Y-BUFF1
Q128 2SA1037K B-Y-BUFF1
Q129 2SA1037K G-Y-BUFF1
Q130 2SA1037K G-Y-BUFF2
Q131 2SA1037K MUTE-SW
Q132 2SA1037K INSERT-PULSE-SW
Q133 MA110 SW10
Q134 MA110 SW9
Q135 MA110 SW8
Q136 MA110 SW5
Q137 MA110 SW6
Q138 MA110 SW4
Q139 MA110 SW3
Q140 MA110 SW2
Q141 MA110 SW1
Q142 MA110 H-BLK-SW1
Q143 MA110 HV-BL-SW2
Q144 MA110 SECAM-SW4
Q145 MA110 SECAM-SW3
Q146 MA110 PULSE-SW
Q147 MA110 LEVEL-SHIFT3
Q148 MA110 LEVEL-SHIFT2
Q149 MA110 LEVEL-SHIFT1
Q150 2SC2412K BPF-SW-BUFF
Q151 MA110 PROTECT1
Q152 MA110 B/W-SW1
Q153 MA110 B/W-SW2
Q154 MA110 SW7
Q155 MA110 SW11
Q156 MA110 SW12
Q157 MA110 SW13
Q158 MA110 SW14
Q159 MA110 SW15
Q160 MA110 SW16
Q161 MA110 SW17
Q162 MA110 SW18
Q163 MA110 SW19
Q164 MA110 SW20
Q165 MA110 SW21
Q166 MA110 SW22
Q167 MA110 SW23
Q168 MA110 SW24
Q169 MA110 SW25
Q170 MA110 SW26
Q171 MA110 SW27
Q172 MA110 SW28
Q173 MA110 SW29
Q174 MA110 SW30
Q175 MA110 SW31
Q176 MA110 SW32
Q177 MA110 SW33
Q178 MA110 SW34
Q179 MA110 SW35
Q180 MA110 SW36
Q181 MA110 SW37
Q182 MA110 SW38
Q183 MA110 SW39
Q184 MA110 SW40
Q185 MA110 SW41
Q186 MA110 SECAM-SW43/35B-SW
Q187 MA110 LEVEL-SHIFT1
Q188 MA110 PROTECT2
Q189 MA110 SW42
Q190 2SA1037K MUTE-SW
Q191 MA110 SW43
Q192 MA110 SW44
Q193 MA110 SW45
Q194 MA110 SW46
Q195 MA110 SW47
Q196 MA110 B/Y-BUFF1
Q197 MA110 SW48
Q198 MA110 SW49
Q199 MA110 SW50
Q200 BTA144SK SECAM-SW2
Q201 2SC2412K PULSE-SW
Q202 2SC2412K VIDEO-IN-BUFF-1
Q203 2SC2412K VIDEO-IN-BUFF-2
D101 MA110 SLICER1
D102 MA110 SLICER2
D103 MA110 V/C SW
D104 MA110 B/W-SW
D105 MA110 SW1
D106 MA110 SW2
D107 MA110 SW3
D108 MA110 SW4
D109 MA110 SW5
D110 MA110 SW6
D111 MA110 HV-BL-SW2
D112 MA110 SW8
D113 MA110 SW9
D114 MA110 SW10
D115 MA110 SW11
D116 MA110 SW12
D117 MA110 SW13
D118 MA110 SW14
D119 MA110 SW15
D120 MA110 SW16
D121 MA110 SW17
D122 MA110 SW18
D123 MA110 SW19
D124 MA110 SW20
D125 MA110 SW21
D126 MA110 SW22
D127 MA110 SW23
D128 MA110 SW24
D129 MA110 SW25
D130 MA110 SW26
D131 MA110 SW27
D132 MA110 SW28
D133 MA110 SW29
D134 MA110 SW30
D135 MA110 SW31
D136 MA110 SW32
D137 MA110 SW33
D138 MA110 SW34
D139 MA110 SW35
D140 MA110 SW36
D141 MA110 SW37
D142 MA110 SW38
D143 MA110 SW39
D144 MA110 SW40
D145 MA110 SW41
D146 MA110 SW42
D147 MA110 SW43
D148 MA110 SW44
D149 MA110 SW45
D150 MA110 SW46
D151 MA110 SW47
D152 MA110 SW48
D153 MA110 SW49
D154 MA110 SW50
D155 MA110 SECAM-SW4
D156 MA110 SECAM-SW3
D157 MA110 PULSE-SW
D158 MA110 LEVEL-SHIFT3
D159 MA110 LEVEL-SHIFT2
D160 MA110 LEVEL-SHIFT1
D161 MA110 PROTECT1
D162 MA110 PROTECT2
D163 MA110 B/W-SW1
D164 MA110 B/W-SW2
D165 MA110 SECAM-SW2
D166 MA110 SECAM-SW1
D167 MA110 SECAM-SW43/35B-SW
D168 MA110 SECAM-SW43/35B-SW
D169 MA110 SECAM-SW43/35B-SW
D170 MA110 SECAM-SW43/35B-SW
D171 MA110 SECAM-SW43/35B-SW
D172 MA110 SECAM-SW43/35B-SW
D173 MA110 SECAM-SW43/35B-SW
D174 MA110 SECAM-SW43/35B-SW
D175 MA110 SECAM-SW43/35B-SW
D176 MA110 SECAM-SW43/35B-SW
D177 MA110 SECAM-SW43/35B-SW
D178 MA110 SECAM-SW43/35B-SW
D179 MA110 SECAM-SW43/35B-SW


15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
A
B
C
D
E
F
G
H
I
J
VOL
A-H/B-L
RGB, COMP
CLP-2
EXT-H
PULSE-2
BLUE-L
RGB-H
B-Y/B
R-Y/R
Y/C
MUTE
UNDER-H
P-LED
CN108 3P WHT S-MICRO
TALLY
NC
GND
TO X BOARD CN21
12V
B/H
HV-DL-L
CLP-H
HV-DL-H
HVE
ABL
V-P
V-BLK
H-BLK
120V
CN104 12P WHT
120V
HV-DL
U/SW PULSE1
POWER-LED
GND
ABL
H-BLK
V-BLK
V-P
COMP-SYNC
50/60
12V
TO D BOARD CN502
CN103 12P
DLY-H-P
BCP
GND
R-Y OUT
B-Y OUT
C-IN
12V
LUM-OUT
SECAM
(COM)DL-IN
(SIG)DL-IN
TO S BOARD CN1101
IC109 XRU4077BF EX-OR
IC120 XRU4044BF SAMPLE
IC12 XRU4053BF BLACK-INSERT
IC123 M35080R HOLD-KILLER-10
IC111 XRU4053BF SYSTEM-SW2
IC115 XRU4052BF SYSTEM-SW3
IC128 LM3508R PAL-60-10
Q115 2SC2412K Y-SYNC-SW
Q116 2SC2412K A/B-SW
Q117 MA110 RGB/COMP-SW1
Q118 MA151WA SW7 B/W-SW
Q119 MA110 SECAM-SW5
Q132 2SA1037K INSERT-PULSE-SW
Q141 2SC2412K B/B-Y-BUFF2
Q142 2SC2412K R/R-Y-BUFF2
Q143 2SC2412K G/Y-BUFF2
Q191 2SC2412K SYNC-CHIP-CLAMP1
Q193 2SC2412K SYNC-CHIP-CLAMP2
Q194 2SC2412K CLAMP-REF
Q189 2SC2412K CLAMP-BUFF-1
Q195 2SA1037K CLAMP-BUFF-2
Q196 2SC2412K AMP-1
Q197 2SA1037K AMP-2
Q198 2SA1037K BUFF
Q199 2SA1037K SYNC-SEP
Q208 2SA1037K SLICER2
Q133 2SC2412K 14.3-SW
Q134 DTC144EC SYSTEM-SW4
Q135 2SC2412K 17.7-SW
Q343 MA151WA PAL-60-1
Q341 MA110 SW1
D343 MA157 PROTECT2
SEP101 PAL U/V
X102 17.7MHz
X101 14.3MHz
12V
5V
BRP WIDTH
SECAM SW IN
SYNC IN
VCC
GND
COM
LUM
SECAM
SYNC


B (2/2)
(SIGNAL PROCESS)
TO H BOARD CN001
TO H BOARD CN002
TO C BOARD CN701
CN107 13P
CN106 8P
CN105 6P
IC124 CXA1478S RGB-MATRIX
IC125 XRU4066BF BLACK-SAMPLING
IC116 XRU4066BF H-BLK-SW2
IC129 LM358DR ON/OFF-MUTE
IC127 XRU4066BF
Q153 2SC2412K BLACK-SLICE-REF
Q151 2SA1037K REF-PULSE-SW4
Q154 2SA1037K REF-PULSE-SW5
Q161 2SA1037K REF-PULSE-BUFF
Q144 2SC2412K BG-SW3
Q147 2SC2551R V-GATE-SW2
Q145 2SC2412K RGB-SW
Q179 DTC144EK V-BLK-SW1
Q164 DTC144EK V-BLK-SW
Q189 IMX111Q
Q177 2SC2412K BLANKING3
Q175 2SA1037K B-BUFF3
Q176 2SA1037K G-BUFF3
Q173 2SA1037K R-BUFF3
Q168 2SA1037K B-BUFF2
Q166 2SA1037K G-BUFF2
Q165 2SA1037K R-BUFF2
Q205 2SA1037K R-Y-BUFF
Q204 2SA1037K B-Y-BUFF
Q170 2SC2412K BL-ONLY-R-Y-BUFF
Q212 2SB709 BL-ONLY-SW2
Q209 2SC2551O R-E.F.1
Q210 2SC2551O R-E.F.2
Q211 2SC2551O R-E.F.3
Q155 2SA1091O R-E.F.
Q152 2SA1037K SW22
Q147 MA110 V-BLK-SW2
Q144 MA110 BLANKING4
Q145 MA110 BLANKING1
Q151 MA110 SW21
Q188 MA157 SW16
Q162 MA110 SW14
Q158 MA110 SW19
Q135 MA110 SLICER5
Q134 MA110 SLICER4
Q133 MA110 SLICER3
Q126 MA110 HV-BL-SW4
Q127 MA110 SW15
Q139 MA110
Q393 MA110 U/S-SW
Q28G MA110 RGB-SW
Q109 DTC144EC
Q130 MA157
Q131 MA157
Q132 MA157
Q135 MA157
Q136 MA157
Q137 MA157
Q138 MA157
Q139 MA157
Q140 MA157
Q141 MA157
Q142 MA157
Q143 MA157
Q150 MA157
Q156 MA157
Q157 MA157
Q158 MA157
Q159 MA157
Q160 MA157
Q169 MA157
Q171 MA157
Q172 MA157
Q174 MA157
Q178 MA157
Q180 MA157
Q181 MA157
Q182 MA157
Q183 MA157
Q184 MA157
Q185 MA157
Q186 MA157
Q187 MA157
Q190 MA157
Q191 MA157
Q192 MA157
Q193 MA157
Q194 MA157
Q195 MA157
Q196 MA157
Q197 MA157
Q198 MA157
Q199 MA157
Q200 MA157
Q201 MA157
Q202 MA157
Q203 MA157
Q206 MA157
Q207 MA157
Q208 MA157
Q213 MA157
Q214 MA157
Q215 MA157
Q216 MA157
Q217 MA157
Q218 MA157
Q219 MA157
Q220 MA157
Q221 MA157
Q222 MA157
Q223 MA157
Q224 MA157
Q225 MA157
Q226 MA157
Q227 MA157
Q228 MA157
Q229 MA157
Q230 MA157
Q231 MA157
Q232 MA157
Q233 MA157
Q234 MA157
Q235 MA157
Q236 MA157
Q237 MA157
Q238 MA157
Q239 MA157
Q240 MA157
Q241 MA157
Q242 MA157
Q243 MA157
Q244 MA157
Q245 MA157
Q246 MA157
Q247 MA157
Q248 MA157
Q249 MA157
Q250 MA157
Q251 MA157
Q252 MA157
Q253 MA157
Q254 MA157
Q255 MA157
Q256 MA157
Q257 MA157
Q258 MA157
Q259 MA157
Q260 MA157
Q261 MA157
Q262 MA157
Q263 MA157
Q264 MA157
Q265 MA157
Q266 MA157
Q267 MA157
Q268 MA157
Q269 MA157
Q270 MA157
Q271 MA157
Q272 MA157
Q273 MA157
Q274 MA157
Q275 MA157
Q276 MA157
Q277 MA157
Q278 MA157
Q279 MA157
Q280 MA157
Q281 MA157
Q282 MA157
Q283 MA157
Q284 MA157
Q285 MA157
Q286 MA157
Q287 MA157
Q288 MA157
Q289 MA157
Q290 MA157
Q291 MA157
Q292 MA157
Q293 MA157
Q294 MA157
Q295 MA157
Q296 MA157
Q297 MA157
Q298 MA157
Q299 MA157
Q300 MA157
Q301 MA157
Q302 MA157
Q303 MA157
Q304 MA157
Q305 MA157
Q306 MA157
Q307 MA157
Q308 MA157
Q309 MA157
Q310 MA157
Q311 MA157
Q312 MA157
Q313 MA157
Q314 MA157
Q315 MA157
Q316 MA157
Q317 MA157
Q318 MA157
Q319 MA157
Q320 MA157
Q321 MA157
Q322 MA157
Q323 MA157
Q324 MA157
Q325 MA157
Q326 MA157
Q327 MA157
Q328 MA157
Q329 MA157
Q330 MA157
Q331 MA157
Q332 MA157
Q333 MA157
Q334 MA157
Q335 MA157
Q336 MA157
Q337 MA157
Q338 MA157
Q339 MA157
Q340 MA157
Q341 MA157
Q342 MA157
Q343 MA157
Q344 MA157
Q345 MA157
Q346 MA157
Q347 MA157
Q348 MA157
Q349 MA157
Q350 MA157
Q351 MA157
Q352 MA157
Q353 MA157
Q354 MA157
Q355 MA157
Q356 MA157
Q357 MA157
Q358 MA157
Q359 MA157
Q360 MA157
Q361 MA157
Q362 MA157
Q363 MA157
Q364 MA157
Q365 MA157
Q366 MA157
Q367 MA157
Q368 MA157
Q369 MA157
Q370 MA157
Q371 MA157
Q372 MA157
Q373 MA157
Q374 MA157
Q375 MA157
Q376 MA157
Q377 MA157
Q378 MA157
Q379 MA157
Q380 MA157
Q381 MA157
Q382 MA157
Q383 MA157
Q384 MA157
Q385 MA157
Q386 MA157
Q387 MA157
Q388 MA157
Q389 MA157
Q390 MA157
Q391 MA157
Q392 MA157
Q394 MA157
Q395 MA157
Q396 MA157
Q397 MA157
Q398 MA157
Q399 MA157
Q400 MA157
Q401 MA157
Q402 MA157
Q403 MA157
Q404 MA157
Q405 MA157
Q406 MA157
Q407 MA157
Q408 MA157
Q409 MA157
Q410 MA157
Q411 MA157
Q412 MA157
Q413 MA157
Q414 MA157
Q415 MA157
Q416 MA157
Q417 MA157
Q418 MA157
Q419 MA157
Q420 MA157
Q421 MA157
Q422 MA157
Q423 MA157
Q424 MA157
Q425 MA157
Q426 MA157
Q427 MA157
Q428 MA157
Q429 MA157
Q430 MA157
Q431 MA157
Q432 MA157
Q433 MA157
Q434 MA157
Q435 MA157
Q436 MA157
Q437 MA157
Q438 MA157
Q439 MA157
Q440 MA157
Q441 MA157
Q442 MA157
Q443 MA157
Q444 MA157
Q445 MA157
Q446 MA157
Q447 MA157
Q448 MA157
Q449 MA157
Q450 MA157
Q451 MA157
Q452 MA157
Q453 MA157
Q454 MA157
Q455 MA157
Q456 MA157
Q457 MA157
Q458 MA157
Q459 MA157
Q460 MA157
Q461 MA157
Q462 MA157
Q463 MA157
Q464 MA157
Q465 MA157
Q466 MA157
Q467 MA157
Q468 MA157
Q469 MA157
Q470 MA157
Q471 MA157
Q472 MA157
Q473 MA157
Q474 MA157
Q475 MA157
Q476 MA157
Q477 MA157
Q478 MA157
Q479 MA157
Q480 MA157
Q481 MA157
Q482 MA157
Q483 MA157
Q484 MA157
Q485 MA157
Q486 MA157
Q487 MA157
Q488 MA157
Q489 MA157
Q490 MA157
Q491 MA157
Q492 MA157
Q493 MA157
Q494 MA157
Q495 MA157
Q496 MA157
Q497 MA157
Q498 MA157
Q499 MA157
Q500 MA157
Q501 MA157
Q502 MA157
Q503 MA157
Q504 MA157
Q505 MA157
Q506 MA157
Q507 MA157
Q508 MA157
Q509 MA157
Q510 MA157
Q511 MA157
Q512 MA157
Q513 MA157
Q514 MA157
Q515 MA157
Q516 MA157
Q517 MA157
Q518 MA157
Q519 MA157
Q520 MA157
Q521 MA157
Q522 MA157
Q523 MA157
Q524 MA157
Q525 MA157
Q526 MA157
Q527 MA157
Q528 MA157
Q529 MA157
Q530 MA157
Q531 MA157
Q532 MA157
Q533 MA157
Q534 MA157
Q535 MA157
Q536 MA157
Q537 MA157
Q538 MA157
Q539 MA157
Q540 MA157
Q541 MA157
Q542 MA157
Q543 MA157
Q544 MA157
Q545 MA157
Q546 MA157
Q547 MA157
Q548 MA157
Q549 MA157
Q550 MA157
Q551 MA157
Q552 MA157
Q553 MA157
Q554 MA157
Q555 MA157
Q556 MA157
Q557 MA157
Q558 MA157
Q559 MA157
Q560 MA157
Q561 MA157
Q562 MA157
Q563 MA157
Q564 MA157
Q565 MA157
Q566 MA157
Q567 MA157
Q568 MA157
Q569 MA157
Q570 MA157
Q571 MA157
Q572 MA157
Q573 MA157
Q574 MA157
Q575 MA157
Q576 MA157
Q577 MA157
Q578 MA157
Q579 MA157
Q580 MA157
Q581 MA157
Q582 MA157
Q583 MA157
Q584 MA157
Q585 MA157
Q586 MA157
Q587 MA157
Q588 MA157
Q589 MA157
Q590 MA157
Q591 MA157
Q592 MA157
Q593 MA157
Q594 MA157
Q595 MA157
Q596 MA157
Q597 MA157
Q598 MA157
Q599 MA157
Q600 MA157
Q601 MA157
Q602 MA157
Q603 MA157
Q604 MA157
Q605 MA157
Q606 MA157
Q607 MA157
Q608 MA157
Q609 MA157
Q610 MA157
Q611 MA157
Q612 MA157
Q613 MA157
Q614 MA157
Q615 MA157
Q616 MA157
Q617 MA157
Q618 MA157
Q619 MA157
Q620 MA157
Q621 MA157
Q622 MA157
Q623 MA157
Q624 MA157
Q625 MA157
Q626 MA157
Q627 MA157
Q628 MA157
Q629 MA157
Q630 MA157
Q631 MA157
Q632 MA157
Q633 MA157
Q634 MA157
Q635 MA157
Q636 MA157
Q637 MA157
Q638 MA157
Q639 MA157
Q640 MA157
Q641 MA157
Q642 MA157
Q643 MA157
Q644 MA157
Q645 MA157
Q646 MA157
Q647 MA157
Q648 MA157
Q649 MA157
Q650 MA157
Q651 MA157
Q652 MA157
Q653 MA157
Q654 MA157
Q655 MA157
Q656 MA157
Q657 MA157
Q658 MA157
Q659 MA157
Q660 MA157
Q661 MA157
Q662 MA157
Q663 MA157
Q664 MA157
Q665 MA157
Q666 MA157
Q667 MA157
Q668 MA157
Q669 MA157
Q670 MA157
Q671 MA157
Q672 MA157
Q673 MA157
Q674 MA157
Q675 MA157
Q676 MA157
Q677 MA157
Q678 MA157
Q679 MA157
Q680 MA157
Q681 MA157
Q682 MA157
Q683 MA157
Q684 MA157
Q685 MA157
Q686 MA157
Q687 MA157
Q688 MA157
Q689 MA157
Q690 MA157
Q691 MA157
Q692 MA157
Q693 MA157
Q694 MA157
Q695 MA157
Q696 MA157
Q697 MA157
Q698 MA157
Q699 MA157
Q700 MA157
Q701 MA157
Q702 MA157
Q703 MA157
Q704 MA157
Q705 MA157
Q706 MA157
Q707 MA157
Q708 MA157
Q709 MA157
Q710 MA157
Q711 MA157
Q712 MA157
Q713 MA157
Q714 MA157
Q715 MA157
Q716 MA157
Q717 MA157
Q718 MA157
Q719 MA157
Q720 MA157
Q721 MA157
Q722 MA157
Q723 MA157
Q724 MA157
Q725 MA157
Q726 MA157
Q727 MA157
Q728 MA157
Q729 MA157
Q730 MA157
Q731 MA157
Q732 MA157
Q733 MA157
Q734 MA157
Q735 MA157
Q736 MA157
Q737 MA157
Q738 MA157
Q739 MA157
Q740 MA157
Q741 MA157
Q742 MA157
Q743 MA157
Q744 MA157
Q745 MA157
Q746 MA157
Q747 MA157
Q748 MA157
Q749 MA157
Q750 MA157
Q751 MA157
Q752 MA157
Q753 MA157
Q754 MA157
Q755 MA157
Q756 MA157
Q757 MA157
Q758 MA157
Q759 MA157
Q760 MA157
Q761 MA157
Q762 MA157
Q763 MA157
Q764 MA157
Q765 MA157
Q766 MA157
Q767 MA157
Q768 MA157
Q769 MA157
Q770 MA157
Q771 MA157
Q772 MA157
Q773 MA157
Q774 MA157
Q775 MA157
Q776 MA157
Q777 MA157
Q778 MA157
Q779 MA157
Q780 MA157
Q781 MA157
Q782 MA157
Q783 MA157
Q784 MA157
Q785 MA157
Q786 MA157
Q787 MA157
Q788 MA157
Q789 MA157
Q790 MA157
Q791 MA157
Q792 MA157
Q793 MA157
Q794 MA157
Q795 MA157
Q796 MA157
Q797 MA157
Q798 MA157
Q799 MA157
Q800 MA157
Q801 MA157
Q802 MA157
Q803 MA157
Q804 MA157
Q805 MA157
Q806 MA157
Q807 MA157
Q808 MA157
Q809 MA157
Q810 MA157
Q811 MA157
Q812 MA157
Q813 MA157
Q814 MA157
Q815 MA157
Q816 MA157
Q817 MA157
Q818 MA157
Q819 MA157
Q820 MA157
Q821 MA157
Q822 MA157
Q823 MA157
Q824 MA157
Q825 MA157
Q826 MA157
Q827 MA157
Q828 MA157
Q829 MA157
Q830 MA157
Q831 MA157
Q832 MA157
Q833 MA157
Q834 MA157
Q835 MA157
Q836 MA157
Q837 MA157
Q838 MA157
Q839 MA157
Q840 MA157
Q841 MA157
Q842 MA157
Q843 MA157
Q844 MA157
Q845 MA157
Q846 MA157
Q847 MA157
Q848 MA157
Q849 MA157
Q850 MA157
Q851 MA157
Q852 MA157
Q853 MA157
Q854 MA157
Q855 MA157
Q856 MA157
Q857 MA157
Q858 MA157
Q859 MA157
Q860 MA157
Q861 MA157
Q862 MA157
Q863 MA157
Q864 MA157
Q865 MA157
Q866 MA157
Q867 MA157
Q868 MA157
Q869 MA157
Q870 MA157
Q871 MA157
Q872 MA157
Q873 MA157
Q874 MA157
Q875 MA157
Q876 MA157
Q877 MA157
Q878 MA157
Q879 MA157
Q880 MA157
Q881 MA157
Q882 MA157
Q883 MA157
Q884 MA157
Q885 MA157
Q886 MA157
Q887 MA157
Q888 MA157
Q889 MA157
Q890 MA157
Q891 MA157
Q892 MA157
Q893 MA157
Q894 MA157
Q895 MA157
Q896 MA157
Q897 MA157
Q898 MA157
Q899 MA157
Q900 MA157
Q901 MA157
Q902 MA157
Q903 MA157
Q904 MA157
Q905 MA157
Q906 MA157
Q907 MA157
Q908 MA157
Q909 MA157
Q910 MA157
Q911 MA157
Q912 MA157
Q913 MA157
Q914 MA157
Q915 MA157
Q916 MA157
Q917 MA157
Q918 MA157
Q919 MA157
Q920 MA157
Q921 MA157
Q922 MA157
Q923 MA157
Q924 MA157
Q925 MA157
Q926 MA157
Q927 MA157
Q928 MA157
Q929 MA157
Q930 MA157
Q931 MA157
Q932 MA157
Q933 MA157
Q934 MA157
Q935 MA157
Q936 MA157
Q937 MA157
Q938 MA157
Q939 MA157
Q940 MA157
Q941 MA157
Q942 MA157
Q943 MA157
Q944 MA157
Q945 MA157
Q946 MA157
Q947 MA157
Q948 MA157
Q949 MA157
Q950 MA157
Q951 MA157
Q952 MA157
Q953 MA157
Q954 MA157
Q955 MA157
Q956 MA157
Q957 MA157
Q958 MA157
Q959 MA157
Q960 MA157
Q961 MA157
Q962 MA157
Q963 MA157
Q964 MA157
Q965 MA157
Q966 MA157
Q967 MA157
Q968 MA157
Q969 MA157
Q970 MA157
Q971 MA157
Q972 MA157
Q973 MA157
Q974 MA157
Q975 MA157
Q976 MA157
Q977 MA157
Q978 MA157
Q979 MA157
Q980 MA157
Q981 MA157
Q982 MA157
Q983 MA157
Q984 MA157
Q985 MA157
Q986 MA157
Q987 MA157
Q988 MA157
Q989 MA157
Q990 MA157
Q991 MA157
Q992 MA157
Q993 MA157
Q994 MA157
Q995 MA157
Q996 MA157
Q997 MA157
Q998 MA157
Q999 MA157
Q1000 MA157

— B Board —

< TRANSISTOR >

		PAL	SECAM	NTSC 3.58	NTSC 4.43	S (Y/C)	ANALOG RGB	COMPO-NENT
Q113	E	0.5	0.5	0.4	0.4	0.5	0.5	0.5
	B	1.0	1.0	0.9	0.9	0.9	0.9	1.0
Q115	E	11.2	9.3	0.0	10.6	0.0	0.0	0.0
	B	2.8	2.2	0.1	2.4	0.1	0.1	0.0
Q118	E	0.0	0.0	1.7	1.7	1.7	1.7	1.7
Q119	B	0.1	0.0	1.7	1.7	1.7	1.7	1.7
Q121	E	0.0	0.0	1.7	1.7	1.7	1.7	1.7
Q122	B	0.0	0.0	1.7	1.7	1.7	1.7	1.7
Q130	E	4.3	4.3	4.4	4.4	4.5	4.4	4.4
	B	3.7	3.7	3.8	3.8	3.9	3.8	3.8
Q132	E	2.3	2.3	2.4	2.3	2.4	2.4	2.4
	C	1.8	1.7	1.7	1.7	1.7	1.8	1.8
	B	2.7	2.6	2.6	2.7	2.8	2.7	2.8
Q146	C	116.7	114.4	110.4	113.2	113.7	114.3	114.1
Q147	E	117.9	115.6	111.6	114.5	115.0	115.5	115.4
	C	126.0	123.5	120.3	123.4	123.8	124.8	124.4
	B	119.8	119.5	110.5	118.4	118.2	114.2	114.2
Q148	C	86.1	84.9	91.2	83.4	82.6	82.5	82.2
	B	94.0	93.3	86.3	92.4	92.1	94.2	90.6
Q149	E	1.6	1.6	1.4	1.7	1.7	1.7	1.7
	C	86.1	84.9	91.2	83.4	82.7	82.5	82.5
Q151	E	90.7	91.4	98.0	87.9	87.0	86.5	86.4
	C	89.2	89.8	96.5	86.4	85.3	84.9	84.7
	B	92.1	92.7	100.2	89.5	92.4	90.5	88.9
Q152	E	86.1	86.0	92.6	82.6	82.9	82.6	82.7
	C	10.6	10.5	9.7	10.9	10.9	10.9	11.0
Q154	B	92.5	92.9	99.8	90.1	88.7	90.4	89.2
Q155	B	86.3	86.5	95.7	85.7	83.9	84.6	83.9
Q157	E	82.4	81.1	87.5	79.9	79.9	80.8	79.4
	B	86.0	84.8	91.2	84.4	82.7	82.5	82.1
Q158	E	1.6	1.5	1.3	1.6	1.6	1.7	1.7
	B	2.1	2.0	1.8	2.1	2.2	2.2	2.2
Q159	E	1.6	1.6	1.3	1.6	1.7	1.7	1.7
	B	2.2	2.1	1.5	2.1	2.2	2.2	2.2
Q163	E	0.2	0.6	2.7	0.5	−0.5	−0.7	−0.6
Q166	B	0.9	0.9	0.6	1.0	1.0	1.0	1.0
Q168	C	2.1	2.0	1.6	2.1	2.2	2.1	2.2
Q170	B	2.3	2.3	2.1	2.4	2.4	2.4	2.4
Q172	B	2.2	2.1	1.9	2.2	2.3	2.2	2.3
Q173	B	1.7	1.6	1.4	1.7	1.7	1.7	1.7
Q174	E	2.1	2.0	1.8	2.1	2.2	2.2	2.2
	B	1.6	1.5	1.3	1.6	1.6	1.7	1.7
Q178	B	6.2	6.3	6.2	6.3	6.1	6.2	6.2
Q209	E	83.4	81.5	87.9	80.3	80.4	80.4	79.8
	C	115.8	113.2	110.7	113.2	113.8	114.5	114.2
	B	87.8	86.4	92.8	85.0	84.3	84.2	83.8
Q210	E	86.5	86.3	93.1	83.0	83.3	83.0	82.8
	C	116.5	114.2	111.5	113.9	114.5	115.1	114.9
Q211	C	115.9	113.6	111.7	113.3	113.8	114.5	114.3

< IC >

		PAL	SECAM	NTSC 3.58	NTSC 4.43	S (Y/C)	ANALOG RGB	COMPO-NENT
IC102	②	6.6	6.8	0.0	6.6	0.0	0.0	0.0
IC106	②	0.2	0.1	0.1	0.1	0.1	0.1	0.2
	④	1.8	1.7	1.7	1.7	1.7	1.8	1.8
IC107	②	10.7	10.7	10.6	10.6	10.6	10.6	10.6
	⑪	1.2	10.7	0.0	0.0	0.0	0.0	0.0
IC108	⑪	9.7	0.4	9.7	9.6	9.6	1.1	9.6
IC109	②	11.3	11.3	0.0	10.6	0.0	0.0	0.0
	③	11.3	11.4	0.0	11.3	0.0	0.0	0.0
	④	11.7	0.0	0.0	11.7	0.0	0.0	0.0
	⑤	11.0	11.1	0.0	11.0	0.0	0.0	0.0
IC110	④	2.1	2.2	2.5	2.5	2.5	2.5	2.5
	⑩	11.3	11.3	0.0	11.3	0.0	0.0	0.0
	⑪	11.3	11.3	0.0	0.0	0.0	0.0	0.0
	⑫	0.8	0.8	2.5	2.5	2.5	2.5	2.5
	⑭	1.7	1.7	2.5	2.6	2.5	2.5	2.5
IC113	④	2.7	1.1	2.6	2.6	2.6	1.1	1.1
	⑦	4.2	4.3	4.2	4.3	4.3	4.8	4.8
	⑪	3.0	2.9	2.8	3.0	2.8	2.9	2.9
	⑮	2.2	2.5	2.9	2.2	1.9	2.8	2.8
IC114	⑩	11.4	11.3	0.0	0.0	0.0	0.0	0.0
	⑬	3.7	3.7	3.8	3.8	3.8	3.9	3.9
IC115	③	1.2	1.1	0.6	0.7	0.7	0.6	0.6
	⑬	3.5	3.5	3.4	2.8	3.4	3.4	3.4
IC116	②	0.0	0.0	1.0	1.1	1.1	1.3	1.1
IC120	③	5.5	5.6	5.6	5.6	5.6	5.6	5.6
	④	5.5	5.6	5.6	5.6	5.6	5.0	5.6
IC121	⑬	5.3	5.3	5.4	5.2	5.2	5.1	5.1
	⑭	5.6	5.7	5.6	5.6	5.7	5.7	5.7
	⑮	5.6	5.7	5.6	5.6	5.7	5.7	5.6
IC122	②	5.3	5.3	5.4	5.2	5.2	5.1	5.1
	③	5.3	5.3	5.4	5.2	5.2	5.1	5.1
IC124	⑱	0.1	0.1	0.2	0.2	0.2	0.2	0.2
IC125	④	1.4	1.4	1.3	1.4	1.5	1.5	1.5
IC126	②	1.6	1.5	1.3	1.6	1.6	1.7	1.6
	⑤	1.6	1.5	1.3	1.6	1.6	1.6	1.7
	⑭	1.7	1.8	1.4	1.7	1.7	1.6	1.7
IC127	①	3.0	2.9	2.8	3.0	3.1	3.0	3.0
	②	1.4	1.4	1.3	1.5	1.5	1.5	1.5
	⑦	2.1	2.7	2.4	2.8	2.8	2.8	2.8

• B BOARD WAVEFORMS







NOTE:

The compone
shading and r
cal for safety
Replace only
specified.

REF.NO.	PART
	*A-11
BPF101	1-23
BPF102	1-23
C101	1-12
C102	1-16
C103	1-12
C104	1-16
C105	1-16
C106	1-12
C107	1-16
C108	1-12
C109	1-12
C110	1-12
C111	1-16
C112	1-16
C113	1-16
C114	1-12
C115	1-16
C116	1-12
C117	1-12
C118	1-12
C119	1-16
C120	1-12
C121	1-12
C122	1-12
C123	1-16
C124	1-16
C125	1-12
C126	1-16
C127	1-12
C128	1-12
C129	1-16
C130	1-16
C131	1-16
C132	1-12
C133	1-12
C134	1-16
C135	1-16
C137	1-16
C138	1-12
C139	1-16
C140	1-16
C141	1-16
C142	1-16

ONY SP-00151/ DRUCK45



SECTION 2
ELECTRICAL PARTS LIST

B

NOTE:

The components identified by shading and mark ⚠ are critical for safety.
Replace only with part number specified.

- Items marked " * " are not stocked since they are seldom required for routine service. Some delay should be anticipated when ordering these items.
- All variable and adjustable resistors have characteristic curve B, unless otherwise noted.

RESISTORS
- All resistors are in ohms
- F : nonflammable

When indicating parts by reference number, please include the board name.

CAPACITORS
- MF : μF, PF : μμF

COILS
- MMH : mH, UH : μH

- The components identified by ⊠ in this manual have been carefully factory-selected for each set in order to satisfy regulations regarding X-ray radiation. Should replacement be required, replace only with the value originally used.

REF.NO.	PART NO.	DESCRIPTION		REMARK
	*A-1135-716-A	B BOARD, COMPLETE		
		**********		
		<FILTER>		
BPF101	1-236-363-11	FILTER, BAND PASS		
BPF102	1-236-364-11	FILTER, BAND PASS		
		<CAPACITOR>		
C101	1-124-589-11	ELECT 47MF	20% 16V	
C102	1-163-031-11	CERAMIC CHIP 0.01MF	50V	
C103	1-126-157-11	ELECT 10MF	20% 16V	
C104	1-163-031-11	CERAMIC CHIP 0.01MF	50V	
C105	1-163-031-11	CERAMIC CHIP 0.01MF	50V	
C106	1-124-477-11	ELECT 47MF	20% 16V	
C107	1-163-031-11	CERAMIC CHIP 0.01MF	50V	
C108	1-124-477-11	ELECT 47MF	20% 16V	
C109	1-124-477-11	ELECT 47MF	20% 16V	
C110	1-124-120-11	ELECT 220MF	20% 16V	
C111	1-163-031-11	CERAMIC CHIP 0.01MF	50V	
C112	1-163-031-11	CERAMIC CHIP 0.01MF	50V	
C113	1-163-031-11	CERAMIC CHIP 0.01MF	50V	
C114	1-124-477-11	ELECT 47MF	20% 16V	
C115	1-163-031-11	CERAMIC CHIP 0.01MF	50V	
C116	1-124-589-11	ELECT 47MF	20% 16V	
C117	1-126-154-11	ELECT 47MF	20% 6.3V	
C118	1-126-154-11	ELECT 47MF	20% 6.3V	
C119	1-163-031-11	CERAMIC CHIP 0.01MF	50V	
C120	1-126-154-11	ELECT 47MF	20% 6.3V	
C121	1-126-154-11	ELECT 47MF	20% 6.3V	
C122	1-124-477-11	ELECT 47MF	20% 16V	
C123	1-163-031-11	CERAMIC CHIP 0.01MF	50V	
C124	1-163-031-11	CERAMIC CHIP 0.01MF	50V	
C125	1-126-154-11	ELECT 47MF	20% 6.3V	
C126	1-163-031-11	CERAMIC CHIP 0.01MF	50V	
C127	1-126-154-11	ELECT 47MF	20% 6.3V	
C128	1-126-154-11	ELECT 47MF	20% 6.3V	
C129	1-163-031-11	CERAMIC CHIP 0.01MF	50V	
C130	1-163-031-11	CERAMIC CHIP 0.01MF	50V	
C131	1-163-031-11	CERAMIC CHIP 0.01MF	50V	
C132	1-124-589-11	ELECT 47MF	20% 16V	
C133	1-124-589-11	ELECT 47MF	20% 16V	
C134	1-163-275-11	CERAMIC CHIP 0.001MF	5% 50V	
C135	1-163-113-00	CERAMIC CHIP 68PF	5% 50V	
C137	1-163-115-00	CERAMIC CHIP 82PF	5% 50V	
C138	1-124-589-11	ELECT 47MF	20% 16V	
C139	1-163-031-11	CERAMIC CHIP 0.01MF	50V	
C140	1-163-205-00	CERAMIC CHIP 0.001MF	5% 50V	
C141	1-163-141-00	CERAMIC CHIP 0.001MF	5% 50V	
C142	1-163-031-11	CERAMIC CHIP 0.01MF	50V	
C143	1-163-121-00	CERAMIC CHIP 150PF	5% 50V	
C144	1-163-101-00	CERAMIC CHIP 22PF	5% 50V	
C145	1-163-131-00	CERAMIC CHIP 390PF	5% 50V	
C146	1-126-157-11	ELECT 10MF	20% 16V	
C147	1-164-232-11	CERAMIC CHIP 0.01MF	10% 50V	
C148	1-126-160-11	ELECT 1MF	20% 50V	
C149	1-163-022-00	CERAMIC CHIP 0.012MF	10% 50V	
C150	1-124-589-11	ELECT 47MF	20% 16V	
C151	1-163-131-00	CERAMIC CHIP 390PF	5% 50V	
C152	1-163-101-00	CERAMIC CHIP 22PF	5% 50V	
C153	1-163-125-00	CERAMIC CHIP 220PF	5% 50V	
C154	1-163-031-11	CERAMIC CHIP 0.01MF	50V	
C155	1-163-133-00	CERAMIC CHIP 470PF	5% 50V	
C156	1-164-299-11	CERAMIC CHIP 0.22MF	10% 25V	
C157	1-163-229-11	CERAMIC CHIP 12PF	5% 50V	
C158	1-124-477-11	ELECT 47MF	20% 16V	
C159	1-163-229-11	CERAMIC CHIP 12PF	5% 50V	
C160	1-163-229-11	CERAMIC CHIP 12PF	5% 50V	
C161	1-124-902-00	ELECT 0.47MF	20% 50V	
C162	1-124-903-11	ELECT 1MF	20% 50V	
C163	1-163-809-11	CERAMIC CHIP 0.047MF	10% 25V	
C164	1-163-809-11	CERAMIC CHIP 0.047MF	10% 25V	
C165	1-163-009-11	CERAMIC CHIP 0.001MF	10% 50V	
C166	1-163-031-11	CERAMIC CHIP 0.01MF	50V	
C167	1-124-477-11	ELECT 47MF	20% 16V	
C168	1-163-031-11	CERAMIC CHIP 0.01MF	50V	
C169	1-163-243-11	CERAMIC CHIP 47PF	5% 50V	
C170	1-163-129-00	CERAMIC CHIP 330PF	5% 50V	
C171	1-163-243-11	CERAMIC CHIP 47PF	5% 50V	
C172	1-163-129-00	CERAMIC CHIP 330PF	5% 50V	
C173	1-124-589-11	ELECT 47MF	20% 16V	
C174	1-124-477-11	ELECT 47MF	20% 16V	
C175	1-108-792-11	MYLAR 0.001MF	5% 50V	
C176	1-163-031-11	CERAMIC CHIP 0.01MF	50V	
C177	1-163-031-11	CERAMIC CHIP 0.01MF	50V	
C178	1-163-031-11	CERAMIC CHIP 0.01MF	50V	
C179	1-126-160-11	ELECT 1MF	20% 50V	
C180	1-163-031-11	CERAMIC CHIP 0.01MF	50V	
C181	1-126-154-11	ELECT 47MF	20% 6.3V	
C182	1-126-163-11	ELECT 4.7MF	20% 16V	
C183	1-164-232-11	CERAMIC CHIP 0.01MF	10% 50V	
C184	1-163-031-11	CERAMIC CHIP 0.01MF	50V	
C185	1-163-031-11	CERAMIC CHIP 0.01MF	50V	
C186	1-163-099-00	CERAMIC CHIP 18PF	5% 50V	
C187	1-163-031-11	CERAMIC CHIP 0.01MF	50V	
C188	1-163-031-11	CERAMIC CHIP 0.01MF	50V	
C189	1-163-035-00	CERAMIC CHIP 0.047MF	50V	
C190	1-163-121-00	CERAMIC CHIP 150PF	5% 50V	
C191	1-163-031-11	CERAMIC CHIP 0.01MF	50V	
C192	1-163-031-11	CERAMIC CHIP 0.01MF	50V	
C193	1-124-589-11	ELECT 47MF	20% 16V	

B

REF.NO.	PART NO.	DESCRIPTION			REMARK
C194	1-124-589-11	ELECT	47MF	20%	16V
C195	1-124-589-11	ELECT	47MF	20%	16V
C196	1-124-589-11	ELECT	47MF	20%	16V
C197	1-124-589-11	ELECT	47MF	20%	16V
C198	1-124-589-11	ELECT	47MF	20%	16V
C199	1-124-589-11	ELECT	47MF	20%	16V
C202	1-124-589-11	ELECT	47MF	20%	16V
C203	1-124-589-11	ELECT	47MF	20%	16V
C204	1-124-589-11	ELECT	47MF	20%	16V
C205	1-163-101-00	CERAMIC CHIP	22PF	5%	50V
C206	1-164-298-11	CERAMIC CHIP	0.15MF	10%	25V
C207	1-164-298-11	CERAMIC CHIP	0.15MF	10%	25V
C208	1-163-101-00	CERAMIC CHIP	22PF	5%	50V
C209	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C210	1-124-589-11	ELECT	47MF	20%	16V
C211	1-124-589-11	ELECT	47MF	20%	16V
C212	1-124-589-11	ELECT	47MF	20%	16V
C213	1-124-589-11	ELECT	47MF	20%	16V
C214	1-126-157-11	ELECT	10MF	20%	16V
C215	1-126-157-11	ELECT	10MF	20%	16V
C216	1-126-157-11	ELECT	10MF	20%	16V
C217	1-163-031-11	CERAMIC CHIP	0.01MF		50V
C218	1-164-298-11	CERAMIC CHIP	0.15MF	10%	25V
C219	1-163-009-11	CERAMIC CHIP	0.001MF	10%	50V
C220	1-163-031-11	CERAMIC CHIP	0.01MF		50V
C221	1-124-903-11	ELECT	1MF	20%	50V
C222	1-163-093-00	CERAMIC CHIP	10PF	5%	50V
C223	1-163-031-11	CERAMIC CHIP	0.01MF		50V
C225	1-124-477-11	ELECT	47MF	20%	16V
C226	1-163-031-11	CERAMIC CHIP	0.01MF		50V
C227	1-163-038-00	CERAMIC CHIP	0.1MF		25V
C228	1-163-986-00	CERAMIC CHIP	0.027MF	10%	25V
C229	1-163-031-11	CERAMIC CHIP	0.01MF		50V
C230	1-163-038-00	CERAMIC CHIP	0.1MF		25V
C231	1-163-986-00	CERAMIC CHIP	0.027MF	10%	25V
C232	1-163-031-11	CERAMIC CHIP	0.01MF		50V
C233	1-163-031-11	CERAMIC CHIP	0.01MF		50V
C234	1-163-038-00	CERAMIC CHIP	0.1MF		25V
C235	1-163-986-00	CERAMIC CHIP	0.027MF	10%	25V
C236	1-163-031-11	CERAMIC CHIP	0.01MF		50V
C237	1-163-031-11	CERAMIC CHIP	0.01MF		50V
C238	1-164-299-11	CERAMIC CHIP	0.22MF	10%	25V
C239	1-163-809-11	CERAMIC CHIP	0.047MF	10%	25V
C240	1-163-809-11	CERAMIC CHIP	0.047MF	10%	25V
C241	1-163-809-11	CERAMIC CHIP	0.047MF	10%	25V
C242	1-163-113-00	CERAMIC CHIP	68PF	5%	50V
C243	1-163-031-11	CERAMIC CHIP	0.01MF		50V
C244	1-163-103-00	CERAMIC CHIP	27PF	5%	50V
C245	1-163-105-00	CERAMIC CHIP	33PF	5%	50V
C246	1-163-809-11	CERAMIC CHIP	0.047MF	10%	25V
C247	1-163-809-11	CERAMIC CHIP	0.047MF	10%	25V
C248	1-163-809-11	CERAMIC CHIP	0.047MF	10%	25V
C249	1-126-101-11	ELECT	100MF	20%	16V
C250	1-163-017-00	CERAMIC CHIP	0.0047MF	10%	50V
C251	1-110-364-11	MYLAR	0.1MF	10%	200V
C252	1-123-935-00	ELECT	33MF	20%	160V
C253	1-124-477-11	ELECT	47MF	20%	16V
C254	1-163-031-11	CERAMIC CHIP	0.01MF		50V
C255	1-124-477-11	ELECT	47MF	20%	16V
C256	1-163-129-00	CERAMIC CHIP	330PF	5%	50V
C257	1-163-129-00	CERAMIC CHIP	330PF	5%	50V
C258	1-163-129-00	CERAMIC CHIP	330PF	5%	50V
C259	1-163-031-11	CERAMIC CHIP	0.01MF		50V
C260	1-124-465-00	ELECT	0.47MF	20%	50V
C261	1-137-193-11	FILM	0.39MF	5%	50V
C262	1-124-465-00	ELECT	0.47MF	20%	50V
C264	1-163-123-00	CERAMIC CHIP	180PF	5%	50V
C265	1-163-129-00	CERAMIC CHIP	330PF	5%	50V
C266	1-126-320-11	ELECT	10MF	20%	16V
C267	1-126-320-11	ELECT	10MF	20%	16V
C268	1-124-477-11	ELECT	47MF	20%	16V
C269	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C270	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C271	1-163-809-11	CERAMIC CHIP	0.047MF	10%	25V
C272	1-163-129-00	CERAMIC CHIP	330PF	5%	50V
C273	1-163-129-00	CERAMIC CHIP	330PF	5%	50V
C274	1-124-477-11	ELECT	47MF	20%	16V
C275	1-163-119-00	CERAMIC CHIP	120PF	5%	50V
C277	1-163-097-00	CERAMIC CHIP	15PF	5%	50V
C278	1-163-809-11	CERAMIC CHIP	0.047MF	10%	25V
C279	1-126-157-11	ELECT	10MF	20%	16V
C280	1-163-117-00	CERAMIC CHIP	100PF	5%	50V
C281	1-163-031-11	CERAMIC CHIP	0.01MF		50V
C282	1-163-031-11	CERAMIC CHIP	0.01MF		50V
C283	1-163-031-11	CERAMIC CHIP	0.01MF		50V
C299	1-163-031-11	CERAMIC CHIP	0.01MF		50V
C300	1-126-157-11	ELECT	10MF	20%	16V
C301	1-163-809-11	CERAMIC CHIP	0.047MF	10%	25V
C302	1-124-589-11	ELECT	47MF	20%	16V
C303	1-126-157-11	ELECT	10MF	20%	16V
C304	1-163-125-00	CERAMIC CHIP	220PF	5%	50V
C305	1-124-257-00	ELECT	2.2MF	20%	50V
C306	1-163-115-00	CERAMIC CHIP	82PF	5%	50V
C307	1-163-145-00	CERAMIC CHIP	0.0015MF	5%	50V
C308	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C309	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C310	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C312	1-163-031-11	CERAMIC CHIP	0.01MF		50V
C313	1-163-115-00	CERAMIC CHIP	82PF	5%	50V
C314	1-126-157-11	ELECT	10MF	20%	16V
C315	1-164-299-11	CERAMIC CHIP	0.22MF	10%	25V
C316	1-126-157-11	ELECT	10MF	20%	16V
C317	1-163-031-11	CERAMIC CHIP	0.01MF		50V
C318	1-163-095-00	CERAMIC CHIP	12PF	5%	50V
C319	1-163-095-00	CERAMIC CHIP	12PF	5%	50V
C320	1-163-095-00	CERAMIC CHIP	12PF	5%	50V
C321	1-163-121-00	CERAMIC CHIP	150PF	5%	50V
C322	1-163-121-00	CERAMIC CHIP	150PF	5%	50V
C324	1-163-119-00	CERAMIC CHIP	120PF	5%	50V
C340	1-163-205-00	CERAMIC CHIP	0.001MF	5%	50V
C344	1-163-092-00	CERAMIC CHIP	9PF	0.25PF	50V
C345	1-163-109-00	CERAMIC CHIP	47PF	5%	50V
C346	1-163-109-00	CERAMIC CHIP	47PF	5%	50V
C347	1-163-109-00	CERAMIC CHIP	47PF	5%	50V
C1293	1-163-119-00	CERAMIC CHIP	120PF	5%	50V
C1294	1-163-119-00	CERAMIC CHIP	120PF	5%	50V
C1295	1-163-119-00	CERAMIC CHIP	120PF	5%	50V
C1296	1-163-115-00	CERAMIC CHIP	82PF	5%	50V
C1297	1-163-103-00	CERAMIC CHIP	27PF	5%	50V
C1298	1-163-113-00	CERAMIC CHIP	68PF	5%	50V
C1299	1-163-093-00	CERAMIC CHIP	10PF	5%	50V
C1300	1-126-160-11	ELECT	1MF	20%	50V
C1301	1-126-160-11	ELECT	1MF	20%	50V
C1302	1-126-160-11	ELECT	1MF	20%	50V
C1303	1-126-160-11	ELECT	1MF	20%	50V

<FILTER BLOCK>

REF.NO.	PART NO.	DESCRIPTION	REMARK
CFM101	1-464-880-11	FILTER BLOCK, COM (CFB-2)	

<CONNECTOR>

CN101	1-506-480-11	PIN, CONNECTOR 15P	
CN102	*1-564-506-11	PLUG, CONNECTOR 3P	
CN103	*1-565-503-11	CONNECTOR, BOARD TO BOARD 12P	
CN104	1-506-477-11	PIN, CONNECTOR 12P	
CN105	*1-564-509-11	PLUG, CONNECTOR 6P	
CN106	1-506-473-11	PIN, CONNECTOR 8P	
CN107	1-506-478-11	PIN, CONNECTOR 13P	
CN108	*1-564-506-11	PLUG, CONNECTOR 3P	

<TRAP MODULE>

CTR101	1-236-366-11	MODULE, TRAP	
CTR102	1-236-365-11	MODULE, TRAP	

<TRIMMER>

CV101	1-141-418-11	CAP, ADJ	
CV102	1-141-418-11	CAP, ADJ	

<DIODE>

D103	8-719-404-46	DIODE MA110	
D104	8-719-404-46	DIODE MA110	
D105	8-719-404-46	DIODE MA110	
D106	8-719-404-46	DIODE MA110	
D107	8-719-404-46	DIODE MA110	
D108	8-719-404-46	DIODE MA110	
D109	8-719-404-46	DIODE MA110	
D110	8-719-404-46	DIODE MA110	
D111	8-719-404-46	DIODE MA110	
D112	8-719-404-46	DIODE MA110	
D113	8-719-404-46	DIODE MA110	
D117	8-719-404-46	DIODE MA110	
D120	8-719-404-46	DIODE MA110	
D121	8-719-404-46	DIODE MA110	
D122	8-719-404-46	DIODE MA110	
D123	8-719-404-46	DIODE MA110	
D125	8-719-404-46	DIODE MA110	
D126	8-719-404-46	DIODE MA110	
D127	8-719-404-46	DIODE MA110	
D128	8-719-400-18	DIODE MA152WK	
D129	8-719-404-46	DIODE MA110	
D130	8-719-800-76	DIODE 1SS226	
D131	8-719-800-76	DIODE 1SS226	
D132	8-719-800-76	DIODE 1SS226	
D133	8-719-404-46	DIODE MA110	
D134	8-719-404-46	DIODE MA110	
D135	8-719-404-46	DIODE MA110	
D136	8-719-404-46	DIODE MA110	
D137	8-719-404-46	DIODE MA110	
D138	8-719-404-46	DIODE MA110	
D139	8-719-404-46	DIODE MA110	
D144	8-719-404-46	DIODE MA110	
D145	8-719-404-46	DIODE MA110	
D146	8-719-404-46	DIODE MA110	
D147	8-719-404-46	DIODE MA110	
D148	8-719-404-46	DIODE MA110	
D149	8-719-404-46	DIODE MA110	
D150	8-719-404-46	DIODE MA110	
D151	8-719-404-46	DIODE MA110	
D152	8-719-404-46	DIODE MA110	
D153	8-719-977-20	DIODE DTZ8.2B	
D154	8-719-404-46	DIODE MA110	
D155	8-719-404-46	DIODE MA110	
D156	8-719-404-46	DIODE MA110	
D157	8-719-901-83	DIODE 1SS83	
D158	8-719-901-83	DIODE 1SS83	
D159	8-719-901-83	DIODE 1SS83	
D160	8-719-404-46	DIODE MA110	
D161	8-719-404-46	DIODE MA110	
D162	8-719-404-46	DIODE MA110	
D170	8-719-404-46	DIODE MA110	
D185	8-719-104-34	DIODE 1S2836	
D186	8-719-400-18	DIODE MA152WK	
D187	8-719-800-76	DIODE 1SS226	
D188	8-719-800-76	DIODE 1SS226	
D191	8-719-104-34	DIODE 1S2836	
D285	8-719-404-46	DIODE MA110	
D289	8-719-404-46	DIODE MA110	
D341	8-719-404-46	DIODE MA110	
D342	8-719-104-34	DIODE 1S2836	
D343	8-719-800-76	DIODE 1SS226	
D344	8-719-105-XX	DIODE RD6.2M-B1	
D345	8-719-901-83	DIODE 1SS83	
D346	8-719-901-83	DIODE 1SS83	
D347	8-719-901-83	DIODE 1SS83	
D348	8-719-800-76	DIODE 1SS226	
D349	8-719-800-76	DIODE 1SS226	
D350	8-719-800-76	DIODE 1SS226	
D390	8-719-800-76	DIODE 1SS226	
D393	8-719-404-46	DIODE MA110	

<DELAY LINE>

DL101	1-415-632-11	DELAY LINE, Y	
DL102	1-415-633-11	DELAY LINE, Y	

<IC>

IC101	8-759-048-09	IC MM1148XF	
IC102	8-759-501-21	IC MM1149XF	
IC103	8-759-501-21	IC MM1149XF	
IC104	8-759-501-21	IC MM1149XF	
IC105	8-759-048-09	IC MM1148XF	
IC106	8-759-009-51	IC MC14538BF	
IC107	8-759-509-57	IC XRU4584BF	
IC108	8-759-509-17	IC XRU4053BF	
IC109	8-759-509-37	IC XRU4070BF	
IC110	8-759-509-17	IC XRU4053BF	
IC111	8-759-509-17	IC XRU4053BF	
IC112	8-759-924-12	IC LM7805CT	
IC113	8-759-631-08	IC M51279FP	
IC114	8-759-509-13	IC XRU4052BF	
IC115	8-759-509-13	IC XRU4052BF	
IC116	8-759-509-05	IC XRU4066BF	
IC117	8-759-711-32	IC NJM2245M	
IC118	8-759-711-32	IC NJM2245M	
IC119	8-759-711-32	IC NJM2245M	
IC120	8-759-509-05	IC XRU4066BF	
IC121	8-759-509-17	IC XRU4053BF	
IC122	8-759-998-98	IC LM358D	
IC123	8-759-998-98	IC LM358D	
IC124	8-752-052-62	IC CXA1478S	

B B

REMARK	REF.NO.	PART NO.	DESCRIPTION
V			
	CFM101	1-464-880-11	FILTER BLOCK, COM (CFB-2)
V			
V			<CONNECTOR>
V	CN101	1-506-480-11	PIN, CONNECTOR 15P
V	CN102	*1-564-506-11	PLUG, CONNECTOR 3P
V	CN103	*1-565-503-11	CONNECTOR, BOARD TO BOARD 12P
V	CN104	1-506-477-11	PIN, CONNECTOR 12P
V	CN105	*1-564-509-11	PLUG, CONNECTOR 6P
V	CN106	1-506-473-11	PIN, CONNECTOR 8P
V	CN107	1-506-478-11	PIN, CONNECTOR 13P
V	CN108	*1-564-506-11	PLUG, CONNECTOR 3P
V			
V			<TRAP MODULE>
V	CTR101	1-236-366-11	MODULE, TRAP
V	CTR102	1-236-365-11	MODULE, TRAP
V			
V			<TRIMMER>
V	CV101	1-141-418-11	CAP, ADJ
V	CV102	1-141-418-11	CAP, ADJ
V			
V			<DIODE>
V	D103	8-719-404-46	DIODE MA110
V	D104	8-719-404-46	DIODE MA110
V	D105	8-719-404-46	DIODE MA110
V	D106	8-719-404-46	DIODE MA110
V	D107	8-719-404-46	DIODE MA110
V	D108	8-719-404-46	DIODE MA110
V	D109	8-719-404-46	DIODE MA110
V	D110	8-719-404-46	DIODE MA110
V	D111	8-719-404-46	DIODE MA110
V	D112	8-719-404-46	DIODE MA110
V	D113	8-719-404-46	DIODE MA110
V	D117	8-719-404-46	DIODE MA110
V	D120	8-719-404-46	DIODE MA110
V	D121	8-719-404-46	DIODE MA110
V	D122	8-719-404-46	DIODE MA110
V	D123	8-719-404-46	DIODE MA110
V	D125	8-719-404-46	DIODE MA110
V	D126	8-719-404-46	DIODE MA110
V	D127	8-719-404-46	DIODE MA110
V	D128	8-719-400-18	DIODE MA152WK
V	D129	8-719-404-46	DIODE MA110
V	D130	8-719-800-76	DIODE 1SS226
V	D131	8-719-800-76	DIODE 1SS226
V	D132	8-719-800-76	DIODE 1SS226
V	D133	8-719-404-46	DIODE MA110
V	D134	8-719-404-46	DIODE MA110
V	D135	8-719-404-46	DIODE MA110
V	D136	8-719-404-46	DIODE MA110
V	D137	8-719-404-46	DIODE MA110
V	D138	8-719-404-46	DIODE MA110
V	D139	8-719-404-46	DIODE MA110
V	D144	8-719-404-46	DIODE MA110
V	D145	8-719-404-46	DIODE MA110
V	D146	8-719-404-46	DIODE MA110
V	D147	8-719-404-46	DIODE MA110
V	D148	8-719-404-46	DIODE MA110
	D149	8-719-404-46	DIODE MA110
	D150	8-719-404-46	DIODE MA110

REMARK	REF.NO.	PART NO.	DESCRIPTION
	D151	8-719-404-46	DIODE MA110
	D152	8-719-404-46	DIODE MA110
	D153	8-719-977-20	DIODE DTZ8.2B
	D154	8-719-404-46	DIODE MA110
	D155	8-719-404-46	DIODE MA110
	D156	8-719-404-46	DIODE MA110
	D157	8-719-901-83	DIODE 1SS83
	D158	8-719-901-83	DIODE 1SS83
	D159	8-719-901-83	DIODE 1SS83
	D160	8-719-404-46	DIODE MA110
	D161	8-719-404-46	DIODE MA110
	D162	8-719-404-46	DIODE MA110
	D170	8-719-404-46	DIODE MA110
	D185	8-719-104-34	DIODE 1S2836
	D186	8-719-400-18	DIODE MA152WK
	D187	8-719-800-76	DIODE 1SS226
	D188	8-719-800-76	DIODE 1SS226
	D191	8-719-104-34	DIODE 1S2836
	D285	8-719-404-46	DIODE MA110
	D289	8-719-404-46	DIODE MA110
	D341	8-719-404-46	DIODE MA110
	D342	8-719-104-34	DIODE 1S2836
	D343	8-719-800-76	DIODE 1SS226
	D344	8-719-105-XX	DIODE RD6.2M-B1
	D345	8-719-901-83	DIODE 1SS83
	D346	8-719-901-83	DIODE 1SS83
	D347	8-719-901-83	DIODE 1SS83
	D348	8-719-800-76	DIODE 1SS226
	D349	8-719-800-76	DIODE 1SS226
	D350	8-719-800-76	DIODE 1SS226
	D390	8-719-800-76	DIODE 1SS226
	D393	8-719-404-46	DIODE MA110
			<DELAY LINE>
	DL101	1-415-632-11	DELAY LINE, Y
	DL102	1-415-633-11	DELAY LINE, Y
			<IC>
	IC101	8-759-048-09	IC MM1148XF
	IC102	8-759-501-21	IC MM1149XF
	IC103	8-759-501-21	IC MM1149XF
	IC104	8-759-501-21	IC MM1149XF
	IC105	8-759-048-09	IC MM1148XF
	IC106	8-759-009-51	IC MC14538BF
	IC107	8-759-509-57	IC XRU4584BF
	IC108	8-759-509-17	IC XRU4053BF
	IC109	8-759-509-37	IC XRU4070BF
	IC110	8-759-509-17	IC XRU4053BF
	IC111	8-759-509-17	IC XRU4053BF
	IC112	8-759-924-12	IC LM7805CT
	IC113	8-759-631-08	IC M51279FP
	IC114	8-759-509-13	IC XRU4052BF
	IC115	8-759-509-13	IC XRU4052BF
	IC116	8-759-509-05	IC XRU4066BF
	IC117	8-759-711-32	IC NJM2245M
	IC118	8-759-711-32	IC NJM2245M
	IC119	8-759-711-32	IC NJM2245M
	IC120	8-759-509-05	IC XRU4066BF
	IC121	8-759-509-17	IC XRU4053BF
	IC122	8-759-998-98	IC LM358D
	IC123	8-759-998-98	IC LM358D
	IC124	8-752-052-62	IC CXA1478S

REMARK	REF.NO.	PART NO.	DESCRIPTION
	IC125	8-759-509-05	IC XRU4066BF
	IC126	8-759-509-17	IC XRU4053BF
	IC127	8-759-998-98	IC LM358D
	IC128	8-759-998-98	IC LM358D
	IC129	8-759-998-98	IC LM358D
			<JUMPER RESISTOR>
	JR105	1-216-295-00	METAL GLAZE 0 5% 1/10W
	JR110	1-216-295-00	METAL GLAZE 0 5% 1/10W
	JR133	1-216-295-00	METAL GLAZE 0 5% 1/10W
	JR138	1-216-295-00	METAL GLAZE 0 5% 1/10W
	JR178	1-216-295-00	METAL GLAZE 0 5% 1/10W
			<COIL>
	L101	1-410-470-11	INDUCTOR 10UH
	L102	1-410-090-41	INDUCTOR 18MMH
	L103	1-412-002-31	INDUCTOR CHIP 4.7UH
	L104	1-412-002-31	INDUCTOR CHIP 4.7UH
	L105	1-412-002-31	INDUCTOR CHIP 4.7UH
	L106	1-410-470-11	INDUCTOR 10UH
	L107	1-410-470-11	INDUCTOR 10UH
	L112	1-408-419-00	INDUCTOR 68UH
	L113	1-410-947-31	INDUCTOR CHIP 33UH
	L114	1-410-947-31	INDUCTOR CHIP 33UH
	L115	1-410-947-31	INDUCTOR CHIP 33UH
	L116	1-412-011-31	INDUCTOR CHIP 27UH
	L117	1-412-011-31	INDUCTOR CHIP 27UH
	L118	1-412-011-31	INDUCTOR CHIP 27UH
	L250	1-410-997-31	INDUCTOR CHIP 2.2UH
	L251	1-410-999-11	INDUCTOR CHIP 3.3UH
	L252	1-410-478-11	INDUCTOR 47UH
	L300	1-410-482-31	INDUCTOR 100UH
			<TRANSISTOR>
	Q101	8-729-422-27	TRANSISTOR 2SD601A-Q
	Q102	8-729-422-27	TRANSISTOR 2SD601A-Q
	Q103	8-729-422-27	TRANSISTOR 2SD601A-Q
	Q104	8-729-422-27	TRANSISTOR 2SD601A-Q
	Q105	8-729-422-27	TRANSISTOR 2SD601A-Q
	Q106	8-729-422-27	TRANSISTOR 2SD601A-Q
	Q107	8-729-422-27	TRANSISTOR 2SD601A-Q
	Q108	8-729-216-22	TRANSISTOR 2SA1162-G
	Q109	8-729-901-01	TRANSISTOR DTC144EK
	Q112	8-729-422-27	TRANSISTOR 2SD601A-Q
	Q113	8-729-422-27	TRANSISTOR 2SD601A-Q
	Q114	8-729-216-22	TRANSISTOR 2SA1162-G
	Q115	8-729-422-27	TRANSISTOR 2SD601A-Q
	Q116	8-729-422-27	TRANSISTOR 2SD601A-Q
	Q117	8-729-216-22	TRANSISTOR 2SA1162-G
	Q118	8-729-422-27	TRANSISTOR 2SD601A-Q
	Q119	8-729-216-22	TRANSISTOR 2SA1162-G
	Q120	8-729-216-22	TRANSISTOR 2SA1162-G
	Q121	8-729-422-27	TRANSISTOR 2SD601A-Q
	Q122	8-729-216-22	TRANSISTOR 2SA1162-G
	Q123	8-729-422-27	TRANSISTOR 2SD601A-Q
	Q124	8-729-216-22	TRANSISTOR 2SA1162-G
	Q125	8-729-422-27	TRANSISTOR 2SD601A-Q
	Q126	8-729-901-01	TRANSISTOR DTC144EK
	Q127	8-729-216-22	TRANSISTOR 2SA1162-G
	Q128	8-729-216-22	TRANSISTOR 2SA1162-G
	Q129	8-729-901-01	TRANSISTOR DTC144EK
	Q130	8-729-216-22	TRANSISTOR 2SA1162-G

REMARK	REF.NO.	PART NO.	DESCRIPTION
	Q131	8-729-422-27	TRANSISTOR 2SD601A-Q
	Q132	8-729-216-22	TRANSISTOR 2SA1162-G
	Q133	8-729-422-27	TRANSISTOR 2SD601A-Q
	Q134	8-729-901-01	TRANSISTOR DTC144EK
	Q135	8-729-422-27	TRANSISTOR 2SD601A-Q
	Q136	8-729-907-26	TRANSISTOR IMX1
	Q137	8-729-907-26	TRANSISTOR IMX1
	Q138	8-729-907-26	TRANSISTOR IMX1
	Q139	8-729-216-22	TRANSISTOR 2SA1162-G
	Q140	8-729-422-27	TRANSISTOR 2SD601A-Q
	Q141	8-729-422-27	TRANSISTOR 2SD601A-Q
	Q142	8-729-422-27	TRANSISTOR 2SD601A-Q
	Q143	8-729-422-27	TRANSISTOR 2SD601A-Q
	Q144	8-729-422-27	TRANSISTOR 2SD601A-Q
	Q145	8-729-422-27	TRANSISTOR 2SD601A-Q
	Q146	8-729-255-12	TRANSISTOR 2SC2551-O
	Q147	8-729-255-12	TRANSISTOR 2SC2551-O
	Q148	8-729-216-22	TRANSISTOR 2SA1162-G
	Q149	8-729-200-17	TRANSISTOR 2SA1091-O
	Q150	8-729-422-27	TRANSISTOR 2SD601A-Q
	Q151	8-729-216-22	TRANSISTOR 2SA1162-G
	Q152	8-729-200-17	TRANSISTOR 2SA1091-O
	Q153	8-729-422-27	TRANSISTOR 2SD601A-Q
	Q154	8-729-216-22	TRANSISTOR 2SA1162-G
	Q155	8-729-200-17	TRANSISTOR 2SA1091-O
	Q157	8-729-326-11	TRANSISTOR 2SC2611
	Q158	8-729-326-11	TRANSISTOR 2SC2611
	Q159	8-729-326-11	TRANSISTOR 2SC2611
	Q160	8-729-422-27	TRANSISTOR 2SD601A-Q
	Q161	8-729-216-22	TRANSISTOR 2SA1162-G
	Q164	8-729-901-01	TRANSISTOR DTC144EK
	Q165	8-729-216-22	TRANSISTOR 2SA1162-G
	Q166	8-729-216-22	TRANSISTOR 2SA1162-G
	Q167	8-729-216-22	TRANSISTOR 2SA1162-G
	Q168	8-729-216-22	TRANSISTOR 2SA1162-G
	Q170	8-729-422-27	TRANSISTOR 2SD601A-Q
	Q171	8-729-422-27	TRANSISTOR 2SD601A-Q
	Q172	8-729-422-27	TRANSISTOR 2SD601A-Q
	Q173	8-729-216-22	TRANSISTOR 2SA1162-G
	Q174	8-729-216-22	TRANSISTOR 2SA1162-G
	Q175	8-729-216-22	TRANSISTOR 2SA1162-G
	Q176	8-729-216-22	TRANSISTOR 2SA1162-G
	Q177	8-729-422-27	TRANSISTOR 2SD601A-Q
	Q178	8-729-422-27	TRANSISTOR 2SD601A-Q
	Q179	8-729-901-01	TRANSISTOR DTC144EK
	Q189	8-729-907-26	TRANSISTOR IMX1
	Q190	8-729-216-22	TRANSISTOR 2SA1162-G
	Q191	8-729-422-27	TRANSISTOR 2SD601A-Q
	Q192	8-729-422-27	TRANSISTOR 2SD601A-Q
	Q193	8-729-422-27	TRANSISTOR 2SD601A-Q
	Q194	8-729-422-27	TRANSISTOR 2SD601A-Q
	Q195	8-729-216-22	TRANSISTOR 2SA1162-G
	Q196	8-729-422-27	TRANSISTOR 2SD601A-Q
	Q197	8-729-216-22	TRANSISTOR 2SA1162-G
	Q198	8-729-216-22	TRANSISTOR 2SA1162-G
	Q199	8-729-216-22	TRANSISTOR 2SA1162-G
	Q200	8-729-901-06	TRANSISTOR DTA144EK
	Q201	8-729-216-22	TRANSISTOR 2SA1162-G
	Q202	8-729-216-22	TRANSISTOR 2SA1162-G
	Q203	8-729-216-22	TRANSISTOR 2SA1162-G
	Q204	8-729-216-22	TRANSISTOR 2SA1162-G
	Q205	8-729-216-22	TRANSISTOR 2SA1162-G
	Q206	8-729-216-22	TRANSISTOR 2SA1162-G

REF.NO.	PART NO.	DESCRIPTION				REMARK
Q208	8-729-216-22	TRANSISTOR 2SA1162-G				
Q209	8-729-255-12	TRANSISTOR 2SC2551-O				
Q210	8-729-255-12	TRANSISTOR 2SC2551-O				
Q211	8-729-255-12	TRANSISTOR 2SC2551-O				
Q212	8-729-109-44	TRANSISTOR 2SK94				
Q299	8-729-422-27	TRANSISTOR 2SD601A-Q				
		<RESISTOR>				
R101	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R102	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R103	1-216-091-00	METAL GLAZE	56K	5%	1/10W	
R104	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R105	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R106	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R107	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R108	1-216-113-00	METAL GLAZE	470K	5%	1/10W	
R109	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R110	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R111	1-216-063-00	METAL GLAZE	3.9K	5%	1/10W	
R112	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R113	1-249-401-11	CARBON	47	5%	1/4W	F
R114	1-216-045-00	METAL GLAZE	680	5%	1/10W	
R115	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R117	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R118	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R119	1-216-647-11	METAL CHIP	680	0.50%	1/10W	
R120	1-216-647-11	METAL CHIP	680	0.50%	1/10W	
R121	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R122	1-216-083-00	METAL GLAZE	27K	5%	1/10W	
R123	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R124	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R125	1-216-083-00	METAL GLAZE	27K	5%	1/10W	
R126	1-216-093-00	METAL GLAZE	68K	5%	1/10W	
R127	1-216-037-00	METAL GLAZE	330	5%	1/10W	
R128	1-216-083-00	METAL GLAZE	27K	5%	1/10W	
R129	1-216-067-00	METAL GLAZE	5.6K	5%	1/10W	
R130	1-216-097-00	METAL GLAZE	100K	5%	1/10W	
R131	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R132	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W	
R133	1-216-079-00	METAL GLAZE	18K	5%	1/10W	
R134	1-216-645-11	METAL CHIP	560	0.50%	1/10W	
R135	1-216-645-11	METAL CHIP	560	0.50%	1/10W	
R136	1-216-091-00	METAL GLAZE	56K	5%	1/10W	
R137	1-216-045-00	METAL GLAZE	680	5%	1/10W	
R138	1-216-657-11	METAL CHIP	1.8K	0.50%	1/10W	
R139	1-216-079-00	METAL GLAZE	18K	5%	1/10W	
R140	1-216-653-11	METAL CHIP	1.2K	0.50%	1/10W	
R141	1-216-063-00	METAL GLAZE	3.9K	5%	1/10W	
R142	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R143	1-216-085-00	METAL GLAZE	33K	5%	1/10W	
R145	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R146	1-216-037-00	METAL GLAZE	330	5%	1/10W	
R147	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R148	1-216-671-11	METAL CHIP	6.8K	0.50%	1/10W	
R155	1-216-655-11	METAL CHIP	1.5K	0.50%	1/10W	
R157	1-216-679-11	METAL CHIP	15K	0.50%	1/10W	
R158	1-216-677-11	METAL CHIP	12K	0.50%	1/10W	
R160	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R161	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R163	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R164	1-216-677-11	METAL CHIP	12K	0.50%	1/10W	
R165	1-216-107-00	METAL GLAZE	270K	5%	1/10W	
R166	1-216-681-11	METAL CHIP	18K	0.50%	1/10W	
R167	1-216-635-11	METAL CHIP	220	0.50%	1/10W	
R168	1-216-103-00	METAL GLAZE	180K	5%	1/10W	
R169	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R170	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R171	1-216-053-00	METAL GLAZE	1.5K	5%	1/10W	
R172	1-216-043-00	METAL GLAZE	560	5%	1/10W	
R173	1-216-093-00	METAL GLAZE	68K	5%	1/10W	
R174	1-216-069-00	METAL GLAZE	6.8K	5%	1/10W	
R175	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W	
R176	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R177	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R178	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R179	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R180	1-216-679-11	METAL CHIP	15K	0.50%	1/10W	
R181	1-216-071-00	METAL GLAZE	8.2K	5%	1/10W	
R182	1-216-683-11	METAL CHIP	22K	0.50%	1/10W	
R183	1-216-691-11	METAL CHIP	47K	0.50%	1/10W	
R184	1-216-699-11	METAL CHIP	100K	0.50%	1/10W	
R185	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R186	1-216-113-00	METAL GLAZE	470K	5%	1/10W	
R187	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R188	1-216-113-00	METAL GLAZE	470K	5%	1/10W	
R189	1-216-103-00	METAL GLAZE	180K	5%	1/10W	
R190	1-216-107-00	METAL GLAZE	270K	5%	1/10W	
R191	1-216-097-00	METAL GLAZE	100K	5%	1/10W	
R192	1-216-103-00	METAL GLAZE	180K	5%	1/10W	
R193	1-216-105-00	METAL GLAZE	220K	5%	1/10W	
R194	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R195	1-216-113-00	METAL GLAZE	470K	5%	1/10W	
R196	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R197	1-216-671-11	METAL CHIP	6.8K	0.50%	1/10W	
R198	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R199	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R200	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R201	1-216-043-00	METAL GLAZE	560	5%	1/10W	
R202	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R203	1-216-045-00	METAL GLAZE	680	5%	1/10W	
R204	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R205	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R206	1-216-043-00	METAL GLAZE	560	5%	1/10W	
R207	1-216-045-00	METAL GLAZE	680	5%	1/10W	
R208	1-216-671-11	METAL CHIP	6.8K	0.50%	1/10W	
R209	1-216-043-00	METAL GLAZE	560	5%	1/10W	
R210	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R211	1-216-099-00	METAL GLAZE	120K	5%	1/10W	
R212	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R213	1-216-043-00	METAL GLAZE	560	5%	1/10W	
R214	1-216-043-00	METAL GLAZE	560	5%	1/10W	
R215	1-216-127-11	METAL GLAZE	1.8M	5%	1/10W	
R216	1-216-043-00	METAL GLAZE	560	5%	1/10W	
R217	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R218	1-216-295-00	METAL GLAZE	0	5%	1/10W	
R219	1-216-043-00	METAL GLAZE	560	5%	1/10W	
R220	1-216-043-00	METAL GLAZE	560	5%	1/10W	
R221	1-216-035-00	METAL GLAZE	270	5%	1/10W	
R222	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R223	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R224	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R225	1-216-095-00	METAL GLAZE	82K	5%	1/10W	
R226	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R227	1-216-035-00	METAL GLAZE	270	5%	1/10W	
R228	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R229	1-216-113-00	METAL GLAZE	470K	5%	1/10W	

B

REF.NO.	PART NO.	DESCRIPTION				REMARK
R230	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R231	1-216-113-00	METAL GLAZE	470K	5%	1/10W	
R232	1-216-105-00	METAL GLAZE	220K	5%	1/10W	
R233	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R234	1-216-041-00	METAL GLAZE	470	5%	1/10W	
R235	1-216-041-00	METAL GLAZE	470	5%	1/10W	
R236	1-216-077-00	METAL GLAZE	15K	5%	1/10W	
R237	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R238	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R239	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R240	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R241	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R242	1-216-051-00	METAL GLAZE	1.2K	5%	1/10W	
R243	1-216-113-00	METAL GLAZE	470K	5%	1/10W	
R244	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R245	1-216-679-11	METAL CHIP	15K	0.50%	1/10W	
R246	1-216-103-00	METAL GLAZE	180K	5%	1/10W	
R247	1-216-093-00	METAL GLAZE	68K	5%	1/10W	
R248	1-216-095-00	METAL GLAZE	82K	5%	1/10W	
R249	1-216-109-00	METAL GLAZE	330K	5%	1/10W	
R250	1-216-101-00	METAL GLAZE	150K	5%	1/10W	
R251	1-216-105-00	METAL GLAZE	220K	5%	1/10W	
R252	1-216-101-00	METAL GLAZE	150K	5%	1/10W	
R253	1-216-101-00	METAL GLAZE	150K	5%	1/10W	
R254	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R255	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R256	1-216-107-00	METAL GLAZE	270K	5%	1/10W	
R258	1-216-041-00	METAL GLAZE	470	5%	1/10W	
R259	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R260	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R261	1-216-035-00	METAL GLAZE	270	5%	1/10W	
R262	1-216-097-00	METAL GLAZE	100K	5%	1/10W	
R263	1-216-029-00	METAL GLAZE	150	5%	1/10W	
R264	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R265	1-216-067-00	METAL GLAZE	5.6K	5%	1/10W	
R266	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R267	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R268	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R269	1-216-103-00	METAL GLAZE	180K	5%	1/10W	
R270	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R271	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R272	1-216-103-00	METAL GLAZE	180K	5%	1/10W	
R273	1-216-113-00	METAL GLAZE	470K	5%	1/10W	
R275	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R276	1-216-037-00	METAL GLAZE	330	5%	1/10W	
R277	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R278	1-216-059-00	METAL GLAZE	2.7K	5%	1/10W	
R280	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R281	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R282	1-216-037-00	METAL GLAZE	330	5%	1/10W	
R283	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R284	1-216-059-00	METAL GLAZE	2.7K	5%	1/10W	
R286	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R287	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R288	1-216-037-00	METAL GLAZE	330	5%	1/10W	
R289	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R290	1-216-059-00	METAL GLAZE	2.7K	5%	1/10W	
R292	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R293	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R295	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W	
R296	1-216-659-11	METAL CHIP	2.2K	0.50%	1/10W	
R297	1-216-659-11	METAL CHIP	2.2K	0.50%	1/10W	
R298	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R300	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R301	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R302	1-216-113-00	METAL GLAZE	470K	5%	1/10W	
R303	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R304	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R305	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R306	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R307	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R308	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R309	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R310	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R311	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R312	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R313	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R314	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R315	1-216-113-00	METAL GLAZE	470K	5%	1/10W	
R316	1-216-105-00	METAL GLAZE	220K	5%	1/10W	
R317	1-216-109-00	METAL GLAZE	330K	5%	1/10W	
R318	1-216-105-00	METAL GLAZE	220K	5%	1/10W	
R319	1-216-099-00	METAL GLAZE	120K	5%	1/10W	
R320	1-216-099-00	METAL GLAZE	120K	5%	1/10W	
R321	1-216-043-00	METAL GLAZE	560	5%	1/10W	
R322	1-216-109-00	METAL GLAZE	330K	5%	1/10W	
R323	1-216-109-00	METAL GLAZE	330K	5%	1/10W	
R324	1-216-109-00	METAL GLAZE	330K	5%	1/10W	
R325	1-216-097-00	METAL GLAZE	100K	5%	1/10W	
R326	1-216-113-00	METAL GLAZE	470K	5%	1/10W	
R328	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R329	1-216-107-00	METAL GLAZE	270K	5%	1/10W	
R330	1-216-105-00	METAL GLAZE	220K	5%	1/10W	
R331	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R332	1-216-097-00	METAL GLAZE	100K	5%	1/10W	
R333	1-216-097-00	METAL GLAZE	100K	5%	1/10W	
R334	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R335	1-216-099-00	METAL GLAZE	120K	5%	1/10W	
R336	1-216-095-00	METAL GLAZE	82K	5%	1/10W	
R337	1-216-105-00	METAL GLAZE	220K	5%	1/10W	
R338	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R339	1-216-099-00	METAL GLAZE	120K	5%	1/10W	
R340	1-216-095-00	METAL GLAZE	82K	5%	1/10W	
R341	1-216-105-00	METAL GLAZE	220K	5%	1/10W	
R342	1-216-047-00	METAL GLAZE	820	5%	1/10W	
R343	1-216-053-00	METAL GLAZE	1.5K	5%	1/10W	
R344	1-216-664-11	METAL CHIP	3.6K	0.50%	1/10W	
R345	1-216-661-11	METAL CHIP	2.7K	0.50%	1/10W	
R346	1-216-105-00	METAL GLAZE	220K	5%	1/10W	
R348	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R349	1-216-650-11	METAL CHIP	910	0.50%	1/10W	
R350	1-216-653-11	METAL CHIP	1.2K	0.50%	1/10W	
R351	1-216-650-11	METAL CHIP	910	0.50%	1/10W	
R352	1-216-653-11	METAL CHIP	1.2K	0.50%	1/10W	
R353	1-216-650-11	METAL CHIP	910	0.50%	1/10W	
R354	1-216-653-11	METAL CHIP	1.2K	0.50%	1/10W	
R355	1-216-113-00	METAL GLAZE	470K	5%	1/10W	
R356	1-216-113-00	METAL GLAZE	470K	5%	1/10W	
R357	1-216-095-00	METAL GLAZE	82K	5%	1/10W	
R358	1-216-113-00	METAL GLAZE	470K	5%	1/10W	
R359	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R360	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R363	1-216-069-00	METAL GLAZE	6.8K	5%	1/10W	
R364	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R365	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R366	1-216-244-00	METAL GLAZE	82K	5%	1/8W	
R367	1-216-244-00	METAL GLAZE	82K	5%	1/8W	

REF.NO.	PART NO.	DESCRIPTION				REMARK
R368	1-216-055-00	METAL GLAZE	1.8K	5%	1/10W	
R369	1-216-248-00	METAL GLAZE	120K	5%	1/8W	
R370	1-216-115-00	METAL GLAZE	560K	5%	1/10W	
R371	1-216-067-00	METAL GLAZE	5.6K	5%	1/10W	
R372	1-216-115-00	METAL GLAZE	560K	5%	1/10W	
R374	1-216-115-00	METAL GLAZE	560K	5%	1/10W	
R375	1-216-683-11	METAL CHIP	22K	0.50%	1/10W	
R376	1-216-663-11	METAL CHIP	3.3K	0.50%	1/10W	
R378	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R379	1-216-641-11	METAL CHIP	390	0.50%	1/10W	
R380	1-216-668-11	METAL CHIP	5.1K	0.50%	1/10W	
R381	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R382	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R383	1-216-641-11	METAL CHIP	390	0.50%	1/10W	
R384	1-216-668-11	METAL CHIP	5.1K	0.50%	1/10W	
R385	1-216-117-00	METAL GLAZE	680K	5%	1/10W	
R386	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R387	1-216-641-11	METAL CHIP	390	0.50%	1/10W	
R388	1-216-668-11	METAL CHIP	5.1K	0.50%	1/10W	
R389	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R390	1-216-105-00	METAL GLAZE	220K	5%	1/10W	
R391	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R392	1-216-113-00	METAL GLAZE	470K	5%	1/10W	
R393	1-216-085-00	METAL GLAZE	33K	5%	1/10W	
R394	1-216-113-00	METAL GLAZE	470K	5%	1/10W	
R397	1-249-437-11	CARBON	47K	5%	1/4W	F
R398	1-249-434-11	CARBON	27K	5%	1/4W	F
R399	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1001	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1002	1-216-047-00	METAL GLAZE	820	5%	1/10W	
R1003	1-216-055-00	METAL GLAZE	1.8K	5%	1/10W	
R1004	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R1005	1-216-047-00	METAL GLAZE	820	5%	1/10W	
R1006	1-216-055-00	METAL GLAZE	1.8K	5%	1/10W	
R1007	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R1008	1-216-047-00	METAL GLAZE	820	5%	1/10W	
R1009	1-216-053-00	METAL GLAZE	1.5K	5%	1/10W	
R1010	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R1011	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R1012	1-216-051-00	METAL GLAZE	1.2K	5%	1/10W	
R1013	1-216-051-00	METAL GLAZE	1.2K	5%	1/10W	
R1014	1-216-246-00	METAL GLAZE	100K	5%	1/8W	
R1015	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R1016	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R1017	1-216-045-00	METAL GLAZE	680	5%	1/10W	
R1018	1-216-043-00	METAL GLAZE	560	5%	1/10W	
R1019	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R1020	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R1021	1-216-045-00	METAL GLAZE	680	5%	1/10W	
R1022	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R1023	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1024	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R1025	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R1026	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R1027	1-216-101-00	METAL GLAZE	150K	5%	1/10W	
R1028	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R1029	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R1030	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R1031	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R1032	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R1033	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R1035	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1036	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R1038	1-216-081-00	METAL GLAZE	22K	5%	1/10W	

REF.NO.	PART NO.	DESCRIPTION				REMARK
R1040	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R1042	1-216-047-00	METAL GLAZE	820	5%	1/10W	
R1043	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W	
R1044	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R1045	1-216-125-00	METAL GLAZE	1.5M	5%	1/10W	
R1046	1-216-689-11	METAL CHIP	39K	0.50%	1/10W	
R1047	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R1048	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R1049	1-216-085-00	METAL GLAZE	33K	5%	1/10W	
R1050	1-216-059-00	METAL GLAZE	2.7K	5%	1/10W	
R1051	1-216-105-00	METAL GLAZE	220K	5%	1/10W	
R1053	1-216-091-00	METAL GLAZE	56K	5%	1/10W	
R1054	1-216-093-00	METAL GLAZE	68K	5%	1/10W	
R1055	1-216-097-00	METAL GLAZE	100K	5%	1/10W	
R1056	1-216-037-00	METAL GLAZE	330	5%	1/10W	
R1057	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R1058	1-216-109-00	METAL GLAZE	330K	5%	1/10W	
R1059	1-216-109-00	METAL GLAZE	330K	5%	1/10W	
R1060	1-216-109-00	METAL GLAZE	330K	5%	1/10W	
R1061	1-216-109-00	METAL GLAZE	330K	5%	1/10W	
R1062	1-216-103-00	METAL GLAZE	180K	5%	1/10W	
R1063	1-216-103-00	METAL GLAZE	180K	5%	1/10W	
R1064	1-216-103-00	METAL GLAZE	180K	5%	1/10W	
R1065	1-216-103-00	METAL GLAZE	180K	5%	1/10W	
R1066	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1067	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1068	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R1069	1-216-133-00	METAL GLAZE	3.3M	5%	1/10W	
R1070	1-216-085-00	METAL GLAZE	33K	5%	1/10W	
R1071	1-216-113-00	METAL GLAZE	470K	5%	1/10W	
R1072	1-216-099-00	METAL GLAZE	120K	5%	1/10W	
R1073	1-216-131-11	METAL GLAZE	2.7M	5%	1/10W	
R1075	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R1076	1-216-101-00	METAL GLAZE	150K	5%	1/10W	
R1077	1-216-103-00	METAL GLAZE	180K	5%	1/10W	
R1079	1-216-131-11	METAL GLAZE	2.7M	5%	1/10W	
R1080	1-216-097-00	METAL GLAZE	100K	5%	1/10W	
R1081	1-216-097-00	METAL GLAZE	100K	5%	1/10W	
R1082	1-216-105-00	METAL GLAZE	220K	5%	1/10W	
R1083	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R1084	1-216-063-00	METAL GLAZE	3.9K	5%	1/10W	
R1086	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1087	1-216-121-00	METAL GLAZE	1M	5%	1/10W	
R1088	1-216-047-00	METAL GLAZE	820	5%	1/10W	
R1090	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R1091	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R1092	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R1093	1-216-121-00	METAL GLAZE	1M	5%	1/10W	
R1094	1-216-075-00	METAL GLAZE	12K	5%	1/10W	
R1095	1-216-075-00	METAL GLAZE	12K	5%	1/10W	
R1096	1-216-075-00	METAL GLAZE	12K	5%	1/10W	
R1200	1-216-699-11	METAL CHIP	100K	0.50%	1/10W	
R1201	1-218-754-11	METAL CHIP	120K	0.50%	1/10W	
R1207	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R1208	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R1220	1-216-055-00	METAL GLAZE	1.8K	5%	1/10W	
R1221	1-216-055-00	METAL GLAZE	1.8K	5%	1/10W	
R1222	1-216-055-00	METAL GLAZE	1.8K	5%	1/10W	
R1223	1-216-689-11	METAL GLAZE	39K	5%	1/10W	
R1225	1-215-876-00	METAL OXIDE	15K	5%	1W	F
R1226	1-215-876-00	METAL OXIDE	15K	5%	1W	F
R1227	1-215-876-00	METAL OXIDE	15K	5%	1W	F
R1228	1-249-421-11	CARBON	2.2K	5%	1/4W	F

B D

REF.NO.	PART NO.	DESCRIPTION				REMARK
R1229	1-249-421-11	CARBON	2.2K	5%	1/4W	F
R1230	1-249-421-11	CARBON	2.2K	5%	1/4W	F
R1231	1-216-029-00	METAL GLAZE	150	5%	1/10W	
R1232	1-216-029-00	METAL GLAZE	150	5%	1/10W	
R1233	1-216-029-00	METAL GLAZE	150	5%	1/10W	
R1234	1-216-029-00	METAL GLAZE	150	5%	1/10W	
R1235	1-216-029-00	METAL GLAZE	150	5%	1/10W	
R1236	1-216-029-00	METAL GLAZE	150	5%	1/10W	
R1237	1-249-419-11	CARBON	1.5K	5%	1/4W	F
R1238	1-249-419-11	CARBON	1.5K	5%	1/4W	F
R1239	1-249-419-11	CARBON	1.5K	5%	1/4W	F
R1270	1-216-079-00	METAL GLAZE	18K	5%	1/10W	
R1271	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W	
R1280	1-216-109-00	METAL GLAZE	330K	5%	1/10W	
R1290	1-216-071-00	METAL GLAZE	8.2K	5%	1/10W	
R1291	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R1294	1-216-069-00	METAL GLAZE	6.8K	5%	1/10W	
R1295	1-216-109-00	METAL GLAZE	330K	5%	1/10W	
R1296	1-216-095-00	METAL GLAZE	82K	5%	1/10W	
R1297	1-216-071-00	METAL GLAZE	8.2K	5%	1/10W	
R1298	1-216-071-00	METAL GLAZE	8.2K	5%	1/10W	
R1299	1-216-071-00	METAL GLAZE	8.2K	5%	1/10W	
R1300	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R1301	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R1302	1-216-113-00	METAL GLAZE	470K	5%	1/10W	
R1303	1-216-113-00	METAL GLAZE	470K	5%	1/10W	
R1304	1-216-091-00	METAL GLAZE	56K	5%	1/10W	
R1305	1-216-093-00	METAL GLAZE	68K	5%	1/10W	
R1306	1-216-063-00	METAL GLAZE	3.9K	5%	1/10W	
R1307	1-216-041-00	METAL GLAZE	470	5%	1/10W	
R1308	1-216-041-00	METAL GLAZE	470	5%	1/10W	
R1309	1-216-063-00	METAL GLAZE	3.9K	5%	1/10W	
R1310	1-216-119-00	METAL GLAZE	820K	5%	1/10W	
R1313	1-216-101-00	METAL GLAZE	150K	5%	1/10W	
R1314	1-216-053-00	METAL GLAZE	1.5K	5%	1/10W	
R1315	1-216-077-00	METAL GLAZE	15K	5%	1/10W	
R1320	1-216-083-00	METAL GLAZE	27K	5%	1/10W	
R1321	1-216-093-00	METAL GLAZE	68K	5%	1/10W	
R1322	1-216-037-00	METAL GLAZE	330	5%	1/10W	
R1323	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W	
R1324	1-216-121-00	METAL GLAZE	1M	5%	1/10W	
R1325	1-216-085-00	METAL GLAZE	33K	5%	1/10W	
R1326	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R1327	1-216-099-00	METAL GLAZE	120K	5%	1/10W	
R1328	1-216-099-00	METAL GLAZE	120K	5%	1/10W	
R1329	1-216-093-00	METAL GLAZE	68K	5%	1/10W	
R1330	1-216-063-00	METAL GLAZE	3.9K	5%	1/10W	
R1331	1-216-051-00	METAL GLAZE	1.2K	5%	1/10W	
R1332	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W	
R1333	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W	
R1334	1-216-055-00	METAL GLAZE	1.8K	5%	1/10W	
R1335	1-216-035-00	METAL GLAZE	270	5%	1/10W	
R1336	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R1337	1-216-113-00	METAL GLAZE	470K	5%	1/10W	
R1338	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R1339	1-216-097-00	METAL GLAZE	100K	5%	1/10W	
R1340	1-216-097-00	METAL GLAZE	100K	5%	1/10W	
R1341	1-216-111-00	METAL GLAZE	390K	5%	1/10W	
R1342	1-216-694-11	METAL CHIP	62K	0.50%	1/10W	
R1343	1-216-121-00	METAL GLAZE	1M	5%	1/10W	
R1344	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1345	1-216-055-00	METAL GLAZE	1.8K	5%	1/10W	
R1346	1-216-047-00	METAL GLAZE	820	5%	1/10W	
R1347	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1348	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1349	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1350	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1351	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1352	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1353	1-216-115-00	METAL GLAZE	560K	5%	1/10W	
R1371	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W	
R1372	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W	
R1373	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W	
R1392	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R1393	1-216-095-00	METAL GLAZE	82K	5%	1/10W	

<VARIABLE RESISTOR>

RV101	1-241-763-11	RES, ADJ, CERMET	4.7K		
RV102	1-241-763-11	RES, ADJ, CERMET	4.7K		
RV103	1-238-009-11	RES, ADJ, CARBON	220		
RV104	1-238-009-11	RES, ADJ, CARBON	220		
RV105	1-241-627-11	RES, ADJ, CARBON	1K		
RV106	1-241-627-11	RES, ADJ, CARBON	1K		
RV107	1-241-627-11	RES, ADJ, CARBON	1K		
RV108	1-241-630-11	RES, ADJ, CARBON	10K		
RV109	1-241-765-11	RES, ADJ, CERMET	22K		
RV110	1-241-630-11	RES, ADJ, CARBON	10K		
RV111	1-241-630-11	RES, ADJ, CARBON	10K		
RV112	1-238-019-11	RES, ADJ, CARBON	47K		
RV113	1-238-019-11	RES, ADJ, CARBON	47K		
RV114	1-238-019-11	RES, ADJ, CARBON	47K		
RV115	1-241-631-11	RES, ADJ, CARBON	22K		
RV116	1-241-631-11	RES, ADJ, CARBON	22K		
RV118	1-241-631-11	RES, ADJ, CARBON	22K		
RV119	1-241-631-11	RES, ADJ, CARBON	22K		
RV120	1-241-631-11	RES, ADJ, CARBON	22K		
RV121	1-241-631-11	RES, ADJ, CARBON	22K		
RV122	1-241-631-11	RES, ADJ, CARBON	22K		
RV123	1-241-628-11	RES, ADJ, CARBON	2.2K		
RV124	1-241-627-11	RES, ADJ, CARBON	1K		
RV125	1-241-627-11	RES, ADJ, CARBON	1K		
RV205	1-241-631-11	RES, ADJ, CARBON	22K		

<MODULE>

SEP101	1-808-654-11	MODULE

<CRYSTAL>

X101	1-527-722-00	OSCILLATOR, CRYSTAL
X102	1-577-259-11	VIBRATOR, CRYSTAL

****

	A-1346-018-A	D BOARD, COMPLETE
		**********
	1-533-189-11	HOLDER, FUSE
	*3-738-015-01	COVER, (DIA. 6) CARBON VR
	4-382-854-01	SCREW (M3X8), P, SW (+)
	4-382-854-11	SCREW (M3X10), P, SW (+)

<CAPACITOR>

C501	1-124-477-11	ELECT	47MF	20%	16V
C502	1-124-907-11	ELECT	10MF	20%	50V
C503	1-126-103-11	ELECT	470MF	20%	16V
C504	1-124-902-00	ELECT	0.47MF	20%	50V
C505	1-106-381-12	MYLAR	0.039MF	10%	100V

REF.NO.	PART NO.	DESCRIPTION			REMARK
C506	1-124-903-11	ELECT	1MF	20%	50V
C507	1-106-367-00	MYLAR	0.01MF	10%	100V
C508	1-124-903-11	ELECT	1MF	20%	50V
C509	1-136-173-00	FILM	0.47MF	5%	50V
C510	1-136-161-00	FILM	0.047MF	5%	50V
C511	1-124-903-11	ELECT	1MF	20%	50V
C512	1-106-375-12	MYLAR	0.022MF	10%	100V
C513	1-106-375-12	MYLAR	0.022MF	10%	100V
C514	1-106-371-00	MYLAR	0.015MF	10%	100V
C515	1-124-925-11	ELECT	2.2MF	20%	50V
C516	1-124-925-11	ELECT	2.2MF	20%	50V
C517	1-130-480-00	FILM	0.0056MF	5%	50V
C518	1-163-245-11	CERAMIC CHIP	56PF	5%	50V
C519	1-124-927-11	ELECT	4.7MF	20%	50V
C520	1-163-129-00	CERAMIC CHIP	330PF	5%	50V
C521	1-124-907-11	ELECT	10MF	20%	50V
C523	1-106-363-00	MYLAR	0.0068MF	10%	100V
C524	1-102-116-00	CERAMIC	680PF	10%	50V
C525	1-102-820-00	CERAMIC	330PF	5%	50V
C526	1-102-973-00	CERAMIC	100PF	5%	50V
C527	1-124-122-11	ELECT	100MF	20%	50V
C528	1-102-125-00	CERAMIC	0.0047MF	10%	50V
C529	1-124-910-11	ELECT	47MF	20%	50V
C530	1-163-097-00	CERAMIC CHIP	15PF	5%	50V
C531	1-131-370-00	TANTALUM	6.8MF	10%	16V
C532	1-124-557-11	ELECT	1000MF	20%	25V
C533	1-124-927-11	ELECT	4.7MF	20%	50V
C534	1-124-768-11	ELECT	4.7MF	20%	50V
C535	1-136-161-00	FILM	0.047MF	5%	50V
C536	1-124-927-11	ELECT	4.7MF	20%	50V
C537	1-124-484-11	ELECT	220MF	20%	35V
C538	1-124-910-11	ELECT	47MF	20%	50V
C539	1-136-113-00	FILM	2MF	5%	200V
C540	1-163-017-00	CERAMIC CHIP	0.0047MF	10%	50V
C541	1-163-035-00	CERAMIC CHIP	0.047MF		50V
C542	1-126-103-11	ELECT	470MF	20%	16V
C545	1-126-101-11	ELECT	100MF	20%	16V
C546	1-124-907-11	ELECT	10MF	20%	50V
C547	1-124-907-11	ELECT	10MF	20%	50V
C548	1-124-907-11	ELECT	10MF	20%	50V
C549	1-124-907-11	ELECT	10MF	20%	50V
C550	1-124-907-11	ELECT	10MF	20%	50V
C551	1-124-927-11	ELECT	4.7MF	20%	50V
C552	1-101-004-00	CERAMIC	0.01MF		50V
C553	1-126-103-11	ELECT	470MF	20%	16V
C563	1-106-383-00	MYLAR	0.047MF	10%	100V
C564	1-163-009-11	CERAMIC CHIP	0.001MF	10%	50V
C567	1-124-907-11	ELECT	10MF	20%	50V
C568	1-130-736-11	FILM	0.01MF	5%	50V
C569	1-130-471-00	FILM	0.001MF	5%	50V
C570	1-163-117-00	CERAMIC CHIP	100PF	5%	50V
C571	1-124-913-11	ELECT	470MF	20%	50V
C572	1-101-004-00	CERAMIC	0.01MF		50V
C574	1-106-351-00	MYLAR	0.0022MF	10%	100V
C575	1-106-351-00	MYLAR	0.0022MF	10%	100V
C831	1-124-907-11	ELECT	10MF	20%	50V
C832	1-124-907-11	ELECT	10MF	20%	50V
C833	1-163-009-11	CERAMIC CHIP	0.001MF	10%	50V
C834	1-163-121-00	CERAMIC CHIP	150PF	5%	50V
C835	1-163-209-00	CERAMIC CHIP	0.0015MF	5%	50V
C836	1-124-907-11	ELECT	10MF	20%	50V
C837	1-163-209-00	CERAMIC CHIP	0.0015MF	5%	50V
C838	1-136-163-00	FILM	0.068MF	5%	50V
C839	1-106-351-00	MYLAR	0.0022MF	10%	100V

REF.NO.	PART NO.	DESCRIPTION			REMARK
C840	1-163-209-00	CERAMIC CHIP	0.0015MF	5%	50V
C841	1-163-209-00	CERAMIC CHIP	0.0015MF	5%	50V
C843	1-124-902-00	ELECT	0.47MF	20%	50V
C844	1-124-902-00	ELECT	0.47MF	20%	50V
C845	1-124-477-11	ELECT	47MF	20%	25V
C846	1-124-907-11	ELECT	10MF	20%	50V
C847	1-124-916-11	ELECT	22MF	20%	50V
C848	1-131-351-00	TANTALUM	4.7MF	10%	35V
C849	1-164-182-11	CERAMIC CHIP	0.0033MF	10%	50V
C1601	1-124-907-11	ELECT	10MF	20%	50V
C1602	1-164-161-11	CERAMIC CHIP	0.0022MF	10%	50V
C1603	1-104-348-11	ELECT	15MF	20%	50V
C1604	1-128-500-51	ELECT	1000MF	20%	50V
C1605	1-124-922-11	ELECT	1000MF	20%	50V
C1606	1-163-009-11	CERAMIC CHIP	0.001MF	10%	50V
C1607	1-124-907-11	ELECT	10MF	20%	50V
C1608	1-124-916-11	ELECT	22MF	20%	50V
C1609	1-163-009-11	CERAMIC CHIP	0.001MF	10%	50V
C1610	1-124-927-11	ELECT	4.7MF	20%	50V
C1611	1-124-482-11	ELECT	33MF	20%	35V
C1612	1-136-257-00	FILM	0.0039MF	5%	50V
C1613	1-163-009-11	CERAMIC CHIP	0.001MF	10%	50V
C1614	1-164-232-11	CERAMIC CHIP	0.01MF	10%	50V
C1615	1-124-465-00	ELECT	0.47MF	20%	50V
C1620	1-163-133-00	CERAMIC CHIP	470PF	5%	50V
C1621	1-163-117-00	CERAMIC CHIP	100PF	5%	50V
C1641	1-163-035-00	CERAMIC CHIP	0.047MF		50V

<CONNECTOR>

CN501	*1-564-506-11	PLUG, CONNECTOR 3P	
CN502	1-506-477-11	PIN, CONNECTOR 12P	
CN504	*1-564-507-11	PLUG, CONNECTOR 4P	
CN505	*1-564-509-11	PLUG, CONNECTOR 6P	
CN507	*1-564-511-11	PLUG, CONNECTOR 8P	
CN508	*1-564-104-00	PIN, CONNECTOR (B3P-VH) 3P	
CN509	*1-564-506-11	PLUG, CONNECTOR 3P	

<DIODE>

D501	8-719-404-46	DIODE MA110
D502	8-719-404-46	DIODE MA110
D503	8-719-404-46	DIODE MA110
D504	8-719-404-46	DIODE MA110
D506	8-719-908-03	DIODE GP08D
D507	8-719-404-46	DIODE MA110
D508	8-719-404-46	DIODE MA110
D511	8-719-404-46	DIODE MA110
D512	8-719-404-46	DIODE MA110
D514	8-719-404-46	DIODE MA110
D520	8-719-800-76	DIODE 1SS226
D521	8-719-800-76	DIODE 1SS226
D831	8-719-404-46	DIODE MA110
D832	8-719-404-46	DIODE MA110
D833	8-719-404-46	DIODE MA110
D834	8-719-404-46	DIODE MA110
D835	8-719-109-89	DIODE RD5.6ES-B2
D836	8-719-977-69	DIODE DTZ24B
D848	8-719-800-76	DIODE 1SS226
D1601	8-719-105-XX	DIODE RD6.2M-B1
D1603	8-719-977-61	DIODE DTZ20B
D1606	8-719-981-00	DIODE ERC81-004
D1607	8-719-981-00	DIODE ERC81-004

D

The components identified by shading and mark ⚠ are critical for safety.
Replace only with part number specified.

REF.NO.	PART NO.	DESCRIPTION	REMARK
D1608	8-719-977-02	DIODE DTZ5.6A	
D1609	8-719-977-49	DIODE DTZ15B	
D1610	8-719-404-46	DIODE MA110	
D1611	8-729-101-31	TRANSISTOR N13T1	
D1612	8-719-404-46	DIODE MA110	
D1615	8-719-404-46	DIODE MA110	
D1617	8-719-977-49	DIODE DTZ15B	
D1618	8-719-977-49	DIODE DTZ15B	
D1620	8-719-400-18	DIODE MA152WK	
D1621	8-719-510-12	DIODE D10SC4M	
D1622	8-719-400-18	DIODE MA152WK	
D1623	8-719-400-18	DIODE MA152WK	
D1626	8-719-404-46	DIODE MA110	
D1627	8-719-404-46	DIODE MA110	
D1628	8-719-404-46	DIODE MA110	
D1635	8-719-404-46	DIODE MA110	
D1699	8-719-404-46	DIODE MA110	
		<FUSE>	
F1601⚠	1-532-777-21	FUSE, MICRO (SECONDARY) (1.25A/125V)	
F1602⚠	1-576-232-11	FUSE (H.B.C) (5.0A/250V)	
		<IC>	
IC501	8-759-909-70	IC CX23025	
IC502	8-759-100-60	IC UPC1377C	
IC503	8-759-801-98	IC LA7830	
IC504	8-759-701-79	IC MC7812CT	
IC505	8-759-009-51	IC MC14538BF	
IC831	8-759-509-29	IC XRU4011BF	
IC832	8-759-509-37	IC XRU4070BF	
IC833	8-759-009-51	IC MC14538BF	
IC1601	8-759-509-91	IC XRA10393F	
		<JUMPER RESISTOR>	
JR510	1-216-295-00	METAL GLAZE 0 5% 1/10W	
		<COIL>	
L501	1-410-093-11	INDUCTOR 33MMH	
L502	1-410-665-31	INDUCTOR 15UH	
L503	1-424-625-11	COIL, CHOKE (PMC) 390UH	
L506	1-412-530-31	INDUCTOR 27UH	
L1601	1-459-155-00	COIL (WITH CORE) 47UH	
L1602	1-402-785-11	COIL, CHOKE 600UH	
L1603	1-410-397-21	FERRITE BEAD INDUCTOR	
		<TRANSISTOR>	
Q501	8-729-901-01	TRANSISTOR DTC144EK	
Q502	8-729-901-01	TRANSISTOR DTC144EK	
Q503	8-729-901-06	TRANSISTOR DTA144EK	
Q504	8-729-901-01	TRANSISTOR DTC144EK	
Q505	8-729-422-27	TRANSISTOR 2SD601A-Q	
Q508	8-729-422-27	TRANSISTOR 2SD601A-Q	
Q509	8-729-422-27	TRANSISTOR 2SD601A-Q	
Q510	8-729-901-06	TRANSISTOR DTA144EK	
Q512	8-729-422-27	TRANSISTOR 2SD601A-Q	
Q513	8-729-216-22	TRANSISTOR 2SA1162-G	
Q514	8-729-216-22	TRANSISTOR 2SA1162-G	
Q515	8-729-313-42	TRANSISTOR 2SD1134-C	
Q518	8-729-422-27	TRANSISTOR 2SD601A-Q	
Q519	8-729-422-27	TRANSISTOR 2SD601A-Q	
Q532	8-729-422-27	TRANSISTOR 2SD601A-Q	
Q569	8-729-907-26	TRANSISTOR IMX1	
Q576	8-729-920-48	TRANSISTOR IMH2	
Q579	8-729-920-48	TRANSISTOR IMH2	
Q599	8-729-920-48	TRANSISTOR IMH2	
Q833	8-729-216-22	TRANSISTOR 2SA1162-G	
Q834	8-729-422-27	TRANSISTOR 2SD601A-Q	
Q835	8-729-422-27	TRANSISTOR 2SD601A-Q	
Q836	8-729-255-12	TRANSISTOR 2SC2551-O	
Q1601	8-729-422-27	TRANSISTOR 2SD601A-Q	
Q1602	8-729-422-27	TRANSISTOR 2SD601A-Q	
Q1603	8-729-422-27	TRANSISTOR 2SD601A-Q	
Q1604	8-729-216-22	TRANSISTOR 2SA1162-G	
Q1605	8-729-119-80	TRANSISTOR 2SC2688-LK	
Q1606	8-729-133-42	TRANSISTOR 2SC2334-L	
Q1607	8-729-422-27	TRANSISTOR 2SD601A-Q	
Q1608	8-729-422-27	TRANSISTOR 2SD601A-Q	
Q1609	8-729-422-27	TRANSISTOR 2SD601A-Q	
Q1610	8-729-422-27	TRANSISTOR 2SD601A-Q	
Q1611	8-729-422-27	TRANSISTOR 2SD601A-Q	
Q1612	8-729-422-27	TRANSISTOR 2SD601A-Q	
Q1613	8-729-422-27	TRANSISTOR 2SD601A-Q	
Q1614	8-729-422-27	TRANSISTOR 2SD601A-Q	
Q1615	8-729-216-22	TRANSISTOR 2SA1162-G	
Q1616	8-729-216-22	TRANSISTOR 2SA1162-G	
Q1617	8-729-216-22	TRANSISTOR 2SA1162-G	
Q1618	8-729-216-22	TRANSISTOR 2SA1162-G	
		<RESISTOR>	
R501	1-216-089-00	METAL GLAZE 47K 5% 1/10W	
R502	1-216-089-00	METAL GLAZE 47K 5% 1/10W	
R503	1-249-437-11	CARBON 47K 5% 1/4W	F
R504	1-216-073-00	METAL GLAZE 10K 5% 1/10W	
R505	1-249-393-11	CARBON 10 5% 1/4W	F
R506	1-216-071-00	METAL GLAZE 8.2K 5% 1/10W	
R507	1-216-059-00	METAL GLAZE 2.7K 5% 1/10W	
R508	1-216-085-00	METAL GLAZE 33K 5% 1/10W	
R509	1-216-687-11	METAL CHIP 33K 0.50% 1/10W	
R510	1-216-683-11	METAL CHIP 22K 0.50% 1/10W	
R511	1-216-675-11	METAL CHIP 10K 0.50% 1/10W	
R512	1-218-761-11	METAL CHIP 240K 0.50% 1/10W	
R513	1-216-065-00	METAL GLAZE 4.7K 5% 1/10W	
R514	1-218-754-11	METAL CHIP 120K 0.50% 1/10W	
R515	1-216-081-00	METAL GLAZE 22K 5% 1/10W	
R516	1-216-073-00	METAL GLAZE 10K 5% 1/10W	
R517	1-218-762-11	METAL CHIP 270K 0.50% 1/10W	
R518	1-249-422-11	CARBON 2.7K 5% 1/4W	F
R519	1-216-085-00	METAL GLAZE 33K 5% 1/10W	
R520	1-216-677-11	METAL CHIP 12K 0.50% 1/10W	
R521	1-216-067-00	METAL GLAZE 5.6K 5% 1/10W	
R522	1-216-107-00	METAL GLAZE 270K 5% 1/10W	
R523	1-216-081-00	METAL GLAZE 22K 5% 1/10W	
R524	1-216-049-00	METAL GLAZE 1K 5% 1/10W	
R525	1-216-434-11	METAL OXIDE 1.8K 5% 1W	F
R526	1-216-079-00	METAL GLAZE 18K 5% 1/10W	
R527	1-249-437-11	CARBON 47K 5% 1/4W	F
R528	1-216-073-00	METAL GLAZE 10K 5% 1/10W	
R529	1-216-073-00	METAL GLAZE 10K 5% 1/10W	
R530	1-216-089-00	METAL GLAZE 47K 5% 1/10W	
R531	1-216-089-00	METAL GLAZE 47K 5% 1/10W	
R532	1-216-097-00	METAL GLAZE 100K 5% 1/10W	
R533	1-216-089-00	METAL GLAZE 47K 5% 1/10W	

REF.NO.	PART NO.	DESCRIPTION				REMARK
R534	1-216-097-00	METAL GLAZE	100K	5%	1/10W	
R535	1-216-053-00	METAL GLAZE	1.5K	5%	1/10W	
R536	1-212-881-11	FUSIBLE	100	5%	1/4W	F
R537	1-215-867-00	METAL OXIDE	470	5%	1W	F
R538	1-216-095-00	METAL GLAZE	82K	5%	1/10W	
R539	1-216-095-00	METAL GLAZE	82K	5%	1/10W	
R540	1-216-101-00	METAL GLAZE	150K	5%	1/10W	
R541	1-216-063-00	METAL GLAZE	3.9K	5%	1/10W	
R542	1-216-075-00	METAL GLAZE	12K	5%	1/10W	
R543	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R544	1-216-101-00	METAL GLAZE	150K	5%	1/10W	
R545	1-216-041-00	METAL GLAZE	470	5%	1/10W	
R546	1-216-091-00	METAL GLAZE	56K	5%	1/10W	
R547	1-216-121-00	METAL GLAZE	1M	5%	1/10W	
R548	1-216-107-00	METAL GLAZE	270K	5%	1/10W	
R549	1-216-101-00	METAL GLAZE	150K	5%	1/10W	
R550	1-216-356-00	METAL OXIDE	3.9	5%	1W	F
R552	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R553	1-216-689-11	METAL GLAZE	39K	5%	1/10W	
R554	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R555	1-216-077-00	METAL GLAZE	15K	5%	1/10W	
R557	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W	
R558	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R559	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R560	1-216-037-00	METAL GLAZE	330	5%	1/10W	
R561	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R562	1-216-053-00	METAL GLAZE	1.5K	5%	1/10W	
R563	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R564	1-249-415-11	CARBON	680	5%	1/4W	F
R565	1-216-059-00	METAL GLAZE	2.7K	5%	1/10W	
R566	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R567	1-216-095-00	METAL GLAZE	82K	5%	1/10W	
R568	1-216-063-00	METAL GLAZE	3.9K	5%	1/10W	
R569	1-216-063-00	METAL GLAZE	3.9K	5%	1/10W	
R570	1-216-093-00	METAL GLAZE	68K	5%	1/10W	
R571	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R572	1-216-095-00	METAL GLAZE	82K	5%	1/10W	
R573	1-216-063-00	METAL GLAZE	3.9K	5%	1/10W	
R574	1-216-063-00	METAL GLAZE	3.9K	5%	1/10W	
R575	1-216-105-00	METAL GLAZE	220K	5%	1/10W	
R576	1-216-109-00	METAL GLAZE	330K	5%	1/10W	
R577	1-216-105-00	METAL GLAZE	220K	5%	1/10W	
R578	1-249-457-11	CARBON	6.8	5%	1/4W	F
R579	1-249-457-11	CARBON	6.8	5%	1/4W	F
R589	1-216-101-00	METAL GLAZE	150K	5%	1/10W	
R591	1-216-063-00	METAL GLAZE	3.9K	5%	1/10W	
R592	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R831	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R832	1-216-075-00	METAL GLAZE	12K	5%	1/10W	
R833	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R834	1-216-059-00	METAL GLAZE	2.7K	5%	1/10W	
R835	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R836	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R837	1-216-075-00	METAL GLAZE	12K	5%	1/10W	
R838	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R839	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R840	1-216-097-00	METAL GLAZE	100K	5%	1/10W	
R841	1-216-093-00	METAL GLAZE	68K	5%	1/10W	
R842	1-216-093-00	METAL GLAZE	68K	5%	1/10W	
R843	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R844	1-216-077-00	METAL GLAZE	15K	5%	1/10W	
R847	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R850	1-216-085-00	METAL GLAZE	33K	5%	1/10W	
R851	1-216-669-11	METAL CHIP	5.6K	0.50%	1/10W	
R852	1-216-675-11	METAL CHIP	10K	0.50%	1/10W	
R853	1-216-105-00	METAL GLAZE	220K	5%	1/10W	
R854	1-218-754-11	METAL CHIP	120K	0.50%	1/10W	
R855	1-216-697-11	METAL CHIP	82K	0.50%	1/10W	
R856	1-216-699-11	METAL CHIP	100K	0.50%	1/10W	
R857	1-216-686-11	METAL CHIP	30K	0.50%	1/10W	
R858	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R859	1-216-436-00	METAL OXIDE	3.9K	5%	1W	F
R860	1-216-675-11	METAL CHIP	10K	0.50%	1/10W	
R861	1-216-671-11	METAL CHIP	6.8K	0.50%	1/10W	
R862	1-216-675-11	METAL CHIP	10K	0.50%	1/10W	
R863	1-249-435-11	CARBON	33K	5%	1/4W	F
R1503	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R1504	1-216-695-11	METAL CHIP	68K	0.50%	1/10W	
R1505	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R1506	1-216-667-11	METAL CHIP	4.7K	0.50%	1/10W	
R1507	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R1508	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1509	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R1510	1-249-425-11	CARBON	4.7K	5%	1/4W	F
R1511	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R1512	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R1513	1-216-017-00	METAL GLAZE	47	5%	1/10W	
R1519	1-216-031-00	METAL GLAZE	180	5%	1/10W	
R1520	1-216-053-00	METAL GLAZE	1.5K	5%	1/10W	
R1601	1-216-685-11	METAL CHIP	27K	0.50%	1/10W	
R1602	1-216-681-11	METAL CHIP	18K	0.50%	1/10W	
R1603	1-216-671-11	METAL CHIP	6.8K	0.50%	1/10W	
R1604	1-249-433-11	CARBON	22K	5%	1/4W	F
R1605	1-216-070-00	METAL GLAZE	7.5K	5%	1/10W	
R1606	1-216-070-00	METAL GLAZE	7.5K	5%	1/10W	
R1607	1-216-071-00	METAL GLAZE	8.2K	5%	1/10W	
R1608	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R1609	1-216-069-00	METAL GLAZE	6.8K	5%	1/10W	
R1610	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W	
R1611	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W	
R1612	1-215-913-11	METAL OXIDE	220	5%	3W	F
R1613	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R1614	1-216-067-00	METAL GLAZE	5.6K	5%	1/10W	
R1615	1-216-657-11	METAL CHIP	1.8K	0.50%	1/10W	
R1616	1-216-629-11	METAL CHIP	120	0.50%	1/10W	
R1617	1-216-659-11	METAL CHIP	2.2K	0.50%	1/10W	
R1618	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1620	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R1621	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1622	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1623	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1624	1-216-246-00	METAL GLAZE	100K	5%	1/8W	
R1625	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R1626	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R1627	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R1628	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1629	1-216-683-11	METAL CHIP	22K	0.50%	1/10W	
R1630	1-216-683-11	METAL CHIP	22K	0.50%	1/10W	
R1631	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W	
R1632	1-216-042-00	METAL GLAZE	510	5%	1/10W	
R1633	1-216-109-00	METAL GLAZE	330K	5%	1/10W	
R1634	1-216-099-00	METAL GLAZE	120K	5%	1/10W	
R1635	1-216-097-00	METAL GLAZE	100K	5%	1/10W	
R1636	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1640	1-216-063-00	METAL GLAZE	3.9K	5%	1/10W	
R1641	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1642	1-216-073-00	METAL GLAZE	10K	5%	1/10W	

D S

• The components identified by ⊠ in this manual have been carefully factory-selected for each set in order to satisfy regulations regarding X-ray radiation. Should replacement be required, replace only with the value originally used.

The components identified by shading and mark ⚠ are critical for safety.
Replace only with part number specified.

REF.NO.	PART NO.	DESCRIPTION			REMARK
R1643	1-216-069-00	METAL GLAZE	6.8K	5% 1/10W	
R1644	1-216-069-00	METAL GLAZE	6.8K	5% 1/10W	
R1645	1-216-073-00	METAL GLAZE	10K	5% 1/10W	
R1646	1-216-073-00	METAL GLAZE	10K	5% 1/10W	
R1647	1-216-685-11	METAL CHIP	27K	0.50% 1/10W	
R1648	1-216-069-00	METAL GLAZE	6.8K	5% 1/10W	
R1649	1-216-069-00	METAL GLAZE	6.8K	5% 1/10W	
R1650	1-216-069-00	METAL GLAZE	6.8K	5% 1/10W	
R1651	1-216-069-00	METAL GLAZE	6.8K	5% 1/10W	
R1652	1-216-069-00	METAL GLAZE	6.8K	5% 1/10W	
R1653	1-216-069-00	METAL GLAZE	6.8K	5% 1/10W	
R1654	1-216-681-11	METAL CHIP	18K	0.50% 1/10W	
R1655	1-216-081-00	METAL GLAZE	22K	5% 1/10W	
R1656	1-216-643-11	METAL CHIP	470	0.50% 1/10W	
R1657	1-216-081-00	METAL GLAZE	22K	5% 1/10W	
R1658	1-216-063-00	METAL GLAZE	3.9K	5% 1/10W	
R1659	1-216-049-00	METAL GLAZE	1K	5% 1/10W	
R1660	1-216-649-11	METAL CHIP	820	0.50% 1/10W	
R1661	1-216-065-00	METAL GLAZE	4.7K	5% 1/10W	
		<VARIABLE RESISTOR>			
RV501	1-238-019-11	RES, ADJ, CARBON 47K			
RV502	1-241-631-11	RES, ADJ, CARBON 22K			
RV503	1-241-763-11	RES, ADJ, CERMET 4.7K			
RV504	1-224-250-XX	RES, ADJ, METAL GLAZE 2.2K			
RV505	1-238-009-11	RES, ADJ, CARBON 220			
RV506	1-241-627-11	RES, ADJ, CARBON 1K			
RV507	1-241-628-11	RES, ADJ, CARBON 2.2K			
RV508	1-241-627-11	RES, ADJ, CARBON 1K			
RV509	1-238-021-11	RES, ADJ, CARBON 220K			
RV511	1-241-629-11	RES, ADJ, CARBON 4.7K			
RV512	1-241-629-11	RES, ADJ, CARBON 4.7K			
RV514	1-238-019-11	RES, ADJ, CARBON 47K			
RV515	1-238-021-11	RES, ADJ, CARBON 220K			
RV516	1-241-763-11	RES, ADJ, CERMET 4.7K			
RV831	1-228-997-00	RES, ADJ, METAL GLAZE 100K			
RV832	1-241-764-11	RES, ADJ, CERMET 10K			
⊠RV833⚠	1-228-996-11	RES, ADJ, METAL GLAZE 47K			
RV1601	1-241-762-11	RES, ADJ, CERMET 2.2K			
RV1602	1-241-627-11	RES, ADJ, CARBON 1K			
⊠RV1603⚠	1-228-996-11	RES, ADJ, METAL GLAZE 47K			
		<RELAY>			
RY1601	1-515-481-21	RELAY (G2R-212P-V)			
		<TRANSFORMER>			
T1601	1-437-216-11	TRANSFORMER, DRIVE			

****

*A-1394-368-A S BOARD, COMPLETE
****

		<CAPACITOR>			
C1101	1-163-119-00	CERAMIC CHIP 120PF	5%	50V	
C1102	1-164-004-11	CERAMIC CHIP 0.1MF	10%	25V	
C1103	1-124-589-11	ELECT 47MF	20%	16V	
C1104	1-163-031-11	CERAMIC CHIP 0.01MF		50V	
C1105	1-163-114-00	CERAMIC CHIP 75PF	5%	50V	
C1106	1-163-101-00	CERAMIC CHIP 22PF	5%	50V	
C1107	1-164-004-11	CERAMIC CHIP 0.1MF	10%	25V	
C1108	1-163-119-00	CERAMIC CHIP 120PF	5%	50V	
C1109	1-163-031-11	CERAMIC CHIP 0.01MF		50V	
C1110	1-163-117-00	CERAMIC CHIP 100PF	5%	50V	
C1111	1-163-018-00	CERAMIC CHIP 0.0056MF	10%	50V	
C1112	1-126-160-11	ELECT 1MF	20%	50V	
C1113	1-163-119-00	CERAMIC CHIP 120PF	5%	50V	
C1114	1-163-103-00	CERAMIC CHIP 27PF	5%	50V	
C1115	1-164-004-11	CERAMIC CHIP 0.1MF	10%	25V	
C1116	1-163-114-00	CERAMIC CHIP 75PF	5%	50V	
C1117	1-124-589-11	ELECT 47MF	20%	16V	
C1118	1-164-004-11	CERAMIC CHIP 0.1MF	10%	25V	
C1119	1-163-020-00	CERAMIC CHIP 0.0082MF	10%	50V	
C1120	1-163-097-00	CERAMIC CHIP 15PF	5%	50V	
C1121	1-163-097-00	CERAMIC CHIP 15PF	5%	50V	
C1122	1-163-222-11	CERAMIC CHIP 5PF	0.25PF	50V	
C1123	1-163-097-00	CERAMIC CHIP 15PF	5%	50V	
C1130	1-163-097-00	CERAMIC CHIP 15PF	5%	50V	
C1131	1-163-097-00	CERAMIC CHIP 15PF	5%	50V	
		<CONNECTOR>			
CN1101*	1-565-488-11	CONNECTOR, BOARD TO BOARD 12P			
		<DIODE>			
D1101	8-719-404-46	DIODE MA110			
D1102	8-719-404-46	DIODE MA110			
		<IC>			
IC1101	8-752-056-67	IC CXA1214P			
		<COIL>			
L1101	1-408-411-00	INDUCTOR 15UH			
L1102	1-404-496-00	COIL			
L1103	1-404-496-00	COIL			
L1104	1-408-411-00	INDUCTOR 15UH			
L1110	1-412-008-31	INDUCTOR CHIP 15UH			
L1111	1-412-008-31	INDUCTOR CHIP 15UH			
		<TRANSISTOR>			
Q1101	8-729-216-22	TRANSISTOR 2SA1162-G			
Q1102	8-729-422-27	TRANSISTOR 2SD601A-Q			
Q1103	8-729-216-22	TRANSISTOR 2SA1162-G			
Q1104	8-729-216-22	TRANSISTOR 2SA1162-G			
Q1105	8-729-901-01	TRANSISTOR DTC144EK			
Q1106	8-729-901-01	TRANSISTOR DTC144EK			
Q1107	8-729-109-44	TRANSISTOR 2SK94			
Q1108	8-729-422-27	TRANSISTOR 2SD601A-Q			
		<RESISTOR>			
R1101	1-216-053-00	METAL GLAZE	1.5K	5% 1/10W	
R1102	1-216-067-00	METAL GLAZE	5.6K	5% 1/10W	
R1103	1-216-059-00	METAL GLAZE	2.7K	5% 1/10W	
R1104	1-216-073-00	METAL GLAZE	10K	5% 1/10W	
R1105	1-216-031-00	METAL GLAZE	180	5% 1/10W	
R1106	1-216-059-00	METAL GLAZE	2.7K	5% 1/10W	
R1107	1-216-071-00	METAL GLAZE	8.2K	5% 1/10W	
R1108	1-216-039-00	METAL GLAZE	390	5% 1/10W	
R1109	1-216-063-00	METAL GLAZE	3.9K	5% 1/10W	
R1110	1-216-069-00	METAL GLAZE	6.8K	5% 1/10W	

REF.NO.	PART NO.	DESCRIPTION				REMARK
R1111	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R1112	1-216-059-00	METAL GLAZE	2.7K	5%	1/10W	
R1113	1-216-069-00	METAL GLAZE	6.8K	5%	1/10W	
R1114	1-216-055-00	METAL GLAZE	1.8K	5%	1/10W	
R1115	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R1116	1-216-069-00	METAL GLAZE	6.8K	5%	1/10W	
R1117	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R1118	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1119	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R1120	1-216-097-00	METAL GLAZE	100K	5%	1/10W	
R1121	1-216-121-00	METAL GLAZE	1M	5%	1/10W	
R1122	1-216-039-00	METAL GLAZE	390	5%	1/10W	
R1123	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R1124	1-216-029-00	METAL GLAZE	150	5%	1/10W	
R1125	1-216-029-00	METAL GLAZE	150	5%	1/10W	
R1126	1-216-053-00	METAL GLAZE	1.5K	5%	1/10W	
R1127	1-216-043-00	METAL GLAZE	560	5%	1/10W	
R1128	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R1129	1-216-091-00	METAL GLAZE	56K	5%	1/10W	
R1131	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1132	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1133	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1134	1-216-091-00	METAL GLAZE	56K	5%	1/10W	

<VARIABLE RESISTOR>

RV1101	1-241-629-11	RES, ADJ, CARBON 4.7K
RV1102	1-241-628-11	RES, ADJ, CARBON 2.2K

<TRANSFORMER>

T1101	1-404-584-11	COIL

9-978-259-81

Sony Corporation
Display Products Group

English
93AL0512-1
Printed in Japan
© 1993. 1

PVM-9041QM/9044QM

SONY
SERVICE MANUAL

AEP Model

PVM-9041QM
Chassis No. SCC-F09B-A
PVM-9044QM
Chassis No. SCC-F09A-A

SUPPLEMENT-3

File this supplement with the service manual.

INTRODUCTION

New Product, which have a changeover switch with both 16 : 9 and 4 : 3, has come from the following Serial Number.

Model	Serial Number
PVM-9041QM	2,500,001 and later
PVM-9044QM	2,500,001 and later

MICROFILM

SPECIFICATIONS

Video signal

Color system	**PVM-9044QM/9041QM:** PAL, SECAM, NTSC, NTSC4.43
Resolution	**PVM-9044QM:** 450 TV lines **PVM-9041QM:** 250 TV lines
Aperture correction	–4.0 dB – +6.0 dB (at 3.0 MHz)
Frequency response	6.0 MHz (–3.0 dB) at all inputs
Synchronization	AFC time constant 1.0 msec.

Picture performance

Normal scan	6% over scan of CRT effective screen area
Underscan	3% underscan of CRT effective screen area
H. linearity	Less than 7.0% (typical)
V. linearity	Less than 7.0% (typical)
Convergence	Central area: 0.43 mm (typical) Peripheral area: 0.53 mm (typical)
Raster size stability	H: 1.0%, V: 1.5%
High voltage regulation	3.0%
Color temperature	D65

Inputs and Outputs

Inputs	Y/C IN: 4-pin mini DIN connector (See the pin assignment on page 10.) VIDEO IN: BNC connector 1Vp-p ± 6 dB, sync negative AUDIO IN: phono jack, –5 dBs, less than 47k ohms R/R-Y, G/Y, B/B-Y: BNC connector R, G, B channels: 0.7 Vp-p, ±6 dB Sync on green: 0.3 Vp-p, negative, R-Y, Y, B-Y channels: 0.7 Vp-p, ±6 dB (Standard color bar signal of 100% chrominance) EXT SYNC IN: BNC connector Composite sync 4 Vp-p, ±6 dB, negative
Loop-through outputs	Y/C OUT: 4-pin mini DIN connector, 75 ohms terminated VIDEO OUT: BNC connector, 75 ohms terminated AUDIO OUT: phono jack Output level 0.5 W EXT SYNC OUT: BNC connector, 75 ohms terminated
Remote input	REMOTE: 8-pin mini DIN connector (See the pin assignment on page 10.)

General

Power consumption	**PVM-9044QM/9041QM** 43 W at AC operation 40 W at DC operation
Power requirements	100 – 240 V AC, 50/60 Hz (for all models) 12 V DC, with the Sony (NP-1A/1B) battery pack (not supplied) or AC-550/550CE AC power adaptor (not supplied)
Operating temperature range	0 – 35°C
Storage temperature range	–10 – +40°C
Humidity	0 – 90%
Dimensions	Approx. 217 × 217 × 352.5 mm (w/h/d) ($8^5/_8 \times 8^5/_8 \times 14$ inches) not incl. projecting parts and controls
Weight	Approx. 7.8 kg (17 lb 3 oz) not incl. battery packs
Accessory supplied	AC power cord (1) Cable with an 8-pin connector (1) AC plug holders (1 set) Tally plate (1)

Design and specifications are subject to change without notice.

Pin Assignment

Y/C IN connector (4-pin mini DIN)



Pin No.	Signal	Description
1	Y-input	1 Vp-p, sync negative, 75 ohms
2	CHROMA sub-carrier-input	300 mVp-p, burst Delay time between Y and C: within 0±100 nsec., 75 ohms
3	GND for Y-input	GND
4	GND for CHROMA-input	GND

REMOTE connector (8-pin mini DIN)



Pin No.	Signal
1	Blue only
2	H/V delay
3	GND
4	INT/EXT SYNC
5	Tally
6	Underscan/normal scan
7	A/B or RGB/Y R-Y B-Y
8	RGB/LINE

For remote control, connect the pin of the desired function to pin 3 (GND).

TABLE OF CONTENTS

Section	Title	Page
1.	**GENERAL**	
1-1.	Features	4
1-2.	Location and Function of Parts and Controls	5
1-3.	Power Sources	9
2.	**DISASSEMBLY**	
2-1.	Cabinet Removal	10
2-2.	B Board Removal	10
2-3.	Switching Regulator Removal	11
2-4.	D Board Removal	11
2-5.	P Board Removal	12
2-6.	Rear Assy Removal	12
2-7.	HA and FA Boards Removal	13
2-8.	Picture Tube Removal	14
3.	**SET-UP ADJUSTMENTS**	
3-1.	Beam Landing	15
3-2.	Convergence	16
3-3.	Focus	18
3-4.	White Balance	18
4.	**SAFETY RELATED ADJUSTMENT**	
4-1.	Safety Related Adjustments	19
5.	**CIRCUIT ADJUSTMENTS**	
5-1.	D Board Adjustments	21
5-2.	B Board Adjustment	24
5-3.	S Board Adjustment	29
6.	**DIAGRAMS**	
6-1.	Block Diagrams (1)	30
	Block Diagrams (2)	34
6-2.	Frame Schematic Diagram	39
6-3.	Circuit Boards Location	43
6-4.	Printed Wiring Boards and Schematic Diagrams	43
	• D Board	44
	• QA Board	55
	• FA Board	56
	• G Board	56
	• HA Board	56
	• X Board	56
	• CA Board	57
	• P Board	57
	• S Board	58
	• B Board (1/2)	59
	• B Board (2/2)	63
6-5.	Semiconductors	69
7.	**EXPLODED VIEWS**	
7-1.	Chassis	71
7-2.	Picture Tube	72
8.	**ELECTRICAL PARTS LIST**	73

SECTION 1
GENERAL

The operating instructions mentioned here are partial abstracts from the Operating Instruction Manual. The page numbers of the Operating Instruction Manual remein as in the manual.

1-1. FEATURES

Four color systems available

(PVM-9044QM/9041QM only)

The monitor can display PAL, SECAM, NTSC and NTSC4.43[1] signals. The appropriate color system is selected automatically.

HR (High Resolution) Trinitron® [2] picture tube

(PVM-9044QM only)

The HR Trinitron picture tube provides a high resolution picture. Horizontal resolution is more than 450 TV lines at the center of the picture.

Blue only picture

(PVM-9044QM/9041QM only)

The picture can be displayed in blue and black only. This facilitates hue adjustment and the observation of video noise.

Analog RGB/component input connectors

(PVM-9044QM/9041QM only)

Analog RGB or component (Y, R-Y and B-Y) signals from video equipment can be input through these connectors.

Y/C input connector

The video signal, split into the chrominance signal (C) and the luminance signal (Y), can be input through this connector, eliminating the interference between the two signals, which tends to occur in a composite video signal, assuring video quality.

Beam current feedback circuit

The built-in beam current feedback circuit assures stable white balance.

Comb filter

(PVM-9044QM/9041QM only)

When NTSC video signals are received, a comb filter activates to increase the resolution, resulting in fine picture detail without color spill or color noise.

Under scan 4:3/16:9 selector[3]

(PVM-9044QM/9041QM only)

The monitor can display the 16:9 signal with the correct ratio of width and height, compressing the picture vertically. Selecting 16:9 with the UNDER SCAN 4:3/16:9 selector on the rear panel in the under scan mode changes the ratio of the picture to 16:9.

Automatic termination

(only connectors marked ⋔[3])

The Y/C, VIDEO IN and EXT SYNC IN[4] connectors are terminated at 75 ohms inside, when no cable is connected to the loop-through output connectors. When a cable is connected to an output connector, the 75-ohm termination is automatically released.

EIA standard 19-inch rack mounting

By using an MB-507 mounting bracket (not supplied), the monitor can be mounted in an EIA standard 19-inch rack. For details on mounting, see the instruction manual of the MB-507.



1) An NTSC4.43 signal is used for playing back NTSC-recorded video cassettes with a video tape recorder/player especially designed for use with this system.
2) Trinitron is a trademark of Sony Corporation.
3) The UNDER SCAN 4:3/16:9 selector and the ⋔ mark have been adopted since the serial No. 2500001 product.
4) The EXT SYNC IN connector is provided with the PVM-9044QM/9041QM only.

1-2. LOCATION AND FUNCTION OF PARTS AND CONTROLS



1 Tally lamp

2 POWER switch and indicator
Depress to turn the monitor on. The indicator will light up in green.
The POWER indicator also functions as the battery indicator. When the internal battery becomes weak or the power supplied through the DC12V IN jack decreases, the indicator flashes.

3 VOLUME control
Turn this control clockwise or counterclockwise to obtain the desired volume.

4 CONTR (contrast) control
Turn clockwise to make the contrast stronger and counterclockwise to make it weaker.

5 PHASE control
This control is effective only for the NTSC and NTSC4.43 color systems. Turn clockwise to make the skin tones greenish and counterclockwise to make them purplish.

6 CHROMA control
Turn clockwise to make the color intensity stronger and counterclockwise to make it weaker.

7 BRIGHT (brightness) control
Turn clockwise for more brightness and counterclockwise for less.

8 APER (aperture) control
Turn clockwise for more sharpness and counterclockwise for less.

Notes

- The PHASE, CHROMA and APER control settings have no effect on an analog RGB signal.
- The PHASE control has no effect on component singals.
- The PHASE control setting is effective only for the NTSC system.

9 SYNC INT/EXT (sync internal/external) selector
Keep this button released (INT) to operate the monitor on the sync signal from the displayed composite video signal.
Depress this button (EXT) to operate the monitor on an external sync signal fed through the EXT SYNC connector on the rear panel.

10 LINE/RGB input selector
Select the program to be monitored. Keep this button released (LINE) for a signal fed through the LINE A or LINE B connectors. Depress this button (RGB) for a signal fed through the RGB connectors.

11 A/B, RGB/Y R-Y B-Y input selector
When the LINE/RGB input selector is set to LINE,
keep this button released (A) for a signal fed through the LINE A connectors. Depress this button (B) for a signal fed through the LINE B connectors.

When the LINE/RGB input selector is set to RGB,
select the RGB signal or the component signal which is fed through the RGB input connectors. Keep this button released (RGB) for the RGB signal. Depress this button (Y R-Y B-Y) for the component signal.

12 BLUE ONLY selector
Depress this button to turn off the red and green signals. A blue signal is displayed as an apparent monochrome picture on the screen. This facilitates "chroma" and "phase" control adjustments and the observation of video noise.

13 UNDER SCAN selector
Depress this button for underscanning. The display size is reduced by approximately 3% so that four corners of the raster are visible.

With this buton depressed, if the UNDER SCAN 4:3/16:9 selector on the rear panel is set to 16:9, the ratio of the picture changes to 16:9.

14 H/V DELAY selector
Depress this button to observe the horizontal and vertical sync signals at the same time. The horizontal sync signal is displayed in the left quarter of the screen; the vertical sync signal is displayed near the center of the screen.

15 R/G/B BIAS and GAIN adjustment controls
Used for white balance fine adjustment.
BIAS and GAIN controls are provided for the R (red), G (green) and B (blue) screens.

BIAS: Adjust the white balance and brightness of the screen at the lowlight.
GAIN: Adjust the white balance and brightness of the screen at the highlight.

ONY SP-00151/ DRUCK49

Rear



16 LINE A connectors
To monitor the signal fed through these connectors, keep the LINE/RGB selector and the A/B, RGB/Y R-Y B-Y selector on the front panel released (LINE and A).

17 LINE B connectors
To monitor the signal fed through these connectors, keep the LINE/RGB selector released (LINE) and depress the A/B, RGB/Y R-Y B-Y selector on the front panel (B).

VIDEO IN (BNC): Connect to the video output of a video camera, VCR or other video equipment.
VIDEO OUT (BNC): Loop-through output of the VIDEO IN connector. Connect to the video input of a VCR or another monitor.
AUDIO IN (phono jack): Connect to the audio output of a VCR or a microphone (through a suitable microphone amplifier).
AUDIO OUT (phono jack): Loop-through output of the AUDIO IN connector. Connect to the audio input of a VCR or another monitor.

18 REMOTE connector (8-pin mini DIN)
Connect to the tally output of a control console, special-effect generator, etc. The tally lamp on the front panel will be turned on and off by the connected equipment. This connector can be used for connecting a remote controller. For the pin assignment of this connector, see "Specifications" on page 10.

Note

The Y/C IN connector has a priority over the VIDEO IN connector.
When a plug is connected to the Y/C IN connector, the VIDEO IN connector is automatically disconnected.

SONY SP-00151/ DRUCK50

19 EXT SYNC (external sync) connectors
IN (BNC): When this monitor operates on an external sync signal, connect the reference signal from a sync generator to this connector. In this case, depress the SYNC INT/EXT selector on the front panel (EXT).
OUT (BNC): Loop-through output of the EXT SYNC IN connector. Connect to the external sync input of video equipment to be synchronized with this monitor.

20 V HOLD (vertical hold) control
Turn to stabilize the picture if it rolls vertically.

21 DC 12V IN jack (XLR, 4 pin)
Connect the Sony AC-550/550CE AC power adaptor (not supplied).

22 UNDER SCAN 4:3/16:9 selector
Set to compress the picture vertically to monitor the 16:9 input signal with the correct ratio.
The function of the UNDER SCAN button on the front panel is changed by the position of this selector.

UNDER SCAN button / 4:3/16:9 selector	Not depressed (⊔)	Depressed (⎓)
When the selector is set to 4:3	The 4:3 input signal is monitored with overscanning.	The 4:3 input signal is monitored with underscanning.
When the selector is set to 16:9	The 4:3 input signal is monitored with overscanning.	The 16:9 input signal is monitored with underscanning. (Compressed vertically)

The UNDER SCAN 4:3/16:9 selector has been adopted since the serial No. 2500001 product.

23 RGB/COMPONENT input connectors

R/R-Y, G/Y, B/B-Y (BNC), AUDIO (phono):
To monitor a signal fed through these connectors, depress the LINE/RGB selector on the front panel (RGB). When the SYNC INT/EXT selector on the front panel is released (INT), the monitor operates on the sync signal from the G/Y channel.

To monitor the analog RGB signal
Connect to the analog RGB signal outputs of a video camera. Keep the A/B, RGB/Y R-Y B-Y selector on the front panel released (RGB).

To monitor the component signal
Connect to the R-Y/Y/B-Y component signal outputs of a Sony BetaCam video camera. Depress the A/B, RGB/Y R-Y B-Y selector on the front panel (Y R-Y B-Y).

24 AC IN socket
Connect the supplied AC power cord to this socket and to a wall outlet.

25 EJECT buttons
Press the EJECT button upwards to remove the battery pack.

26 BATTERY compartments
Insert the NP-1A/1B battery pack (not supplied).

1-3. POWER SOURCES

House current (for all models)

Connect the supplied AC power cord to the AC IN socket and to a wall outlet.



For the PVM-9044QM/9041QM
When the AC power cord is plugged into the AC IN socket, the battery pack (if installed) or the AC power adaptor (if connected) is automatically disconnected.

To connect an AC power cord securely with AC plug holders



1 Remove the AC IN socket screws and then use them to attach the AC plug holder A (supplied) to the AC IN socket.

2 Plug the power cord to the AC IN socket. Then, attach the supplied AC plug holder B on top of the AC power cord.

3 Slide AC plug holder B over the cord until it locks.

To remove the AC power cord
Pull out AC plug holder B by squeezing the left and right sides.

Rechargeable Battery (PVM-9044QM/9041QM only)

The monitor can operate with one or two battery packs. For extended use, two battery packs are recommended.



To remove the battery pack, press the EJECT button upwards.

For charging, use the BC-1WA battery charger (not supplied) for the NP-1A or the BC-1WB for the NP-1B.

Note

Make sure that the AC power cord and the AC power adaptor are disconnected from the monitor. Otherwise, the monitor cannot operate on the battery pack(s).

SECTION 2
DISASSEMBLY

2-1. CABINET REMOVAL



2-2. B BOARD REMOVAL



2-3. SWITCHING REGULATOR REMOVAL



2-4. D BOARD REMOVAL



2-5. P BOARD REMOVAL



2-6. REAR ASSY REMOVAL



2-7. HA AND FA BOARDS REMOVAL



2-8. PICTURE TUBE REMOVAL

Note : Caution for ANODE CAP installation.
When you replace PICTURE TUBE or FBT, remove RTV on ANODE CAP so that PICTURE TUBE and FBT can be separated. Please adhere picture tube and anode cap in accordance with the following procedure.

ADHERING PROCEDURE OF ANODE CAP.

1. Clean PICTURE TUBE ANODE CAP with ethnaol to remove original RTV.
2. Dry clean face with air.
3. Use KE-490RTV (RTV silicone adhesive, SHIN-ETSU CHEMICAL).

Part. No.	Description
7-322-065-19	Silicone (RTV) KE-490W

4. Install ANODE CAP.
5. Adeguately apply RTV to the entire picture tube anode area, piace the anode cap onto the picture tube and push it down securety so that no air pockets remain beneath the cap.
6. Dry more than 12 hours at room temperature.



- **REMOVAL OF ANODE-CAP**
- **REMOVING PROCEDURES**



① Turn up one side of the rubber cap in the direction indicated by the arrow ⓐ.



② Using a thumb pull up the rubber cap firmly in the direction indicated by the arrow ⓑ.



③ When one side of the rubber cap is separated from the anode button, the anode-cap can be removed by turning up the rubber cap and pulling up it in the direction of the arrow ⓒ.

- **HOW TO HANDLE AN ANODE-CAP**

① Don't hurt the surface of anode-caps with sharp shaped material!
② Don't press the rubber hardly not to hurt inside of anode-caps!
A metal fitting called as shatter-hook terminal is built in the rubber.
③ Don't turn the foot of rubber over hardly!





SECTION 3
SET-UP ADJUSTMENTS

- The following adjustments should be made when a complete realignment is required or a new picture tube is installed.
- These adjustments should be performed with rated power supply voltage unless otherwise noted.

The control and switch below should be set as follows unless otherwise noted:

CONTRAST control 80%
BRIGHTNESS control 50%

Perform the adjustments in order as follows:

3-1. Beam Landing
3-2. Convergence
3-3. Focus
3-4. White Balance

Note: Test equipment Required.

1. Color Bar/Pattern Generator
2. Degausser
3. Color Analyzer (Minolta)
4. Luminance Level Meter

3-1. BEAM LANDING

Precaution

1. Set the side of the unit with the PICTURE TUBE so that it faces east or west in order to reduce the influence of external magnetic force.
2. Turn the power switch for the unit ON and erase the magnetic force using a degausser.

(1) Beam Landing

1. Receive an entirely white signal with the pattern generator.
   CONTRAST ..... MAX.
   BRIGHTNESS ..... set easy to observe
2. Adjust the white balance, G2 voltage and convergence roughly.
3. Loosen the deflection yoke mounting screw, and set the purity control to the center as shown in Fig.3-1.
4. Switch over the pattern generator to green.
5. Move the deflection yoke backward, and adjust with the purity control so that green is in the center and blue and red are at the sides, evenly. (Fig.3-2)
6. Move the deflection yoke forward, and adjust so that the entire screen becomes green. Repeat 5 to 7 as to red and blue.
7. When landing at the corners is not right, correct by using the magnet. (Fig.3-3)
8. When the position of the deflection yoke is determined, tighten it with a deflection yoke mounting screw.

CAUTION: When correction magnet is used, be sure to degauss the unit.





Fig.3-1



Fig.3-2



Fig.3-3

3-2. CONVERGENCE

(1) Horizontal and vertical Static Convergence Adjustment on the Center of Screen.

- Before starting, perform V. SIZE, V. CENT, H.SIZE, H.CENT and Screen Distortion Adjustment rightly.

(Static Convergence Adjustment)

1. Receive a dot signal, setting BRIGHTNESS minimum and set CONTRAST to normal.
2. Adjust H.STAT VR to coincide red, green and blue dots on the center of screen. (Horizontal movement)
3. Adjust V.STAT magnet to coincide red, green and blue dots on the center of screen. (Vertical movement)



* If the red, green and blue dots do not coincide on the center of screen with H.STAT VR, perform adjustment using V.STAT at the same time while tracking.
(Tilt the V.STAT magnet and adjust static convergence to open or close the V.STAT magnet.)



4. When the V.STAT magnet is moved in the direction of arrow A and b, red, green and blue dots move as shown below.

① When moving the V.STAT Magnet open or close.



② When moving the V.STAT magnet counterclockwise.



③ When moving the V.STAT magnet clockwise.



④ When tilt the V.STAT magnet and open or close.



* If the red and green dots do not coincide with blue dot, adjustment with BMC (6-poles) magnet.

5. HMC and VMC correction for BMC (6-Poles) magnet.

① HMC (Horizontal Misconvergence) correction and motion of the Electron Beam with the BMC (6-poles) magnet.



② VMC (Vertical Misconvergence) correction and motion of the Electron Beam with the BMC (6-poles) magnet.



(2) Horizontal and Vertical Dynamic Convergence Adjustment at the Environs of the Screen (Dynamic Convergence Adjustment)

1. When there is misconvergence at the sides of screen, adjust for best convergence as follows by moving the deflection yoke.
2. Loosen deflection yoke screw. Remove deflection yoke spacers. Move the deflection yoke for best convergence. Tighten the deflection yoke screw. Install three deflection yoke spacers.



Screen-corner Convergence





3-3. FOCUS

1. Receive a monoscope signal.
2. CONTRAST → Normal
3. Adjust FOCUS control so that the focus on the center of screen becomes to the best.



3-4. WHITE BALANCE

[Screen (G2) Voltage Adjustment]

1. Receive a dot signal with the pattern generator.
2. Adjust R. G. B cut-off controls so that respective cathode voltage against ground becomes 103V DC.
3. Observing the screen, adjust SCREEN control so that the background of the dot signal is bright dimly.



[White Balance]

1. Receive a color-bar pattern signal with the pattern generator. (Make black and white screen by chroma switch off.)
2. • BRIGHTNESS 50%
   • CONTRAST .....Minimum
   • CHROMA 50%
   • DRIVE control .....Mechanical center
   • BKG control .....Mechanical center
3. Adjust RV118 (SUB BRT) on B board so that the blue stripe portion on the color-bar pattern signal is bright dimly.



4. Receive an entirely white signal from the pattern generator.
5. CONTRAST .....70% (90 degree clockwise from mechanical center.)
6. Using the luminance level meter, adjust the luminance level of the pattern generator becomes 3 Nits. (The condition the screen is bright dimly.)
7. Adjust white balance at cut-off using RV119 (G-C/O) and RV121 (B-C/0).
8. Change the all-white signal luminance level to 100 IREs.
9. Adjust white balance at high-light using RV120 (G-GAIN) and RV121 (B-GAIN).
10. Change the unit to blue ONLY mode.
11. Adjust white balance (at high-light) in blue ONLY mode using RV124 *R-GAIN/BL) and RV125 (G-GAIN/BL).
12. Using the luminance level meter, adjust the luminance level of the pattern generator becomes 8 Nits. Confirm that white balance at cut-off is satisfactory..

SECTION 4
SAFETY RELATED ADJUSTMENT

4-1. SAFETY RELATED ADJUSTMENTS

B+ ADJUSTMENT AND B+ MAX CHECK FOR SERVICING (⊠ RV651)

The following adjustments should always be performed when replacing the following components (marked with ◪ on the schematic diagram).

◪ on G board : (Power supply block)
IC601, IC651, PH601, C654, R653, R655, R656, R657, RV651.

1. Input the AC power supply voltage 240V $^{+1}_{-0}$ V.
2. Input the monoscope signal.
3. Set as follows.
   - CONTRAST 80%
   - BRIGHTNESS 50%
4. Connect the digital multimeter to RY1601 pin-⑦ on the D board.
5. Adjust RV651 on the G board so that the +B voltage becomes 40.0 ± 0.1V.
6. After adjusting RV651, fix it with an epoxy.
7. Input the AC power supply voltage 240V $^{+1}_{-0}$ V.
8. Input the dot signal.
9. Set as follows.
   - CONTRAST ..... Minimum
   - BRIGHTNESS ..... Minimum
10. Check that the B+ voltage is below 41.9V.
    If it is above this value, repeat from step 1.

B+ MAX IN DC POWER INPUT MODE, CONFIRMATION (⊠ RV1603)

The following adjustments should always be performed when replacing the following components (marked with ◪ on the schematic diagram).

◪ on D board :
Q1601, Q1602, Q1603, D1601, D1602, D1603, D1622, C1601, C1602, R1601, R1602, R1603, R1604, R1605, R1606, R1607, R1608, R1628, R1629, R1630, RV1601, RV1603.

1. Supply DC 12V $^{+0.4}_{-0}$ V from DC 12V IN connector.
2. Receive a dot signal.
3. • CONTRAST ..... Minimum
   • BRIGHTNESS ..... Minimum
4. Connect a digital multimeter to C1605 positive + side of D board.
5. Turn RV1601 on the D board fully clockwise. Confirm that the voltage of C1605 + pin is less than 41.9V DC.
6. If step 5 is not satisfied, readjust the RV1603. After adjusting, fasten RV1603 in place with epoxy.

HOLD-DOWN CIRCUIT CONFIRMATION (⊠ RV833) AND READJUSTMENTS

The following adjustments should always be performed when replacing the following components (marked with ◪ on the schematic diagram).

◪ on D board :
IC502, Q833, Q834, Q835, Q836, D835, D836, C519, C843, C844, C845, C846, C847, C848, RV833, R523, R850, R851, R852, R853, R854, R855, R856, R857, R858, R859, R860, R861, R862, R863.
◪ on P board : C814, NL801, T802 (FBT)

1. Receive an entire white signal.
2. • CONTRAST ..... Maximum
   • BRIGHTNESS ..... Maximum
3. Connect a digital multimeter to the TP85 (CN503 pin-⑥).
4. Confirm the voltage is 14.1 ± 3.0V DC.
5. Receive a dot signal.
6. Connect an ammeter between D board CN503 pin-⑧ and P board CN801 pin-⑧.
7. Adjust BRIGHTNESS and CONTRAST so that the current is IABL = 160 ± 30 µA.
8. Apply an external DC voltage gradually to TP85. When the voltage becomes 18.5V ± 0.1V DC, confirm the HOLD-DOWN circuit operates immediately and raster disappears.
9. When external DC voltage at TP85 becomes 17.5V ± 0.1V DC, confirm the HOLD-DOWN circuit doesn't operate.
10. Receive an entire white signal.
11. Adjust with BRIGHTNESS and CONTRAST controls so that the current is IABL = 520 ± 30 µA.
12. Apply DC voltage of 17.8V ± 0.1V to TP85. Confirm the HOLD-DOWN circuit operates immediately and raster disappears.
13. With the same set-up as steps 10 and 11, supply 16.8V ± 0.1V DC to TP85. Confirm that the HOLD-DOWN circuit doesn't operate.
14. When above specifications are not satisfied, readjust RV833. After adjusting, fasten RV833 in place with epoxy.



SECTION 5
CIRCUIT ADJUSTMENTS

5-1. D BOARD ADJUSTMENTS

—D BOARD (COMPONENT SIDE)—



HORIZONTAL OSCILLATION FREQUENCY ADJUSTMENT (RV503)

1. Receive a monoscope signal.
2. Connect pin-① of IC502 to ground with 100μF/16V electrolytic capacitor.
3. Adjust RV503 (H.FREQ) so that the screen streaming to stops.

SCREEN PHASE ADJUSTMENTS (RV502, RV512, RV516)

1. Receive a monoscope signal.
2. Set U/S (Under Scan) switch to Under mode.
   Set U/S 4:3/16:9 SW to 4:3 mode.
3. • CONTRAST ..... Minimum
   • BRIGHTNESS ..... Maximum.
4. Adjust RV512 (U/H. SIZE) so that the white frame of monoscope signal becomes visible.
5. Adjust RV516 (H.BLK) for minimum BLKG width so that all the deflection area becomes visible.
6. Adjust RV502 (VIDEO PHASE) so that the monoscope's white frames should have equal width.



H.V BLK ADJUSTMENTS (RV501,RV516)

1. Receive a monoscope signal.
2. Set U/S (Under Scan) switch to Under mode.
   Set U/S 4:3/16:9 SW to 4:3 mode.
3. • CONTRAST ..... Minimum
   • BRIGHTNESS ..... Maximum.
4. V. BLK Adjustment (RV501)

(1) Adjust RV501(V. BLK) so that the upper side white frame of monoscope signal is not blanked.



5. H. BLK Adjustment (RV516)

(1) Adjust with RV516 (H. BLK) so that the left end white vertical line of the white frame of monoscope signal is not blanked as following figure.



Make not to blank the left end white vertical line of the white frame of monoscope signal.

VERTICAL DEFLECTION PART ADJUSTMENTS (RV504, RV505, RV507, RV517, RV518)

1. Receive a monoscope signal.
2. • CONTRAST 70%
   • BRIGHTNESS 50%
3. Adjust RV505 (V. SIZE) so that the vertical size of monoscope signal becomes 12 frames.



4. Adjust RV507 (V.LIN) the vertical linearity.



5. Adjust RV504 (V. CENT) the vertical position.



6. 16:9/V.SIZE ADJUSTMENT (RV518)

(1) Set U/S (Under Scan) switch to Under mode.
(2) Set 16:9/4:3 switch to 16:9 mode.
(3) Adjust the 16:9/V.SIZE with RV518 (16:9/V.SIZE) as follows.



Screen is not wane on the four corners.

HORIZONTAL DEFLECTION PART ADJUSTMENTS (RV508, RV509, RV511, RV514, RV515, RV801/P board)

1. Receive a monoscope signal.
2. • CONTRAST 70%
   • BRIGHTNESS 50%
3. H. CENT Adjustment (RV801 on P board)

(1) Adjust RV801 on P board (H. CENT) the horizontal position.



4. H. SIZE Adjustment (RV511)

(1) Adjust RV511 (H. SIZE) the horizontal size of 16 frames of monoscope signal.



5. PIN AMP. PIN PHASE, V. ANG, BOW ADJUSTMENTS (RV508 RV509, RV514, RV515)

Adjust RV514 (V. ANG) and RV515 (BOW) to correct vertical angular distortion and bow distortion. Adjust RV509 (PIN AMP) and RV508 (PIN PHASE) so that vertical lines become straight.

- V. ANG (RV514)

- BOW (RV515)

- PIN AMP (RV509)

- PIN PHASE (RV508)



6. H. SIZE ADJUSTMENT (RV511)

(1) Adjust RV511 (H. SIZE) so that the horizontal size becomes 16 ± 0.2 frames.

7. UNDERSCAN MODE H.SIZE ADJUSTMENT (RV512)

(1) Set U/S (Under Scan) switch to Under mode.

(2) Adjust RV512 (U/H. SIZE) the Under H. SIZE as shown in the figure.



H V DELAY ADJUSTMENT (RV831, RV832)

1. Receive a monoscope signal.
2. • CONTRAST 70%
   • BRIGHTNESS 50%
3. Set H V DELAY switch to DELAY mode.
4. H. DELAY Adjustment (RV832)

(1) Connect an oscilloscope to pin-④ of IC831.

(2) Adjust RV832 (H. DELAY) to becomes 41 ± 1 µsec.



5. V. DELAY Adjustment (RV831)

(1) Connect an oscilloscope to pin-⑨ of IC833.

(2) Adjust RV831 to become 8.0 ± 0.4msec as follows.



SHUT-DOWN VOLTAGE ADJUSTMENT (RV1602)

1. Fully rotate RV1602 in the direction that does not shut-down.
2. Supply a 9.4V $^{+0.1}_{-0}$V voltage to the C1602 side of L1602 on the D board.
3. Turn AC power switch ON.
4. Rotate D board RV1602 (SHT DOWN) slowly to the point that shuts-down the unit.

B+ VOLTAGE DURING DC OPERATE MODE, ADJUSTMENT (RV1601)

1. Supply DC12V±0.2V to DC 12V IN connector.
2. Receive a monoscope signal.
3. • CONTRAST 80%
   • BRIGHTNESS 50%
4. Connect a digital voltmeter to C1605 + positive side on D board.
5. Adjust RV1601 on the D board for 40.0±0.1V DC.

5-2. B BOARD ADJUSTMENT

-B BOARD (COMPONENT SIDE)-



-B BOARD (CONDUCTOR SIDE)-



PRIMARY COLOR MATRIX ADJUSTMENT (RV115, RV116, RV123)

1. Supply component color bar signal (75% chroma color bar) to the equipment so that Y signal is supplied to EXT SYNC and R-Y signal to R-Y connectors Operate the equipment in external sync mode.
2. Connect oscilloscope to IC124 pin-㉚ (B-OUT).
3. Adjust RV115 (SUB HUE) to obtain the Blue output as shown in figure.

(B-OUT)



4. Supply component color bar signal (75% color bar) to the component input connector to feed R-Y and B-Y signals. Operate the equipment in internal SYNC mode.
5. Connect oscilloscope to IC124 pin-㉚ (SUB-COL). Adjust RV116 (SUB-COL) so that waveform peaks should have the same level.

(B-OUT)



(Adjust so that the first and the 4th peaks should have the same level.)

6. Connect oscilloscope to IC124 pin-㊶ (R-OUT).
7. Adjust RV123 ((R-Y)-IN) so that waveform peaks should have the same level.

(R-OUT)



BURST GATE PULSE WIDTH ADJUSTMENT (RV109)

1. Receive color bar signal.
2. Connect dual trace oscilloscope to CN104 connector pin-⑩ (COMP-SYNC) and IC113 (M51279) pin-① (BGP-WIDTH). Adjust RV109 (BGP-WIDTH) to obtain the relationship as shown in the figure.



VXO ADJUSTMENT (CV101,CV102)

1. 3.58MHz VXO adjustment (CV101)
(1) Receive NTSC color bar signal.
(2) Connect +5V power line to IC113 pin-㉖ (ID-FILT-REF) via a 4700Ω resistor.
(3) Ground IC109 pin-② by connecting it to ground.
(4) Ground C162 – negative side by connecting it to ground.
(5) Connect frequency counter to IC113 pin-㉑. Adjust CV101 (358FO) for 3579545±20Hz.
(This adjustment can be alternatively done by observing screen as below.)

Adjust color synchronization by CV101 (358FO).



Adjust so that color stripes disappear and the hue change is stabilized extremely.

2. 4.43MHz VXO adjustment (CV102)
(1) Receive PAL colour bar signal.
(2) Connect +12V power line to IC109 pin-②.
(3) Connect frequency counter to IC113 pin-㉑. Adjust CV102 (443FO) for 4433619±20Hz.
(This adjustment can be alternatively done by observing screen as below.)

Adjust colour synchronization by CV102(443FO).



Adjust so that colour stripes disappear and the hue change is stabilized extremely.

NTSC COMB FILTER ADJUSTMENT (RV1,T1/CFM101 BOARD)

1. Receive NTSC 3.58 color bar signal.
2. Connect an oscilloscope to C202 – negative side.
3. Confirm the Y OUT is 0.78±0.5 Vp p.
4. Confirm the residual chroma is 32 mVp-p below. If it is above 35 mVp-p, adjust with RV1 and T1 on CFM101 board while tracking



NTSC COLOR DEMODULATION ADJUSTMENT (RV114,RV111,RV104,RV107)

1. NTSC 3.58MHz - HUE adjustment (RV114)
(1) Supply NTSC color bar signal including burst and R-Y component. (For example, Tektronix 1410SG output color bar signal with B-Y component removed.)
(2) Connect an oscilloscope to Q128 emitter (B-Y OUT).
(3) Adjust RV114 (358NT - HUE) so that all the waveform peaks should have equal amplitude (look flat) except burst. (Level difference should be less than 10mV p-p.)

2. NTSC 3.58MHz - COLOR adjustment (RV111)
(1) Receive NTSC 3.58 color bar signal.
(2) Connect an oscilloscope to IC124 pin-㉚ (B-OUT).
(3) Adjust RV111(358NT-COL) so that waveform peaks should have the same level (most flat).



3. NTSC 3.58MHz - COLOR (R-Y) adjustment (RV104, RV107)
(1) Receive the color bar signal.
(2) Connect an oscilloscope to the Q127 emitter (R-Y OUT), and adjust RV104 (358NT-SHIFT) so that the output of the burst section (B-Y axis signal output) becomes 0.
(3) Connect an oscilloscope to IC124 pin-㊶ (R-OUT). Adjust RV107 (358NT-COL (R-Y)) so that the level difference should be minimum.



(Adjust for B=D. [less than 20mV] Also level difference between B and C should be less than 60mV.)

NTSC 4.43MHZ COLOR DEMODULATION ADJUSTMENT (RV108,RV112,RV103,RV106)

1. NTSC 4.43MHz - COLOR adjustment (RV108,RV112)

(1) Receive NTSC 4.43 color bar signal (75% color bar).

(2) Connect an oscilloscope to IC124 pin-㉚ (B-OUT).

(3) Adjust RV108 (443NT-COL) so that waveform peaks should have the same level (most flat).



(4) When cyan and magenta have level difference, adjust RV112 (443NT-HUE) and RV108 (443NT-COL) alternatively to remove, by tracking.



When cyan and magenta have level difference, adjust RV112 and RV108 alternatively to remove.

2. NTSC 4.43MHz - COLOR (R-Y) adjustment (RV103, RV106)

(1) Receive the NTSC 4.43 color bar signal (75%, chroma color bar).

(2) Connect an oscilloscope to the Q127 emitter (R-Y OUT), and adjust RV103(443NT-SHIFT) so that the output of the burst section (B-Y axis signal output) becomes 0.

(3) Connect an oscilloscope to IC124 pin-㊶ (R-OUT). Adjust RV106 (443NT-COL (R-Y)) so that the level difference should be minimum.



(Adjust for B=D. [less than 20mV] Also level difference between B and C should be less than 60mV.)

PAL COLOR DEMODULATION ADJUSTMENT (RV113, RV2/SEP101, RV110, RV105)

1. PAL PHASE Adjustment (RV113,RV2/SEP101)

(1) Receive the special PAL color-bar.

(2) Connect an oscilloscope to emitter of Q127 (R-Y OUT).

(3) Adjust RV113 (PAL-PHASE) so that B-Y (0/180°) anti-PAL portion (in the R-Y demodulated output) becomes "0" (flat) as following figure.



* The anti-PAL portion has a small level difference in every other horizontal period. So, adjust so that average becomes "0".

(4) Connect an oscilloscope to emitter of Q128 (B-Y OUT).

(5) Adjust RV2 inside SEP101 so that R-Y (90°/90°) anti-PAL portion (in B-Y demodulated output) becomes "0" (flat) as following figure.



* The anti-PAL portion has a small level difference in every other horizontal period. So, adjust so that average becomes "0".

(For the adjustments of (3) and (5), it is also possible to set the color level to MAX with the chroma adjusting knob of the unit and erase the color of the anti-pal signal section.)

2. PAL COLOR ADJUSTMENT (RV110)

(1) Receive PAL color bar signal (75% color bar).
(2) Connect an oscilloscope to IC124 pin-㉚ (B-OUT).
(3) Adjust RV110 (PAL-COL) so that waveform peaks should have the same level (most flat).



3. PAL-COLOR-(R-Y) ADJUSTMENT (RV105)

(1) Connect an oscilloscope to IC124 pin-㊶ (R-OUT).
(2) Adjust RV105 (PAL-COL-(R-Y)) so that waveform peaks should have the same level (most flat).



(Adjust for B=D. [less than 20mV] Also level difference between B and C should be less than 60mV.)

SUB-SHARP ADJUSTMENT (RV205)

(1) Receive a sweep signal (or multi-burst).
* • Bandwidth should be more than 10MHz (flat).
• Composite sync should be included.
• Turn burst off.
(2) Connect an oscilloscope to IC124 pin-㊱ (G-OUT).
(3) Adjust RV205 (SUB-SHARP) as shown.



Example of sweep signal output waveform

[specification]
6MHz/0.5MHz=0±0.5dB

CHROMA H PULSE POSITION ADJUSTMENT (RV101,RV102)

(1) Receive the SECAM color bar signal.
(The left edge of the screen should not be colored.)
(2) Set to the under-scan mode.
(3) Adjust RV101 (PLUSE-WIDTH) until the point immediately before the color on the left edge of the screen disappears.
(4) Release the under-scan mode.
(5) Set the HV DELAY mode.
(6) Adjust RV102 (PULSE-POSI) untill the point immediately before the rising color of the image after back porch diappears.

Note : If image phase adjustment or HV DELAY amount adjustment during HV DELAY is performed after completing the adjustment in this section, re-adjustments will be required. Therefore, performed this adjustment after the two mentioned have been performed.

5-3. S BOARD ADJUSTMENTS

—S BOARD (COMPONENT SIDE)—



SECAM (T1101,L1102,L1103)

1. Receive SECAM color-bar.
2. Bell Filter Adjustment (T1101)
(1) Connect an oscilloscope to IC1101 pin-㉔.
(2) Adjust T1101 (Bell Filter) so that the chroma waveform becomes smooth. (Uneven level should be minimum.)



3. Color Balance Adjustment (L1102,L1103)
(1) Connect an oscilloscope to pin-⑨ (R-Y) of CN1101 connector.
(2) Adjust L1102 (R-Y) so that the non-colored portion level becomes flat.



(3) Connect an oscilloscope to pin-⑧ (B-Y) of CN1101 connector.
(4) Adjust L1103 (B-Y) so that the non-colored portion level becomes flat.



(5) When adjusting the color level of the unit to MAX or MIN using the chroma adjusting knob, check that the white balance of the colorless section does not change.

DEMODULATION LEVEL ADJUSTMENT (RV1101,RV1102)

1. Receive SECAM color-bar.
2. Connect an oscilloscope to IC124 pin-㉚ (B-OUT).
3. Adjust S board RV1101 (SEC-COL) so that waveform peaks should have the same level (most flat).



4. Connect an oscilloscope to IC124 pin-㊶ (R-OUT).
5. Adjust S board RV1102 (SEC-COL (R-Y)) so that the level difference should be minimum.



(Adjust for B=D. [less than 20mV] Also level difference between B and C should be less than 60mV.)

SECTION 6 DIAGRAMS

6-1. BLOCK DIAGRAMS (1)



Sup 3

(INPUT SIGNAL SELECTOR)

VIDEO BUFF Q401
VIDEO BUFF Q402
Y BUFF Q404
C BUFF Q405
R BUFF Q406
G BUFF Q407
B BUFF Q409
S BUFF Q410
AUDIO BUFF Q412
AUDIO BUFF Q413
A RGB BUFF Q414
RGB/LINE Q424
TALLY SW Q421,422
U/S SW Q423
SYNC SW Q418
B ONLY SW Q419,420
DELAY SW Q417
TALLY SW Q411
BUFFER Q426
S401 4:3/16:9 SW
IC401 VIDEO SW
IC402 AUDIO SW
IC403 AUDIO OUT
Y BUFF Q403
Y/C SW Q408
SP
VOL
RV401 V HOLD
12V

Y/VIDEO
Y/C-H
Y/C-C,BL-ONLY
R-Y/R
Y/G
B-Y/B
SYNC
LINE/RGB
A/B
NOR/UNDER
NOR/EXT
V HOLD
NOR/DELAY
TALLY
4:3/16:9

(SWITCHING REGULATOR)

AC ON OFF SW
L601,602 LFT
AC RECT D601
T601 SRT
B+ RECT D201,651
40V
REG OUT Q601
D602
IC601 POWER CONT
OCP
OUT
OVP
D604
D605
FEED BACK
PH601 ISOLATION
SHUNT REG IC651
RV651 B+ADJ

— 30 —

D (DEFLECTION SYSTEM)

NOR/UNDER
NOR/UNDER
50/60
4:3/16:9
V HOLD
COMP SYNC
NOR/DELAY
HP
H FREQ
DC 12V IN
DC 12V
BATT
D.D COM
40V ON SW OFF
DC 12V

D837 PROTECT
IC831(4/4)
IC831(1/4)
IC833(2/2) V DELAY
RV831 V DELAY
IC832(1/4)
IC832(2/4)
D834 H SYNC
IC832(3/4)
D832 H SYNC 1
IC832(4/4)
D833 H SYNC 2
IC831(2/4)
RV832 H DELAY
IC831(3/4)

V ZOMMING Q512
RV507 V LIN
RV505 V SIZE
V BLK SW Q503
D503 V BLK SW
RV501 V BLKG
IC833(1/2) V DELAY
V SYNC SEP
IC502(1/3)
D501 V SYNC SW
IC502(2/3) V BLK
V OSC
V DRIVE
DEFLECTION
IC505(2/2) H.V. PLUSE
V BLK BUF Q569(1/2)
IC503 V OUT
V PULSE SW Q501
H PULSE SW Q502
IC501 50/60 SW
D509 PROTECT
D510 PROTECT
RV502 VIDEO PHASE
RV503 H FREQ
SYNC SEP
H AFC
H OSC
H DRIVE
PROTECT
IC502(3/3) DEFLECTION
H BLK 1 Q532
IC505(1/2)
H BLK 2 Q569(1/2)
H BLK Q534
RV516 H BLK
RV833 H/DΔR
IC507
V SIZE SW Q571
IC506
U/V SW Q570
U/V SIZE SW Q579
RV517 U/V SIZE
RV509 PIN AMP
Q576 V CENT SW
Q599 PIN AMP SW
Q513 PIN COMP Q514
PIN OUT Q515
D507 PIN AMP
RV511 H. SIZE
RV512 U/H. SIZE
RV508 PIN PHASE
RV515 BOW
BOW Q519
V ANG Q518
RV514 V ANG
+B
D836 HV PROTECT2
D835 HV PROTECT
HV BUFF2 Q835
HV BUFF1 Q836
CURR LIM2 Q833
CURR LIM1 Q834
TP85

PULSE Q508,505
H TRIGGER Q1617
TRIANGLE GEN Q1616, 1611
DC LEVEL SIRT Q1613,1614,1615
COMPARATOR Q1612,1610
RV1601 B+ ADJ
RV1603 B+ΔR
ERROR AMP Q1601
COMPARATOR Q1602,1603
PRE DRIVE Q1604
SPEED UP Q1618
DRIVE Q1605
T1601 DRVT
CHOPPER OUT Q1606
+40V RECT D1606,1607
RY1601
LIMIT SW Q509
LED DRIVE Q1609
+12V
COMPARATOR IC1601 (2/2)
COMPARATOR IC1601 (1/2)
RV1602 SHUT DOWN
+40V/RELAY SW Q1607
RELAY SW Q1608
POWER

— 31 —

PVM-9041QM/9044QM



PVM-9041QM/9044QM PVM-9041QM/9044QM

BLOCK DIAGRAMS (2)



PVM-9041QM/9044QM PV




IC124 RGB MATRIX
VCA
Y BUFF Q204
B-Y BUFF Q205
R-Y BUFF Q206
G BUFF Q202
B BUFF Q201
R BUFF Q203
MATRIX
COMP/RGB SW
OSD
R GAIN CONT
G GAIN CONT
B GAIN CONT
R C/O CONT
G C/O CON
B C/O CONT
R BUFF Q165
G BUFF Q166
B BUFF Q167
B BUFF Q168
IC126
R BUFF Q173
G BUFF Q174
B BUFF Q175
R DRIVE Q157
G DRIVE Q158
B DRIVE Q159
D145
D146
R REF PULSE SW Q148
G REF PULSE SW Q151
B REF PULSE SW Q154
R-E.F Q149,209
G-E.F Q152,210
B-E.F Q155,211
V901 PICTURER TUBE
CA (CRT SOCKET)
RV701 H STAT
FOCUS
SCREEN
H1,H2
HV
IC125 BLACK SAMPLING
IC127 HOLD
RV124 BL ONLY W/B-R
RV125 BL ONLY W/B-G
BL-ONLY-RCH-BUFF Q170
BL-ONLY-BCH-BUFF Q172
IC116 H BLK SW
H BLK
V GATE SW Q146,147
D133 D134 D135 SLICER
BLUE ONLY SW Q212
BLACK SLISE RER Q153
D162
BLUE-L
V BLK SW Q164
REF PULSE BUFF Q161
V BLK SW Q179
BLKNKING Q177
REF PULSE SW Q160
OFF MUTE SW Q299
IC129 ON/OFF MUTE
RV122 B GAIN
RV119 G C/O
RV121 B C/O
RV120 G GAIN
D153
D151
D152
D143
D142
D125 HV DL SW
HV DL SW Q126
D127 SW
D393 U/S SW
PIX ABL Q162
BRT ABL Q163
RV205 SUB SHARP
RV116 SUB COL
RV118 SUB BRT
RV115 SUB HUE
RV117 SUB PIX
R GAIN
G GAIN
B GAIN
R BIAS
G BIAS
B BIAS
VP PIX
BRT
CLP
HP
IK F.B
V BLK
MUTE
COL
MODE SELECT
B/W SW Q144
MODE SW Q145
D289
B-Y/B BUFF Q141
R-Y/R BUFF Q142
INSERT PULSE SW Q132
IC123(2/2) HOLD
IC121(2/2)
IC122(2/2) HOLD
IC120
+12V
D123
JTE SW Q190
COMP SYNC
B-Y/B
R-Y/R
B/W
ABL
U/S
TP106 COMP SYNC
TP104
TP110 H-BLK
TP107 V.P
RV123 MATRIX R-Y LEVEL
IC107(5/6)
IC109(4/4)
IC107(4/6)
H DL
HV DL SW Q129
RV102 PULSE DLY ADJ
IC106
IC106 H PULSE GEN
Y/C-C/ BL-ONLY
NOR/ BL-ONLY
H BLK
H DL
POWER LED
POWER LED
COMP SYNC
ABL
NOR/UNDER
NOR/UNDER
CHROMA
APT
VP
CONTRAST
HOR/DELAY
BRT
TALLY
X (TALLY LAMP)
HA (USER CONTROL, WHITE BALANSE)
LINE/RGB
NOR/DELAY
NOR/BL ONLY
NOR/UNDER
HOR/EXT
A/B
APERTURE
BRT
CHROMA
PHASE
CONTRAST
VOL
POWER LED
S002 A/B
S001 LINE/RGB
S006 SYNC INT/EXT
S004 BLUE ONLY
S005 U/S
S003 H/V DELAY
BIAS
GAIN
RV006 APT
RV004 CHROMA
RV002 CONTR
RV005 BRT
RV003 PHASE
RV001 VOL
D001 POWER
B (SIGNAL PROCESS)
DY
H
V
V(+)
V(−)
CS
PIN
H DRV
D.DCON
HP
HV
ABL
H DRIVE Q801
TB01 HDT
H OUT Q802
H(+)
H(−)
120V REG D802
15V REG D803, 813
24V REG D801
120V
B+
15V
24V
T802 FBT
FOCUS
SCREEN
+120V
DEGAUS D807 D808 D809
DGC SW
DGC
H1
H2
P (H OUT, FBT)


CN601 4P :VH
AC SW 1
NC 2
NC 3
AC SW 4
F601 3.15A
S601
R602 1.5M 1/2W :RC
CN602 3P :MINI
1 AC OUT
2 NC
3 AC OUT
FA (AC/DC SW)
1 ON
2 SW
3 OFF
4 NC
CN603 4P WHT :S-MICRO
CN610 3P :MINI
AC OUT 1
NC 2
AC OUT 3
G
(SWITCHING REGULATOR)
CN651 3P
1 40V
2 NC
3 GND
CN403 4P WHT(L) :VH
AC NC NC AC
1 2 3 4
AC IN
VIDEO
LINE A IN
LINE A OUT
LINE B IN
LINE B OUT
Y/C IN
Y/C OUT
RGB/COMPONENT
R/R-Y IN
G/Y IN
B/B-Y IN
EXT SYNC IN
EXT SYNC OUT
TALLY/REMOTE
AUDIO
LINE A IN
LINE A OUT
LINE B IN
LINE B OUT
RGB
QA
(INPUT SIGNAL SELECTOR)
CN401 15P WHT
15 EXT SYNC
14 HV DL
13 Y/COMPOSITE
12 GND
11 12V
10 VOL
9 B/B-Y
8 RGB/LINE
7 G/G-Y
6 A/B
5 R/R-Y
4 TALLY
3 SYNC
2 Y/C-C/BL-ONLY
1 Y/C-H
CN402 3P WHT
1 SP
2 GND
3 GND (SP)
SP
CN404 5P WHT
1 U/S
2 15V
3 V.HOLD
4 GND
5 4:3/16:9
BATTERY
CN507 8P WHT
1 BATT-IN
2 BATT-IN
3 E
4 E
5 BATT-IN
6 BATT-IN
7 E
8 E
CN505 6P WHT
1 ON
CN501 3P WHT :S-MICRO
H·FREQ 1
NC 2
GND 3
CN502 12P WHT-L
120V 1
H·V-DL 2
U/S(H-PLS) 3
POW-LED 4
GND 5
ABL 6
H-BLK 7
V-BLK 8
V·P 9
COMP-SYNC 10
50/60 11
12V 12
CN509 3P WHT :S-MICRO
GND 1
GND 2
GND 3
TO GND (REAR CHASSIS)
U/S 1
15V 2
V.HOLD 3
GND 4
4:3/16:9 5
CN504 5P WHT
D
(DEFLECTION

CN102
3P
WHT
:S-MICRO

GND	3
GND	2
GND	1

TO GND
(REAR CHASSIS)

EXT SYNC	15
HV DL	14
Y/VIDEO	13
GND	12
12V	11
VOL	10
B/B-Y	9
RGB/$\overline{\text{LINE}}$	8
G-Y	7
A/$\overline{\text{B}}$	6
R/R-Y	5
TALLY	4
SYNC	3
Y/C-C/$\overline{\text{BL-ONLY}}$	2
Y/C-H	1

CN101
15P
WHT-L

CN651
3P

1	40V
2	NC
3	GND

CN108
3P
WHT
:S-MICRO

1	TALLY
2	NC
3	GND

CN107
13P

1	GND
2	12V
3	POW-LED
4	VOL
5	CONTRAST
6	PHASE
7	CHROMA
8	BRT
9	APERTURE
10	$\overline{\text{LINE}}$/RGB
11	$\overline{\text{NORM}}$/DELAY
12	NORM/ $\overline{\text{B70}}$
13	$\overline{\text{NORM}}$/UNDER

CN001
13P
WHT

GND	
12V	
POW-LED	
VOL	
CONTRAST	
PHASE	
CHROMA	
BRT	
APERTURE	
$\overline{\text{LINE}}$/RGB	
$\overline{\text{NORM}}$/DELAY	
NORM/ $\overline{\text{B70}}$	
$\overline{\text{NORM}}$/UNDER	

B
(SIGNAL PROCESS)

1	$\overline{\text{NORM}}$/ EXT
2	A/ $\overline{\text{B}}$
3	R BIAS
4	G BIAS
5	B BIAS
6	G GAIN
7	B GAIN
8	R GAIN

CN106
8P

CN002
8P
WHT

$\overline{\text{NORM}}$/ EXT	
A/ $\overline{\text{B}}$	
R BIAS	
G BIAS	
B BIAS	
G GAIN	
B GAIN	
R GAIN	

1	B
2	NC
3	G
4	NC
5	NC
6	R

CN105
6P
WHT
:S-MICRO

CN104
12P
WHT-L

1	120V
2	HV-DL
3	U/S (H-PLS)
4	POW-LED
5	GND
6	ABL
7	H-BLK
8	V-BLK
9	V.P.
10	COMP-SYNC
11	50/$\overline{60}$
12	12V

CN103
12P
WHT

1	(SIG)DL
2	(COM)DL
3	SECAM
4	LIM
5	I2V
6	C
7	60/$\overline{50}$ LINE/RGB
8	B-Y
9	R-Y
10	GND
11	BGP
12	DL Y-H.P.

CN1101
12P
WHT

1	(SIG)DL
2	(COM)DL
3	SECAM
4	LIM
5	I2V
6	C
7	60/$\overline{50}$ LINE/RGB
8	B-Y
9	R-Y
10	GND
11	BGP
12	DL Y-H.P.

S
(SECAM DEMODULATION)

DC 12V IN

CN505
6P
WHT

1	ON
2	SW
3	OFF
4	GND
5	NC
6	40V

CN508
3P
WHT

3	E
2	BATT 12V
1	DC 12V

CN503
14P
WHT
BORAD IN

1	E
2	15V
3	24V
4	D·D·CON
5	H·DRIVE
6	△HV
7	+B
8	ABL
9	PIN
10	V (+)
11	V (−)
12	CS
13	HP
14	120V

CN801
14P
WHT
:S-MICRO

E	1
15V	2
24V	3
D·D·CON	4
H·DRIVE	5
△HV	6
+B	7
ABL	8
PIN	9
V (+)	10
V (−)	11
CS	12
HP	13
120V	14

D
(DEFLECTION SYSTEM)

P
(H OUT,FBT)

FBT H
FBT FOCU
FBT SCREE

H (+)	1
H (−)	2
V (−)	3
V (+)	4

CN802
4P
WHT
:MINI

DEFLECTION YOKE
H.DY
H.DY
V.DY
V.DY

6 | 7 | 8 | 9 | 10 | 11 | 12 | 13 | 14 | 15 | 16 | 17

CN102
3P
WHT
:S-MICRO

GND	3
GND	2
GND	1

TO GND
(REAR CHASSIS)

CN101
15P
WHT-L

EXT SYNC	15
HV DL	14
Y/VIDEO	13
GND	12
12V	11
VOL	10
B/B-Y	9
RGB/LINE	8
G-Y	7
A/B	6
R/R-Y	5
TALLY	4
SYNC	3
Y/C-C/BL-ONLY	2
Y/C-H	1

CN610
3P
:MINI

AC OUT	1
NC	2
AC OUT	3

G
(SWITCHING REGULATOR)

CN651
3P

1	40V
2	NC
3	GND

B
(SIGNAL PROCESS

CN104
12P
WHT-L

1	120V
2	HV-DL
3	U/S (H-PLS)
4	POW-LED
5	GND
6	ABL
7	H-BLK
8	V-BLK
9	V.P.
10	COMP-SYNC
11	50/60
12	12V

CN1101
12P
WHT

DC 12V IN

BATTERY

CN507
8P
WHT

1	BATT-IN
2	BATT-IN
3	E
4	E
5	BATT-IN
6	BATT-IN
7	E
8	E

CN505
6P
WHT

1	ON
2	SW
3	OFF
4	GND
5	NC
6	40V

CN508
3P
WHT

3	E
2	BATT 12V
1	DC 12V

CN503
14P
WHT
BORAD
IN

1	E
2	15V
3	24V
4	D·D·CON
5	H·DRIVE
6	△HV
7	+B
8	ABL
9	PIN
10	V (+)
11	V (−)
12	CS
13	HP
14	120V

CN801
14P
WHT
:S-MICRO

E	1
15V	2
24V	3
D·D·CON	4
H·DRIVE	5
△HV	6
+B	7
ABL	8
PIN	9
V (+)	10
V (−)	11
CS	12
HP	13
120V	14

CN501
3P
WHT
:S-MICRO

H·FREQ	1
NC	2
GND	3

SP

CN502
12P
WHT-L

120V	1
H·V-DL	2
U/S(H-PLS)	3
POW-LED	4
GND	5
ABL	6
H-BLK	7
V-BLK	8
V·P	9
COMP-SYNC	10
50/60	11
12V	12

D
(DEFLECTION SYSTEM)

DEFLECTION YOKE

H.DY
H.DY
V.DY
V.DY

CN802
4P
WHT
:MINI

H (+)	1
H (−)	2
V (−)	3
V (+)	4

CN509
3P
WHT
:S-MICRO

GND	1
GND	2
GND	3

TO GND
REAR CHASSIS)

CN504
5P
WHT

U/S	1
15V	2
V.HOLD	3
GND	4
4:3/16:9	5

18 19 20 21 22 23 24 25 26 27 28 29

CN108
3P
WHT
:S-MICRO

1	TALLY
2	NC
3	GND

CN21
3P
WHT-L
:S-MICRO

TALLY	1
NC	2
GND	3

X
(TALLY LAMP)

CN107
13P

1	GND
2	12V
3	POW-LED
4	VOL
5	CONTRAST
6	PHASE
7	CHROMA
8	BRT
9	APERTURE
10	LINE/RGB
11	NORM/DELAY
12	NORM/B70
13	NORM/UNDER

CN001
13P
WHT

GND	1
12V	2
POW-LED	3
VOL	4
CONTRAST	5
PHASE	6
CHROMA	7
BRT	8
APERTURE	9
LINE/RGB	10
NORM/DELAY	11
NORM/B70	12
NORM/UNDER	13

HA
(USER CONTROL
WHITE BALANSE)

1	NORM/EXT
2	A/B
3	R BIAS
4	G BIAS
5	B BIAS
6	G GAIN
7	B GAIN
8	R GAIN

CN106
8P

CN002
8P
WHT

NORM/EXT	1
A/B	2
R BIAS	3
G BIAS	4
B BIAS	5
G GAIN	6
B GAIN	7
R GAIN	8

B
AL PROCESS)

1	B
2	NC
3	G
4	NC
5	NC
6	R

CN105
6P
WHT
:S-MICRO

KG KB G2
H
CV KR G1 G4 HV
PICTURE
TUBE

CN1103
12P
WHT

(SIG)DL	1
(COM)DL	2
SECAM	3
LIM	4
12V	5
C	6
60/50 LINE/RGB	7
B-Y	8
R-Y	9
GND	10
BGP	11
DLY-H.P.	12

CN1101
12P
WHT

(SIG)DL	1
(COM)DL	2
SECAM	3
LIM	4
12V	5
C	6
60/50 LINE/RGB	7
B-Y	8
R-Y	9
GND	10
BGP	11
DLY-H.P.	12

S
(SECAM DEMODULATION)

CN701
6P
WHT
:S-MICRO

B	1
NC	2
G	3
NC	4
NC	5
R	6

CN702
1P
WHT
:MINI

1	CRT-GND

FBT HV
FBT FOCUS
FBT SCREEN

FBT FOCUS
FBT SCREEN

CA
(CRT SOCKET)

CN803
5P
WHT
:S-MICRO

1	120V
2	E
3	NC
4	H1
5	H2

CN703
5P
WHT
:S-MICRO

120V	1
E	2
NC	3
H1	4
H2	5

CN801
14P
WHT
S-MICRO

E	1
15V	2
24V	3
D CON	4
H DRIVE	5
△HV	6
+B	7
ABL	8
PIN	9
V (+)	10
V (−)	11
CS	12
HP	13
120V	14

P
(H OUT,FBT)

CN805
3P
WHT
S-MICRO

1	DGC
2	NC
3	DGC

DGC

H (+)	1
H (−)	2
V (−)	3
V (+)	4

CN802
4P
WHT
:MINI

6-3. CIRCUIT BOARDS LOCATION



6-4. PRINTED WIRING BOARDS AND SCHEMATIC DIAGRAMS

Note:

- All capacitors are in μF unless otherwise noted. pF: μμF 50WV or less are not indicated except for electrolytics.
- Indication of resistance, which does not have one for rating electrical power, is as follows.

  Pitch: 5 mm
  Rating electrical power 1/4W

- All resistors are in ohms.
- : nonflammable resistor.
- : fusible resistor.
- : internal component.
- : panel designation.
- All variable and adjustable resistors have characteristic curve B, unless otherwise noted.
- The components identified by ⋈ in this basic schematic diagram have been carefully factory-selected for each set in order to satisfy regulations regarding X-ray radiation. Should replacement be required, replace only with the value originally used.
- When replacing components identified by ◪, make the necessary adjustments indicated. If results do not meet the specified value, change the component identified by ⋈ and repeat the adjustment until the specified value is achieved. (Refer to RV651, RV1603 and RV833 adjust on Page 19 and 20.)
- When replacing the part in below table be sure to parform the related adjustment.

Part replaced (◪)	Adjustment (⋈)
IC601, IC651, PH601, C654, R653, R655, R656, R657, RV651— G BOARD	RV651 (B+ MAX)
Q1601, Q1602, Q1603, D1601, D1602, D1603, D1622, C1601, C1602, R1601, R1602, R1603, R1604, R1605, R1606, R1607, R1608, R1628, R1629, R1630, RV1601, RV1603 — D BOARD	RV1603 (B+ MAX IN DC POWER INPUT MODE)
IC502, Q833, Q834, Q835, Q836, D835, D836, C519, C843, C844, C845, C846, C847, C848, RV833, R523, R850, R851, R852, R853, R854, R855, R856, R857, R858, R859, R860, R861, R862, R863 — D BOARD NL801, T802, C814 — P BOARD	RV833 (HOLD-DOWN)

- All voltages are in V.
- Voltage are dc with respect to ground unless otherwise noted.
- Readings are taken with a color-bar signal input.
- Readings are taken with a PAL color-bar signal input.
- : adjustment for repair.
- Voltage variations may be noted due to normal production tolerance.
- : B+ bus.
- : B- bus.
- : signal path.
- No mark : with PAL coior-bar signal received or common voltage.
- ( ) : with SECAM color-bar signal received.
- < > : with NTSC 3.58 color-bar signal received.
- (( )) : with NTSC 4.43 color-bar signal received.
- [ ] : with S (Y/C) color-bar signal received.
- { } : with analog RGB color-bar signal received.
- << >> : with component color-bar signal received.

Reference information

RESISTOR	: RN	METAL FILM
	: RC	SOLID
	: FPRD	NONFLAMMABLE CARBON
	: FUSE	NONFLAMMABLE FUSIBLE
	: RS	NONFLAMMABLEWIREWOUND
	: RB	NONFLAMMABLE CEMENT
COIL	: LF-8L	MICRO INDUCTOR
CAPACITOR	: TA	TANTALUM
	: PS	STYROL
	: PP	POLYPROPYLENE
	: PT	MYLAR
	: MPS	METALIZED POLYESTER
	: MPP	METALIZED POLYPROPYLENE
	: ALB	BIPOLAR
	: ALT	HIGH TEMPERATURE
	: ALR	HIGH RIPPLE

Note: The components identified by shading and mark ⚠ are critical for safety. Replace only with part number specified.

D BOARD



• D BOARD W



D BOARD IC501 CX23025



D BOARD IC503 LA7830



• D BOARD WAVEFORMS





stm_it (⊠)
RV651
3+ I X)
RV1ɔd3
MAX IN DC
VEF NPUT
MO :)
RV 3
LD-DOWN)

nless otherwise

gn input.
ar signal input.

due o normal

ved or common

rec ved.
nal received.
nal received.
rec ed.
gnal received.
nal received.

LE ARBON
LE FUSIBLE
EWIREWOUND
LE EMENT
TOF

ENE

OLYESTER
YP OPYLENE

ATURE

ing and mark
nly with part

tic diagram
D board ➡

D BOARD IC501 CX23025



• D BOARD WAVEFORMS

① 11Vp-p (V)	② 11Vp-p (H)	③ 0.25Vp-p (V)	④ 10.5Vp-p (V)
⑤ 3.5Vp-p (V)	⑥ 3Vp-p (V)	⑦ 6.0Vp-p (V)	⑧ 1.5Vp-p (V)
⑨ 1.3Vp-p (V)	⑩ 10Vp-p (V)	⑪ 6Vp-p (H)	⑫ 4.4Vp-p (H)
⑬ 1.1Vp-p (H)	⑭ 6.4Vp-p (H)	⑮ 36Vp-p (H)	⑯ 2.2Vp-p (V)
⑰ 1Vp-p (V)	⑱ 1Vp-p (V)	⑲ 46Vp-p (V)	⑳ 1.1Vp-p (V)
㉑ 12Vp-p (V)	㉒ 12Vp-p (V)	㉓ 12Vp-p (H)	㉔ 12Vp-p (H)
㉕ 12Vp-p (H)	㉖ 32Vp-p (H)	㉗ 12Vp-p (H)	㉘ 0.5Vp-p (V)
㉙ 2.2Vp-p (V)	㉚ 0.32Vp-p (H)	㉛ 0.6Vp-p (V)	㉜ 12Vp-p (V)
㉝ 12Vp-p (V)	㉞ 12Vp-p (V)	㉟ 12Vp-p (H)	㊱ 12Vp-p (V)

D BOARD IC503 LA78





D BOARD IC503 LA7830








D
(DEFLECTION SYSTEM)
CN502 14P WHT BOARD-IN TO P BOARD CN801
GND
+15V
+24V
B.G CON
H.GRY
4HV
+B
ABL
PIN
V (-)
V (+)
CS
HP
+120V
CN504 2P WHT V/H TO G BOARD CN404
DC.12V
BATT 12V
GND
CN508 3P WHT V.M TO G BOARD CN801
4:3 /16:9
V.HOLD
GND
+15V
U/S
CN505 6P WHT -S-MICRO
ON
SW
OFF
GND
NC
40V
TO FA BOARD CN603
CN507 8P WHT -S-MICRO
BATT IN 1
BATT IN 2
E
TO BATT-IN
CN509 3P WHT -S-MICRO
E
TO GND
GEAR CHASSIS
B-553037A<U/C>-0..
SHUT DOWN
PROTECT1
PROTECT2
PROTECT3
PROTECT4
PROTECT5
PROTECT6
PROTECT7
PROTECT8
PROTECT9
PROTECT10
PROTECT11
PROTECT12
PROTECT13
PROTECT14
PROTECT15
PROTECT16
PROTECT17
PROTECT18
PROTECT19
DISCHARGER1
DISCHARGER2
DISCHARGER3
DISCHARGER4
DISCHARGER5
DISCHARGER6
DISCHARGER7
DISCHARGER8
DISCHARGER9
DISCHARGER10
DISCHARGER11
DISCHARGER12
DISCHARGER13
DISCHARGER14
DISCHARGER15
DISCHARGER16
DISCHARGER17
DISCHARGER18
DISCHARGER19
DISCHARGER20
DISCHARGER21
DISCHARGER22
DISCHARGER23
DISCHARGER24
DISCHARGER25
DISCHARGER26
DISCHARGER27
DISCHARGER28
DISCHARGER29
DISCHARGER30
DISCHARGER31
DISCHARGER32
DISCHARGER33
DISCHARGER34
DISCHARGER35
DISCHARGER36
DISCHARGER37
DISCHARGER38
DISCHARGER39
DISCHARGER40

D [DEFLECTION SYSTEM]

– D BOARD – 〈Component Side〉

D BOARD (Component Side)

IC	
IC501	B – 1
IC502	B – 2
IC503	C – 6
IC504	B – 5
IC505	B – 5
IC506	C – 4
IC507	C – 3
IC831	C – 7
IC832	A – 6
IC833	B – 6
IC1601	D – 8

TRANSISTOR	
Q505	D – 8
Q508	D – 8
Q509	C – 8
Q512	C – 2
Q514	A – 5
Q515	D – 1
Q532	A – 4
Q569	A – 4
Q571	C – 3
Q576	D – 2
Q579	D – 2
Q599	C – 1
Q836	B – 3
Q1605	B – 7
Q1606	A – 8
Q1607	E – 8
Q1610	D – 7
Q1611	D – 8
Q1612	C – 8
Q1613	D – 9
Q1614	D – 8
Q1615	C – 8
Q1616	C – 8
Q1617	C – 8
Q1618	C – 8

DIODE	
D506	D – 6
D508	A – 4
D512	B – 4
D514	A – 5
D520	B – 1
D521	D – 8
D833	A – 6
D834	A – 6
D835	B – 3
D836	B – 3
D848	C – 6
D1606	C – 8
D1607	A – 8
D1609	D – 7
D1610	D – 7
D1611	D – 9
D1621	A – 9
D1626	D – 8
D1627	D – 8
D1628	D – 8

VARIABLE RESISTOR	
RV501	A – 3
RV502	D – 3
RV503	C – 2
RV504	D – 4
RV505	D – 3
RV507	D – 3
RV508	D – 3
RV509	D – 3
RV511	D – 2
RV512	D – 2
RV514	D – 3
RV515	C – 3
RV516	A – 3
RV517	D – 3
RV518	C – 2
RV831	A – 6
RV832	A – 6
RV833	B – 3
RV1601	D – 8
RV1602	D – 8
RV1603	D – 8



– D BOARD –



– **D BOARD** – 〈Conductor Side〉



D BOARD (Conductor Side)

IC	
IC501	B – 9
IC502	B – 8
IC503	C – 5
IC504	B – 6

TRANSISTOR	
Q501	B – 9
Q502	B – 9
Q503	A – 8
Q504	B – 8
Q513	D – 9
Q514	E – 8
Q515	D – 9
Q518	C – 7
Q519	C – 7
Q570	D – 8
Q833	B – 7
Q834	B – 7
Q835	B – 7
Q836	B – 7
Q1601	C – 2
Q1602	C – 2
Q1603	D – 2
Q1604	C – 2
Q1605	A – 3
Q1606	A – 2
Q1608	C – 4
Q1609	E – 3

DIODE	
D501	A – 8
D502	A – 8
D503	A – 8
D504	B – 9
D506	D – 5
D507	D – 9
D511	B – 5
D831	C – 4
D832	A – 5
D835	B – 7
D1601	C – 3
D1603	C – 3
D1606	B – 2
D1607	B – 2
D1608	D – 1
D1611	D – 2
D1612	D – 4
D1615	E – 2
D1617	B – 3
D1618	B – 3
D1620	B – 4
D1621	A – 1
D1622	C – 2
D1623	D – 2
D1635	D – 3
D1699	D – 1

VARIABLE RESISTOR	
RV501	A – 7
RV502	D – 7
RV503	C – 8
RV504	C – 6
RV505	D – 8
RV507	D – 7
RV508	D – 7
RV509	D – 7
RV511	D – 8
RV512	D – 8
RV514	D – 7
RV515	D – 7
RV516	A – 7
RV517	D – 8
RV518	C – 8
RV831	A – 4
RV832	A – 4
RV833	B – 7
RV6101	D – 2
RV1602	D – 2
RV1603	D – 2

Note :

- : Pattern from the side which enables seeing.
- : Pattern of the rear side.

P [H OUT, FBT] **G** [SWITCHING REGULATOR] **X** [TALLY LAMP] **FA** [AC/DC SW] **HA** [USER CONTROL WHITE BALANSE] **CA** [CRT SOCKET] **QA** [INPUT SIGNAL SELECTOR] **S** [SECAM DEMODULATION]

– P BOARD –



Note :

- : Pattern from the side which enables seeing.
- : Pattern of the rear side.

– X BOARD –



– FA BOARD –



– HA BOARD –



– G BOARD –



– CA BOARD –



– S BOARD – 〈Component Side〉 〈Conductor Side〉





Note :

- : Pa
- : Pa

CN21

QA BOARD



〈Conductor Side〉



Note :

- ▩ : Pattern from the side which enables seeing.
- ▩ : Pattern of the rear side.

IC	
IC401	B-3
IC402	C-3
IC403	E-3

TRANSISTOR	
Q401	B-5
Q402	B-4
Q403	B-3
Q404	B-6
Q405	B-7
Q406	D-7
Q407	D-5
Q408	A-7
Q409	C-4
Q410	D-2
Q411	C-1
Q412	B-5
Q413	B-3
Q414	D-3
Q416	E-2
Q417	C-1
Q418	B-1
Q419	B-1
Q420	A-1
Q421	B-2
Q422	B-2
Q423	B-1
Q424	B-2
Q426	D-7

DIODE	
D401	C-2
D402	C-2
D403	D-2
D404	B-6
D405	B-6
D406	B-4
D407	B-4
D408	B-6
D409	C-6
D410	C-1
D411	C-1
D412	B-1
D413	B-1
D414	B-7
D415	B-7
D416	D-6
D417	D-6
D418	D-5
D419	D-5
D420	D-4
D421	D-4
D422	D-2
D423	D-3
D424	B-1
D425	B-1
D426	B-1
D427	A-2
D428	B-1
D429	B-1
D430	B-2
D431	A-2

VARIABLE RESISTOR	
RV401	D-4

– QA BOARD –











QA BOARD IC403 AN5265











• CA BOARD WAVEFORMS

① 40.5 Vp-p (H)	② 16.0 Vp-p (H)
③ 48.0 Vp-p (H)	④ 50.5 Vp-p (H)

S BOARD IC1101 CXA1214P



• S BOARD WAVEFORMS

① SECAM 0.8Vp-p (H)	② SECAM 0.7Vp-p (H)	③ SECAM 0.1Vp-p (H)	④ SECAM 3Vp-p (H)
⑤ SECAM 0.6Vp-p (H)	⑥ SECAM 0.7Vp-p (H)	⑦ SECAM 3.4Vp-p (H)	⑧ SECAM 6Vp-p (H)













• CA BOARD WAVEFORMS

① 40.5 Vp-p (H)	② 16.0 Vp-p (H)
③ 48.0 Vp-p (H)	④ 50.5 Vp-p (H)

• S B







• P BOARD WAVEFORMS

① 2.5Vp-p (H)	② 80Vp-p (H)	③ 46Vp-p (H)
④ 22Vp-p (H)	⑤ 320Vp-p (H)	

• CA BOARD WAVEFORMS

① 40.5 Vp-p (H)	② 16.0 Vp-p (H)
③ 48.0 Vp-p (H)	④ 50.5 Vp-p (H)

S BOARD IC1101 CXA1214P



• S BOARD WAVEFORMS

① SECAM 0.8Vp-p (H)	② SECAM 0.7Vp-p (H)	③ SECAM 0.1Vp-p (H)	④ SECAM 3Vp-p (H)
⑤ SECAM 0.6Vp-p (H)	⑥ SECAM 0.7Vp-p (H)	⑦ SECAM 3.4Vp-p (H)	⑧ SECAM 6Vp-p (H)







S BOARD IC1101 CXA1214P

• P BOARD WAVEFORMS

① 2.5Vp-p (H)	② 80Vp-p (H)	③ 46Vp-p (H)
④ 22Vp-p (H)	⑤ 320Vp-p (H)	

ARD WAVEFORMS

0.8Vp-p (H)	② SECAM 0.7Vp-p (H)	③ SECAM 0.1Vp-p (H)	④ SECAM 3Vp-p (H)
0.6Vp-p (H)	⑥ SECAM 0.7Vp-p (H)	⑦ SECAM 3.4Vp-p (H)	⑧ SECAM 6Vp-p (H)



B BOARD

As to the voltage value shown by the mark ※ on the Schematic Diagram, see another list.

< TRANSISTOR >

		PAL	SECAM	NTSC 3.58	NTSC 4.43	S (Y/C)	ANALOG RGB	COMPO-NENT
Q113	E	0.5	0.5	0.4	0.4	0.5	0.5	0.5
	B	1.0	1.0	0.9	0.9	0.9	0.9	1.0
Q115	E	11.2	9.3	0.0	10.6	0.0	0.0	0.0
	B	2.8	2.2	0.1	2.4	0.1	0.1	0.0
Q118	E	0.0	0.0	1.7	1.7	1.7	1.7	1.7
Q119	B	0.1	0.0	1.7	1.7	1.7	1.7	1.7
Q121	E	0.0	0.0	1.7	1.7	1.7	1.7	1.7
Q122	B	0.0	0.0	1.7	1.7	1.7	1.7	1.7
Q130	E	4.3	4.3	4.4	4.4	4.5	4.4	4.4
	B	3.7	3.7	3.8	3.8	3.9	3.8	3.8
Q132	E	2.3	2.3	2.4	2.3	2.4	2.4	2.4
	C	1.8	1.7	1.7	1.7	1.7	1.8	1.8
	B	2.7	2.6	2.6	2.7	2.8	2.7	2.8
Q146	C	116.7	114.4	110.4	113.2	113.7	114.3	114.1
Q147	E	117.9	115.6	111.6	114.5	115.0	115.5	115.4
	C	126.0	123.5	120.3	123.4	123.8	124.6	124.4
	B	119.8	119.5	110.5	118.4	118.2	114.2	114.2
Q148	C	86.1	84.9	91.2	83.4	82.6	82.5	82.2
	B	94.0	93.3	86.3	92.4	92.1	94.2	90.6
Q149	E	1.6	1.6	1.4	1.7	1.7	1.7	1.7
	C	86.1	84.9	91.2	83.4	82.7	82.5	82.5
Q151	E	90.7	91.4	98.0	87.9	87.0	86.5	86.4
	C	89.2	89.8	96.5	86.4	85.3	84.9	84.7
	B	92.1	92.7	100.2	89.5	92.4	90.5	88.9
Q152	E	86.1	86.0	92.6	82.6	82.9	82.6	82.7
	C	10.8	10.5	9.7	10.9	10.9	10.9	11.0
Q154	B	92.5	92.9	99.8	90.1	88.7	90.4	89.2
Q155	B	88.3	88.5	95.7	85.7	83.9	84.6	83.9
Q157	E	82.4	81.1	87.5	79.9	79.9	80.8	79.4
	B	86.0	84.8	91.2	84.4	82.7	82.5	82.1
Q158	E	1.6	1.5	1.3	1.6	1.6	1.7	1.7
	B	2.1	2.0	1.8	2.1	2.2	2.2	2.2
Q159	E	1.6	1.6	1.3	1.6	1.7	1.7	1.7
	B	2.2	2.1	1.5	2.1	2.2	2.2	2.2
Q163	E	0.2	0.6	2.7	0.5	−0.5	−0.7	−0.6
Q166	B	0.9	0.9	0.6	1.0	1.0	1.0	1.0
Q168	C	2.1	2.0	1.6	2.1	2.2	2.1	2.2
Q170	B	2.3	2.3	2.1	2.4	2.4	2.4	2.4
Q172	B	2.2	2.1	1.9	2.2	2.3	2.2	2.3
Q173	B	1.7	1.6	1.4	1.7	1.7	1.7	1.7
Q174	E	2.1	2.0	1.8	2.1	2.2	2.2	2.2
	B	1.6	1.5	1.3	1.6	1.6	1.7	1.7
Q178	B	6.2	6.3	6.2	6.3	6.1	6.2	6.2
Q209	E	83.4	81.5	87.9	80.3	80.4	80.4	79.8
	C	115.8	113.2	110.7	113.2	113.8	114.5	114.2
	B	87.8	86.4	92.8	85.0	84.3	84.2	83.8
Q210	E	86.5	86.3	93.1	83.0	83.3	83.0	82.8
	C	116.5	114.2	111.5	113.9	114.5	115.1	114.9
Q211	C	115.9	113.6	111.7	113.3	113.8	114.5	114.3

< IC >

		PAL	SECAM	NTSC 3.58	NTSC 4.43	S (Y/C)	ANALOG RGB	COMPO-NENT
IC102	②	6.6	6.6	0.0	6.6	0.0	0.0	0.0
IC106	②	0.2	0.1	0.1	0.1	0.1	0.1	0.2
	④	1.8	1.7	1.7	1.7	1.7	1.8	1.8
IC107	②	10.7	10.7	10.6	10.6	10.6	10.6	10.6
	⑪	1.2	10.7	0.0	0.0	0.0	0.0	0.0
IC108	①	9.7	0.4	9.7	9.6	9.6	1.1	9.6
IC109	②	11.3	11.3	0.0	10.8	0.0	0.0	0.0
	③	11.3	11.4	0.0	11.3	0.0	0.0	0.0
	④	11.7	0.0	0.0	11.7	0.0	0.0	0.0
	⑤	11.0	11.1	0.0	11.0	0.0	0.0	0.0
IC110	④	2.1	2.2	2.5	2.5	2.5	2.5	2.5
	⑩	11.3	11.3	0.0	11.3	0.0	0.0	0.0
	⑪	11.3	11.3	0.0	0.0	0.0	0.0	0.0
	⑫	0.8	0.8	2.5	2.5	2.5	2.5	2.5
	⑬	1.7	1.7	2.5	2.6	2.5	2.5	2.5
IC113	④	2.7	1.1	2.6	2.6	2.6	1.1	1.1
	⑦	4.2	4.3	4.2	4.3	4.3	4.6	4.8
	⑪	3.0	2.9	2.8	3.0	2.6	2.9	2.9
	⑤	2.2	2.5	2.9	2.2	1.9	2.8	2.8
IC114	⑭	11.4	11.3	0.0	0.0	0.0	0.0	0.0
	⑬	3.7	3.7	3.8	3.8	3.8	3.9	3.9
IC115	⑪	1.2	1.1	0.6	0.7	0.7	0.6	0.6
	⑭	3.5	3.5	3.4	2.8	3.4	3.4	3.4
IC116	②	0.0	0.0	1.0	1.1	1.1	1.3	1.1
IC120	③	5.5	5.6	5.6	5.6	5.6	5.6	5.6
	④	5.5	5.6	5.6	5.6	5.6	5.0	5.6
IC121	⑮	5.3	5.3	5.4	5.2	5.2	5.1	5.1
	⑭	5.6	5.7	5.6	5.6	5.7	5.7	5.7
	⑬	5.6	5.7	5.6	5.6	5.7	5.7	5.6
IC122	②	5.3	5.3	5.4	5.2	5.2	5.1	5.1
	③	5.3	5.3	5.4	5.2	5.2	5.1	5.1
IC124	⑱	0.1	0.1	0.2	0.2	0.2	0.2	0.2
IC125	④	1.4	1.4	1.3	1.4	1.5	1.5	1.5
IC126	②	1.6	1.5	1.3	1.6	1.6	1.7	1.6
	⑤	1.6	1.5	1.3	1.6	1.6	1.6	1.7
	⑭	1.7	1.6	1.4	1.7	1.7	1.6	1.7
IC127	①	3.0	2.9	2.6	3.0	3.1	3.0	3.0
	②	1.4	1.4	1.3	1.5	1.5	1.5	1.5
	⑦	2.1	2.7	2.4	2.8	2.8	2.8	2.8



Schematic diagrams

← QA FA G S boards

CA X P HA

Schematic diagram

B (1/2) board →


B (1/2)
(SIGNAL PROCESS)
TO S BOARD CN1101
TO Θ BOARD CN502
CN103 12P
CN104 12P WHT
IC101 MM1149XFF SECAM-IMPUT-SW
IC102 MM1113XFF Y-SW
IC103 MM1113XFF BPF-SW
IC104 MM1113XFF Y-D.L.-SW
IC105 MM1113XFF SYNC-SIG-SW
IC106 MM1114XFF B-Y-SW
IC107 XRU4584BF NOT-GATE
IC108 MC14538BF H-PULSE-GEN
IC109 MM1114XFF R-Y-SW
IC110 XRU4053BF SYSTEM-SW1
IC111 MM1114XFF G/Y-SW
IC112 μPC78D5H 5V-REG
IC113 M51279EP CHROMA-DEMOD
IC114 XRU4052BF SYSTEM-SW3
IC115 XRU4052BF SYSTEM-SW5
IC116 MM1114XFF B/B-Y-SW
IC117 MM1114XFF B/B-Y-SW
IC118 MM1114XFF R/R-Y-SW
IC119 MM1114XFF G/Y-SW
IC128 LM5808R PAL-60-1B2
Q101 2SC2412K CHROMA-AMP
Q102 2SC2412K Y-SW-BUFF
Q103 2SC2412K 6V-REG
Q104 2SC2412K C-SW-BUFF
Q105 2SC2412K C-SW
Q106 2SC2412K SYNC-SIG-BUFF
Q107 2SC2412K Y-AMP-1
Q108 2SA1037K Y-AMP-2
Q109 2SA1037K Y-D.L.-BUFF
Q110 2SA1037K B-Y-BUFF1
Q111 2SA1037K B-Y-BUFF2
Q112 2SC2412K SYNC-BUFF
Q113 2SC2412K V-SYNC-SEP-1
Q114 2SA1037K V-SYNC-SEP-2
Q115 2SA1037K SLICER1
Q116 2SA1037K BL-SHIFT-2
Q117 2SA1037K LEVEL-SHIFT3
Q118 2SA1037K R-Y-BUFF1
Q119 2SA1037K G/Y-BUFF1
Q120 2SA1037K R-Y-BUFF2
Q121 2SA1037K 9XO-BUFF
Q122 2SA1037K 14.3-SW
Q123 2SA1037K 17.7-SW
Q124 2SA1037K B-Y-BUFF2
Q125 2SA1037K R-Y-BUFF2
Q126 BTC144EK PAL/NT-SW
Q127 2SA1037K R-Y-BUFF1
Q128 2SA1037K B-Y-BUFF1
Q129 BTC124EK HV-BL-SW1
Q130 2SA1037K R-Y-BUFF2
Q131 2SA1037K Y-BUFF
Q132 BTC144EK SECAM-SW1
Q133 2SC2412K 14.3-SW
Q134 BTC124EK SYSTEM-SW4
Q135 2SC2412K 17.7-SW
Q136 2SA1037K B/B-Y-BUFF1
Q137 2SA1037K R/R-Y-BUFF1
Q138 2SA1037K G/Y-BUFF1
Q139 2SA1037K Y-BUFF
Q140 2SA1037K MUTE-SW
Q141 MA110 SW1
Q142 2SA1037K BL-SHIFT-1
Q143 2SA1037K LAMP-BUFF-1
Q144 2SA1037K LAMP-BUFF-2
Q145 2SA1037K SLICER2
Q146 2SA1037K BUFF
Q147 2SA1037K SYNC-SEP
Q148 2SA1037K AMP-1
Q149 2SA1037K AMP-2
Q150 2SC2412K BPF-SW-BUFF
Q151 2SC2412K Y-AMP-2
Q152 2SC2412K SYNC-BUFF
Q153 2SC2412K V-SYNC-SEP-1
Q154 2SA1037K V-SYNC-SEP-2
Q155 2SA1037K MUTE-SW
Q156 MA110 SW2
Q157 MA110 SW3
Q158 MA110 SW4
Q159 MA110 SW5
Q160 MA110 SW6
Q161 MA110 SW7
Q162 MA110 SW8
Q163 MA110 SW9
Q164 MA110 SW10
Q165 MA110 B/W-SW1
Q166 MA110 PULSE-ADJ
Q167 MA110 LEVEL-SHIFT1
Q168 MA110 LEVEL-SHIFT2
Q169 MA110 LEVEL-SHIFT3
Q170 MA110 SYNC-SEP-1
Q171 MA110 SYNC-SEP-2
Q172 MA110 SYNC-SEP-3
Q173 MA110 SYNC-SEP-4
Q174 MA110 SYNC-SEP-5
Q175 MA110 SYNC-SEP-6
Q176 MA110 SYNC-SEP-7
Q177 MA110 SYNC-SEP-8
Q178 MA110 SYNC-SEP-9
Q179 MA110 SYNC-SEP-10
Q180 MA110 SYNC-SEP-11
Q181 MA110 SYNC-SEP-12
Q182 MA110 SYNC-SEP-13
Q183 MA110 SYNC-SEP-14
Q184 MA110 SYNC-SEP-15
Q185 MA110 SYNC-SEP-16
Q186 MA151WK SECAM-SW1
Q187 MA157 LEVEL-SHIFT1
Q188 MA157 LEVEL-SHIFT2
Q189 MA157 LEVEL-SHIFT3
Q190 MA157 PROTECT1
Q191 MA157 PROTECT2
Q192 MA151VA PAL-60-1B1
Q193 MA110 SLICER1
Q194 MA110 SLICER2
Q195 MA110 SLICER3
Q196 MA110 SLICER4
Q197 MA110 SLICER5
Q198 MA110 SLICER6
Q199 MA110 SLICER7
Q200 MA110 SLICER8
Q201 MA110 SLICER9
Q202 MA110 SLICER10
Q203 MA110 SLICER11
Q204 MA110 SLICER12
Q205 MA110 SLICER13
Q206 MA110 SLICER14
Q207 MA110 SLICER15
Q208 MA110 SLICER16
CFIL01 CFB-2
BPF101 BPF3.58
BPF102 4.43 BPF
CTR102 TRAP
X101 14.3MHz
X102 17.7MHz
L101 10uH
L102 10uH
L103 10uH
L104 10uH
L105 10uH
L106 10uH
L107 10uH
L108 10uH
L109 10uH
L110 10uH
L111 10uH
L112 10uH
L113 10uH
L114 10uH
L115 10uH
L116 10uH
L117 10uH
L118 10uH
L119 10uH
L120 10uH

TSC .43	Y (Y/C)	ANALOG RGB	COMPO-NENT
6.6	0.0	0.0	0.0
0.1	0.1	0.1	0.2
1.7	1.7	1.8	1.8
10.6	10.8	10.8	10.6
0.0	0.0	0.0	0.0
9.6	9.6	1.1	9.5
10.8	0.0	0.0	0.0
11.3	0.0	0.0	0.0
11.7	0.0	0.0	0.0
11.0	0.0	0.0	0.0
2.5	2.5	2.5	2.5
11.3	0.0	0.0	0.0
0.0	0.0	0.0	0.0
2.5	2.5	2.5	2.5
2.6	2.5	2.5	2.5
2.6	2.6	1.1	1.1
4.3	4.3	4.8	4.8
3.0	2.8	2.9	2.9
2.2	1.9	2.8	2.8
0.0	0.0	0.0	0.0
3.8	3.8	3.9	3.9
0.7	0.7	0.8	0.8
2.8	3.4	3.4	3.4
1.1	1.1	1.3	1.1
5.6	5.6	5.6	5.6
5.6	5.6	5.0	5.6
5.2	5.2	5.1	5.1
5.6	5.7	5.7	5.7
5.6	5.7	5.7	5.6
5.2	5.2	5.1	5.1
5.2	5.2	5.1	5.1
0.2	0.2	0.2	0.2
1.4	1.5	1.5	1.5
1.6	1.6	1.7	1.6
1.8	1.8	1.8	1.7
1.7	1.7	1.6	1.7
3.0	3.1	3.0	3.0
1.5	1.5	1.5	1.5
2.8	2.8	2.8	2.8

: di ram

board ➡


B (1/2)
(SIGNAL PROCESS)
TO S BOARD CN1101
TO B BOARD CN502
CN104
12V
WHT
50/60
COMP-SYNC
V.P.
V-BLK
H-BLK
ABL
GND
POWER-LED
U/SW PULSE
HV-DL
120V
12V
B/W
HV-DL-L
CLP-1
HV-DL-H
HVE
ABL
V.P.
V-BLK
H-BLK
120V
B-Y (SECAM)
R-Y (SECAM)
CHROMA
Y/G
R-Y/R
B-Y/B
V/R-Y
U/B-Y
PULSE-WIDTH
PULSE-POSITION
PULSE-POSI-ADJ
H-PULSE-GEN
NOT-GATE
H-BLK-SW1
HV-DL-SW2
PULSE-SW
CLAMP-PULSE-SW
SYNC-SIG-BUFF
SYNC-SIG-SW
SYNC-BUFF
V-SYNC-SEP-1
V-SYNC-SEP-2
LEVEL-SHIFT1
LEVEL-SHIFT2
LEVEL-SHIFT3
SYNC-SW
MUTE-SW
INSERT-PULSE-SW
B/W-SW1
B/W-SW2
B/W-SW3
B/W-SW4
B/W-SW5
B/W-SW6
B/W-SW7
B/W-SW8
B/W-SW9
B/W-SW10
B/W-BUFF1
B-Y/B-BUFF1
R-Y/R-BUFF1
G/Y-BUFF1
B-Y-BUFF1
R-Y-BUFF1
G/Y-BUFF
Y-BUFF1
R-Y-BUFF2
B-Y-BUFF2
VXO-BUFF
14.3-SW
17.7-SW
SYSTEM-SW1
SYSTEM-SW2
SYSTEM-SW3
SYSTEM-SW4
SYSTEM-SW5
B-Y/B-SW1
B-Y/B-SW2
B-Y/B-SW3
B-Y/B-SW4
R-Y/R-SW1
R-Y/R-SW2
R-Y/R-SW3
R-Y/R-SW4
R-Y/R-SW5
R-Y/R-SW6
R-Y/R-SW7
R-Y/R-SW8
R-Y/R-SW9
R-Y/R-SW10
G/Y-SW1
G/Y-SW2
G/Y-SW3
G/Y-SW4
G/Y-SW5
G/Y-SW6
G/Y-SW7
G/Y-SW8
G/Y-SW9
G/Y-SW10
Y-D.L-SW
Y-AMP-1
Y-AMP-2
Y/C-SW
B/W-SW
SECAM-SW1
SECAM-SW2
SECAM-SW3
SECAM-SW4
SECAM-SW5
SECAM-SW6
SECAM-SW7
SECAM-SW8
SECAM-SW9
SECAM-SW10
SECAM-SW11
SECAM-SW12
SECAM-SW13
SECAM-SW14
SECAM-SW15
SECAM-SW16
SECAM-SW17
SECAM-SW18
SECAM-SW19
SECAM-SW20
SECAM-SW21
SECAM-SW22
SECAM-SW23
SECAM-SW24
SECAM-SW25
SECAM-SW26
SECAM-SW27
SECAM-SW28
SECAM-SW29
SECAM-SW30
SECAM-SW31
SECAM-SW32
SECAM-SW33
SECAM-SW34
SECAM-SW35
SECAM-SW36
SECAM-SW37
SECAM-SW38
SECAM-SW39
SECAM-SW40
SECAM-SW41
SECAM-SW42
SECAM-SW43
SECAM-SW44
SECAM-SW45
SECAM-SW46
SECAM-SW47
SECAM-SW48
SECAM-SW49
SECAM-SW50
SECAM-SW51
SECAM-SW52
SECAM-SW53
SECAM-SW54
SECAM-SW55
SECAM-SW56
SECAM-SW57
SECAM-SW58
SECAM-SW59
SECAM-SW60
SECAM-SW61
SECAM-SW62
SECAM-SW63
SECAM-SW64
SECAM-SW65
SECAM-SW66
SECAM-SW67
SECAM-SW68
SECAM-SW69
SECAM-SW70
SECAM-SW71
SECAM-SW72
SECAM-SW73
SECAM-SW74
SECAM-SW75
SECAM-SW76
SECAM-SW77
SECAM-SW78
SECAM-SW79
SECAM-SW80
SECAM-SW81
SECAM-SW82
SECAM-SW83
SECAM-SW84
SECAM-SW85
SECAM-SW86
SECAM-SW87
SECAM-SW88
SECAM-SW89
SECAM-SW90
SECAM-SW91
SECAM-SW92
SECAM-SW93
SECAM-SW94
SECAM-SW95
SECAM-SW96
SECAM-SW97
SECAM-SW98
SECAM-SW99
SECAM-SW100
SECAM-SW101
SECAM-SW102
SECAM-SW103
SECAM-SW104
SECAM-SW105
SECAM-SW106
SECAM-SW107
SECAM-SW108
SECAM-SW109
SECAM-SW110
SECAM-SW111
SECAM-SW112
SECAM-SW113
SECAM-SW114
SECAM-SW115
SECAM-SW116
SECAM-SW117
SECAM-SW118
SECAM-SW119
SECAM-SW120
SECAM-SW121
SECAM-SW122
SECAM-SW123
SECAM-SW124
SECAM-SW125
SECAM-SW126
SECAM-SW127
SECAM-SW128
SECAM-SW129
SECAM-SW130
SECAM-SW131
SECAM-SW132
SECAM-SW133
SECAM-SW134
SECAM-SW135
SECAM-SW136
SECAM-SW137
SECAM-SW138
SECAM-SW139
SECAM-SW140
SECAM-SW141
SECAM-SW142
SECAM-SW143
SECAM-SW144
SECAM-SW145
SECAM-SW146
SECAM-SW147
SECAM-SW148
SECAM-SW149
SECAM-SW150
SECAM-SW151
SECAM-SW152
SECAM-SW153
SECAM-SW154
SECAM-SW155
SECAM-SW156
SECAM-SW157
SECAM-SW158
SECAM-SW159
SECAM-SW160
SECAM-SW161
SECAM-SW162
SECAM-SW163
SECAM-SW164
SECAM-SW165
SECAM-SW166
SECAM-SW167
SECAM-SW168
SECAM-SW169
SECAM-SW170
SECAM-SW171
SECAM-SW172
SECAM-SW173
SECAM-SW174
SECAM-SW175
SECAM-SW176
SECAM-SW177
SECAM-SW178
SECAM-SW179
SECAM-SW180
SECAM-SW181
SECAM-SW182
SECAM-SW183
SECAM-SW184
SECAM-SW185
SECAM-SW186
SECAM-SW187
SECAM-SW188
SECAM-SW189
SECAM-SW190
SECAM-SW191
SECAM-SW192
SECAM-SW193
SECAM-SW194
SECAM-SW195
SECAM-SW196
SECAM-SW197
SECAM-SW198
SECAM-SW199
SECAM-SW200
SECAM-SW201
SECAM-SW202
SECAM-SW203
SECAM-SW204
SECAM-SW205
SECAM-SW206
SECAM-SW207
SECAM-SW208
SECAM-SW209
SECAM-SW210
SECAM-SW211
SECAM-SW212
SECAM-SW213
SECAM-SW214
SECAM-SW215
SECAM-SW216
SECAM-SW217
SECAM-SW218
SECAM-SW219
SECAM-SW220
SECAM-SW221
SECAM-SW222
SECAM-SW223
SECAM-SW224
SECAM-SW225
SECAM-SW226
SECAM-SW227
SECAM-SW228
SECAM-SW229
SECAM-SW230
SECAM-SW231
SECAM-SW232
SECAM-SW233
SECAM-SW234
SECAM-SW235
SECAM-SW236
SECAM-SW237
SECAM-SW238
SECAM-SW239
SECAM-SW240
SECAM-SW241
SECAM-SW242
SECAM-SW243
SECAM-SW244
SECAM-SW245
SECAM-SW246
SECAM-SW247
SECAM-SW248
SECAM-SW249
SECAM-SW250
SECAM-SW251
SECAM-SW252
SECAM-SW253
SECAM-SW254
SECAM-SW255
SECAM-SW256
SECAM-SW257
SECAM-SW258
SECAM-SW259
SECAM-SW260
SECAM-SW261
SECAM-SW262
SECAM-SW263
SECAM-SW264
SECAM-SW265
SECAM-SW266
SECAM-SW267
SECAM-SW268
SECAM-SW269
SECAM-SW270
SECAM-SW271
SECAM-SW272
SECAM-SW273
SECAM-SW274
SECAM-SW275
SECAM-SW276
SECAM-SW277
SECAM-SW278
SECAM-SW279
SECAM-SW280
SECAM-SW281
SECAM-SW282
SECAM-SW283
SECAM-SW284
SECAM-SW285
SECAM-SW286
SECAM-SW287
SECAM-SW288
SECAM-SW289
SECAM-SW290
SECAM-SW291
SECAM-SW292
SECAM-SW293
SECAM-SW294
SECAM-SW295
SECAM-SW296
SECAM-SW297
SECAM-SW298
SECAM-SW299
SECAM-SW300
SECAM-SW301
SECAM-SW302
SECAM-SW303
SECAM-SW304
SECAM-SW305
SECAM-SW306
SECAM-SW307
SECAM-SW308
SECAM-SW309
SECAM-SW310
SECAM-SW311
SECAM-SW312
SECAM-SW313
SECAM-SW314
SECAM-SW315
SECAM-SW316
SECAM-SW317
SECAM-SW318
SECAM-SW319
SECAM-SW320
SECAM-SW321
SECAM-SW322
SECAM-SW323
SECAM-SW324
SECAM-SW325
SECAM-SW326
SECAM-SW327
SECAM-SW328
SECAM-SW329
SECAM-SW330
SECAM-SW331
SECAM-SW332
SECAM-SW333
SECAM-SW334
SECAM-SW335
SECAM-SW336
SECAM-SW337
SECAM-SW338
SECAM-SW339
SECAM-SW340
SECAM-SW341
SECAM-SW342
SECAM-SW343
SECAM-SW344
SECAM-SW345
SECAM-SW346
SECAM-SW347
SECAM-SW348
SECAM-SW349
SECAM-SW350
SECAM-SW351
SECAM-SW352
SECAM-SW353
SECAM-SW354
SECAM-SW355
SECAM-SW356
SECAM-SW357
SECAM-SW358
SECAM-SW359
SECAM-SW360
SECAM-SW361
SECAM-SW362
SECAM-SW363
SECAM-SW364
SECAM-SW365
SECAM-SW366
SECAM-SW367
SECAM-SW368
SECAM-SW369
SECAM-SW370
SECAM-SW371
SECAM-SW372
SECAM-SW373
SECAM-SW374
SECAM-SW375
SECAM-SW376
SECAM-SW377
SECAM-SW378
SECAM-SW379
SECAM-SW380
SECAM-SW381
SECAM-SW382
SECAM-SW383
SECAM-SW384
SECAM-SW385
SECAM-SW386
SECAM-SW387
SECAM-SW388
SECAM-SW389
SECAM-SW390
SECAM-SW391
SECAM-SW392
SECAM-SW393
SECAM-SW394
SECAM-SW395
SECAM-SW396
SECAM-SW397
SECAM-SW398
SECAM-SW399
SECAM-SW400
SECAM-SW401
SECAM-SW402
SECAM-SW403
SECAM-SW404
SECAM-SW405
SECAM-SW406
SECAM-SW407
SECAM-SW408
SECAM-SW409
SECAM-SW410
SECAM-SW411
SECAM-SW412
SECAM-SW413
SECAM-SW414
SECAM-SW415
SECAM-SW416
SECAM-SW417
SECAM-SW418
SECAM-SW419
SECAM-SW420
SECAM-SW421
SECAM-SW422
SECAM-SW423
SECAM-SW424
SECAM-SW425
SECAM-SW426
SECAM-SW427
SECAM-SW428
SECAM-SW429
SECAM-SW430
SECAM-SW431
SECAM-SW432
SECAM-SW433
SECAM-SW434
SECAM-SW435
SECAM-SW436
SECAM-SW437
SECAM-SW438
SECAM-SW439
SECAM-SW440
SECAM-SW441
SECAM-SW442
SECAM-SW443
SECAM-SW444
SECAM-SW445
SECAM-SW446
SECAM-SW447
SECAM-SW448
SECAM-SW449
SECAM-SW450
SECAM-SW451
SECAM-SW452
SECAM-SW453
SECAM-SW454
SECAM-SW455
SECAM-SW456
SECAM-SW457
SECAM-SW458
SECAM-SW459
SECAM-SW460
SECAM-SW461
SECAM-SW462
SECAM-SW463
SECAM-SW464
SECAM-SW465
SECAM-SW466
SECAM-SW467
SECAM-SW468
SECAM-SW469
SECAM-SW470
SECAM-SW471
SECAM-SW472
SECAM-SW473
SECAM-SW474
SECAM-SW475
SECAM-SW476
SECAM-SW477
SECAM-SW478
SECAM-SW479
SECAM-SW480
SECAM-SW481
SECAM-SW482
SECAM-SW483
SECAM-SW484
SECAM-SW485
SECAM-SW486
SECAM-SW487
SECAM-SW488
SECAM-SW489
SECAM-SW490
SECAM-SW491
SECAM-SW492
SECAM-SW493
SECAM-SW494
SECAM-SW495
SECAM-SW496
SECAM-SW497
SECAM-SW498
SECAM-SW499
SECAM-SW500
SECAM-SW501
SECAM-SW502
SECAM-SW503
SECAM-SW504
SECAM-SW505
SECAM-SW506
SECAM-SW507
SECAM-SW508
SECAM-SW509
SECAM-SW510
SECAM-SW511
SECAM-SW512
SECAM-SW513
SECAM-SW514
SECAM-SW515
SECAM-SW516
SECAM-SW517
SECAM-SW518
SECAM-SW519
SECAM-SW520
SECAM-SW521
SECAM-SW522
SECAM-SW523
SECAM-SW524
SECAM-SW525
SECAM-SW526
SECAM-SW527
SECAM-SW528
SECAM-SW529
SECAM-SW530
SECAM-SW531
SECAM-SW532
SECAM-SW533
SECAM-SW534
SECAM-SW535
SECAM-SW536
SECAM-SW537
SECAM-SW538
SECAM-SW539
SECAM-SW540
SECAM-SW541
SECAM-SW542
SECAM-SW543
SECAM-SW544
SECAM-SW545
SECAM-SW546
SECAM-SW547
SECAM-SW548
SECAM-SW549
SECAM-SW550
SECAM-SW551
SECAM-SW552
SECAM-SW553
SECAM-SW554
SECAM-SW555
SECAM-SW556
SECAM-SW557
SECAM-SW558
SECAM-SW559
SECAM-SW560
SECAM-SW561
SECAM-SW562
SECAM-SW563
SECAM-SW564
SECAM-SW565
SECAM-SW566
SECAM-SW567
SECAM-SW568
SECAM-SW569
SECAM-SW570
SECAM-SW571
SECAM-SW572
SECAM-SW573
SECAM-SW574
SECAM-SW575
SECAM-SW576
SECAM-SW577
SECAM-SW578
SECAM-SW579
SECAM-SW580
SECAM-SW581
SECAM-SW582
SECAM-SW583
SECAM-SW584
SECAM-SW585
SECAM-SW586
SECAM-SW587
SECAM-SW588
SECAM-SW589
SECAM-SW590
SECAM-SW591
SECAM-SW592
SECAM-SW593
SECAM-SW594
SECAM-SW595
SECAM-SW596
SECAM-SW597
SECAM-SW598
SECAM-SW599
SECAM-SW600
SECAM-SW601
SECAM-SW602
SECAM-SW603
SECAM-SW604
SECAM-SW605
SECAM-SW606
SECAM-SW607
SECAM-SW608
SECAM-SW609
SECAM-SW610
SECAM-SW611
SECAM-SW612
SECAM-SW613
SECAM-SW614
SECAM-SW615
SECAM-SW616
SECAM-SW617
SECAM-SW618
SECAM-SW619
SECAM-SW620
SECAM-SW621
SECAM-SW622
SECAM-SW623
SECAM-SW624
SECAM-SW625
SECAM-SW626
SECAM-SW627
SECAM-SW628
SECAM-SW629
SECAM-SW630
SECAM-SW631
SECAM-SW632
SECAM-SW633
SECAM-SW634
SECAM-SW635
SECAM-SW636
SECAM-SW637
SECAM-SW638
SECAM-SW639
SECAM-SW640
SECAM-SW641
SECAM-SW642
SECAM-SW643
SECAM-SW644
SECAM-SW645
SECAM-SW646
SECAM-SW647
SECAM-SW648
SECAM-SW649
SECAM-SW650
SECAM-SW651
SECAM-SW652
SECAM-SW653
SECAM-SW654
SECAM-SW655
SECAM-SW656
SECAM-SW657
SECAM-SW658
SECAM-SW659
SECAM-SW660
SECAM-SW661
SECAM-SW662
SECAM-SW663
SECAM-SW664
SECAM-SW665
SECAM-SW666
SECAM-SW667
SECAM-SW668
SECAM-SW669
SECAM-SW670
SECAM-SW671
SECAM-SW672
SECAM-SW673
SECAM-SW674
SECAM-SW675
SECAM-SW676
SECAM-SW677
SECAM-SW678
SECAM-SW679
SECAM-SW680
SECAM-SW681
SECAM-SW682
SECAM-SW683
SECAM-SW684
SECAM-SW685
SECAM-SW686
SECAM-SW687
SECAM-SW688
SECAM-SW689
SECAM-SW690
SECAM-SW691
SECAM-SW692
SECAM-SW693
SECAM-SW694
SECAM-SW695
SECAM-SW696
SECAM-SW697
SECAM-SW698
SECAM-SW699
SECAM-SW700
SECAM-SW701
SECAM-SW702
SECAM-SW703
SECAM-SW704
SECAM-SW705
SECAM-SW706
SECAM-SW707
SECAM-SW708
SECAM-SW709
SECAM-SW710
SECAM-SW711
SECAM-SW712
SECAM-SW713
SECAM-SW714
SECAM-SW715
SECAM-SW716
SECAM-SW717
SECAM-SW718
SECAM-SW719
SECAM-SW720
SECAM-SW721
SECAM-SW722
SECAM-SW723
SECAM-SW724
SECAM-SW725
SECAM-SW726
SECAM-SW727
SECAM-SW728
SECAM-SW729
SECAM-SW730
SECAM-SW731
SECAM-SW732
SECAM-SW733
SECAM-SW734
SECAM-SW735
SECAM-SW736
SECAM-SW737
SECAM-SW738
SECAM-SW739
SECAM-SW740
SECAM-SW741
SECAM-SW742
SECAM-SW743
SECAM-SW744
SECAM-SW745
SECAM-SW746
SECAM-SW747
SECAM-SW748
SECAM-SW749
SECAM-SW750
SECAM-SW751
SECAM-SW752
SECAM-SW753
SECAM-SW754
SECAM-SW755
SECAM-SW756
SECAM-SW757
SECAM-SW758
SECAM-SW759
SECAM-SW760
SECAM-SW761
SECAM-SW762
SECAM-SW763
SECAM-SW764
SECAM-SW765
SECAM-SW766
SECAM-SW767
SECAM-SW768
SECAM-SW769
SECAM-SW770
SECAM-SW771
SECAM-SW772
SECAM-SW773
SECAM-SW774
SECAM-SW775
SECAM-SW776
SECAM-SW777
SECAM-SW778
SECAM-SW779
SECAM-SW780
SECAM-SW781
SECAM-SW782
SECAM-SW783
SECAM-SW784
SECAM-SW785
SECAM-SW786
SECAM-SW787
SECAM-SW788
SECAM-SW789
SECAM-SW790
SECAM-SW791
SECAM-SW792
SECAM-SW793
SECAM-SW794
SECAM-SW795
SECAM-SW796
SECAM-SW797
SECAM-SW798
SECAM-SW799
SECAM-SW800
SECAM-SW801
SECAM-SW802
SECAM-SW803
SECAM-SW804
SECAM-SW805
SECAM-SW806
SECAM-SW807
SECAM-SW808
SECAM-SW809
SECAM-SW810
SECAM-SW811
SECAM-SW812
SECAM-SW813
SECAM-SW814
SECAM-SW815
SECAM-SW816
SECAM-SW817
SECAM-SW818
SECAM-SW819
SECAM-SW820
SECAM-SW821
SECAM-SW822
SECAM-SW823
SECAM-SW824
SECAM-SW825
SECAM-SW826
SECAM-SW827
SECAM-SW828
SECAM-SW829
SECAM-SW830
SECAM-SW831
SECAM-SW832
SECAM-SW833
SECAM-SW834
SECAM-SW835
SECAM-SW836
SECAM-SW837
SECAM-SW838
SECAM-SW839
SECAM-SW840
SECAM-SW841
SECAM-SW842
SECAM-SW843
SECAM-SW844
SECAM-SW845
SECAM-SW846
SECAM-SW847
SECAM-SW848
SECAM-SW849
SECAM-SW850
SECAM-SW851
SECAM-SW852
SECAM-SW853
SECAM-SW854
SECAM-SW855
SECAM-SW856
SECAM-SW857
SECAM-SW858
SECAM-SW859
SECAM-SW860
SECAM-SW861
SECAM-SW862
SECAM-SW863
SECAM-SW864
SECAM-SW865
SECAM-SW866
SECAM-SW867
SECAM-SW868
SECAM-SW869
SECAM-SW870
SECAM-SW871
SECAM-SW872
SECAM-SW873
SECAM-SW874
SECAM-SW875
SECAM-SW876
SECAM-SW877
SECAM-SW878
SECAM-SW879
SECAM-SW880
SECAM-SW881
SECAM-SW882
SECAM-SW883
SECAM-SW884
SECAM-SW885
SECAM-SW886
SECAM-SW887
SECAM-SW888
SECAM-SW889
SECAM-SW890
SECAM-SW891
SECAM-SW892
SECAM-SW893
SECAM-SW894
SECAM-SW895
SECAM-SW896
SECAM-SW897
SECAM-SW898
SECAM-SW899
SECAM-SW900
SECAM-SW901
SECAM-SW902
SECAM-SW903
SECAM-SW904
SECAM-SW905
SECAM-SW906
SECAM-SW907
SECAM-SW908
SECAM-SW909
SECAM-SW910
SECAM-SW911
SECAM-SW912
SECAM-SW913
SECAM-SW914
SECAM-SW915
SECAM-SW916
SECAM-SW917
SECAM-SW918
SECAM-SW919
SECAM-SW920
SECAM-SW921
SECAM-SW922
SECAM-SW923
SECAM-SW924
SECAM-SW925
SECAM-SW926
SECAM-SW927
SECAM-SW928
SECAM-SW929
SECAM-SW930
SECAM-SW931
SECAM-SW932
SECAM-SW933
SECAM-SW934
SECAM-SW935
SECAM-SW936
SECAM-SW937
SECAM-SW938
SECAM-SW939
SECAM-SW940
SECAM-SW941
SECAM-SW942
SECAM-SW943
SECAM-SW944
SECAM-SW945
SECAM-SW946
SECAM-SW947
SECAM-SW948
SECAM-SW949
SECAM-SW950
SECAM-SW951
SECAM-SW952
SECAM-SW953
SECAM-SW954
SECAM-SW955
SECAM-SW956
SECAM-SW957
SECAM-SW958
SECAM-SW959
SECAM-SW960
SECAM-SW961
SECAM-SW962
SECAM-SW963
SECAM-SW964
SECAM-SW965
SECAM-SW966
SECAM-SW967
SECAM-SW968
SECAM-SW969
SECAM-SW970
SECAM-SW971
SECAM-SW972
SECAM-SW973
SECAM-SW974
SECAM-SW975
SECAM-SW976
SECAM-SW977
SECAM-SW978
SECAM-SW979
SECAM-SW980
SECAM-SW981
SECAM-SW982
SECAM-SW983
SECAM-SW984
SECAM-SW985
SECAM-SW986
SECAM-SW987
SECAM-SW988
SECAM-SW989
SECAM-SW990
SECAM-SW991
SECAM-SW992
SECAM-SW993
SECAM-SW994
SECAM-SW995
SECAM-SW996
SECAM-SW997
SECAM-SW998
SECAM-SW999
SECAM-SW1000


9
10
11
12
13
14
15
16
PULSE-WIDTH
PULSE-POSITION
IC106 MC14538BF H-PULSE-GEN
IC107 XRU4584BF NOT-GATE
IC109 XRU4070BF EX-OR
IC117 MM1114XFF B/B-Y-SW
IC118 MM1114XFF R/R-Y-SW
IC119 MM1114XFF G/Y-SW
IC120 XRU4066BF SAMPLE
IC121 XRU4053BF BLACK-INSERT
IC122 LM358BR HOLD-KILLER-IB
IC123 LM358BR HOLD-KILLER-IB
IC108 XRU4053BF CLAMP-PULSE-SW
Q129 DTC122EK HV-BL-SW1
Q110 MA110 H-BLK-SW1
Q111 MA110 HV-BL-SW2
Q117 MA110 RGB/COMP-SW1
Q191 MA151WA SW2 B/W-SW1
Q121 MA110 SECAM-SW3
Q128 MA151WK PULSE-SW
Q185 MA151WA SWCAM-SW4 SW6
Q285 MA110 SW12
Q112 2SC2412K SYNC-BUFF
Q113 2SC2412K V-SYNC-SEP-1
Q114 2SA1037K V-SYNC-SEP-2
Q115 2SC2412K V-SYNC-SW
Q116 2SC2412K A/B-SW
Q140 2SC2412K B/W-SW2
Q132 2SA1037K INSERT-PULSE-SW
Q141 2SC2412K B/B-Y-BUFF2
Q142 2SC2412K R/R-Y-BUFF2
Q143 2SC2412K G/Y-BUFF2
Q139 2SA1037K Y-BUFF1
Q190 2SA1037K MUTE-SW
Q170 MA110 PULSE-POSI-ADJ
Q171 MA110 LEVEL-SHIFT3
B187 MA157 LEVEL-SHIFT1
LEVEL-SHIFT2
CN108 3P WHT :S-MICRO
1 TALLY
2 NC
3 GND
TO X BOARD CN21
P-LED
UNDER-H
MUTE
Y/G
R-Y/R
B-Y/B
RGB-H
PULSE-2
BLUE-L
EXT-H
CLP-2
RGB. COMP
A-H/B-L
VOL
12V
B/W
HV-DL-L
CLP-1
HV-DL-H
HVE
ABL
V.P.
V-BLK
H-BLK
120V
R-Y (SECAM)
B-Y (SECAM)
B-SS3167A<AUS>-B..-P1
B (1/2)
SIGNAL PROCESS)

B (2/2)
(SIGNAL PROCESS)





• B BOARD WAVEFORMS



• B BOARD WAVEFORMS



FORMS


②
RGB 1Vp-p (H)
COMPONENT 0.5Vp-p (H)
③
RGB 1Vp-p (H)
COMPONENT 1Vp-p (H)
COMPONENT 0.75Vp-p (H)
⑤
PAL 1Vp-p (H)
S (Y/C) 1Vp-p (H)
⑥
PAL 0.9Vp-p (H)
NTSC3.58 1Vp-p (H)
NTSC4.43 1Vp-p (H)
S (Y/C) 1Vp-p (H)
⑦
S (Y/C) 0.5Vp-p (H)
⑧
SECAM 1Vp-p (H)
NTSC4.43 1Vp-p (H)
S (Y/C) 1Vp-p (H)
⑨
PAL 0.75Vp-p (H)
SECAM 0.75Vp-p (H)
NTSC3.58 1Vp-p (H)
⑩
PAL 0.2Vp-p (H)
NTSC3.58 0.3Vp-p (H)
NTSC4.43 0.15Vp-p (H)
⑪
PAL 0.3Vp-p (H)
NTSC3.58 0.2Vp-p (H)
NTSC4.43 0.3Vp-p (H)
⑫
S (Y/C) 0.2Vp-p (H)
⑬
PAL 0.9Vp-p (H)
SECAM 0.9Vp-p (H)
NTSC3.58 1Vp-p (H)
NTSC4.43 1Vp-p (H)
S (Y/C) 1Vp-p (H)
COMPONENT 1Vp-p (H)
⑭
4Vp-p (H)
⑮
12Vp-p (H)
⑯
12Vp-p (H)
⑱
12Vp-p (H)
⑲
12Vp-p (H)
⑳
SECAM 0.6Vp-p (H)
㉑
SECAM 0.5Vp-p (H)
SECAM 0.8Vp-p (H)
NTSC3.58 1Vp-p (H)
NTSC4.43 1Vp-p (H)
S (Y/C) 1Vp-p (H)
㉓
12Vp-p (H)
㉔
12Vp-p (H)
㉖
PAL 1.2Vp-p (H)
SECAM 1.2Vp-p (H)
NTSC3.58 1.2Vp-p (H)
NTSC4.43 1.2Vp-p (H)
S (Y/C) 1.2Vp-p (H)
㉗
COMPONENT 1.4Vp-p (H)
PAL 1.3Vp-p (H)
SECAM 1.2Vp-p (H)
NTSC3.58 1.3Vp-p (H)
NTSC4.43 1.3Vp-p (H)
S (Y/C) 1.3Vp-p (H)
㉘
COMPONENT 1.4Vp-p (H)
PAL 1.2Vp-p (H)
SECAM 1.2Vp-p (H)
COMPONENT 1.4Vp-p (H)
NTSC3.58 1.5Vp-p (H)
NTSC4.43 1.5Vp-p (H)
S (Y/C) 1.5Vp-p (H)
RGB 1.4Vp-p (H)
㉚
PAL 1Vp-p (H)
SECAM 1Vp-p (H)
NTSC3.58 1Vp-p (H)
NTSC4.43 1Vp-p (H)
S (Y/C) 1Vp-p (H)
㉛
PAL 0.36Vp-p (H)
NTSC3.58 0.3Vp-p (H)
NTSC4.43 0.3Vp-p (H)
S (Y/C) 0.32Vp-p (H)
㉜
PAL 0.2Vp-p (H)
㉝
PAL 0.7Vp-p (H)
SECAM 1.1Vp-p (H)
NTSC3.58 1.0Vp-p (H) (3.58MHz)
NTSC4.43 0.6Vp-p (H) (4.43MHz)
S (Y/C) 1.0Vp-p (H) (3.58MHz)
㉞
PAL 1.2Vp-p (H)
㉟
PAL 0.5Vp-p (H)
NTSC3.58 1.2Vp-p (H)
NTSC4.43 0.6Vp-p (H)
S (Y/C) 1.2Vp-p (H)
㊱
PAL 0.4Vp-p (H)
SECAM 0.1Vp-p (H)
㊲
PAL 0.55Vp-p (H)
SECAM 0.1Vp-p (H)
NTSC3.58 0.4Vp-p (H)
S (Y/C) 0.4Vp-p (H)
㊳
PAL 0.4Vp-p (H)
SECAM 1Vp-p (H)
RGB 0.4Vp-p (H)
COMPONENT 0.4Vp-p (H)


㊳
NTSC3.58 0.4Vp-p (H)
NTSC4.43 0.4Vp-p (H)
S (Y/C) 0.4Vp-p (H)
㊴
12Vp-p (H)
㊵
PAL 11Vp-p (H)
㊶
PAL 1.8Vp-p (H)
㊷
PAL 0.5Vp-p (H)
SECAM 1Vp-p (H)
NTSC3.58 1Vp-p (H)
NTSC4.43 1Vp-p (H)
S (Y/C) 1Vp-p (H)
RGB 0.5Vp-p (H)
COMPONENT 0.5Vp-p (H)
㊸
PAL 0.35Vp-p (H)
SECAM 0.35Vp-p (H)
NTSC3.58 0.35Vp-p (H)
NTSC4.43 0.32Vp-p (H)
S (Y/C) 0.35Vp-p (H)
COMPONENT 0.28Vp-p (H)
㊹
PAL 0.45Vp-p (H)
㊹
SECAM 0.45Vp-p (H)
NTSC3.58 0.45Vp-p (H)
NTSC4.43 0.4Vp-p (H)
S (Y/C) 0.33Vp-p (H)
COMPONENT 0.36Vp-p (H)
㊺
PAL 0.5Vp-p (H)
SECAM 0.5Vp-p (H)
COMPONENT 0.6Vp-p (H)
NTSC3.58 0.8Vp-p (H)
NTSC4.43 0.8Vp-p (H)
S (Y/C) 0.6Vp-p (H)
㊻
PAL 0.36Vp-p (H)
SECAM 0.35Vp-p (H)
NTSC3.58 0.8Vp-p (H)
NTSC4.43 0.6Vp-p (H)
S (Y/C) 0.8Vp-p (H)
㊻
COMPONENT 0.3Vp-p (H)
㊼
4.6Vp-p (V)
㊽
10.4Vp-p (V)
㊾
3.5Vp-p (V)
㊿
3.5Vp-p (H)
(51)
PAL 2.6Vp-p (H)
SECAM 3Vp-p (H)
NTSC3.58 3.2Vp-p (H)
NTSC4.43 3.2Vp-p (H)
S (Y/C) 3.2Vp-p (H)
COMPONENT 3Vp-p (H)
RGB 2.7Vp-p (H)
(52)
PAL 2.6Vp-p (H)
SECAM 2.6Vp-p (H)
NTSC3.58 3.4Vp-p (H)
NTSC4.43 3.4Vp-p (H)
S (Y/C) 3.4Vp-p (H)
RGB 2.7Vp-p (H)
COMPONENT 3Vp-p (H)
(53)
PAL 2.5Vp-p (H)
SECAM 2.6Vp-p (H)
NTSC3.58 3.1Vp-p (H)
NTSC4.43 3.1Vp-p (H)
S (Y/C) 3.1Vp-p (H)
RGB 2.6Vp-p (H)
COMPONENT 2.8Vp-p (H)
(54)
PAL 0.6Vp-p (V)
SECAM 0.6Vp-p (V)
RGB 0.6Vp-p (V)
COMPONENT 0.6Vp-p (V)
NTSC3.58 0.9Vp-p (V)
NTSC4.43 1Vp-p (H)
S (Y/C) 0.7Vp-p (V)
(55)
11Vp-p (H)
(56)
10Vp-p (H)
(57)
2.4Vp-p (H)
(58)
PAL 72Vp-p (H)
SECAM 80Vp-p (H)
NTSC3.58 86Vp-p (H)
NTSC4.43 90Vp-p (H)
S (Y/C) 86Vp-p (H)
RGB 70Vp-p (H)
COMPONENT 80Vp-p (H)
(59)
PAL 76Vp-p (H)
SECAM 72Vp-p (H)
NTSC3.58 72Vp-p (H)
NTSC4.43 90Vp-p (H)
S (Y/C) 86Vp-p (H)
RGB 70Vp-p (H)
COMPONENT 80Vp-p (H)
(60)
PAL 66Vp-p (H)
SECAM 64Vp-p (H)
NTSC3.58 80Vp-p (H)
NTSC4.43 90Vp-p (H)
S (Y/C) 80Vp-p (H)
RGB 70Vp-p (H)
COMPONENT 80Vp-p (H)

B [SIGNAL PROCESS]

B BOARD (Component Side)

– B BOARD – 〈Component Side〉



IC

IC101	D – 5
IC102	D – 6
IC103	E – 5
IC104	C – 6
IC105	D – 4
IC106	D – 1
IC107	C – 1
IC108	C – 1
IC109	B – 2
IC110	D – 7
IC111	C – 7
IC112	D – 8
IC113	D – 9
IC114	D – 8
IC115	C – 9
IC116	B – 7
IC117	D – 4
IC118	D – 3
IC119	D – 3
IC120	B – 3
IC121	B – 3
IC122	C – 3
IC123	C – 3
IC124	B – 6
IC125	B – 7
IC126	B – 7
IC127	A – 8
IC128	C – 8
IC129	B – 3

TRANSISTOR

Q101	D – 4
Q104	D – 6
Q109	A – 8
Q115	B – 1
Q119	D – 8
Q121	C – 8
Q124	D – 7
Q129	D – 2
Q132	B – 3
Q136	C – 4
Q137	D – 3
Q138	D – 4
Q141	B – 4
Q146	B – 8
Q147	C – 8
Q149	A – 9
Q150	E – 5
Q152	B – 9
Q155	B – 9
Q157	A – 8
Q158	B – 8
Q159	B – 8
Q164	A – 8
Q166	B – 8
Q171	D – 6
Q176	D – 6
Q189	D – 2
Q191	A – 2
Q193	B – 1
Q196	A – 1
Q197	A – 1
Q198	A – 2
Q200	D – 5
Q204	A – 6
Q205	A – 6
Q206	A – 5
Q208	B – 2
Q209	A – 9
Q210	B – 9
Q211	B – 9
Q212	B – 7
Q299	A – 7

DIODE

D103	D – 5
D107	C – 1
D121	C – 2
D122	C – 2
D123	B – 2
D128	C – 1
D130	A – 8
D131	B – 8
D132	B – 8
D137	E – 7
D138	C – 8
D139	B – 8
D146	C – 8
D151	B – 3
D152	B – 3
D153	B – 2
D154	A – 8
D156	B – 8
D157	A – 8
D162	A – 7
D188	B – 6
D191	B – 1
D342	C – 7
D343	E – 1
D344	D – 5
D345	A – 9
D346	B – 9
D347	B – 9
D348	A – 9
D349	B – 9
D350	B – 9
D390	B – 1
D393	D – 2

VARIABLE RESISTOR

RV101	D – 1
RV102	D – 2
RV103	C – 7
RV104	D – 8
RV105	E – 7
RV106	E – 8
RV107	E – 7
RV108	C – 9
RV109	D – 9
RV110	C – 9
RV111	C – 9
RV112	C – 9
RV113	D – 8
RV114	C – 9
RV115	A – 4
RV116	A – 3
RV118	A – 3
RV119	A – 3
RV120	A – 3
RV121	A – 3
RV122	A – 4
RV123	A – 5
RV124	A – 7
RV125	A – 7
RV205	A – 3

B BOARD (Conductor Side)

– B BOARD – 〈Conductor Side〉



IC

IC101	D – 6
IC124	C – 4

TRANSISTOR

Q102	D – 6
Q103	C – 6
Q105	D – 5
Q106	D – 7
Q107	C – 4
Q108	C – 5
Q112	C – 9
Q113	B – 9
Q114	C – 9
Q116	C – 9
Q117	D – 2
Q118	C – 3
Q120	D – 3
Q122	D – 3
Q123	D – 3
Q125	E – 2
Q126	E – 2
Q127	E – 2
Q128	E – 2
Q129	E – 2
Q130	D – 3
Q131	D – 1
Q133	D – 1
Q134	D – 2
Q135	D – 2
Q139	D – 8
Q140	C – 7
Q142	B – 7
Q143	B – 7
Q144	A – 4
Q145	B – 5
Q146	A – 2
Q147	C – 2
Q148	A – 2
Q149	A – 2
Q151	A – 1
Q152	B – 1
Q153	B – 4
Q154	B – 1
Q155	B – 1
Q156	D – 8
Q157	A – 2
Q158	B – 2
Q159	B – 2
Q160	A – 2
Q161	B – 2
Q165	C – 3
Q167	B – 3
Q168	B – 3
Q170	B – 3
Q172	B – 3
Q173	C – 3
Q174	B – 2
Q175	B – 3
Q177	A – 3
Q178	E – 5
Q179	A – 3
Q190	B – 8
Q192	A – 9
Q194	A – 9
Q195	A – 9
Q199	A – 9
Q201	B – 5
Q202	B – 5
Q203	B – 5
Q209	A – 1
Q210	B – 1
Q211	B – 1

DIODE

D104	D – 5
D105	E – 5
D106	C – 9
D108	C – 9
D109	C – 9
D110	D – 9
D111	D – 9
D112	B – 9
D113	B – 9
D117	C – 9
D120	E – 2
D125	A – 6
D126	A – 6
D127	D – 8
D129	E – 1
D133	A – 4
D134	B – 4
D135	B – 4
D136	C – 2
D144	C – 2
D145	C – 2
D147	A – 3
D149	A – 2
D150	B – 2
D155	A – 2
D158	A – 2
D159	B – 1
D160	B – 8
D161	B – 8
D170	D – 8
D185	C – 9
D186	D – 5
D187	D – 9
D285	C – 7
D289	B – 5
D341	B – 9

VARIABLE RESISTOR

RV101	D – 9
RV102	D – 9
RV103	C – 3
RV104	D – 2
RV105	E – 3
RV106	E – 3
RV107	D – 3
RV108	C – 2
RV109	D – 1
RV110	C – 1
RV111	C – 1
RV112	C – 1
RV113	D – 2
RV114	C – 2
RV115	A – 6
RV116	A – 7
RV118	A – 7
RV119	A – 7
RV120	A – 7
RV121	A – 7
RV122	A – 7
RV123	A – 3
RV124	A – 3
RV125	A – 3
RV205	A – 7

Schematic diagram

← B (2/2) board

Note :

- : Pattern from the side which enables seeing.
- : Pattern of the rear side.





6-5. SEMICONDUCTORS

AN5265



LM7805CT
TA7812S
µPC7805H



CXA1214P



MC14538BF



CXA1478S



M51279FP



CX23025



TC4S01F
TC4S11F



LA7830



µPC1377C



LM358DR
MM1111XFF
MM1113XFF
MM1114XFF
MM1148XFF
MM1149XF
NJM2245M
XRA10393F



XRU4011BF
XRU4070BF



Note :

- : Pattern from the side which enables seeing.
- : Pattern of the rear side.

Side〉



Side〉



6-5. SEMICONDUCTORS

AN5265



CXA1214P



(Top view)

CXA1478S

(TOP VIEW)

CX23025



(Top view)

LA7830



LM358DR
MM1111XFF
MM1113XFF
MM1114XFF
MM1148XFF
MM1149XF
NJM2245M
XRA10393F



(TOP VIEW)

LM7805CT
TA7812S
µPC7805H



MC14538BF



M51279FP



TOP VIEW

TC4S01F
TC4S11F



µPC1377C



(Top view)

XRU4011BF
XRU4070BF



(TOP VIEW)

XRU4052BCF
XRU4053BCF
XRU4066BCF



(TOP VIEW)

XRU4584BF



(TOP VIEW)

DTA144EK
DTC124EK
DTC144EK
2SA1037K
2SC2412K

IMH2
IMX1T110



2SA1091-0
2SC1890-A
2SC2551-0
2SC2551R



2SC2334-L
2SD1134
2SD835



2SC2555



2SC2611
2SC2688



2SC2958



2SD874A-R



2SK94

CR02AM-4



DTZ15B
DTZ20B
DTZ24B
DTZ5.6A
DTZ6.2A
DTZ6.2B
DTZ8.2B
RD15SB1



D10SC4M



ERC81-004



GP08DPK23
HSM83-TL
RD5.6EBZ7STN
RGP10GPKG23
RGP15J



MA110



MA151WA



MA151WK



MA157



N13T1



RD3.6ESB1
RD8.2ESB3



SEL3810DLC05
TLG123A

SECTION 7
EXPLODED VIEWS

NOTE :
- Items with on part number and on description are not stocked because they are seldom required for routine service.
- The construction parts of an assembled part are indicated with a collation number in the remark column.
- Items marked "*" are not stocked since they are seldom required for routine service. Some delay should be anticipated when ordering these items.

The components identified by shading and mark ⚠ are critical for safety.
Replace only with part number specified.

7-1. CHASSIS

●: BVTP 3 × 8 7-685-646-79
▲: BVTP 3 × 12 7-685-648-79



REF.NO.	PART NO.	DESCRIPTION	REMARK
1	X-4032-139-1	BEZEL ASSY (PVM-9044QM)	
1	X-4030-164-6	BEZEL ASSY (PVM-9041QM)	
2	4-037-569-01	HANDLE, PROTECTOR	
3	*4-034-845-01	BRACKET (L), BEZEL	
4	*4-034-846-01	BRACKET (U), BEZEL	
5	*4-035-388-01	PLATE, LIGHT INTERCEPTION	
6	*A-1390-276-A	X BOARD, CMOPLET	
7	1-544-252-11	SPEAKER	
8	*A-1135-716-A	B BOARD, COMPLETE	
9	*A-1394-368-A	S BOARD, COMPLETE	
10	⚠1-413-720-24	SWITCHING REGULATOR (SOPS-1021(A))	
11	*A-1346-251-A	D BOARD, COMPLETE	
12	⚠1-576-232-11	FUSE (H.B.C.) (5.0A/250V)	
13	*A-1195-048-A	P BOARD, COMPLETE	
14	⚠1-439-526-12	TRANSFORMER ASSY, FLYBACK	
15	4-034-847-01	HANDLE (BASE)	
16	3-419-372-31	HANDLE	
17	*4-034-867-01	CABINET	
18	*X-4030-273-1	REINFORCEMENT ASSY, HANDLE	
19	4-035-452-01	SCREW (M4X10)	
20	4-034-834-01	SCREW (CLAW) (4X6), CASE	
21	*A-1275-121-A	QA BOARD, COMPLETE	
22	*4-034-864-71	CHASSIS, A	
23	4-035-802-01	SCREW (M2.6X.6)	
24	*4-034-870-02	CABINET, BOTTOM	
25	*4-035-691-01	CLOTH, VIBRATION PROOF	
26	4-389-025-01	SCREW (M4X8)(EXT TOOTH WASHER)	
27	*4-036-058-01	SPONGE	
28	1-941-913-02	CORE ASSY, FERRITE	
29	1-941-866-12	CONNECTOR ASSY	

7-2. PICTURE TUBE

▲: BVTP 3 × 12 7-685-648-79



The components identified by shading and mark ⚠ are critical for safety.
Replace only with part number specified.

REF.NO.	PART NO.	DESCRIPTION	REMARK
51	4-304-511-00	NUT (M5), FLANGE	
52	⚠8-737-154-05	PICTURE TUBE (O9NDX) (PVM-9041QM)	
52	⚠8-737-651-05	PICTURE TUBE (O9FX) (PVM-9044QM)	
53	4-035-332-01	CLOTH, PROTECTION	
54	*4-034-856-01	HOLDER, HV CABLE	
55	4-309-369-00	SPACER, DEFLECTION YOKE	
56	⚠1-451-319-22	DEFLECTION YOKE (Y9FXC)	
57	*A-1331-183-A	CA BOARD, COMPLETE	
58	*4-376-133-11	COVER (MAIN), CV VOL	
59	*4-376-132-11	COVER (REAR LID), CV VOL	
60	⚠1-426-043-12	COIL, DEGAUSSING	
61	4-380-534-01	CAP, DGC	
62	*4-034-850-01	INSULATOR	
63	*A-1371-782-A	HA BOARD, COMPLETE	
64	4-034-849-01	SWITCH (SMALL), PUSH	
65	X-4030-162-2	KNOB ASSY, CONTROL	
66	*A-1241-070-A	FA BOARD, COMPLETE	
67	1-692-050-11	SWITCH, PUSH (AC POWER) (1KEY)	
68	4-034-841-11	BUTTOM, POWER SWICH	
69	*X-4030-166-1	CHASSIS ASSY, BOTTOM	70
70	4-034-840-01	RUBBER, FOOT	
71	*X-4030-163-1	GUIDE ASSY, BATTERY	72,73
72	4-034-861-01	KNOB, BATTERY	
73	4-876-347-01	SPRING, COMPRESSION	
74	3-669-594-00	SPRING, COMPRESSION	
75	4-308-870-00	CLIP, LEAD WIRE	
76	1-452-126-11	MAGNET	
77	1-452-094-00	MAGNET, ROTATABLE DISK; 15MMφ	
78	X-4308-815-0	PERMALLOY ASSY, CONVERGENCE	
79	*4-036-047-02	RUBBER, VIBRATION PROOF	
80	3-839-640-00	CUSHION	
81	3-831-441-11	CUSHION (F)	
82	*4-035-691-01	CLOTH, VIBRATION PROOF	

SECTION 8
ELECTRICAL PARTS LIST

B

NOTE :

The components identified by shading and mark ⚠ are critical for safety.
Replace only with part number specified.

- Items marked "*" are not stocked since they are seldom required for routine service. Some delay should be anticipated when ordering these items.
- All variable and adjustable resistors have characteristic curve B, unless otherwise noted.

RESISTORS
- All resistors are in ohms.
- F : nonflammable

When indicating parts by reference number, please include the board name.

CAPACITORS
- MF : μF, PF : μμF

COILS
- MMH : mH, UH : μH

- The components identified by ⊠ in this manual have been carefully factory-selected for each set in order to satisfy regulations regarding X-ray radiation.
  Should replacement be required, replace only with the value originally used.
- There are some cases the reference number on one board overlaps on the other board. Therefore, when ordering parts by the reference number, please include the board name.

REF.NO.	PART NO.	DESCRIPTION			REMARK
	*A-1135-716-A	B BOARD, COMPLETE **********			
		<FILTER>			
BPF101	1-236-363-11	FILTER, BAND PASS			
BPF102	1-236-364-11	FILTER, BAND PASS			
		<CAPACITOR>			
C101	1-124-589-11	ELECT 47MF	20%	16V	
C102	1-163-031-11	CERAMIC CHIP 0.01MF		50V	
C103	1-126-157-11	ELECT 10MF	20%	16V	
C104	1-163-031-11	CERAMIC CHIP 0.01MF		50V	
C105	1-163-031-11	CERAMIC CHIP 0.01MF		50V	
C106	1-124-477-11	ELECT 47MF	20%	16V	
C107	1-163-031-11	CERAMIC CHIP 0.01MF		50V	
C108	1-124-477-11	ELECT 47MF	20%	16V	
C109	1-124-477-11	ELECT 47MF	20%	16V	
C110	1-124-120-11	ELECT 220MF	20%	16V	
C111	1-163-031-11	CERAMIC CHIP 0.01MF		50V	
C112	1-163-031-11	CERAMIC CHIP 0.01MF		50V	
C113	1-163-031-11	CERAMIC CHIP 0.01MF		50V	
C114	1-124-477-11	ELECT 47MF	20%	16V	
C115	1-163-031-11	CERAMIC CHIP 0.01MF		50V	
C116	1-124-589-11	ELECT 47MF	20%	16V	
C117	1-126-154-11	ELECT 47MF	20%	6.3V	
C118	1-126-154-11	ELECT 47MF	20%	6.3V	
C119	1-163-031-11	CERAMIC CHIP 0.01MF		50V	
C120	1-126-154-11	ELECT 47MF	20%	6.3V	
C121	1-126-154-11	ELECT 47MF	20%	6.3V	
C122	1-124-477-11	ELECT 47MF	20%	16V	
C123	1-163-031-11	CERAMIC CHIP 0.01MF		50V	
C124	1-163-031-11	CERAMIC CHIP 0.01MF		50V	
C125	1-126-154-11	ELECT 47MF	20%	6.3V	
C126	1-163-031-11	CERAMIC CHIP 0.01MF		50V	
C127	1-126-154-11	ELECT 47MF	20%	6.3V	
C128	1-126-154-11	ELECT 47MF	20%	6.3V	
C129	1-163-031-11	CERAMIC CHIP 0.01MF		50V	
C130	1-163-031-11	CERAMIC CHIP 0.01MF		50V	
C131	1-163-031-11	CERAMIC CHIP 0.01MF		50V	
C132	1-124-589-11	ELECT 47MF	20%	16V	
C133	1-124-589-11	ELECT 47MF	20%	16V	
C134	1-163-275-11	CERAMIC CHIP 0.001MF	5%	50V	
C135	1-163-113-00	CERAMIC CHIP 68PF	5%	50V	
C137	1-163-249-11	CERAMIC CHIP 82PF	5%	50V	
C138	1-124-589-11	ELECT 47MF	20%	16V	
C139	1-163-031-11	CERAMIC CHIP 0.01MF		50V	
C140	1-163-205-00	CERAMIC CHIP 0.001MF	5%	50V	
C141	1-163-141-00	CERAMIC CHIP 0.001MF	5%	50V	
C142	1-163-031-11	CERAMIC CHIP 0.01MF		50V	
C143	1-163-121-00	CERAMIC CHIP 150PF	5%	50V	
C144	1-163-101-00	CERAMIC CHIP 22PF	5%	50V	
C145	1-163-131-00	CERAMIC CHIP 390PF	5%	50V	
C146	1-126-157-11	ELECT 10MF	20%	16V	
C147	1-164-232-11	CERAMIC CHIP 0.01MF	10%	50V	
C148	1-126-160-11	ELECT 1MF	20%	50V	
C149	1-163-022-00	CERAMIC CHIP 0.012MF	10%	50V	
C150	1-124-589-11	ELECT 47MF	20%	16V	
C151	1-163-131-00	CERAMIC CHIP 390PF	5%	50V	
C152	1-163-101-00	CERAMIC CHIP 22PF	5%	50V	
C153	1-163-125-00	CERAMIC CHIP 220PF	5%	50V	
C154	1-163-031-11	CERAMIC CHIP 0.01MF		50V	
C155	1-163-133-00	CERAMIC CHIP 470PF	5%	50V	
C156	1-164-299-11	CERAMIC CHIP 0.22MF	10%	25V	
C157	1-163-229-11	CERAMIC CHIP 12PF	5%	50V	
C158	1-124-477-11	ELECT 47MF	20%	16V	
C159	1-163-229-11	CERAMIC CHIP 12PF	5%	50V	
C160	1-163-229-11	CERAMIC CHIP 12PF	5%	50V	
C161	1-124-902-00	ELECT 0.47MF	20%	50V	
C162	1-124-903-11	ELECT 1MF	20%	50V	
C163	1-163-809-11	CERAMIC CHIP 0.047MF	10%	25V	
C164	1-163-809-11	CERAMIC CHIP 0.047MF	10%	25V	
C165	1-163-009-11	CERAMIC CHIP 0.001MF	10%	50V	
C166	1-163-031-11	CERAMIC CHIP 0.01MF		50V	
C167	1-124-477-11	ELECT 47MF	20%	16V	
C168	1-163-031-11	CERAMIC CHIP 0.01MF		50V	
C169	1-163-243-11	CERAMIC CHIP 47PF	5%	50V	
C170	1-163-129-00	CERAMIC CHIP 330PF	5%	50V	
C171	1-163-243-11	CERAMIC CHIP 47PF	5%	50V	
C172	1-163-129-00	CERAMIC CHIP 330PF	5%	50V	
C173	1-124-589-11	ELECT 47MF	20%	16V	
C174	1-124-477-11	ELECT 47MF	20%	16V	
C175	1-108-792-11	MYLAR 0.001MF	5%	50V	
C176	1-163-031-11	CERAMIC CHIP 0.01MF		50V	
C177	1-163-031-11	CERAMIC CHIP 0.01MF		50V	
C178	1-163-031-11	CERAMIC CHIP 0.01MF		50V	
C179	1-126-160-11	ELECT 1MF	20%	50V	
C180	1-163-031-11	CERAMIC CHIP 0.01MF		50V	
C181	1-126-154-11	ELECT 47MF	20%	6.3V	
C182	1-126-163-11	ELECT 4.7MF	20%	16V	
C183	1-164-232-11	CERAMIC CHIP 0.01MF	10%	50V	
C184	1-163-031-11	CERAMIC CHIP 0.01MF		50V	
C185	1-163-031-11	CERAMIC CHIP 0.01MF		50V	
C186	1-163-099-00	CERAMIC CHIP 18PF	5%	50V	
C187	1-163-031-11	CERAMIC CHIP 0.01MF		50V	
C188	1-163-031-11	CERAMIC CHIP 0.01MF		50V	
C189	1-163-035-00	CERAMIC CHIP 0.047MF		50V	
C190	1-163-121-00	CERAMIC CHIP 150PF	5%	50V	
C191	1-163-031-11	CERAMIC CHIP 0.01MF		50V	
C192	1-163-031-11	CERAMIC CHIP 0.01MF		50V	
C193	1-124-589-11	ELECT 47MF	20%	16V	

B

REF.NO.	PART NO.	DESCRIPTION			REMARK
C194	1-124-589-11	ELECT	47MF	20%	16V
C195	1-124-589-11	ELECT	47MF	20%	16V
C196	1-124-589-11	ELECT	47MF	20%	16V
C197	1-124-589-11	ELECT	47MF	20%	16V
C198	1-124-589-11	ELECT	47MF	20%	16V
C199	1-124-589-11	ELECT	47MF	20%	16V
C202	1-124-589-11	ELECT	47MF	20%	16V
C203	1-124-589-11	ELECT	47MF	20%	16V
C204	1-124-589-11	ELECT	47MF	20%	16V
C205	1-163-101-00	CERAMIC CHIP	22PF	5%	50V
C206	1-164-298-11	CERAMIC CHIP	0.15MF	10%	25V
C207	1-164-298-11	CERAMIC CHIP	0.15MF	10%	25V
C208	1-163-101-00	CERAMIC CHIP	22PF	5%	50V
C209	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C210	1-124-589-11	ELECT	47MF	20%	16V
C211	1-124-589-11	ELECT	47MF	20%	16V
C212	1-124-589-11	ELECT	47MF	20%	16V
C213	1-124-589-11	ELECT	47MF	20%	16V
C214	1-126-157-11	ELECT	10MF	20%	16V
C215	1-126-157-11	ELECT	10MF	20%	16V
C216	1-126-157-11	ELECT	10MF	20%	16V
C217	1-163-031-11	CERAMIC CHIP	0.01MF		50V
C218	1-164-298-11	CERAMIC CHIP	0.15MF	10%	25V
C219	1-163-009-11	CERAMIC CHIP	0.001MF	10%	50V
C220	1-163-031-11	CERAMIC CHIP	0.01MF		50V
C221	1-124-903-11	ELECT	1MF	20%	50V
C222	1-163-093-00	CERAMIC CHIP	10PF	5%	50V
C223	1-163-031-11	CERAMIC CHIP	0.01MF		50V
C225	1-124-477-11	ELECT	47MF	20%	16V
C226	1-163-031-11	CERAMIC CHIP	0.01MF		50V
C227	1-163-038-00	CERAMIC CHIP	0.1MF		25V
C228	1-163-986-00	CERAMIC CHIP	0.027MF	10%	25V
C229	1-163-031-11	CERAMIC CHIP	0.01MF		50V
C230	1-163-038-00	CERAMIC CHIP	0.1MF		25V
C231	1-163-986-00	CERAMIC CHIP	0.027MF	10%	25V
C232	1-163-031-11	CERAMIC CHIP	0.01MF		50V
C233	1-163-031-11	CERAMIC CHIP	0.01MF		50V
C234	1-163-038-00	CERAMIC CHIP	0.1MF		25V
C235	1-163-986-00	CERAMIC CHIP	0.027MF	10%	25V
C236	1-163-031-11	CERAMIC CHIP	0.01MF		50V
C237	1-163-031-11	CERAMIC CHIP	0.01MF		50V
C238	1-164-299-11	CERAMIC CHIP	0.22MF	10%	25V
C239	1-163-809-11	CERAMIC CHIP	0.047MF	10%	25V
C240	1-163-809-11	CERAMIC CHIP	0.047MF	10%	25V
C241	1-163-809-11	CERAMIC CHIP	0.047MF	10%	25V
C242	1-163-113-00	CERAMIC CHIP	68PF	5%	50V
C243	1-163-031-11	CERAMIC CHIP	0.01MF		50V
C244	1-163-103-00	CERAMIC CHIP	27PF	5%	50V
C245	1-163-105-00	CERAMIC CHIP	33PF	5%	50V
C246	1-163-809-11	CERAMIC CHIP	0.047MF	10%	25V
C247	1-163-809-11	CERAMIC CHIP	0.047MF	10%	25V
C248	1-163-809-11	CERAMIC CHIP	0.047MF	10%	25V
C249	1-126-101-11	ELECT	100MF	20%	16V
C250	1-163-017-00	CERAMIC CHIP	0.0047MF	10%	50V
C251	1-110-364-11	MYLAR	0.1MF	10%	200V
C252	1-123-935-00	ELECT	33MF	20%	160V
C253	1-124-477-11	ELECT	47MF	20%	16V
C254	1-163-031-11	CERAMIC CHIP	0.01MF		50V
C255	1-124-477-11	ELECT	47MF	20%	16V
C256	1-163-129-00	CERAMIC CHIP	330PF	5%	50V
C257	1-163-129-00	CERAMIC CHIP	330PF	5%	50V
C258	1-163-129-00	CERAMIC CHIP	330PF	5%	50V
C259	1-163-031-11	CERAMIC CHIP	0.01MF		50V
C260	1-124-465-00	ELECT	0.47MF	20%	50V

REF.NO.	PART NO.	DESCRIPTION			REMARK
C261	1-137-193-11	FILM	0.39MF	5%	50V
C262	1-124-465-00	ELECT	0.47MF	20%	50V
C264	1-163-123-00	CERAMIC CHIP	180PF	5%	50V
C265	1-163-129-00	CERAMIC CHIP	330PF	5%	50V
C266	1-126-320-11	ELECT	10MF	20%	16V
C267	1-126-320-11	ELECT	10MF	20%	16V
C268	1-124-477-11	ELECT	47MF	20%	16V
C269	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C270	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C271	1-163-809-11	CERAMIC CHIP	0.047MF	10%	25V
C272	1-163-129-00	CERAMIC CHIP	330PF	5%	50V
C273	1-163-129-00	CERAMIC CHIP	330PF	5%	50V
C274	1-124-477-11	ELECT	47MF	20%	16V
C275	1-163-119-00	CERAMIC CHIP	120PF	5%	50V
C277	1-163-097-00	CERAMIC CHIP	15PF	5%	50V
C278	1-163-809-11	CERAMIC CHIP	0.047MF	10%	25V
C279	1-126-157-11	ELECT	10MF	20%	16V
C280	1-163-117-00	CERAMIC CHIP	100PF	5%	50V
C281	1-163-031-11	CERAMIC CHIP	0.01MF		50V
C282	1-163-031-11	CERAMIC CHIP	0.01MF		50V
C283	1-163-031-11	CERAMIC CHIP	0.01MF		50V
C299	1-163-031-11	CERAMIC CHIP	0.01MF		50V
C300	1-126-157-11	ELECT	10MF	20%	16V
C301	1-163-809-11	CERAMIC CHIP	0.047MF	10%	25V
C302	1-124-589-11	ELECT	47MF	20%	16V
C303	1-126-157-11	ELECT	10MF	20%	16V
C304	1-163-125-00	CERAMIC CHIP	220PF	5%	50V
C305	1-124-257-00	ELECT	2.2MF	20%	50V
C306	1-163-115-00	CERAMIC CHIP	82PF	5%	50V
C307	1-163-145-00	CERAMIC CHIP	0.0015MF	5%	50V
C308	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C309	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C310	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C312	1-163-031-11	CERAMIC CHIP	0.01MF		50V
C313	1-163-115-00	CERAMIC CHIP	82PF	5%	50V
C314	1-126-157-11	ELECT	10MF	20%	16V
C315	1-164-299-11	CERAMIC CHIP	0.22MF	10%	25V
C316	1-126-157-11	ELECT	10MF	20%	16V
C317	1-163-031-11	CERAMIC CHIP	0.01MF		50V
C318	1-163-095-00	CERAMIC CHIP	12PF	5%	50V
C319	1-163-095-00	CERAMIC CHIP	12PF	5%	50V
C320	1-163-095-00	CERAMIC CHIP	12PF	5%	50V
C321	1-163-121-00	CERAMIC CHIP	150PF	5%	50V
C322	1-163-121-00	CERAMIC CHIP	150PF	5%	50V
C324	1-163-119-00	CERAMIC CHIP	120PF	5%	50V
C340	1-163-205-00	CERAMIC CHIP	0.001MF	5%	50V
C344	1-163-092-00	CERAMIC CHIP	9PF	0.25PF	50V
C345	1-163-109-00	CERAMIC CHIP	47PF	5%	50V
C346	1-163-109-00	CERAMIC CHIP	47PF	5%	50V
C347	1-163-109-00	CERAMIC CHIP	47PF	5%	50V
C1293	1-163-119-00	CERAMIC CHIP	120PF	5%	50V
C1294	1-163-119-00	CERAMIC CHIP	120PF	5%	50V
C1295	1-163-119-00	CERAMIC CHIP	120PF	5%	50V
C1296	1-163-115-00	CERAMIC CHIP	82PF	5%	50V
C1297	1-163-103-00	CERAMIC CHIP	27PF	5%	50V
C1298	1-163-113-00	CERAMIC CHIP	68PF	5%	50V
C1299	1-163-093-00	CERAMIC CHIP	10PF	5%	50V
C1300	1-126-160-11	ELECT	1MF	20%	50V
C1301	1-126-160-11	ELECT	1MF	20%	50V
C1302	1-126-160-11	ELECT	1MF	20%	50V
C1303	1-126-160-11	ELECT	1MF	20%	50V

<FILTER>

REF.NO.	PART NO.	DESCRIPTION	REMARK
CFM101	1-464-880-11	FILTER BLOCK, COM (CFB-2)	
		<CONNECTOR>	
CN101	1-506-480-11	PIN, CONNECTOR 15P	
CN102	*1-564-506-11	PLUG, CONNECTOR 3P	
CN103	*1-565-503-11	CONNECTOR, BOARD TO BOARD 12P	
CN104	*1-564-011-11	PIN, CONNECTOR 12P	
CN105	*1-564-509-11	PLUG, CONNECTOR 6P	
CN106	1-506-473-11	PIN, CONNECTOR 8P	
CN107	1-506-478-11	PIN, CONNECTOR 13P	
CN108	*1-564-506-11	PLUG, CONNECTOR 3P	
		<TRAP MODULE>	
CTR101	1-236-366-11	MODULE, TRAP	
CTR102	1-236-365-11	MODULE, TRAP	
		<TRIMMER>	
CV101	1-141-418-11	CAP, ADJ	
CV102	1-141-418-11	CAP, ADJ	
		<DIODE>	
D103	8-719-404-46	DIODE MA110	
D104	8-719-404-46	DIODE MA110	
D105	8-719-404-46	DIODE MA110	
D106	8-719-404-46	DIODE MA110	
D107	8-719-404-46	DIODE MA110	
D108	8-719-404-46	DIODE MA110	
D109	8-719-404-46	DIODE MA110	
D110	8-719-404-46	DIODE MA110	
D111	8-719-404-46	DIODE MA110	
D112	8-719-404-46	DIODE MA110	
D113	8-719-404-46	DIODE MA110	
D117	8-719-404-46	DIODE MA110	
D120	8-719-404-46	DIODE MA110	
D121	8-719-404-46	DIODE MA110	
D122	8-719-404-46	DIODE MA110	
D123	8-719-404-46	DIODE MA110	
D125	8-719-404-46	DIODE MA110	
D126	8-719-404-46	DIODE MA110	
D127	8-719-404-46	DIODE MA110	
D128	8-719-801-78	DIODE 1SS184	
D129	8-719-404-46	DIODE MA110	
D130	8-719-800-76	DIODE 1SS226	
D131	8-719-800-76	DIODE 1SS226	
D132	8-719-800-76	DIODE 1SS226	
D133	8-719-404-46	DIODE MA110	
D134	8-719-404-46	DIODE MA110	
D135	8-719-404-46	DIODE MA110	
D136	8-719-404-46	DIODE MA110	
D137	8-719-404-46	DIODE MA110	
D138	8-719-404-46	DIODE MA110	
D139	8-719-404-46	DIODE MA110	
D144	8-719-404-46	DIODE MA110	
D145	8-719-404-46	DIODE MA110	
D146	8-719-404-46	DIODE MA110	
D147	8-719-404-46	DIODE MA110	
D148	8-719-404-46	DIODE MA110	
D149	8-719-404-46	DIODE MA110	
D150	8-719-404-46	DIODE MA110	
D151	8-719-404-46	DIODE MA110	
D152	8-719-404-46	DIODE MA110	
D153	8-719-977-20	DIODE DTZ8.2B	
D154	8-719-404-46	DIODE MA110	
D155	8-719-404-46	DIODE MA110	
D156	8-719-404-46	DIODE MA110	
D157	8-719-901-83	DIODE 1SS83	
D158	8-719-901-83	DIODE 1SS83	
D159	8-719-901-83	DIODE 1SS83	
D160	8-719-404-46	DIODE MA110	
D161	8-719-404-46	DIODE MA110	
D162	8-719-404-46	DIODE MA110	
D170	8-719-404-46	DIODE MA110	
D185	8-719-104-34	DIODE 1S2836	
D186	8-719-801-78	DIODE 1SS184	
D187	8-719-800-76	DIODE 1SS226	
D188	8-719-800-76	DIODE 1SS226	
D191	8-719-104-34	DIODE 1S2836	
D285	8-719-404-46	DIODE MA110	
D289	8-719-404-46	DIODE MA110	
D341	8-719-404-46	DIODE MA110	
D342	8-719-104-34	DIODE 1S2836	
D343	8-719-800-76	DIODE 1SS226	
D344	8-719-105-99	DIODE RD6.2M-B1	
D345	8-719-901-83	DIODE 1SS83	
D346	8-719-901-83	DIODE 1SS83	
D347	8-719-901-83	DIODE 1SS83	
D348	8-719-800-76	DIODE 1SS226	
D349	8-719-800-76	DIODE 1SS226	
D350	8-719-800-76	DIODE 1SS226	
D390	8-719-800-76	DIODE 1SS226	
D393	8-719-404-46	DIODE MA110	
		<DELAY LINE>	
DL101	1-415-632-11	DELAY LINE, Y	
DL102	1-415-633-11	DELAY LINE, Y	
		<IC>	
IC101	8-759-084-76	IC MM1111XF	
IC102	8-759-287-89	IC MM1113XFF	
IC103	8-759-287-89	IC MM1113XFF	
IC104	8-759-287-89	IC MM1113XFF	
IC105	8-759-084-76	IC MM1111XF	
IC106	8-759-009-51	IC MC14538BF	
IC107	8-759-509-57	IC XRU4584BF	
IC108	8-759-509-17	IC XRU4053BCF	
IC109	8-759-509-37	IC XRU4070BF	
IC110	8-759-509-17	IC XRU4053BCF	
IC111	8-759-509-17	IC XRU4053BCF	
IC112	8-759-924-12	IC LM7805CT	
IC113	8-759-631-08	IC M51279FP	
IC114	8-759-932-64	IC BU4052BCF	
IC115	8-759-932-64	IC BU4052BCF	
IC116	8-759-509-05	IC XRU4066BCF	
IC117	8-759-711-32	IC NJM2245M	
IC118	8-759-711-32	IC NJM2245M	
IC119	8-759-711-32	IC NJM2245M	
IC120	8-759-509-05	IC XRU4066BCF	
IC121	8-759-509-17	IC XRU4053BCF	
IC122	8-759-998-98	IC LM358D	
IC123	8-759-998-98	IC LM358D	
IC124	8-752-052-62	IC CXA1478S	

B

REF.NO.	PART NO.	DESCRIPTION	REMARK
IC125	8-759-509-05	IC XRU4066BCF	
IC126	8-759-509-17	IC XRU4053BCF	
IC127	8-759-998-98	IC LM358D	
IC128	8-759-998-98	IC LM358D	
IC129	8-759-998-98	IC LM358D	
		<COIL>	
L101	1-410-470-11	INDUCTOR 10UH	
L102	1-410-090-41	INDUCTOR 18MMH	
L103	1-412-002-31	INDUCTOR CHIP 4.7UH	
L104	1-412-002-31	INDUCTOR CHIP 4.7UH	
L105	1-412-002-31	INDUCTOR CHIP 4.7UH	
L106	1-410-470-11	INDUCTOR 10UH	
L107	1-410-470-11	INDUCTOR 10UH	
L112	1-408-419-00	INDUCTOR 68UH	
L113	1-410-947-31	INDUCTOR CHIP 33UH	
L114	1-410-947-31	INDUCTOR CHIP 33UH	
L115	1-410-947-31	INDUCTOR CHIP 33UH	
L116	1-412-011-31	INDUCTOR CHIP 27UH	
L117	1-412-011-31	INDUCTOR CHIP 27UH	
L118	1-412-011-31	INDUCTOR CHIP 27UH	
L250	1-410-997-31	INDUCTOR CHIP 2.2UH	
L251	1-410-999-11	INDUCTOR CHIP 3.3UH	
L252	1-410-478-11	INDUCTOR 47UH	
L300	1-410-482-31	INDUCTOR 100UH	
		<TRANSISTOR>	
Q101	8-729-120-28	TRANSISTOR 2SC1623-L5L6	
Q102	8-729-120-28	TRANSISTOR 2SC1623-L5L6	
Q103	8-729-120-28	TRANSISTOR 2SC1623-L5L6	
Q104	8-729-120-28	TRANSISTOR 2SC1623-L5L6	
Q105	8-729-120-28	TRANSISTOR 2SC1623-L5L6	
Q106	8-729-120-28	TRANSISTOR 2SC1623-L5L6	
Q107	8-729-120-28	TRANSISTOR 2SC1623-L5L6	
Q108	8-729-216-22	TRANSISTOR 2SA1162-G	
Q109	8-729-901-01	TRANSISTOR DTC144EK	
Q112	8-729-120-28	TRANSISTOR 2SC1623-L5L6	
Q113	8-729-120-28	TRANSISTOR 2SC1623-L5L6	
Q114	8-729-216-22	TRANSISTOR 2SA1162-G	
Q115	8-729-120-28	TRANSISTOR 2SC1623-L5L6	
Q116	8-729-120-28	TRANSISTOR 2SC1623-L5L6	
Q117	8-729-216-22	TRANSISTOR 2SA1162-G	
Q118	8-729-120-28	TRANSISTOR 2SC1623-L5L6	
Q119	8-729-216-22	TRANSISTOR 2SA1162-G	
Q120	8-729-216-22	TRANSISTOR 2SA1162-G	
Q121	8-729-120-28	TRANSISTOR 2SC1623-L5L6	
Q122	8-729-216-22	TRANSISTOR 2SA1162-G	
Q123	8-729-120-28	TRANSISTOR 2SC1623-L5L6	
Q124	8-729-216-22	TRANSISTOR 2SA1162-G	
Q125	8-729-120-28	TRANSISTOR 2SC1623-L5L6	
Q126	8-729-901-01	TRANSISTOR DTC144EK	
Q127	8-729-216-22	TRANSISTOR 2SA1162-G	
Q128	8-729-216-22	TRANSISTOR 2SA1162-G	
Q129	8-729-901-01	TRANSISTOR DTC144EK	
Q130	8-729-216-22	TRANSISTOR 2SA1162-G	
Q131	8-729-120-28	TRANSISTOR 2SC1623-L5L6	
Q132	8-729-216-22	TRANSISTOR 2SA1162-G	
Q133	8-729-120-28	TRANSISTOR 2SC1623-L5L6	
Q134	8-729-901-01	TRANSISTOR DTC144EK	
Q135	8-729-120-28	TRANSISTOR 2SC1623-L5L6	
Q136	8-729-907-26	TRANSISTOR IMX1	
Q137	8-729-907-26	TRANSISTOR IMX1	
Q138	8-729-907-26	TRANSISTOR IMX1	
Q139	8-729-216-22	TRANSISTOR 2SA1162-G	
Q140	8-729-120-28	TRANSISTOR 2SC1623-L5L6	
Q141	8-729-120-28	TRANSISTOR 2SC1623-L5L6	
Q142	8-729-120-28	TRANSISTOR 2SC1623-L5L6	
Q143	8-729-120-28	TRANSISTOR 2SC1623-L5L6	
Q144	8-729-120-28	TRANSISTOR 2SC1623-L5L6	
Q145	8-729-120-28	TRANSISTOR 2SC1623-L5L6	
Q146	8-729-255-12	TRANSISTOR 2SC2551-O	
Q147	8-729-255-12	TRANSISTOR 2SC2551-O	
Q148	8-729-216-22	TRANSISTOR 2SA1162-G	
Q149	8-729-200-17	TRANSISTOR 2SA1091-O	
Q150	8-729-120-28	TRANSISTOR 2SC1623-L5L6	
Q151	8-729-216-22	TRANSISTOR 2SA1162-G	
Q152	8-729-200-17	TRANSISTOR 2SA1091-O	
Q153	8-729-120-28	TRANSISTOR 2SC1623-L5L6	
Q154	8-729-216-22	TRANSISTOR 2SA1162-G	
Q155	8-729-200-17	TRANSISTOR 2SA1091-O	
Q157	8-729-326-11	TRANSISTOR 2SC2611	
Q158	8-729-326-11	TRANSISTOR 2SC2611	
Q159	8-729-326-11	TRANSISTOR 2SC2611	
Q160	8-729-120-28	TRANSISTOR 2SC1623-L5L6	
Q161	8-729-216-22	TRANSISTOR 2SA1162-G	
Q164	8-729-901-01	TRANSISTOR DTC144EK	
Q165	8-729-216-22	TRANSISTOR 2SA1162-G	
Q166	8-729-216-22	TRANSISTOR 2SA1162-G	
Q167	8-729-216-22	TRANSISTOR 2SA1162-G	
Q168	8-729-216-22	TRANSISTOR 2SA1162-G	
Q170	8-729-120-28	TRANSISTOR 2SC1623-L5L6	
Q171	8-729-120-28	TRANSISTOR 2SC1623-L5L6	
Q172	8-729-120-28	TRANSISTOR 2SC1623-L5L6	
Q173	8-729-216-22	TRANSISTOR 2SA1162-G	
Q174	8-729-216-22	TRANSISTOR 2SA1162-G	
Q175	8-729-216-22	TRANSISTOR 2SA1162-G	
Q176	8-729-216-22	TRANSISTOR 2SA1162-G	
Q177	8-729-120-28	TRANSISTOR 2SC1623-L5L6	
Q178	8-729-120-28	TRANSISTOR 2SC1623-L5L6	
Q179	8-729-901-01	TRANSISTOR DTC144EK	
Q189	8-729-907-26	TRANSISTOR IMX1	
Q190	8-729-216-22	TRANSISTOR 2SA1162-G	
Q191	8-729-120-28	TRANSISTOR 2SC1623-L5L6	
Q192	8-729-120-28	TRANSISTOR 2SC1623-L5L6	
Q193	8-729-120-28	TRANSISTOR 2SC1623-L5L6	
Q194	8-729-120-28	TRANSISTOR 2SC1623-L5L6	
Q195	8-729-216-22	TRANSISTOR 2SA1162-G	
Q196	8-729-120-28	TRANSISTOR 2SC1623-L5L6	
Q197	8-729-216-22	TRANSISTOR 2SA1162-G	
Q198	8-729-216-22	TRANSISTOR 2SA1162-G	
Q199	8-729-216-22	TRANSISTOR 2SA1162-G	
Q200	8-729-901-06	TRANSISTOR DTA144EK	
Q201	8-729-216-22	TRANSISTOR 2SA1162-G	
Q202	8-729-216-22	TRANSISTOR 2SA1162-G	
Q203	8-729-216-22	TRANSISTOR 2SA1162-G	
Q204	8-729-216-22	TRANSISTOR 2SA1162-G	
Q205	8-729-216-22	TRANSISTOR 2SA1162-G	
Q206	8-729-216-22	TRANSISTOR 2SA1162-G	
Q208	8-729-216-22	TRANSISTOR 2SA1162-G	
Q209	8-729-255-12	TRANSISTOR 2SC2551-O	
Q210	8-729-255-12	TRANSISTOR 2SC2551-O	
Q211	8-729-255-12	TRANSISTOR 2SC2551-O	
Q212	8-729-141-53	TRANSISTOR 2SK94-X2X3X4	
Q299	8-729-120-28	TRANSISTOR 2SC1623-L5L6	

<RESISTOR>

REF.NO.	PART NO.	DESCRIPTION				REMARK
JR105	1-216-295-91	METAL GLAZE	0	5%	1/10W	
JR110	1-216-295-91	METAL GLAZE	0	5%	1/10W	
JR133	1-216-295-91	METAL GLAZE	0	5%	1/10W	
JR138	1-216-295-91	METAL GLAZE	0	5%	1/10W	
JR178	1-216-295-91	METAL GLAZE	0	5%	1/10W	
R101	1-216-089-91	METAL GLAZE	47K	5%	1/10W	
R102	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R103	1-216-091-00	METAL GLAZE	56K	5%	1/10W	
R104	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R105	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R106	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R107	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R108	1-216-113-00	METAL GLAZE	470K	5%	1/10W	
R109	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R110	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R111	1-216-063-00	METAL GLAZE	3.9K	5%	1/10W	
R112	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R113	1-249-401-11	CARBON	47	5%	1/4W	F
R114	1-216-045-00	METAL GLAZE	680	5%	1/10W	
R115	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R117	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R118	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R119	1-216-647-11	METAL CHIP	680	0.50%	1/10W	
R120	1-216-647-11	METAL CHIP	680	0.50%	1/10W	
R121	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R122	1-216-083-00	METAL GLAZE	27K	5%	1/10W	
R123	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R124	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R125	1-216-083-00	METAL GLAZE	27K	5%	1/10W	
R126	1-216-093-00	METAL GLAZE	68K	5%	1/10W	
R127	1-216-037-00	METAL GLAZE	330	5%	1/10W	
R128	1-216-083-00	METAL GLAZE	27K	5%	1/10W	
R129	1-216-067-00	METAL GLAZE	5.6K	5%	1/10W	
R130	1-216-097-00	METAL GLAZE	100K	5%	1/10W	
R131	1-216-089-91	METAL GLAZE	47K	5%	1/10W	
R132	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W	
R133	1-216-079-00	METAL GLAZE	18K	5%	1/10W	
R134	1-216-645-11	METAL CHIP	560	0.50%	1/10W	
R135	1-216-645-11	METAL CHIP	560	0.50%	1/10W	
R136	1-216-091-00	METAL GLAZE	56K	5%	1/10W	
R137	1-216-045-00	METAL GLAZE	680	5%	1/10W	
R138	1-216-657-11	METAL CHIP	1.8K	0.50%	1/10W	
R139	1-216-079-00	METAL GLAZE	18K	5%	1/10W	
R140	1-216-653-11	METAL CHIP	1.2K	0.50%	1/10W	
R141	1-216-063-00	METAL GLAZE	3.9K	5%	1/10W	
R142	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R143	1-216-085-00	METAL GLAZE	33K	5%	1/10W	
R145	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R146	1-216-037-00	METAL GLAZE	330	5%	1/10W	
R147	1-216-089-91	METAL GLAZE	47K	5%	1/10W	
R148	1-216-671-11	METAL CHIP	6.8K	0.50%	1/10W	
R155	1-216-655-11	METAL CHIP	1.5K	0.50%	1/10W	
R157	1-216-679-11	METAL CHIP	15K	0.50%	1/10W	
R158	1-216-677-11	METAL CHIP	12K	0.50%	1/10W	
R160	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R161	1-216-089-91	METAL GLAZE	47K	5%	1/10W	
R163	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R164	1-216-677-11	METAL CHIP	12K	0.50%	1/10W	
R165	1-216-107-00	METAL GLAZE	270K	5%	1/10W	
R166	1-208-812-11	METAL CHIP	18K	0.50%	1/10W	
R167	1-216-635-11	METAL CHIP	220	0.50%	1/10W	
R168	1-216-103-91	METAL GLAZE	180K	5%	1/10W	
R169	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R170	1-216-089-91	METAL GLAZE	47K	5%	1/10W	
R171	1-216-053-00	METAL GLAZE	1.5K	5%	1/10W	
R172	1-216-043-00	METAL GLAZE	560	5%	1/10W	
R173	1-216-093-00	METAL GLAZE	68K	5%	1/10W	
R174	1-216-069-00	METAL GLAZE	6.8K	5%	1/10W	
R175	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W	
R176	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R177	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R178	1-216-089-91	METAL GLAZE	47K	5%	1/10W	
R179	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R180	1-216-679-11	METAL CHIP	15K	0.50%	1/10W	
R181	1-216-071-00	METAL GLAZE	8.2K	5%	1/10W	
R182	1-216-683-11	METAL CHIP	22K	0.50%	1/10W	
R183	1-216-691-11	METAL CHIP	47K	0.50%	1/10W	
R184	1-216-699-11	METAL CHIP	100K	0.50%	1/10W	
R185	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R186	1-216-113-00	METAL GLAZE	470K	5%	1/10W	
R187	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R188	1-216-113-00	METAL GLAZE	470K	5%	1/10W	
R189	1-216-103-91	METAL GLAZE	180K	5%	1/10W	
R190	1-216-107-00	METAL GLAZE	270K	5%	1/10W	
R191	1-216-097-00	METAL GLAZE	100K	5%	1/10W	
R192	1-216-103-91	METAL GLAZE	180K	5%	1/10W	
R193	1-216-105-00	METAL GLAZE	220K	5%	1/10W	
R194	1-216-089-91	METAL GLAZE	47K	5%	1/10W	
R195	1-216-113-00	METAL GLAZE	470K	5%	1/10W	
R196	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R197	1-216-671-11	METAL CHIP	6.8K	0.50%	1/10W	
R198	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R199	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R200	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R201	1-216-043-00	METAL GLAZE	560	5%	1/10W	
R202	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R203	1-216-045-00	METAL GLAZE	680	5%	1/10W	
R204	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R205	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R206	1-216-043-00	METAL GLAZE	560	5%	1/10W	
R207	1-216-045-00	METAL GLAZE	680	5%	1/10W	
R208	1-216-671-11	METAL CHIP	6.8K	0.50%	1/10W	
R209	1-216-043-00	METAL GLAZE	560	5%	1/10W	
R210	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R211	1-216-099-00	METAL GLAZE	120K	5%	1/10W	
R212	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R213	1-216-043-00	METAL GLAZE	560	5%	1/10W	
R214	1-216-043-00	METAL GLAZE	560	5%	1/10W	
R215	1-216-127-11	METAL GLAZE	1.8M	5%	1/10W	
R216	1-216-043-00	METAL GLAZE	560	5%	1/10W	
R217	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R218	1-216-295-91	METAL GLAZE	0	5%	1/10W	
R219	1-216-043-00	METAL GLAZE	560	5%	1/10W	
R220	1-216-043-00	METAL GLAZE	560	5%	1/10W	
R221	1-216-035-00	METAL GLAZE	270	5%	1/10W	
R222	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R223	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R224	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R225	1-216-095-00	METAL GLAZE	82K	5%	1/10W	
R226	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R227	1-216-035-00	METAL GLAZE	270	5%	1/10W	
R228	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R229	1-216-113-00	METAL GLAZE	470K	5%	1/10W	
R230	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R231	1-216-113-00	METAL GLAZE	470K	5%	1/10W	

B

REF.NO.	PART NO.	DESCRIPTION				REMARK
R232	1-216-105-00	METAL GLAZE	220K	5%	1/10W	
R233	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R234	1-216-041-00	METAL GLAZE	470	5%	1/10W	
R235	1-216-041-00	METAL GLAZE	470	5%	1/10W	
R236	1-216-077-00	METAL GLAZE	15K	5%	1/10W	
R237	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R238	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R239	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R240	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R241	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R242	1-216-051-00	METAL GLAZE	1.2K	5%	1/10W	
R243	1-216-113-00	METAL GLAZE	470K	5%	1/10W	
R244	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R245	1-216-679-11	METAL CHIP	15K	0.50%	1/10W	
R246	1-216-103-91	METAL GLAZE	180K	5%	1/10W	
R247	1-216-093-00	METAL GLAZE	68K	5%	1/10W	
R248	1-216-095-00	METAL GLAZE	82K	5%	1/10W	
R249	1-216-109-00	METAL GLAZE	330K	5%	1/10W	
R250	1-216-101-00	METAL GLAZE	150K	5%	1/10W	
R251	1-216-105-00	METAL GLAZE	220K	5%	1/10W	
R252	1-216-101-00	METAL GLAZE	150K	5%	1/10W	
R253	1-216-101-00	METAL GLAZE	150K	5%	1/10W	
R254	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R255	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R256	1-216-107-00	METAL GLAZE	270K	5%	1/10W	
R258	1-216-041-00	METAL GLAZE	470	5%	1/10W	
R259	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R260	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R261	1-216-035-00	METAL GLAZE	270	5%	1/10W	
R262	1-216-097-00	METAL GLAZE	100K	5%	1/10W	
R263	1-216-029-00	METAL GLAZE	150	5%	1/10W	
R264	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R265	1-216-067-00	METAL GLAZE	5.6K	5%	1/10W	
R266	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R267	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R268	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R269	1-216-103-91	METAL GLAZE	180K	5%	1/10W	
R270	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R271	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R272	1-216-103-91	METAL GLAZE	180K	5%	1/10W	
R273	1-216-113-00	METAL GLAZE	470K	5%	1/10W	
R275	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R276	1-216-037-00	METAL GLAZE	330	5%	1/10W	
R277	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R278	1-216-059-00	METAL GLAZE	2.7K	5%	1/10W	
R280	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R281	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R282	1-216-037-00	METAL GLAZE	330	5%	1/10W	
R283	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R284	1-216-059-00	METAL GLAZE	2.7K	5%	1/10W	
R286	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R287	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R288	1-216-037-00	METAL GLAZE	330	5%	1/10W	
R289	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R290	1-216-059-00	METAL GLAZE	2.7K	5%	1/10W	
R292	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R293	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R295	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W	
R296	1-216-659-11	METAL CHIP	2.2K	0.50%	1/10W	
R297	1-216-659-11	METAL CHIP	2.2K	0.50%	1/10W	
R298	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R300	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R301	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R302	1-216-113-00	METAL GLAZE	470K	5%	1/10W	
R303	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R304	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R305	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R306	1-216-089-91	METAL GLAZE	47K	5%	1/10W	
R307	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R308	1-216-089-91	METAL GLAZE	47K	5%	1/10W	
R309	1-216-089-91	METAL GLAZE	47K	5%	1/10W	
R310	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R311	1-216-089-91	METAL GLAZE	47K	5%	1/10W	
R312	1-216-089-91	METAL GLAZE	47K	5%	1/10W	
R313	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R314	1-216-089-91	METAL GLAZE	47K	5%	1/10W	
R315	1-216-113-00	METAL GLAZE	470K	5%	1/10W	
R316	1-216-105-00	METAL GLAZE	220K	5%	1/10W	
R317	1-216-109-00	METAL GLAZE	330K	5%	1/10W	
R318	1-216-105-00	METAL GLAZE	220K	5%	1/10W	
R319	1-216-099-00	METAL GLAZE	120K	5%	1/10W	
R320	1-216-099-00	METAL GLAZE	120K	5%	1/10W	
R321	1-216-043-00	METAL GLAZE	560	5%	1/10W	
R322	1-216-109-00	METAL GLAZE	330K	5%	1/10W	
R323	1-216-109-00	METAL GLAZE	330K	5%	1/10W	
R324	1-216-109-00	METAL GLAZE	330K	5%	1/10W	
R325	1-216-097-00	METAL GLAZE	100K	5%	1/10W	
R326	1-216-113-00	METAL GLAZE	470K	5%	1/10W	
R328	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R329	1-216-107-00	METAL GLAZE	270K	5%	1/10W	
R330	1-216-105-00	METAL GLAZE	220K	5%	1/10W	
R331	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R332	1-216-097-00	METAL GLAZE	100K	5%	1/10W	
R333	1-216-097-00	METAL GLAZE	100K	5%	1/10W	
R334	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R335	1-216-099-00	METAL GLAZE	120K	5%	1/10W	
R336	1-216-095-00	METAL GLAZE	82K	5%	1/10W	
R337	1-216-105-00	METAL GLAZE	220K	5%	1/10W	
R338	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R339	1-216-099-00	METAL GLAZE	120K	5%	1/10W	
R340	1-216-095-00	METAL GLAZE	82K	5%	1/10W	
R341	1-216-105-00	METAL GLAZE	220K	5%	1/10W	
R342	1-216-047-00	METAL GLAZE	820	5%	1/10W	
R343	1-216-053-00	METAL GLAZE	1.5K	5%	1/10W	
R344	1-216-664-11	METAL CHIP	3.6K	0.50%	1/10W	
R345	1-216-661-11	METAL CHIP	2.7K	0.50%	1/10W	
R346	1-216-105-00	METAL GLAZE	220K	5%	1/10W	
R348	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R349	1-216-650-11	METAL CHIP	910	0.50%	1/10W	
R350	1-216-653-11	METAL CHIP	1.2K	0.50%	1/10W	
R351	1-216-650-11	METAL CHIP	910	0.50%	1/10W	
R352	1-216-653-11	METAL CHIP	1.2K	0.50%	1/10W	
R353	1-216-650-11	METAL CHIP	910	0.50%	1/10W	
R354	1-216-653-11	METAL CHIP	1.2K	0.50%	1/10W	
R355	1-216-113-00	METAL GLAZE	470K	5%	1/10W	
R356	1-216-113-00	METAL GLAZE	470K	5%	1/10W	
R357	1-216-095-00	METAL GLAZE	82K	5%	1/10W	
R358	1-216-113-00	METAL GLAZE	470K	5%	1/10W	
R359	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R360	1-216-089-91	METAL GLAZE	47K	5%	1/10W	
R363	1-216-069-00	METAL GLAZE	6.8K	5%	1/10W	
R364	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R365	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R368	1-216-055-00	METAL GLAZE	1.8K	5%	1/10W	
R369	1-216-248-00	METAL GLAZE	120K	5%	1/8W	
R370	1-216-115-00	METAL GLAZE	560K	5%	1/10W	
R371	1-216-067-00	METAL GLAZE	5.6K	5%	1/10W	

REF.NO.	PART NO.	DESCRIPTION				REMARK
R372	1-216-115-00	METAL GLAZE	560K	5%	1/10W	
R374	1-216-115-00	METAL GLAZE	560K	5%	1/10W	
R375	1-216-683-11	METAL CHIP	22K	0.50%	1/10W	
R376	1-216-663-11	METAL CHIP	3.3K	0.50%	1/10W	
R378	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R379	1-216-641-11	METAL CHIP	390	0.50%	1/10W	
R380	1-208-799-11	METAL CHIP	5.1K	0.50%	1/10W	
R381	1-216-089-91	METAL GLAZE	47K	5%	1/10W	
R382	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R383	1-216-641-11	METAL CHIP	390	0.50%	1/10W	
R384	1-208-799-11	METAL CHIP	5.1K	0.50%	1/10W	
R385	1-216-117-00	METAL GLAZE	680K	5%	1/10W	
R386	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R387	1-216-641-11	METAL CHIP	390	0.50%	1/10W	
R388	1-208-799-11	METAL CHIP	5.1K	0.50%	1/10W	
R389	1-216-089-91	METAL GLAZE	47K	5%	1/10W	
R390	1-216-105-00	METAL GLAZE	220K	5%	1/10W	
R391	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R392	1-216-113-00	METAL GLAZE	470K	5%	1/10W	
R393	1-216-085-00	METAL GLAZE	33K	5%	1/10W	
R394	1-216-113-00	METAL GLAZE	470K	5%	1/10W	
R397	1-249-437-11	CARBON	47K	5%	1/4W	F
R398	1-249-434-11	CARBON	27K	5%	1/4W	F
R399	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1001	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1002	1-216-047-00	METAL GLAZE	820	5%	1/10W	
R1003	1-216-055-00	METAL GLAZE	1.8K	5%	1/10W	
R1004	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R1005	1-216-047-00	METAL GLAZE	820	5%	1/10W	
R1006	1-216-055-00	METAL GLAZE	1.8K	5%	1/10W	
R1007	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R1008	1-216-047-00	METAL GLAZE	820	5%	1/10W	
R1009	1-216-053-00	METAL GLAZE	1.5K	5%	1/10W	
R1010	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R1011	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R1012	1-216-051-00	METAL GLAZE	1.2K	5%	1/10W	
R1013	1-216-051-00	METAL GLAZE	1.2K	5%	1/10W	
R1014	1-216-246-91	METAL GLAZE	100K	5%	1/8W	
R1015	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R1016	1-216-089-91	METAL GLAZE	47K	5%	1/10W	
R1017	1-216-045-00	METAL GLAZE	680	5%	1/10W	
R1018	1-216-043-00	METAL GLAZE	560	5%	1/10W	
R1019	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R1020	1-216-089-91	METAL GLAZE	47K	5%	1/10W	
R1021	1-216-045-00	METAL GLAZE	680	5%	1/10W	
R1022	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R1023	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1024	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R1025	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R1026	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R1027	1-216-101-00	METAL GLAZE	150K	5%	1/10W	
R1028	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R1029	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R1030	1-216-089-91	METAL GLAZE	47K	5%	1/10W	
R1031	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R1032	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R1033	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R1035	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1036	1-216-089-91	METAL GLAZE	47K	5%	1/10W	
R1038	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R1040	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R1042	1-216-047-00	METAL GLAZE	820	5%	1/10W	
R1043	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W	
R1044	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R1045	1-216-125-00	METAL GLAZE	1.5M	5%	1/10W	
R1046	1-216-689-11	METAL CHIP	39K	0.50%	1/10W	
R1047	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R1048	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R1049	1-216-085-00	METAL GLAZE	33K	5%	1/10W	
R1050	1-216-059-00	METAL GLAZE	2.7K	5%	1/10W	
R1051	1-216-105-00	METAL GLAZE	220K	5%	1/10W	
R1053	1-216-091-00	METAL GLAZE	56K	5%	1/10W	
R1054	1-216-093-00	METAL GLAZE	68K	5%	1/10W	
R1055	1-216-097-00	METAL GLAZE	100K	5%	1/10W	
R1056	1-216-037-00	METAL GLAZE	330	5%	1/10W	
R1057	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R1058	1-216-109-00	METAL GLAZE	330K	5%	1/10W	
R1059	1-216-109-00	METAL GLAZE	330K	5%	1/10W	
R1060	1-216-109-00	METAL GLAZE	330K	5%	1/10W	
R1061	1-216-109-00	METAL GLAZE	330K	5%	1/10W	
R1062	1-216-103-91	METAL GLAZE	180K	5%	1/10W	
R1063	1-216-103-91	METAL GLAZE	180K	5%	1/10W	
R1064	1-216-103-91	METAL GLAZE	180K	5%	1/10W	
R1065	1-216-103-91	METAL GLAZE	180K	5%	1/10W	
R1066	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1067	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1068	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R1069	1-216-133-00	METAL GLAZE	3.3M	5%	1/10W	
R1070	1-216-085-00	METAL GLAZE	33K	5%	1/10W	
R1071	1-216-113-00	METAL GLAZE	470K	5%	1/10W	
R1072	1-216-099-00	METAL GLAZE	120K	5%	1/10W	
R1073	1-216-131-11	METAL GLAZE	2.7M	5%	1/10W	
R1075	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R1076	1-216-101-00	METAL GLAZE	150K	5%	1/10W	
R1077	1-216-103-91	METAL GLAZE	180K	5%	1/10W	
R1079	1-216-131-11	METAL GLAZE	2.7M	5%	1/10W	
R1080	1-216-097-00	METAL GLAZE	100K	5%	1/10W	
R1081	1-216-097-00	METAL GLAZE	100K	5%	1/10W	
R1082	1-216-105-00	METAL GLAZE	220K	5%	1/10W	
R1083	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R1084	1-216-063-00	METAL GLAZE	3.9K	5%	1/10W	
R1086	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1087	1-216-121-00	METAL GLAZE	1M	5%	1/10W	
R1088	1-216-047-00	METAL GLAZE	820	5%	1/10W	
R1090	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R1091	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R1092	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R1093	1-216-121-00	METAL GLAZE	1M	5%	1/10W	
R1094	1-216-075-00	METAL GLAZE	12K	5%	1/10W	
R1095	1-216-075-00	METAL GLAZE	12K	5%	1/10W	
R1096	1-216-075-00	METAL GLAZE	12K	5%	1/10W	
R1200	1-216-699-11	METAL CHIP	100K	0.50%	1/10W	
R1201	1-218-754-11	METAL CHIP	120K	0.50%	1/10W	
R1207	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R1208	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R1220	1-216-055-00	METAL GLAZE	1.8K	5%	1/10W	
R1221	1-216-055-00	METAL GLAZE	1.8K	5%	1/10W	
R1222	1-216-055-00	METAL GLAZE	1.8K	5%	1/10W	
R1223	1-216-689-11	METAL GLAZE	39K	5%	1/10W	
R1225	1-215-876-00	METAL OXIDE	15K	5%	1W	F
R1226	1-215-876-00	METAL OXIDE	15K	5%	1W	F
R1227	1-215-876-00	METAL OXIDE	15K	5%	1W	F
R1228	1-249-421-11	CARBON	2.2K	5%	1/4W	F
R1229	1-249-421-11	CARBON	2.2K	5%	1/4W	F
R1230	1-249-421-11	CARBON	2.2K	5%	1/4W	F
R1231	1-216-029-00	METAL GLAZE	150	5%	1/10W	
R1232	1-216-029-00	METAL GLAZE	150	5%	1/10W	

B P

The components identified by shading and mark ⚠ are critical for safety.
Replace only with part number specified.

REF.NO.	PART NO.	DESCRIPTION				REMARK
R1233	1-216-029-00	METAL GLAZE	150	5%	1/10W	
R1234	1-216-029-00	METAL GLAZE	150	5%	1/10W	
R1235	1-216-029-00	METAL GLAZE	150	5%	1/10W	
R1236	1-216-029-00	METAL GLAZE	150	5%	1/10W	
R1237	1-249-419-11	CARBON	1.5K	5%	1/4W	F
R1238	1-249-419-11	CARBON	1.5K	5%	1/4W	F
R1239	1-249-419-11	CARBON	1.5K	5%	1/4W	F
R1270	1-216-079-00	METAL GLAZE	18K	5%	1/10W	
R1271	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W	
R1280	1-216-109-00	METAL GLAZE	330K	5%	1/10W	
R1288	1-216-105-00	METAL GLAZE	220K	5%	1/10W	
R1290	1-216-071-00	METAL GLAZE	8.2K	5%	1/10W	
R1291	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R1294	1-216-069-00	METAL GLAZE	6.8K	5%	1/10W	
R1295	1-216-109-00	METAL GLAZE	330K	5%	1/10W	
R1296	1-216-095-00	METAL GLAZE	82K	5%	1/10W	
R1297	1-216-071-00	METAL GLAZE	8.2K	5%	1/10W	
R1298	1-216-071-00	METAL GLAZE	8.2K	5%	1/10W	
R1299	1-216-071-00	METAL GLAZE	8.2K	5%	1/10W	
R1300	1-216-089-91	METAL GLAZE	47K	5%	1/10W	
R1301	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R1302	1-216-113-00	METAL GLAZE	470K	5%	1/10W	
R1303	1-216-113-00	METAL GLAZE	470K	5%	1/10W	
R1304	1-216-091-00	METAL GLAZE	56K	5%	1/10W	
R1305	1-216-093-00	METAL GLAZE	68K	5%	1/10W	
R1306	1-216-063-00	METAL GLAZE	3.9K	5%	1/10W	
R1307	1-216-041-00	METAL GLAZE	470	5%	1/10W	
R1308	1-216-041-00	METAL GLAZE	470	5%	1/10W	
R1309	1-216-063-00	METAL GLAZE	3.9K	5%	1/10W	
R1310	1-216-119-00	METAL GLAZE	820K	5%	1/10W	
R1313	1-216-101-00	METAL GLAZE	150K	5%	1/10W	
R1314	1-216-053-00	METAL GLAZE	1.5K	5%	1/10W	
R1315	1-216-077-00	METAL GLAZE	15K	5%	1/10W	
R1320	1-216-083-00	METAL GLAZE	27K	5%	1/10W	
R1321	1-216-093-00	METAL GLAZE	68K	5%	1/10W	
R1322	1-216-037-00	METAL GLAZE	330	5%	1/10W	
R1323	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W	
R1324	1-216-121-00	METAL GLAZE	1M	5%	1/10W	
R1325	1-216-085-00	METAL GLAZE	33K	5%	1/10W	
R1326	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R1327	1-216-099-00	METAL GLAZE	120K	5%	1/10W	
R1328	1-216-099-00	METAL GLAZE	120K	5%	1/10W	
R1329	1-216-093-00	METAL GLAZE	68K	5%	1/10W	
R1330	1-216-063-00	METAL GLAZE	3.9K	5%	1/10W	
R1331	1-216-051-00	METAL GLAZE	1.2K	5%	1/10W	
R1332	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W	
R1333	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W	
R1334	1-216-055-00	METAL GLAZE	1.8K	5%	1/10W	
R1335	1-216-035-00	METAL GLAZE	270	5%	1/10W	
R1336	1-216-089-91	METAL GLAZE	47K	5%	1/10W	
R1337	1-216-113-00	METAL GLAZE	470K	5%	1/10W	
R1338	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R1339	1-216-097-00	METAL GLAZE	100K	5%	1/10W	
R1340	1-216-097-00	METAL GLAZE	100K	5%	1/10W	
R1341	1-216-111-00	METAL GLAZE	390K	5%	1/10W	
R1342	1-216-694-11	METAL CHIP	62K	0.50%	1/10W	
R1343	1-216-121-00	METAL GLAZE	1M	5%	1/10W	
R1344	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1345	1-216-055-00	METAL GLAZE	1.8K	5%	1/10W	
R1346	1-216-047-00	METAL GLAZE	820	5%	1/10W	
R1347	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1348	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1349	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1350	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1351	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1352	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1353	1-216-115-00	METAL GLAZE	560K	5%	1/10W	
R1371	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W	
R1372	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W	
R1373	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W	
R1392	1-216-089-91	METAL GLAZE	47K	5%	1/10W	
R1393	1-216-095-00	METAL GLAZE	82K	5%	1/10W	

<VARIABLE RESISTOR>

RV101	1-241-763-11	RES, ADJ, CERMET	4.7K
RV102	1-241-763-11	RES, ADJ, CERMET	4.7K
RV103	1-241-759-21	RES, ADJ, CARBON	220
RV104	1-241-759-21	RES, ADJ, CARBON	220
RV105	1-241-761-11	RES, ADJ, CARBON	1K
RV106	1-241-761-11	RES, ADJ, CARBON	1K
RV107	1-241-761-11	RES, ADJ, CARBON	1K
RV108	1-241-630-11	RES, ADJ, CARBON	10K
RV109	1-241-765-11	RES, ADJ, CERMET	22K
RV110	1-241-630-11	RES, ADJ, CARBON	10K
RV111	1-241-630-11	RES, ADJ, CARBON	10K
RV112	1-238-019-11	RES, ADJ, CARBON	47K
RV113	1-238-019-11	RES, ADJ, CARBON	47K
RV114	1-238-019-11	RES, ADJ, CARBON	47K
RV115	1-241-765-11	RES, ADJ, CARBON	22K
RV116	1-241-765-11	RES, ADJ, CARBON	22K
RV118	1-241-765-11	RES, ADJ, CARBON	22K
RV119	1-241-765-11	RES, ADJ, CARBON	22K
RV120	1-241-765-11	RES, ADJ, CARBON	22K
RV121	1-241-765-11	RES, ADJ, CARBON	22K
RV122	1-241-765-11	RES, ADJ, CARBON	22K
RV123	1-241-628-11	RES, ADJ, CARBON	2.2K
RV124	1-241-761-11	RES, ADJ, CARBON	1K
RV125	1-241-761-11	RES, ADJ, CARBON	1K
RV205	1-241-765-11	RES, ADJ, CARBON	22K

<MODULE>

SEP101	1-808-654-11	MODULE

<CRYSTAL>

X101	1-527-722-00	OSCILLATOR, CRYSTAL
X102	1-577-259-11	VIBRATOR, CRYSTAL

****

*A-1195-048-A P BOARD, COMPLETE
****

<CAPACITOR>

C801	1-126-104-11	ELECT	470MF	20%	35V
C802	1-162-318-11	CERAMIC	0.001MF	10%	500V
C803	1-102-228-00	CERAMIC	470PF	10%	500V
C804	1-123-935-00	ELECT	33MF	20%	160V
C806	1-124-480-11	ELECT	470MF	20%	25V
C807	1-102-228-00	CERAMIC	470PF	10%	500V
C808	1-106-367-00	MYLAR	0.01MF	10%	100V
C809	1-106-375-12	MYLAR	0.022MF	10%	100V
C810	1-162-318-11	CERAMIC	0.001MF	10%	500V
C811	⚠ 1-137-544-91	FILM	0.01MF	3%	600V
C812	⚠ 1-137-545-91	FILM	0.013MF	3%	600V

The components identified by shading and mark ⚠ are critical for safety.
Replace only with part number specified.

P FA QA

REF.NO.	PART NO.	DESCRIPTION			REMARK
C813	1-106-385-00	MYLAR	0.056MF	5%	200V
C814	1-106-383-00	MYLAR	0.047MF	10%	100V
C815	1-124-916-11	ELECT	22MF	20%	50V
C816	1-124-798-11	ELECT	1MF	20%	160V
C817	1-130-800-00	FILM	2.2MF	10%	250V
C818	1-102-228-00	CERAMIC	470PF	10%	500V
C819	1-162-116-00	CERAMIC	680PF	10%	2KV
C820	1-162-116-00	CERAMIC	680PF	10%	2KV
C821	1-162-116-00	CERAMIC	680PF	10%	2KV
C825	1-123-024-21	ELECT	33MF		160V
C880	1-163-031-11	CERAMIC CHIP	0.01MF		50V
		<CONNECTOR>			
CN801	1-564-595-11	PLUG, CONNECTOR 14P			
CN802	*1-508-766-00	PIN, CONNECTOR (5MM PITCH) 4P			
CN803	*1-564-508-11	PLUG, CONNECTOR 5P			
CN805	*1-560-123-00	PLUG, CONNECTOR (2.5MM) 3P			
		<DIODE>			
D801	8-719-302-43	DIODE EL1Z			
D802	8-719-302-43	DIODE EL1Z			
D803	8-719-302-43	DIODE EL1Z			
D804	8-719-979-85	DIODE EGP20G			
D805	8-719-302-43	DIODE EL1Z			
D806	8-719-302-43	DIODE EL1Z			
D807	8-719-105-99	DIODE RD6.2M-B1			
D808	8-719-018-72	THYRISTOR CR02AM-4TB			
D809	8-719-908-03	DIODE GP08D			
D810	8-719-908-03	DIODE GP08D			
D811	8-719-908-03	DIODE GP08D			
D813	8-719-302-43	DIODE EL1Z			
		<COIL>			
L802	1-459-442-00	COIL (WITH CORE)			
L803	1-422-613-11	COIL, AIR CORE			
L804	1-459-109-00	COIL,DUST CORE			
L805	1-460-225-11	COIL, HORIZONTAL LINEARITY			
L806	1-414-098-11	MICRO INDUCTOR 10MMH			
L807	1-414-098-11	MICRO INDUCTOR 10MMH			
L810	1-412-529-11	INDUCTOR	22UH		
		<NEON LAMP>			
NL801	1-519-108-99	LAMP, NEON			
		<TRANSISTOR>			
Q801	8-729-195-82	TRANSISTOR 2SC2958-L			
Q802	8-729-201-62	TRANSISTOR 2SC2555-2			
	*4-043-154-01	HOLDER, IC; Q802			
	4-382-854-01	SCREW (M3X8), P, SW (+); Q802			
	4-879-937-00	SHEET, MICA; Q802			
Q803	8-729-906-24	TRANSISTOR 2SD835			
		<RESISTOR>			
R801	1-249-383-11	CARBON	1.5	5% 1/4W	F
R802	1-249-377-11	CARBON	0.47	5% 1/4W	F
R803	1-216-049-00	METAL GLAZE	1K	5% 1/10W	
R804	1-249-419-11	CARBON	1.5K	5% 1/4W	F
R805	1-215-892-11	METAL OXIDE	1K	5% 2W	F
R807	1-216-425-11	METAL OXIDE	56	5% 1W	F
R808	1-202-846-00	SOLID	470K	20% 1/2W	
R809	1-216-089-91	METAL GLAZE	47K	5% 1/10W	
R810	1-249-421-11	CARBON	2.2K	5% 1/4W	F
R811	1-216-049-00	METAL GLAZE	1K	5% 1/10W	
R812	1-249-439-11	CARBON	68K	5% 1/4W	F
R813	1-249-414-11	CARBON	560	5% 1/4W	F
R814	1-249-377-11	CARBON	0.47	5% 1/4W	F
		<VARIABLE RESISTOR>			
RV801	1-223-102-00	RES, ADJ, WIREWOUND 120			
		<TRANSFORMER>			
T801	1-437-082-31	HDT			
T802	⚠1-439-526-12	TRANSFORMER ASSY, FLYBACK			

****

*A-1241-070-A FA BOARD, COMPLETE
****

<CAPACITOR>

C601	1-136-185-00	FILM	0.22MF	20%	250V

<CONNECTOR>

CN601	*1-580-689-11	PIN, CONNECTOR (PC BOARD) 4P
CN602	*1-508-765-00	PIN, CONNECTOR (5MM PITCH) 3P
CN603	*1-564-507-11	PLUG, CONNECTOR 4P

<FUSE>

F601	⚠1-576-230-11	FUSE (H.B.C.) (3.15A/250V)
	1-533-223-11	CLIP, FUSE

<RESISTOR>

R602	1-214-945-00	METAL	2.2M	5%	1/2W

<SWITCH>

S601	1-692-050-11	SWITCH, PUSH (AC POWER) (1KEY)

****

*A-1275-121-A QA BOARD, CONPLETE
****

1-537-408-21	TERMINAL BOARD B, INPUT/OUTPUT
1-537-410-11	TERMINAL BOARD A, INPUT/OUTPUT

<CAPACITOR>

C401	1-124-234-00	ELECT	22MF	20%	16V
C402	1-124-234-00	ELECT	22MF	20%	16V
C403	1-124-234-00	ELECT	22MF	20%	16V
C404	1-124-234-00	ELECT	22MF	20%	16V
C405	1-124-234-00	ELECT	22MF	20%	16V
C406	1-124-234-00	ELECT	22MF	20%	16V
C407	1-124-234-00	ELECT	22MF	20%	16V
C408	1-124-463-00	ELECT	0.1MF	20%	50V
C409	1-124-234-00	ELECT	22MF	20%	16V
C410	1-124-234-00	ELECT	22MF	20%	16V
C411	1-124-234-00	ELECT	22MF	20%	16V

QA

REF.NO.	PART NO.	DESCRIPTION			REMARK
C412	1-124-234-00	ELECT	22MF	20% 16V	
C413	1-124-234-00	ELECT	22MF	20% 16V	
C414	1-126-157-11	ELECT	10MF	20% 16V	
C415	1-126-157-11	ELECT	10MF	20% 16V	
C416	1-126-157-11	ELECT	10MF	20% 16V	
C417	1-126-157-11	ELECT	10MF	20% 16V	
C418	1-126-157-11	ELECT	10MF	20% 16V	
C419	1-126-157-11	ELECT	10MF	20% 16V	
C420	1-126-157-11	ELECT	10MF	20% 16V	
C421	1-102-125-00	CERAMIC	0.0047MF	10% 50V	
C422	1-124-464-11	ELECT	0.22MF	20% 50V	
C423	1-126-157-11	ELECT	10MF	20% 16V	
C424	1-126-157-11	ELECT	10MF	20% 16V	
C425	1-108-634-11	MYLAR	0.047MF	10% 100V	
C426	1-128-499-11	ELECT	220MF	20% 16V	
C427	1-128-499-11	ELECT	220MF	20% 16V	
C428	1-124-589-11	ELECT	47MF	20% 16V	
C429	1-124-234-00	ELECT	22MF	20% 16V	
C430	1-163-033-00	CERAMIC CHIP	0.022MF	50V	
C431	1-124-234-00	ELECT	22MF	20% 16V	
C432	1-163-033-00	CERAMIC CHIP	0.022MF	50V	
C433	1-124-234-00	ELECT	22MF	20% 16V	
C434	1-163-033-00	CERAMIC CHIP	0.022MF	50V	
C435	1-124-234-00	ELECT	22MF	20% 16V	
C436	1-163-033-00	CERAMIC CHIP	0.022MF	50V	
C437	1-163-033-00	CERAMIC CHIP	0.022MF	50V	
C438	1-124-234-00	ELECT	22MF	20% 16V	
C439	1-163-033-00	CERAMIC CHIP	0.022MF	50V	
C440	1-163-033-00	CERAMIC CHIP	0.022MF	50V	
C441	1-124-234-00	ELECT	22MF	20% 16V	
C442	1-163-033-00	CERAMIC CHIP	0.022MF	50V	
C443	1-163-033-00	CERAMIC CHIP	0.022MF	50V	
C444	1-163-033-00	CERAMIC CHIP	0.022MF	50V	
C445	1-163-031-11	CERAMIC CHIP	0.01MF	50V	
C446	1-163-031-11	CERAMIC CHIP	0.01MF	50V	
C447	1-126-301-11	ELECT	1MF	20% 50V	
C448	1-124-234-00	ELECT	22MF	20% 16V	
C449	1-163-031-11	CERAMIC CHIP	0.01MF	50V	
C450	1-124-234-00	ELECT	22MF	20% 16V	
C451	1-163-033-00	CERAMIC CHIP	0.022MF	50V	
C452	1-128-499-11	ELECT	220MF	20% 16V	
C453	1-124-234-00	ELECT	22MF	20% 16V	
C454	1-128-499-11	ELECT	220MF	20% 16V	
C460	1-126-301-11	ELECT	1MF	20% 50V	
C461	1-126-301-11	ELECT	1MF	20% 50V	
C462	1-126-301-11	ELECT	1MF	20% 50V	
C464	1-163-031-11	CERAMIC CHIP	0.01MF	50V	
C465	1-163-031-11	CERAMIC CHIP	0.01MF	50V	
C466	1-163-031-11	CERAMIC CHIP	0.01MF	50V	
C467	1-163-031-11	CERAMIC CHIP	0.01MF	50V	
C475	1-163-031-11	CERAMIC CHIP	0.01MF	50V	

<CONNECTOR>

CN401	1-506-494-11	PIN, CONNECTOR 15P	
CN402	*1-564-518-11	PLUG, CONNECTOR 3P	
CN403	*1-580-690-11	PIN, CONNECTOR (PC BOARD) 2P	
CN404	*1-564-520-11	PLUG, CONNECTOR 5P	

<DIODE>

D401	8-719-404-46	DIODE MA110	
D402	8-719-404-46	DIODE MA110	
D403	8-719-110-09	DIODE RD8.2ESB3	
D404	8-719-404-46	DIODE MA110	
D405	8-719-404-46	DIODE MA110	
D406	8-719-404-46	DIODE MA110	
D407	8-719-404-46	DIODE MA110	
D408	8-719-404-46	DIODE MA110	
D409	8-719-404-46	DIODE MA110	
D410	8-719-404-46	DIODE MA110	
D411	8-719-404-46	DIODE MA110	
D412	8-719-404-46	DIODE MA110	
D413	8-719-404-46	DIODE MA110	
D414	8-719-404-46	DIODE MA110	
D415	8-719-404-46	DIODE MA110	
D416	8-719-404-46	DIODE MA110	
D417	8-719-404-46	DIODE MA110	
D418	8-719-404-46	DIODE MA110	
D419	8-719-404-46	DIODE MA110	
D420	8-719-404-46	DIODE MA110	
D421	8-719-404-46	DIODE MA110	
D422	8-719-404-46	DIODE MA110	
D423	8-719-404-46	DIODE MA110	
D424	8-719-404-46	DIODE MA110	
D425	8-719-404-46	DIODE MA110	
D426	8-719-404-46	DIODE MA110	
D427	8-719-404-46	DIODE MA110	
D428	8-719-404-46	DIODE MA110	
D429	8-719-404-46	DIODE MA110	
D430	8-719-404-46	DIODE MA110	
D431	8-719-404-46	DIODE MA110	

<IC>

IC401	8-759-287-89	IC MM1113XFF
IC402	8-759-287-89	IC MM1113XFF
IC403	8-759-420-04	IC AN5265

<COIL>

L401	1-410-682-31	INDUCTOR	470UH
L402	1-410-682-31	INDUCTOR	470UH

<TRANSISTOR>

Q401	8-729-120-28	TRANSISTOR 2SC1623-L5L6
Q402	8-729-120-28	TRANSISTOR 2SC1623-L5L6
Q403	8-729-216-22	TRANSISTOR 2SA1162-G
Q404	8-729-120-28	TRANSISTOR 2SC1623-L5L6
Q405	8-729-120-28	TRANSISTOR 2SC1623-L5L6
Q406	8-729-120-28	TRANSISTOR 2SC1623-L5L6
Q407	8-729-120-28	TRANSISTOR 2SC1623-L5L6
Q408	8-729-120-28	TRANSISTOR 2SC1623-L5L6
Q409	8-729-120-28	TRANSISTOR 2SC1623-L5L6
Q410	8-729-120-28	TRANSISTOR 2SC1623-L5L6
Q411	8-729-216-22	TRANSISTOR 2SA1162-G
Q412	8-729-216-22	TRANSISTOR 2SA1162-G
Q413	8-729-216-22	TRANSISTOR 2SA1162-G
Q414	8-729-216-22	TRANSISTOR 2SA1162-G
Q416	8-729-420-81	TRANSISTOR 2SD874A-R
Q417	8-729-901-06	TRANSISTOR DTA144EK
Q418	8-729-901-06	TRANSISTOR DTA144EK
Q419	8-729-901-06	TRANSISTOR DTA144EK
Q420	8-729-901-01	TRANSISTOR DTC144EK
Q421	8-729-901-06	TRANSISTOR DTA144EK
Q422	8-729-901-01	TRANSISTOR DTC144EK

QA CA

REF.NO.	PART NO.	DESCRIPTION				REMARK
Q423	8-729-901-06	TRANSISTOR DTA144EK				
Q424	8-729-901-06	TRANSISTOR DTA144EK				
Q426	8-729-120-28	TRANSISTOR 2SC1623-L5L6				
		<RESISTOR>				
R401	1-214-702-00	METAL	75	1%	1/4W	
R402	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R403	1-216-093-00	METAL GLAZE	68K	5%	1/10W	
R404	1-216-091-00	METAL GLAZE	56K	5%	1/10W	
R405	1-216-063-00	METAL GLAZE	3.9K	5%	1/10W	
R406	1-216-037-00	METAL GLAZE	330	5%	1/10W	
R407	1-216-689-11	METAL GLAZE	39K	5%	1/10W	
R408	1-216-085-00	METAL GLAZE	33K	5%	1/10W	
R409	1-214-702-00	METAL	75	1%	1/4W	
R410	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R411	1-216-093-00	METAL GLAZE	68K	5%	1/10W	
R412	1-216-091-00	METAL GLAZE	56K	5%	1/10W	
R413	1-216-063-00	METAL GLAZE	3.9K	5%	1/10W	
R414	1-216-037-00	METAL GLAZE	330	5%	1/10W	
R415	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R416	1-216-023-00	METAL GLAZE	82	5%	1/10W	
R417	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R418	1-216-093-00	METAL GLAZE	68K	5%	1/10W	
R419	1-216-091-00	METAL GLAZE	56K	5%	1/10W	
R420	1-216-063-00	METAL GLAZE	3.9K	5%	1/10W	
R421	1-216-027-00	METAL GLAZE	120	5%	1/10W	
R422	1-214-702-00	METAL	75	1%	1/4W	
R423	1-214-702-00	METAL	75	1%	1/4W	
R424	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R425	1-216-093-00	METAL GLAZE	68K	5%	1/10W	
R426	1-216-091-00	METAL GLAZE	56K	5%	1/10W	
R427	1-216-063-00	METAL GLAZE	3.9K	5%	1/10W	
R428	1-216-037-00	METAL GLAZE	330	5%	1/10W	
R429	1-214-702-00	METAL	75	1%	1/4W	
R430	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R431	1-216-093-00	METAL GLAZE	68K	5%	1/10W	
R432	1-216-091-00	METAL GLAZE	56K	5%	1/10W	
R433	1-216-063-00	METAL GLAZE	3.9K	5%	1/10W	
R434	1-216-027-00	METAL GLAZE	120	5%	1/10W	
R435	1-214-702-00	METAL	75	1%	1/4W	
R436	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R437	1-216-093-00	METAL GLAZE	68K	5%	1/10W	
R438	1-216-091-00	METAL GLAZE	56K	5%	1/10W	
R439	1-216-063-00	METAL GLAZE	3.9K	5%	1/10W	
R440	1-216-027-00	METAL GLAZE	120	5%	1/10W	
R441	1-216-089-91	METAL GLAZE	47K	5%	1/10W	
R442	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R443	1-216-689-11	METAL GLAZE	39K	5%	1/10W	
R444	1-214-702-00	METAL	75	1%	1/4W	
R445	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R446	1-216-093-00	METAL GLAZE	68K	5%	1/10W	
R447	1-216-091-00	METAL GLAZE	56K	5%	1/10W	
R448	1-216-063-00	METAL GLAZE	3.9K	5%	1/10W	
R449	1-216-027-00	METAL GLAZE	120	5%	1/10W	
R450	1-214-702-00	METAL	75	1%	1/4W	
R451	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R452	1-216-091-00	METAL GLAZE	56K	5%	1/10W	
R453	1-216-093-00	METAL GLAZE	68K	5%	1/10W	
R454	1-216-063-00	METAL GLAZE	3.9K	5%	1/10W	
R455	1-216-037-00	METAL GLAZE	330	5%	1/10W	
R456	1-216-085-00	METAL GLAZE	33K	5%	1/10W	
R457	1-216-085-00	METAL GLAZE	33K	5%	1/10W	
R458	1-247-707-11	CARBON	390	5%	1/4W	
R459	1-216-689-11	METAL GLAZE	39K	5%	1/10W	
R460	1-216-089-91	METAL GLAZE	47K	5%	1/10W	
R461	1-216-097-00	METAL GLAZE	100K	5%	1/10W	
R462	1-216-115-00	METAL GLAZE	560K	5%	1/10W	
R463	1-216-105-00	METAL GLAZE	220K	5%	1/10W	
R464	1-216-077-00	METAL GLAZE	15K	5%	1/10W	
R465	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R466	1-216-097-00	METAL GLAZE	100K	5%	1/10W	
R467	1-216-115-00	METAL GLAZE	560K	5%	1/10W	
R468	1-216-105-00	METAL GLAZE	220K	5%	1/10W	
R469	1-216-077-00	METAL GLAZE	15K	5%	1/10W	
R470	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R471	1-216-097-00	METAL GLAZE	100K	5%	1/10W	
R472	1-216-115-00	METAL GLAZE	560K	5%	1/10W	
R473	1-216-105-00	METAL GLAZE	220K	5%	1/10W	
R474	1-216-077-00	METAL GLAZE	15K	5%	1/10W	
R475	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R477	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R479	1-216-085-00	METAL GLAZE	33K	5%	1/10W	
R480	1-247-711-11	CARBON	680	5%	1/4W	
R481	1-247-720-11	CARBON	3.9K	5%	1/4W	
R482	1-249-455-11	CARBON	4.7	5%	1/4W	
R483	1-249-389-11	CARBON	4.7	5%	1/4W	F
R484	1-216-041-00	METAL GLAZE	470	5%	1/10W	
R485	1-247-688-11	CARBON	10	5%	1/4W	F
R486	1-216-037-00	METAL GLAZE	330	5%	1/10W	
R487	1-249-468-11	CARBON	82K	5%	1/4W	
R488	1-249-468-11	CARBON	82K	5%	1/4W	
R489	1-249-468-11	CARBON	82K	5%	1/4W	
R490	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W	
R491	1-216-089-91	METAL GLAZE	47K	5%	1/10W	
R492	1-216-089-91	METAL GLAZE	47K	5%	1/10W	
R493	1-216-089-91	METAL GLAZE	47K	5%	1/10W	
R494	1-216-089-91	METAL GLAZE	47K	5%	1/10W	
R495	1-216-295-91	METAL GLAZE	0	5%	1/10W	
R496	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W	
R497	1-216-089-91	METAL GLAZE	47K	5%	1/10W	
R498	1-216-089-91	METAL GLAZE	47K	5%	1/10W	
R499	1-216-089-91	METAL GLAZE	47K	5%	1/10W	
R1401	1-216-097-00	METAL GLAZE	100K	5%	1/10W	
R1403	1-216-295-91	METAL GLAZE	0	5%	1/10W	
R1404	1-216-097-00	METAL GLAZE	100K	5%	1/10W	
R1410	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R1411	1-216-089-91	METAL GLAZE	47K	5%	1/10W	
R1412	1-216-113-00	METAL GLAZE	470K	5%	1/10W	
		<VARIABLE RESISTOR>				
RV401	1-237-994-11	RES, VAR, CARBON 20K				
		<SWITCH>				
S401	1-570-145-11	SWITCH, SLIDE				
**********						
	*A-1331-183-A	CA BOARD, COMPLETE				
		**********				
	1-251-244-11	SOCKET, PICTURE TUBE				
		<CAPACITOR>				
C701	1-162-114-00	CERAMIC	0.0047MF	10%	2KV	

CA D

REF.NO.	PART NO.	DESCRIPTION			REMARK
C710	1-161-830-00	CERAMIC	0.0047MF	99%	500V
		<CONNECTOR>			
CN701	*1-564-509-11	PLUG, CONNECTOR 6P			
CN702	1-508-784-00	PIN, CONNECTOR (5MM PITCH) 1P			
CN703	*1-564-508-11	PLUG, CONNECTOR 5P			
		<COIL>			
L701	1-410-668-11	INDUCTOR	27UH		
		<RESISTOR>			
R701	1-202-822-00	SOLID	2.2K	20% 1/2W	
R702	1-202-822-00	SOLID	2.2K	20% 1/2W	
R703	1-202-822-00	SOLID	2.2K	20% 1/2W	
R704	1-202-838-00	SOLID	100K	20% 1/2W	
R706	1-202-842-11	SOLID	220K	20% 1/2W	
		<VARIABLE RESISTOR>			
RV701	1-230-164-00	RES, ADJ, METAL GLAZE 55M			
	*4-376-132-11	COVER (REAR LID), CV VOL; RV701			
	*4-376-133-11	COVER (MAIN), CV VOL; RV701			
**********					
	*A-1346-251-A	D BOARD, COMPLETE			
		**********			
		<CAPACITOR>			
C501	1-124-477-11	ELECT	47MF	20%	16V
C502	1-124-907-11	ELECT	10MF	20%	50V
C503	1-126-103-11	ELECT	470MF	20%	16V
C504	1-124-902-00	ELECT	0.47MF	20%	50V
C505	1-106-381-12	MYLAR	0.039MF	10%	100V
C506	1-124-903-11	ELECT	1MF	20%	50V
C507	1-106-367-00	MYLAR	0.01MF	10%	100V
C508	1-124-903-11	ELECT	1MF	20%	50V
C509	1-136-173-00	FILM	0.47MF	5%	50V
C510	1-136-161-00	FILM	0.047MF	5%	50V
C511	1-124-903-11	ELECT	1MF	20%	50V
C512	1-106-375-12	MYLAR	0.022MF	10%	100V
C513	1-106-375-12	MYLAR	0.022MF	10%	100V
C514	1-106-371-00	MYLAR	0.015MF	10%	100V
C515	1-124-925-11	ELECT	2.2MF	20%	50V
C516	1-124-925-11	ELECT	2.2MF	20%	50V
C517	1-130-480-00	FILM	0.0056MF	5%	50V
C518	1-163-245-11	CERAMIC CHIP	56PF	5%	50V
C519	1-124-927-11	ELECT	4.7MF	20%	50V
C520	1-163-129-00	CERAMIC CHIP	330PF	5%	50V
C521	1-124-907-11	ELECT	10MF	20%	50V
C523	1-106-363-00	MYLAR	0.0068MF	10%	100V
C524	1-102-116-00	CERAMIC	680PF	10%	50V
C525	1-102-820-00	CERAMIC	330PF	5%	50V
C526	1-102-074-00	CERAMIC	0.001MF	10%	50V
C527	1-124-122-11	ELECT	100MF	20%	50V
C528	1-102-125-00	CERAMIC	0.0047MF	10%	50V
C529	1-124-910-11	ELECT	47MF	20%	50V
C530	1-163-097-00	CERAMIC CHIP	15PF	5%	50V
C531	1-131-370-00	TANTALUM	6.8MF	10%	16V
C532	1-124-557-11	ELECT	1000MF	20%	25V
C533	1-124-927-11	ELECT	4.7MF	20%	50V
C534	1-124-768-11	ELECT	4.7MF	20%	50V
C535	1-136-161-00	FILM	0.047MF	5%	50V
C536	1-124-927-11	ELECT	4.7MF	20%	50V
C537	1-124-484-11	ELECT	220MF	20%	35V
C538	1-124-910-11	ELECT	47MF	20%	50V
C539	1-136-113-00	FILM	2MF	5%	200V
C540	1-163-017-00	CERAMIC CHIP	0.0047MF	10%	50V
C541	1-163-035-00	CERAMIC CHIP	0.047MF		50V
C542	1-126-103-11	ELECT	470MF	20%	16V
C545	1-126-101-11	ELECT	100MF	20%	16V
C546	1-124-907-11	ELECT	10MF	20%	50V
C547	1-124-907-11	ELECT	10MF	20%	50V
C548	1-124-907-11	ELECT	10MF	20%	50V
C549	1-124-907-11	ELECT	10MF	20%	50V
C550	1-124-907-11	ELECT	10MF	20%	50V
C551	1-124-927-11	ELECT	4.7MF	20%	50V
C552	1-101-004-00	CERAMIC	0.01MF		50V
C553	1-126-103-11	ELECT	470MF	20%	16V
C563	1-106-383-00	MYLAR	0.047MF	10%	100V
C564	1-163-009-11	CERAMIC CHIP	0.001MF	10%	50V
C567	1-124-907-11	ELECT	10MF	20%	50V
C568	1-130-736-11	FILM	0.01MF	5%	50V
C569	1-130-471-00	FILM	0.001MF	5%	50V
C570	1-163-117-00	CERAMIC CHIP	100PF	5%	50V
C571	1-124-913-11	ELECT	470MF	20%	50V
C572	1-101-004-00	CERAMIC	0.01MF		50V
C574	1-106-351-00	MYLAR	0.0022MF	10%	100V
C575	1-106-351-00	MYLAR	0.0022MF	10%	100V
C578	1-163-031-11	CERAMIC CHIP	0.01MF		50V
C831	1-124-907-11	ELECT	10MF	20%	50V
C832	1-124-907-11	ELECT	10MF	20%	50V
C833	1-163-009-11	CERAMIC CHIP	0.001MF	10%	50V
C834	1-163-121-00	CERAMIC CHIP	150PF	5%	50V
C835	1-163-209-00	CERAMIC CHIP	0.0015MF	5%	50V
C836	1-124-907-11	ELECT	10MF	20%	50V
C837	1-163-209-00	CERAMIC CHIP	0.0015MF	5%	50V
C838	1-136-163-00	FILM	0.068MF	5%	50V
C839	1-106-351-00	MYLAR	0.0022MF	10%	100V
C840	1-163-209-00	CERAMIC CHIP	0.0015MF	5%	50V
C841	1-163-209-00	CERAMIC CHIP	0.0015MF	5%	50V
C843	1-124-902-00	ELECT	0.47MF	20%	50V
C844	1-124-902-00	ELECT	0.47MF	20%	50V
C845	1-124-477-11	ELECT	47MF	20%	25V
C846	1-124-907-11	ELECT	10MF	20%	50V
C847	1-124-916-11	ELECT	22MF	20%	50V
C848	1-131-351-00	TANTALUM	4.7MF	10%	35V
C849	1-164-182-11	CERAMIC CHIP	0.0033MF	10%	50V
C1601	1-124-907-11	ELECT	10MF	20%	50V
C1602	1-164-161-11	CERAMIC CHIP	0.0022MF	10%	50V
C1603	1-104-348-11	ELECT	15MF	20%	50V
C1604	1-128-500-51	ELECT	1000MF	20%	50V
C1605	1-124-922-11	ELECT	1000MF	20%	50V
C1606	1-163-009-11	CERAMIC CHIP	0.001MF	10%	50V
C1607	1-124-907-11	ELECT	10MF	20%	50V
C1608	1-124-916-11	ELECT	22MF	20%	50V
C1609	1-163-009-11	CERAMIC CHIP	0.001MF	10%	50V
C1610	1-124-927-11	ELECT	4.7MF	20%	50V
C1611	1-124-482-11	ELECT	33MF	20%	35V
C1612	1-136-257-00	FILM	0.0039MF	5%	50V

REF.NO.	PART NO.	DESCRIPTION		REMARK
C1613	1-163-009-11	CERAMIC CHIP 0.001MF	10%	50V
C1614	1-164-232-11	CERAMIC CHIP 0.01MF	10%	50V
C1615	1-124-465-00	ELECT 0.47MF	20%	50V
C1620	1-163-133-00	CERAMIC CHIP 470PF	5%	50V
C1621	1-163-117-00	CERAMIC CHIP 100PF	5%	50V
C1641	1-163-035-00	CERAMIC CHIP 0.047MF		50V
		<CONNECTOR>		
CN501	*1-564-506-11	PLUG, CONNECTOR 3P		
CN502	*1-564-011-11	PIN, CONNECTOR 12P		
CN504	*1-564-508-11	PLUG, CONNECTOR 5P		
CN505	*1-564-509-11	PLUG, CONNECTOR 6P		
CN507	1-564-511-11	PLUG, CONNECTOR 8P		
CN508	*1-564-104-00	PIN, CONNECTOR (B3P-VH) 3P		
CN509	*1-564-506-11	PLUG, CONNECTOR 3P		
		<DIODE>		
D501	8-719-404-46	DIODE MA110		
D502	8-719-404-46	DIODE MA110		
D503	8-719-404-46	DIODE MA110		
D504	8-719-404-46	DIODE MA110		
D506	8-719-908-03	DIODE GP08D		
D507	8-719-404-46	DIODE MA110		
D508	8-719-404-46	DIODE MA110		
D511	8-719-404-46	DIODE MA110		
D512	8-719-404-46	DIODE MA110		
D514	8-719-404-46	DIODE MA110		
D520	8-719-800-76	DIODE 1SS226		
D521	8-719-800-76	DIODE 1SS226		
D831	8-719-404-46	DIODE MA110		
D832	8-719-404-46	DIODE MA110		
D833	8-719-404-46	DIODE MA110		
D834	8-719-404-46	DIODE MA110		
D835	8-719-109-89	DIODE RD5.6ESB2		
D836	8-719-977-69	DIODE DTZ24B		
D848	8-719-800-76	DIODE 1SS226		
D1601	8-719-105-99	DIODE RD6.2M-B1		
D1603	8-719-977-61	DIODE DTZ20B		
D1606	8-719-981-00	DIODE ERC81-004		
D1607	8-719-981-00	DIODE ERC81-004		
D1608	8-719-977-02	DIODE DTZ5.6A		
D1609	8-719-977-49	DIODE DTZ15B		
D1610	8-719-404-46	DIODE MA110		
D1611	8-729-101-31	TRANSISTOR N13T1		
D1612	8-719-404-46	DIODE MA110		
D1615	8-719-404-46	DIODE MA110		
D1617	8-719-977-49	DIODE DTZ15B		
D1618	8-719-977-49	DIODE DTZ15B		
D1620	8-719-801-78	DIODE 1SS184		
D1621	8-719-510-12	DIODE D10SC4M		
	4-382-854-11	SCREW (M3X10), P, SW (+); Q1621		
D1622	8-719-801-78	DIODE 1SS184		
D1623	8-719-801-78	DIODE 1SS184		
D1626	8-719-404-46	DIODE MA110		
D1627	8-719-404-46	DIODE MA110		
D1628	8-719-404-46	DIODE MA110		
D1635	8-719-404-46	DIODE MA110		
D1699	8-719-404-46	DIODE MA110		
		<FUSE>		
F1601⚠	1-532-777-21	FUSE, MICRO (SECONDARY) (1.25A/125V)		
F1602	1-533-189-11	HOLDER, FUSE		
		<IC>		
IC501	8-759-909-70	IC CX23025		
IC502	8-759-100-60	IC UPC1377C		
IC503	8-759-801-98	IC LA7830		
	4-382-854-01	SCREW (M3X8), P, SW (+); IC503		
IC504	8-759-231-58	IC TA7812S		
	4-382-854-01	SCREW (M3X8), P, SW (+); IC504		
IC505	8-759-009-51	IC MC14538BF		
IC506	8-759-209-54	IC TC4S01F		
IC507	8-759-209-69	IC TC4S11F		
IC831	8-759-509-29	IC XRU4011BF		
IC832	8-759-509-37	IC XRU4070BF		
IC833	8-759-009-51	IC MC14538BF		
IC1601	8-759-509-91	IC XRA10393F		
		<COIL>		
L501	1-410-093-11	INDUCTOR 33MMH		
L502	1-410-665-31	INDUCTOR 15UH		
L503	1-424-625-11	COIL, CHOKE (PMC) 381.4UH		
L506	1-412-530-31	INDUCTOR 27UH		
L1601	1-459-155-00	COIL (WITH CORE) 45UH		
L1602	1-402-785-11	COIL, CHOKE 600UH		
L1603	1-410-397-21	FERRITE BEAD INDUCTOR 1.1UH		
		<TRANSISTOR>		
Q501	8-729-901-01	TRANSISTOR DTC144EK		
Q502	8-729-901-01	TRANSISTOR DTC144EK		
Q503	8-729-901-06	TRANSISTOR DTA144EK		
Q504	8-729-901-01	TRANSISTOR DTC144EK		
Q505	8-729-120-28	TRANSISTOR 2SC1623-L5L6		
Q508	8-729-120-28	TRANSISTOR 2SC1623-L5L6		
Q509	8-729-120-28	TRANSISTOR 2SC1623-L5L6		
Q512	8-729-120-28	TRANSISTOR 2SC1623-L5L6		
Q513	8-729-216-22	TRANSISTOR 2SA1162-G		
Q514	8-729-216-22	TRANSISTOR 2SA1162-G		
Q515	8-729-313-42	TRANSISTOR 2SD1134-C		
	4-382-854-01	SCREW (M3X8), P, SW (+); Q515		
Q518	8-729-120-28	TRANSISTOR 2SC1623-L5L6		
Q519	8-729-120-28	TRANSISTOR 2SC1623-L5L6		
Q532	8-729-120-28	TRANSISTOR 2SC1623-L5L6		
Q569	8-729-907-26	TRANSISTOR IMX1		
Q570	8-729-901-00	TRANSISTOR DTC124EK		
Q571	8-729-901-00	TRANSISTOR DTC124EK		
Q576	8-729-901-01	TRANSISTOR DTC144EK		
Q579	8-729-920-48	TRANSISTOR IMH2		
Q599	8-729-920-48	TRANSISTOR IMH2		
Q833	8-729-216-22	TRANSISTOR 2SA1162-G		
Q834	8-729-120-28	TRANSISTOR 2SC1623-L5L6		
Q835	8-729-120-28	TRANSISTOR 2SC1623-L5L6		
Q836	8-729-255-12	TRANSISTOR 2SC2551-O		
Q1601	8-729-120-28	TRANSISTOR 2SC1623-L5L6		
Q1602	8-729-120-28	TRANSISTOR 2SC1623-L5L6		
Q1603	8-729-120-28	TRANSISTOR 2SC1623-L5L6		
Q1604	8-729-216-22	TRANSISTOR 2SA1162-G		
Q1605	8-729-119-80	TRANSISTOR 2SC2688-LK		
Q1606	8-729-133-42	TRANSISTOR 2SC2334-L		
	4-382-854-01	SCREW (M3X8), P, SW (+); Q1606		
Q1607	8-729-120-28	TRANSISTOR 2SC1623-L5L6		

D

REF.NO.	PART NO.	DESCRIPTION				REMARK
Q1608	8-729-120-28	TRANSISTOR 2SC1623-L5L6				
Q1609	8-729-120-28	TRANSISTOR 2SC1623-L5L6				
Q1610	8-729-120-28	TRANSISTOR 2SC1623-L5L6				
Q1611	8-729-120-28	TRANSISTOR 2SC1623-L5L6				
Q1612	8-729-120-28	TRANSISTOR 2SC1623-L5L6				
Q1613	8-729-120-28	TRANSISTOR 2SC1623-L5L6				
Q1614	8-729-120-28	TRANSISTOR 2SC1623-L5L6				
Q1615	8-729-216-22	TRANSISTOR 2SA1162-G				
Q1616	8-729-216-22	TRANSISTOR 2SA1162-G				
Q1617	8-729-216-22	TRANSISTOR 2SA1162-G				
Q1618	8-729-216-22	TRANSISTOR 2SA1162-G				
		<RESISTOR>				
JR510	1-216-295-91	METAL GLAZE	0	5%	1/10W	
JR517	1-216-295-91	METAL GLAZE	0	5%	1/10W	
R501	1-216-089-91	METAL GLAZE	47K	5%	1/10W	
R502	1-216-089-91	METAL GLAZE	47K	5%	1/10W	
R503	1-249-437-11	CARBON	47K	5%	1/4W	F
R504	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R505	1-249-393-11	CARBON	10	5%	1/4W	F
R506	1-216-071-00	METAL GLAZE	8.2K	5%	1/10W	
R507	1-216-059-00	METAL GLAZE	2.7K	5%	1/10W	
R508	1-216-085-00	METAL GLAZE	33K	5%	1/10W	
R509	1-216-687-11	METAL CHIP	33K	0.50%	1/10W	
R510	1-216-683-11	METAL CHIP	22K	0.50%	1/10W	
R511	1-216-675-11	METAL CHIP	10K	0.50%	1/10W	
R512	1-218-761-11	METAL CHIP	240K	0.50%	1/10W	
R513	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R514	1-218-754-11	METAL CHIP	120K	0.50%	1/10W	
R515	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R516	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R517	1-218-762-11	METAL CHIP	270K	0.50%	1/10W	
R518	1-249-422-11	CARBON	2.7K	5%	1/4W	F
R519	1-216-085-00	METAL GLAZE	33K	5%	1/10W	
R520	1-216-677-11	METAL CHIP	12K	0.50%	1/10W	
R521	1-216-067-00	METAL GLAZE	5.6K	5%	1/10W	
R522	1-216-107-00	METAL GLAZE	270K	5%	1/10W	
R523	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R524	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R525	1-216-434-11	METAL OXIDE	1.8K	5%	1W	F
R526	1-216-079-00	METAL GLAZE	18K	5%	1/10W	
R527	1-249-437-11	CARBON	47K	5%	1/4W	F
R528	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R529	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R530	1-216-089-91	METAL GLAZE	47K	5%	1/10W	
R531	1-216-089-91	METAL GLAZE	47K	5%	1/10W	
R532	1-216-097-00	METAL GLAZE	100K	5%	1/10W	
R533	1-216-089-91	METAL GLAZE	47K	5%	1/10W	
R534	1-216-097-00	METAL GLAZE	100K	5%	1/10W	
R535	1-216-053-00	METAL GLAZE	1.5K	5%	1/10W	
R536	1-212-881-11	FUSIBLE	100	5%	1/4W	F
R537	1-215-867-00	METAL OXIDE	470	5%	1W	F
R538	1-216-095-00	METAL GLAZE	82K	5%	1/10W	
R539	1-216-095-00	METAL GLAZE	82K	5%	1/10W	
R540	1-216-101-00	METAL GLAZE	150K	5%	1/10W	
R541	1-216-063-00	METAL GLAZE	3.9K	5%	1/10W	
R542	1-216-075-00	METAL GLAZE	12K	5%	1/10W	
R543	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R544	1-216-101-00	METAL GLAZE	150K	5%	1/10W	
R545	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R546	1-216-091-00	METAL GLAZE	56K	5%	1/10W	
R547	1-216-121-00	METAL GLAZE	1M	5%	1/10W	
R548	1-216-107-00	METAL GLAZE	270K	5%	1/10W	
R549	1-216-101-00	METAL GLAZE	150K	5%	1/10W	
R550	1-216-357-00	METAL OXIDE	4.7	5%	1W	F
R552	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R553	1-216-689-11	METAL GLAZE	39K	5%	1/10W	
R554	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R555	1-216-077-00	METAL GLAZE	15K	5%	1/10W	
R557	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W	
R558	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R559	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R560	1-216-037-00	METAL GLAZE	330	5%	1/10W	
R561	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R562	1-216-053-00	METAL GLAZE	1.5K	5%	1/10W	
R563	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R564	1-249-415-11	CARBON	680	5%	1/4W	F
R565	1-216-059-00	METAL GLAZE	2.7K	5%	1/10W	
R566	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R567	1-216-095-00	METAL GLAZE	82K	5%	1/10W	
R568	1-216-063-00	METAL GLAZE	3.9K	5%	1/10W	
R569	1-216-063-00	METAL GLAZE	3.9K	5%	1/10W	
R570	1-216-093-00	METAL GLAZE	68K	5%	1/10W	
R571	1-216-089-91	METAL GLAZE	47K	5%	1/10W	
R572	1-216-095-00	METAL GLAZE	82K	5%	1/10W	
R573	1-216-063-00	METAL GLAZE	3.9K	5%	1/10W	
R574	1-216-063-00	METAL GLAZE	3.9K	5%	1/10W	
R575	1-216-105-00	METAL GLAZE	220K	5%	1/10W	
R576	1-216-109-00	METAL GLAZE	330K	5%	1/10W	
R577	1-216-105-00	METAL GLAZE	220K	5%	1/10W	
R578	1-249-457-11	CARBON	6.8	5%	1/4W	F
R579	1-249-457-11	CARBON	6.8	5%	1/4W	F
R589	1-216-101-00	METAL GLAZE	150K	5%	1/10W	
R591	1-216-063-00	METAL GLAZE	3.9K	5%	1/10W	
R592	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R593	1-216-101-00	METAL GLAZE	150K	5%	1/10W	
R594	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R831	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R832	1-216-075-00	METAL GLAZE	12K	5%	1/10W	
R833	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R834	1-216-059-00	METAL GLAZE	2.7K	5%	1/10W	
R835	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R836	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R837	1-216-075-00	METAL GLAZE	12K	5%	1/10W	
R838	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R839	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R840	1-216-097-00	METAL GLAZE	100K	5%	1/10W	
R841	1-216-093-00	METAL GLAZE	68K	5%	1/10W	
R842	1-216-093-00	METAL GLAZE	68K	5%	1/10W	
R843	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R844	1-216-077-00	METAL GLAZE	15K	5%	1/10W	
R847	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R850	1-216-085-00	METAL GLAZE	33K	5%	1/10W	
R851	1-208-800-11	METAL CHIP	5.6K	0.50%	1/10W	
R852	1-216-675-11	METAL CHIP	10K	0.50%	1/10W	
R853	1-216-105-00	METAL GLAZE	220K	5%	1/10W	
R854	1-218-754-11	METAL CHIP	120K	0.50%	1/10W	
R855	1-216-697-91	METAL CHIP	82K	0.50%	1/10W	
R856	1-216-699-11	METAL CHIP	100K	0.50%	1/10W	
R857	1-216-686-11	METAL CHIP	30K	0.50%	1/10W	
R858	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R859	1-216-436-00	METAL OXIDE	3.9K	5%	1W	F
R860	1-216-675-11	METAL CHIP	10K	0.50%	1/10W	
R861	1-216-671-11	METAL CHIP	6.8K	0.50%	1/10W	
R862	1-216-675-11	METAL CHIP	10K	0.50%	1/10W	
R863	1-249-435-11	CARBON	33K	5%	1/4W	F

D | HA

The components identified by shading and mark ⚠ are critical for safety.
Replace only with part number specified.

- The components identified by ⊠ in this manual have been carefully factory-selected for each set in order to satisfy regulations regarding X-ray radiation.
Should replacement be required, replace only with the value originally used.

REF.NO.	PART NO.	DESCRIPTION				REMARK
R1503	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R1504	1-216-695-11	METAL CHIP	68K	0.50%	1/10W	
R1505	1-216-089-91	METAL GLAZE	47K	5%	1/10W	
R1506	1-216-667-11	METAL CHIP	4.7K	0.50%	1/10W	
R1507	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R1508	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1509	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R1510	1-249-425-11	CARBON	4.7K	5%	1/4W	F
R1511	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R1512	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R1513	1-216-017-00	METAL GLAZE	47	5%	1/10W	
R1519	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R1520	1-216-053-00	METAL GLAZE	1.5K	5%	1/10W	
R1601	1-216-685-11	METAL CHIP	27K	0.50%	1/10W	
R1602	1-208-812-11	METAL CHIP	18K	0.50%	1/10W	
R1603	1-216-671-11	METAL CHIP	6.8K	0.50%	1/10W	
R1604	1-249-433-11	CARBON	22K	5%	1/4W	F
R1605	1-216-070-00	METAL GLAZE	7.5K	5%	1/10W	
R1606	1-216-070-00	METAL GLAZE	7.5K	5%	1/10W	
R1607	1-216-071-00	METAL GLAZE	8.2K	5%	1/10W	
R1608	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R1609	1-216-069-00	METAL GLAZE	6.8K	5%	1/10W	
R1610	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W	
R1611	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W	
R1612	1-215-913-11	METAL OXIDE	220	5%	3W	F
R1613	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R1614	1-216-067-00	METAL GLAZE	5.6K	5%	1/10W	
R1615	1-216-657-11	METAL CHIP	1.8K	0.50%	1/10W	
R1616	1-216-629-11	METAL CHIP	120	0.50%	1/10W	
R1617	1-216-659-11	METAL CHIP	2.2K	0.50%	1/10W	
R1618	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1620	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R1621	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1622	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1623	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1624	1-216-246-91	METAL GLAZE	100K	5%	1/8W	
R1625	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R1626	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R1627	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R1628	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1629	1-216-683-11	METAL CHIP	22K	0.50%	1/10W	
R1630	1-216-683-11	METAL CHIP	22K	0.50%	1/10W	
R1631	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W	
R1632	1-216-042-00	METAL GLAZE	510	5%	1/10W	
R1633	1-216-109-00	METAL GLAZE	330K	5%	1/10W	
R1634	1-216-099-00	METAL GLAZE	120K	5%	1/10W	
R1635	1-216-097-00	METAL GLAZE	100K	5%	1/10W	
R1636	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1640	1-216-063-00	METAL GLAZE	3.9K	5%	1/10W	
R1641	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1642	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1643	1-216-069-00	METAL GLAZE	6.8K	5%	1/10W	
R1644	1-216-069-00	METAL GLAZE	6.8K	5%	1/10W	
R1645	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1646	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1647	1-216-685-11	METAL CHIP	27K	0.50%	1/10W	
R1648	1-216-069-00	METAL GLAZE	6.8K	5%	1/10W	
R1649	1-216-069-00	METAL GLAZE	6.8K	5%	1/10W	
R1650	1-216-069-00	METAL GLAZE	6.8K	5%	1/10W	
R1651	1-216-069-00	METAL GLAZE	6.8K	5%	1/10W	
R1652	1-216-069-00	METAL GLAZE	6.8K	5%	1/10W	
R1653	1-216-069-00	METAL GLAZE	6.8K	5%	1/10W	
R1654	1-208-812-11	METAL CHIP	18K	0.50%	1/10W	
R1655	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R1656	1-216-643-11	METAL CHIP	470	0.50%	1/10W	
R1657	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R1658	1-216-063-00	METAL GLAZE	3.9K	5%	1/10W	
R1659	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R1660	1-216-649-11	METAL CHIP	820	0.50%	1/10W	
R1661	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R1691	1-216-073-00	METAL GLAZE	10K	5%	1/10W	

<VARIABLE RESISTOR>

RV501	1-238-019-11	RES, ADJ, CARBON 47K	
RV502	1-241-765-11	RES, ADJ, CARBON 22K	
RV503	1-241-763-11	RES, ADJ, CERMET 4.7K	
RV504	1-224-250-XX	RES, ADJ, METAL GLAZE 2.2K	
RV505	1-241-759-21	RES, ADJ, CARBON 220	
RV507	1-241-628-11	RES, ADJ, CARBON 2.2K	
RV508	1-241-761-11	RES, ADJ, CARBON 1K	
RV509	1-241-768-11	RES, ADJ, CARBON 220K	
RV511	1-241-763-11	RES, ADJ, CARBON 4.7K	
RV512	1-241-763-11	RES, ADJ, CARBON 4.7K	
RV514	1-238-019-11	RES, ADJ, CARBON 47K	
RV515	1-241-768-11	RES, ADJ, CARBON 220K	
RV516	1-241-763-11	RES, ADJ, CERMET 4.7K	
RV517	1-241-760-11	RES, ADJ, CARBON 470	
RV518	1-241-763-11	RES, ADJ, CARBON 4.7K	
RV831	1-228-997-00	RES, ADJ, METAL GLAZE 100K	
RV832	1-241-764-11	RES, ADJ, CERMET 10K	
⊠RV833⚠		RES, ADJ, METAL GLAZE	
	*3-738-015-01	COVER, (DIA. 6) CARBON VR; RV833	
RV1601	1-241-762-11	RES, ADJ, CERMET 2.2K	
RV1602	1-241-761-11	RES, ADJ, CARBON 1K	
⊠RV1603⚠		RES, ADJ, METAL GLAZE	
	*3-738-015-01	COVER, (DIA. 6) CARBON VR; RV1603	

<RELAY>

RY1601	1-755-022-11	RELAY, POWER

<TRANSFORMER>

T1601	1-437-216-11	TRANSFORMER, DRIVE

****

	*A-1371-782-A	HA BOARD,COMPLETE
		**********
	*4-348-208-00	HOLDER, LED

<CONNECTOR>

CN001	1-506-478-11	PIN, CONNECTOR 13P
CN002	*1-564-007-11	PIN, CONNECTOR 8P

<DIODE>

D001	8-719-920-05	DIODE SLP281C-50
D002	8-719-109-68	DIODE RD3.6ESB1

<RESISTOR>

JW009	1-216-295-91	METAL GLAZE	0	5%	1/10W
JW024	1-216-295-91	METAL GLAZE	0	5%	1/10W
R001	1-247-713-11	CARBON	1K	5%	1/4W

HA X S

REF.NO.	PART NO.	DESCRIPTION				REMARK
R002	1-216-295-91	METAL GLAZE	0	5%	1/10W	
R003	1-216-295-91	METAL GLAZE	0	5%	1/10W	
R004	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
		<VARIABLE RESISTOR>				
RV001	1-223-504-21	RES, VAR, CARBON 20K				
RV002	1-223-504-21	RES, VAR, CARBON 20K				
RV003	1-223-735-11	RES, VAR, CARBON 20K				
RV004	1-223-735-11	RES, VAR, CARBON 20K				
RV005	1-223-735-11	RES, VAR, CARBON 20K				
RV006	1-223-735-11	RES, VAR, CARBON 20K				
RV007	1-226-773-11	RES, ADJ, METAL GLAZE 22K				
RV008	1-226-773-11	RES, ADJ, METAL GLAZE 22K				
RV009	1-226-773-11	RES, ADJ, METAL GLAZE 22K				
RV010	1-226-773-11	RES, ADJ, METAL GLAZE 22K				
RV011	1-226-773-11	RES, ADJ, METAL GLAZE 22K				
RV012	1-226-773-11	RES, ADJ, METAL GLAZE 22K				
		<SWITCH>				
S001	1-554-419-00	SWITCH, PUSH (1 KEY)				
S002	1-554-419-00	SWITCH, PUSH (1 KEY)				
S003	1-554-419-00	SWITCH, PUSH (1 KEY)				
S004	1-554-419-00	SWITCH, PUSH (1 KEY)				
S005	1-554-419-00	SWITCH, PUSH (1 KEY)				
S006	1-554-419-00	SWITCH, PUSH (1 KEY)				
**********						
	*A-1390-276-A	X BOARD, COMPLETE				
		**********				
		<CONNECTOR>				
CN21	*1-564-518-11	PLUG, CONNECTOR 3P				
		<DIODE>				
D21	8-719-023-78	DIODE SEL3810DLC05				
D22	8-719-023-78	DIODE SEL3810DLC05				
D23	8-719-023-78	DIODE SEL3810DLC05				
**********						
	*A-1394-368-A	S BOARD, COMPLETE				
		**********				
		<CAPACITOR>				
C1101	1-163-119-00	CERAMIC CHIP	120PF	5%	50V	
C1102	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	
C1103	1-124-589-11	ELECT	47MF	20%	16V	
C1104	1-163-031-11	CERAMIC CHIP	0.01MF		50V	
C1105	1-163-114-00	CERAMIC CHIP	75PF	5%	50V	
C1106	1-163-101-00	CERAMIC CHIP	22PF	5%	50V	
C1107	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	
C1108	1-163-119-00	CERAMIC CHIP	120PF	5%	50V	
C1109	1-163-031-11	CERAMIC CHIP	0.01MF		50V	
C1110	1-163-117-00	CERAMIC CHIP	100PF	5%	50V	
C1111	1-163-018-00	CERAMIC CHIP	0.0056MF	10%	50V	
C1112	1-126-160-11	ELECT	1MF	20%	50V	
C1113	1-163-119-00	CERAMIC CHIP	120PF	5%	50V	
C1114	1-163-103-00	CERAMIC CHIP	27PF	5%	50V	
C1115	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	
C1116	1-163-114-00	CERAMIC CHIP	75PF	5%	50V	
C1117	1-124-589-11	ELECT	47MF	20%	16V	
C1118	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	
C1119	1-163-020-00	CERAMIC CHIP	0.0082MF	10%	50V	
C1120	1-163-097-00	CERAMIC CHIP	15PF	5%	50V	
C1121	1-163-097-00	CERAMIC CHIP	15PF	5%	50V	
C1122	1-163-222-11	CERAMIC CHIP	5PF	0.25PF	50V	
C1123	1-163-097-00	CERAMIC CHIP	15PF	5%	50V	
C1130	1-163-097-00	CERAMIC CHIP	15PF	5%	50V	
C1131	1-163-097-00	CERAMIC CHIP	15PF	5%	50V	
		<CONNECTOR>				
CN1101	*1-565-488-11	CONNECTOR, BOARD TO BOARD 12P				
		<DIODE>				
D1101	8-719-404-46	DIODE MA110				
D1102	8-719-404-46	DIODE MA110				
		<IC>				
IC1101	8-752-056-67	IC CXA1214P				
		<COIL>				
L1101	1-408-411-00	INDUCTOR	15UH			
L1102	1-404-496-00	COIL				
L1103	1-404-496-00	COIL				
L1104	1-408-411-00	INDUCTOR	15UH			
L1110	1-412-008-31	INDUCTOR CHIP	15UH			
L1111	1-412-008-31	INDUCTOR CHIP	15UH			
		<TRANSISTOR>				
Q1101	8-729-216-22	TRANSISTOR 2SA1162-G				
Q1102	8-729-120-28	TRANSISTOR 2SC1623-L5L6				
Q1103	8-729-216-22	TRANSISTOR 2SA1162-G				
Q1104	8-729-216-22	TRANSISTOR 2SA1162-G				
Q1105	8-729-901-01	TRANSISTOR DTC144EK				
Q1106	8-729-901-01	TRANSISTOR DTC144EK				
Q1107	8-729-109-44	TRANSISTOR 2SK94-X4				
Q1108	8-729-120-28	TRANSISTOR 2SC1623-L5L6				
		<RESISTOR>				
R1101	1-216-053-00	METAL GLAZE	1.5K	5%	1/10W	
R1102	1-216-067-00	METAL GLAZE	5.6K	5%	1/10W	
R1103	1-216-059-00	METAL GLAZE	2.7K	5%	1/10W	
R1104	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1105	1-216-031-00	METAL GLAZE	180	5%	1/10W	
R1106	1-216-059-00	METAL GLAZE	2.7K	5%	1/10W	
R1107	1-216-071-00	METAL GLAZE	8.2K	5%	1/10W	
R1108	1-216-039-00	METAL GLAZE	390	5%	1/10W	
R1109	1-216-063-00	METAL GLAZE	3.9K	5%	1/10W	
R1110	1-216-069-00	METAL GLAZE	6.8K	5%	1/10W	
R1111	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R1112	1-216-059-00	METAL GLAZE	2.7K	5%	1/10W	
R1113	1-216-069-00	METAL GLAZE	6.8K	5%	1/10W	
R1114	1-216-055-00	METAL GLAZE	1.8K	5%	1/10W	
R1115	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R1116	1-216-069-00	METAL GLAZE	6.8K	5%	1/10W	
R1117	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R1118	1-216-073-00	METAL GLAZE	10K	5%	1/10W	

S G

The components identified by shading and mark ⚠ are critical for safety.
Replace only with part number specified.

- The components identified by ⊠ in this manual have been carefully factory-selected for each set in order to satisfy regulations regarding X-ray radiation.
Should replacement be required, replace only with the value originally used.

REF.NO.	PART NO.	DESCRIPTION				REMARK
R1119	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R1120	1-216-097-00	METAL GLAZE	100K	5%	1/10W	
R1121	1-216-121-00	METAL GLAZE	1M	5%	1/10W	
R1122	1-216-039-00	METAL GLAZE	390	5%	1/10W	
R1123	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R1124	1-216-029-00	METAL GLAZE	150	5%	1/10W	
R1125	1-216-029-00	METAL GLAZE	150	5%	1/10W	
R1126	1-216-053-00	METAL GLAZE	1.5K	5%	1/10W	
R1127	1-216-043-00	METAL GLAZE	560	5%	1/10W	
R1128	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R1129	1-216-091-00	METAL GLAZE	56K	5%	1/10W	
R1131	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1132	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1133	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1134	1-216-091-00	METAL GLAZE	56K	5%	1/10W	

<VARIABLE RESISTOR>

RV1101	1-241-763-11	RES, ADJ, CARBON 4.7K
RV1102	1-241-628-11	RES, ADJ, CARBON 2.2K

<TRANSFORMER>

T1101	1-404-584-11	COIL

****

G BOARD (SOPS-1021(A))
****

	4-812-134-11	RIVET NYLON, 3.5φ

<CAPACITOR>

C602 ⚠	1-136-889-11	METALIZED FILM	0.22MF	20%	250V
C603 ⚠	1-161-741-00	CERAMIC	0.001MF B	10%	400V
C604 ⚠	1-161-741-00	CERAMIC	0.001MF B	10%	400V
C605 ⚠	1-161-741-00	CERAMIC	0.001MF B	10%	400V
C608 ⚠	1-162-599-12	CERAMIC	0.0047MF	20%	400V
C609 ⚠	1-162-599-12	CERAMIC	0.0047MF	20%	400V
C610 ⚠	1-125-724-11	ELECT	180MF	20%	400V
C611 ⚠	1-136-206-21	METALIZED FILM	0.033MF	10%	630V
C612 ⚠	1-124-910-51	ELECT	47MF	20%	50V
C613 ⚠	1-137-190-91	METALIZED FILM	0.22MF	5%	50V
C614 ⚠	1-137-190-91	METALIZED FILM	0.22MF	5%	50V
C615 ⚠	1-130-471-91	PE TEREPHTHALATE	0.001MF	5%	50V
C616 ⚠	1-130-479-00	FILM	0.0047MF	5%	50V
C651 ⚠	1-161-825-11	CERAMIC	220PF B	10%	500V
C652 ⚠	1-128-486-51	ELECT	680MF	20%	50V
C653 ⚠	1-128-485-51	ELECT	220MF	20%	50V
C654 ⚠	1-130-483-91	PE TEREPHTHALATE	0.01MF	5%	50V

<CONNECTOR>

CN610 ⚠*	1-560-436-11	HORIZONTAL PIN ASSY 3P
CN651 ⚠*	1-564-518-11	PLUG, CONNECTOR 3P

<DIODE>

D201 ⚠	8-719-971-08	DIODE ESAC39M 06C
D601 ⚠	8-719-510-27	DIODE D3SB60
D602 ⚠	8-719-921-20	DIODE 1SS119TD
D603 ⚠	8-719-981-47	DIODE ERA38-06TP1
D604 ⚠	8-719-981-47	DIODE ERA38-06TP1
D605 ⚠	8-719-113-44	DIODE RD20ES-T1B3
D651 ⚠	8-719-971-08	DIODE ESAC39M 06C

<IC>

IC601 ⚠	1-809-086-12	HIC CH-1018
IC651 ⚠	8-759-908-15	IC TL431CLP
PH601 ⚠	8-759-045-81	IC TLP732GR-LF2

<COIL>

L601 ⚠	1-424-616-11	TRANSFORMER, LINE FILTER
L602 ⚠	1-424-574-11	L.F.T
L651 ⚠	1-424-255-41	COIL, CHOKE (MOLDE) 10UH
L652 ⚠	1-424-615-11	COIL, CHOKE

<TRANSISTOR>

Q601 ⚠	8-729-322-18	TRANSISTOR 2SK1402A

<RESISTOR>

R601 ⚠	1-205-940-51	CEMENT	1.5	5%	5W	F
R602 ⚠	1-205-940-51	CEMENT	1.5	5%	5W	F
R603 ⚠	1-215-904-11	METAL OXIDE	100K	5%	2W	F
R604 ⚠	1-215-904-11	METAL OXIDE	100K	5%	2W	F
R605 ⚠	1-212-865-61	FUSIBLE	22	5%	1/4W	F
R606 ⚠	1-247-805-91	CARBON	82	5%	1/4W	
R607 ⚠	1-260-128-91	CARBON	270K	5%	1/2W	
R608 ⚠	1-260-128-91	CARBON	270K	5%	1/2W	
R609 ⚠	1-215-904-51	METAL OXIDE	100K	5%	2W	F
R610 ⚠	1-207-455-11	WIRE	0.22	10%	1/2W	
R611 ⚠	1-249-395-11	CARBON(SMALL)	15	5%	1/4W	
R612 ⚠	1-247-795-91	CARBON	33	5%	1/4W	
R613 ⚠	1-215-904-51	METAL OXIDE	100K	5%	2W	F
R614 ⚠	1-247-815-91	CARBON	220	5%	1/4W	
R620 ⚠	1-218-265-11	METAL OXIDE	8.2M	5%	1W	
R651 ⚠	1-215-886-51	METAL OXIDE	100	5%	2W	F
R652 ⚠	1-215-886-51	METAL OXIDE	100	5%	2W	F
R653 ⚠	1-260-107-91	CARBON	4.7K	5%	1/2W	
R654 ⚠	1-260-107-91	CARBON	4.7K	5%	1/2W	
R655 ⚠	1-247-867-91	CARBON	33K	5%	1/4W	
R656 ⚠	1-247-867-91	CARBON	33K	5%	1/4W	
R657 ⚠	1-247-837-91	CARBON	1.8K	5%	1/4W	
R658 ⚠	1-249-435-11	CARBON(SMALL)	33K	5%	1/4W	

<VARIABLE RESISTOR>

⊠RV651 ⚠	1-237-443-11	RES, ADJ, CARBON 1K

<TRANSFORMER>

T601 ⚠	1-450-760-11	TRANSFORMER, CONVERTER

****

MISCELLANEOUS
****

⚠	1-413-720-24	SWITCHING REGULATOR (SOPS-1021(A))
⚠	1-426-043-12	COIL, DEGAUSSING
⚠	1-451-319-22	DEFLECTION YOKE (Y9FXC)
	1-452-126-11	MAGNET
	1-544-252-11	SPEAKER
⚠	1-576-232-11	FUSE (H.B.C.) (5.0A/250V)
	1-690-871-11	CABLE (MINI DIN) 8P

The components identified by shading and mark ⚠ are critical for safety.
Replace only with part number specified.

REF.NO.	PART NO.	DESCRIPTION	REMARK
	1-941-866-12	CONNECTOR ASSY	
	1-941-913-02	CORE ASSY, FERRITE	
V901	⚠ 8-737-154-05	PICTURE TUBE (09NDX) (PVM-9041QM)	
V901	⚠ 8-737-651-05	PICTURE TUBE (09FX) (PVM-9044QM)	
	**********		
		ACCESSORIES AND PACKING MATERIALS	
		**********	
	⚠ 1-590-910-11	CORD SET, POWER (10A/250V)	
	1-690-871-11	CABLE (MINI DIN) 8P	
	2-990-241-02	HOLDER (A), PLUG	
	3-170-078-01	HOLDER (B), PLUG	
	*3-704-301-01	BAG (STANDARD), PROTECTION	
	3-754-506-24	MANUAL, INSTRUCTION	
	4-034-835-01	PLATE, TALLY	
	*4-034-955-01	CUSHION (UPPER) (ASSY)	
	*4-034-956-01	CUSHION (LOWER) (ASSY)	
	*4-046-435-01	INDIVIDUAL CARTON (PVM-9041QM)	
	*4-046-436-01	INDIVIDUAL CARTON (PVM-9044QM)	

9-978-259-84

Sony Corporation
B&I Systems Company

English
94HZ0211-1
Printed in Japan
©1994.8